

E04NEF – NAG Fortran Library Routine Document

Note. Before using this routine, please read the Users' Note for your implementation to check the interpretation of bold italicised terms and other implementation-dependent details.

1 Purpose

To supply individual optional parameters to E04NCF.

2 Specification

```
SUBROUTINE E04NEF (STRING)
CHARACTER*(*)      STRING
```

3 Description

E04NEF may be used to supply values for optional parameters to E04NCF. It is only necessary to call E04NEF for those parameters whose values are to be different from their default values. One call to E04NEF sets one parameter value.

Each optional parameter is defined by a single character string of up to 72 characters, consisting of one or more items. The items associated with a given option must be separated by spaces, or equal signs [=]. Alphabetic characters may be upper or lower case. The string

```
Print Level = 1
```

is an example of a string used to set an optional parameter. For each option the string contains one or more of the following items:

- (a) A mandatory keyword.
- (b) A phrase that qualifies the keyword.
- (c) A number that specifies an INTEGER or *real* value. Such numbers may be up to 16 contiguous characters in Fortran 77's I, F, E or D formats, terminated by a space if this is not the last item on the line.

Blank strings and comments are ignored. A comment begins with an asterisk (*) and all subsequent characters in the string are regarded as part of the comment.

Normally, each user-specified option is printed as it is defined, on the current advisory message unit (see X04ABF), but this printing may be suppressed using the keyword **nolist**. Thus the statement

```
CALL E04NEF ('Nolist')
```

suppresses printing of this and subsequent options. Printing will automatically be turned on again after a call to E04NCF, and may be turned on again at any time by the user, by using the keyword **list**.

Optional parameter settings are preserved following a call to E04NCF, and so the keyword **defaults** is provided to allow the user to reset all the optional parameters to their default values by the statement,

```
CALL E04NEF ('Defaults')
```

prior to a subsequent call to E04NCF.

A complete list of optional parameters, their abbreviations, synonyms and default values is given in Section 11 of the document for E04NCF.

4 References

None.

5 Parameters

- 1: STRING — CHARACTER*(*) *Input*
On entry: a single valid option string (as described in Section 3 above and in Section 11 of the document for E04NCF).

6 Error Indicators and Warnings

If the parameter STRING is not recognized as a valid option string, then a warning message is output on the current advisory message unit (see X04ABF).

7 Accuracy

Not applicable.

8 Further Comments

E04NDF may also be used to supply optional parameters to E04NCF.

9 Example

See the example for E04NDF.
