

E04NLF – NAG Fortran Library Routine Document

Note. Before using this routine, please read the Users' Note for your implementation to check the interpretation of bold italicised terms and other implementation-dependent details.

1 Purpose

To supply optional parameters to E04NKF from an external file.

2 Specification

```
SUBROUTINE E04NLF(IOPTNS, INFORM)
INTEGER           IOPTNS, INFORM
```

3 Description

E04NLF may be used to supply values for optional parameters to E04NKF. E04NLF reads an external file and each line of the file defines a single optional parameter. It is only necessary to supply values for those parameters whose values are to be different from their default values.

Each optional parameter is defined by a single character string of up to 72 characters, consisting of one or more items. The items associated with a given option must be separated by spaces, or equal signs [=]. Alphabetic characters may be upper or lower case. The string

```
Print Level = 1
```

is an example of a string used to set an optional parameter. For each option the string contains one or more of the following items:

- (a) A mandatory keyword.
- (b) A phrase that qualifies the keyword.
- (c) A number that specifies an INTEGER or *real* value. Such numbers may be up to 16 contiguous characters in Fortran 77's I, F, E or D formats, terminated by a space if this is not the last item on the line.

Blank strings and comments are ignored. A comment begins with an asterisk (*) and all subsequent characters in the string are regarded as part of the comment.

The file containing the options must start with **begin** and must finish with **end**. An example of a valid options file is:

```
Begin * Example options file
      Print Level = 1
      End
```

Normally each line of the file is printed as it is read, on the current advisory message unit (see X04ABF), but printing may be suppressed using the keyword **nolist**. To suppress printing of **begin**, **nolist** must be the first option supplied as in the file:

```
Begin
      Nolist
      Print Level = 1
      End
```

Printing will automatically be turned on again after a call to E04NKF and may be turned on again at any time using the keyword **list**.

Optional parameter settings are preserved following a call to E04NKF, and so the keyword **defaults** is provided to allow the user to reset all the optional parameters to their default values prior to a subsequent call to E04NKF.

A complete list of optional parameters, their abbreviations, synonyms and default values is given in Section 11 of the document for E04NKF.

4 References

None.

5 Parameters

- | | |
|--|---------------|
| 1: IOPTNS — INTEGER | <i>Input</i> |
| <p><i>On entry:</i> the unit number of the options file to be read.</p> <p><i>Constraint:</i> $0 \leq \text{IOPTNS} \leq 99$.</p> | |
| 2: INFORM — INTEGER | <i>Output</i> |
| <p><i>On exit:</i> contains zero if the options file has been successfully read and a value > 0 otherwise, as indicated below.</p> | |
| <p>INFORM = 1</p> | |
| <p> IOPTNS is not in the range [0, 99].</p> | |
| <p>INFORM = 2</p> | |
| <p> begin was found, but end-of-file was found before end was found.</p> | |
| <p>INFORM = 3</p> | |
| <p> end-of-file was found before begin was found.</p> | |

6 Error Indicators and Warnings

If a line is not recognized as a valid option, then a warning message is output on the current advisory message unit (see X04ABF).

7 Accuracy

Not applicable.

8 Further Comments

E04NMF may also be used to supply optional parameters to E04NKF.

9 Example

This example solves the same problem as the example for E04NKF, but in addition illustrates the use of E04NLF and E04NMF to set optional parameters for E04NKF.

In this example the options file read by E04NLF is appended to the data file for the program (see Section 9.2). It would usually be more convenient in practice to keep the data file and the options file separate.

9.1 Program Text

Note. The listing of the example program presented below uses bold italicised terms to denote precision-dependent details. Please read the Users' Note for your implementation to check the interpretation of these terms. As explained in the Essential Introduction to this manual, the results produced may not be identical for all implementations.

```
*      E04NLF Example Program Text.
*      Mark 19 Revised. NAG Copyright 1999.
*      .. Parameters ..
      INTEGER             NIN, NOUT
      PARAMETER          (NIN=5,NOUT=6)
```

```

      INTEGER           IDUMMY
      PARAMETER        (IDUMMY=-11111)
      INTEGER           NMAX, MMAX, NNZMAX, LENIZ, LENZ
      PARAMETER        (NMAX=100,MMAX=100,NNZMAX=100,LENIZ=10000,
+                      LENZ=10000)
*   .. Local Scalars ..
      real              OBJ, SINF
      INTEGER           I, ICOL, IFAIL, INFORM, IOBJ, J, JCOLUMN, M,
+                      MINIZ, MINZ, N, NCOLH, NINF, NNAME, NNZ, NS
      CHARACTER         START
*   .. Local Arrays ..
      real              A(NNZMAX), BL(NMAX+MMAX), BU(NMAX+MMAX),
+                      CLAMDA(NMAX+MMAX), XS(NMAX+MMAX), Z(LENZ)
      INTEGER           HA(NNZMAX), ISTATE(NMAX+MMAX), IZ(LENIZ),
+                      KA(NMAX+1)
      CHARACTER*8        CRNAME(NMAX+MMAX), NAMES(5)
*   .. External Subroutines ..
      EXTERNAL          E04NKF, E04NLF, E04NMF, QPHX, X04ABF
*   .. Executable Statements ..
      WRITE (NOUT,*) 'E04NLF Example Program Results'
*   Skip heading in data file.
      READ (NIN,*)
      READ (NIN,*) N, M
      IF (N.LE.NMAX .AND. M.LE.MMAX) THEN
*
*       Read NNZ, IOBJ, NCOLH, START and NNAME from data file.
*
      READ (NIN,*) NNZ, IOBJ, NCOLH, START, NNAME
*
*       Read NAMES and CRNAME from data file.
*
      READ (NIN,*) (NAMES(I),I=1,5)
      READ (NIN,*) (CRNAME(I),I=1,NNAME)
*
*       Read the matrix A from data file. Set up KA.
*
      JCOLUMN = 1
      KA(JCOLUMN) = 1
      DO 40 I = 1, NNZ
*
*       Element ( HA( I ), ICOL ) is stored in A( I ).
*
      READ (NIN,*) A(I), HA(I), ICOL
*
      IF (ICOL.LT.JCOLUMN) THEN
*
*       Elements not ordered by increasing column index.
*
      WRITE (NOUT,99999) 'Element in column', ICOL,
+                      ' found after element in column', JCOLUMN, '. Problem',
+                      ' abandoned.'
      STOP
      ELSE IF (ICOL.EQ.JCOLUMN+1) THEN
*
*       Index in A of the start of the ICOL-th column equals I.
*
      KA(ICOL) = I
      JCOLUMN = ICOL

```

```

        ELSE IF (ICOL.GT.JCOL+1) THEN
*
*      Index in A of the start of the ICOL-th column equals I,
*      but columns JCOL+1,JCOL+2,...,ICOL-1 are empty. Set the
*      corresponding elements of KA to I.
*
      DO 20 J = JCOL + 1, ICOL - 1
          KA(J) = I
20      CONTINUE
          KA(ICOL) = I
          JCOL = ICOL
      END IF
40      CONTINUE
*
      KA(N+1) = NNZ + 1
*
      IF (N.GT.ICOL) THEN
*
*      Columns N,N-1,...,ICOL+1 are empty. Set the corresponding
*      elements of KA accordingly.
*
      DO 60 I = N, ICOL + 1, -1
          IF (KA(I).EQ.IDUMMY) KA(I) = KA(I+1)
60      CONTINUE
      END IF
*
*      Read BL, BU, ISTATE and XS from data file.
*
      READ (NIN,*) (BL(I),I=1,N+M)
      READ (NIN,*) (BU(I),I=1,N+M)
      IF (START.EQ.'C') THEN
          READ (NIN,*) (ISTATE(I),I=1,N)
      ELSE IF (START.EQ.'W') THEN
          READ (NIN,*) (ISTATE(I),I=1,N+M)
      END IF
      READ (NIN,*) (XS(I),I=1,N)
*
*      Set three options using E04NMF.
*
      CALL E04NMF(' Check Frequency = 10 ')
*
      CALL E04NMF(' Crash Tolerance = 0.05 ')
*
      CALL E04NMF(' Infinite Bound Size = 1.0E+25 ')
*
*      Set the unit number for advisory messages to NOUT.
*
      CALL X04ABF(1,NOUT)
*
*      Read the options file for the remaining options.
*
      CALL E04NLF(NIN,INFORM)
*
      IF (INFORM.NE.0) THEN
          WRITE (NOUT,99998) 'E04NLF terminated with INFORM = ',
+
              INFORM
          STOP
      END IF

```

```

*
*      Solve the QP problem.
*
*      IFAIL = -1
*
*      CALL E04NKF(N,M,NNZ,IOBJ,NCOLH,QPHX,A,HA,KA,BL,BU,START,NAMES,
+                  NNAME,CRNAME,NS,XS,ISTATE,MINIZ,MINZ,NINF,SINF,OBJ,
+                  CLAMDA,IZ,LENIZ,Z,LENZ,IFAIL)
*
*      END IF
*      STOP
*
*      99999 FORMAT (/1X,A,I5,A,I5,A,A)
99998 FORMAT (1X,A,I3)
      END
*
      SUBROUTINE QPHX(NSTATE,NCOLH,X,HX)
*
*      Routine to compute H*x. (In this version of QPHX, the Hessian
*      matrix H is not referenced explicitly.)
*
*      .. Parameters ..
      INTEGER          NOUT
      PARAMETER        (NOUT=6)
      real             TWO
      PARAMETER        (TWO=2.0e+0)
*
*      .. Scalar Arguments ..
      INTEGER          NCOLH, NSTATE
*
*      .. Array Arguments ..
      real             HX(NCOLH), X(NCOLH)
*
*      .. Executable Statements ..
      IF (NSTATE.EQ.1) THEN
*
*      First entry.
*
*      WRITE (NOUT,99999) NCOLH
*
      END IF
*
*      Normal entry.
*
*      HX(1) = TWO*X(1)
*      HX(2) = TWO*X(2)
*      HX(3) = TWO*(X(3)+X(4))
*      HX(4) = HX(3)
*      HX(5) = TWO*X(5)
*      HX(6) = TWO*(X(6)+X(7))
*      HX(7) = HX(6)
*
*      IF (NSTATE.GE.2) THEN
*
*      Final entry.
*
*      WRITE (NOUT,99998)
*
      END IF
*
      RETURN

```

```

*
99999 FORMAT ('/ This is the E04NKF example.  NCOLH =',I4,'.')
99998 FORMAT ('/ Finished the E04NKF example.')
END

```

9.2 Program Data

E04NLF Example Program Data

7	8		:Values of N and M						
48	8	7	'C' 15 :Values of NNZ, IOBJ, NCOLH, START and NNAME						
,	,	,	,	,	,	,	,	:	End of NAMES
'...X1...	'...X2...	'...X3...	'...X4...	'...X5...					
'...X6...	'...X7...	'...ROW1...	'...ROW2...	'...ROW3...					
'...ROW4...	'...ROW5...	'...ROW6...	'...ROW7...	'...COST...	:	End of CRNAME			
0.02	7	1							
0.02	5	1							
0.03	3	1							
1.00	1	1							
0.70	6	1							
0.02	4	1							
0.15	2	1							
-200.00	8	1							
0.06	7	2							
0.75	6	2							
0.03	5	2							
0.04	4	2							
0.05	3	2							
0.04	2	2							
1.00	1	2							
-2000.00	8	2							
0.02	2	3							
1.00	1	3							
0.01	4	3							
0.08	3	3							
0.08	7	3							
0.80	6	3							
-2000.00	8	3							
1.00	1	4							
0.12	7	4							
0.02	3	4							
0.02	4	4							
0.75	6	4							
0.04	2	4							
-2000.00	8	4							
0.01	5	5							
0.80	6	5							
0.02	7	5							
1.00	1	5							
0.02	2	5							
0.06	3	5							
0.02	4	5							
-2000.00	8	5							
1.00	1	6							
0.01	2	6							
0.01	3	6							
0.97	6	6							
0.01	7	6							
400.00	8	6							

```

 0.97   7   7
 0.03   2   7
 1.00   1   7
 400.00   8   7                               :End of matrix A
 0.0     0.0     4.0E+02   1.0E+02   0.0     0.0     0.0     2.0E+03
-1.0E+25 -1.0E+25 -1.0E+25 -1.0E+25  1.5E+03  2.5E+02 -1.0E+25 :End of BL
 2.0E+02  2.5E+03  8.0E+02  7.0E+02  1.5E+03  1.0E+25  1.0E+25  2.0E+03
 6.0E+01  1.0E+02  4.0E+01  3.0E+01  1.0E+25  3.0E+02  1.0E+25  :End of BU
 0     0     0     0     0     0     0     0 :End of ISTATE
 0.0   0.0   0.0   0.0   0.0   0.0   0.0   0.0 :End of XS
Begin * Example options file for E04NLF
  Iteration Limit = 25 * (Default = 75)
  Print Level = 1 * (Default = 10)
End

```

9.3 Program Results

E04NLF Example Program Results

Calls to E04NMF

```

-----
Check Frequency = 10
Crash Tolerance = 0.05
Infinite Bound Size = 1.0E+25

```

OPTIONS file

```

-----
Begin * Example options file for E04NLF
  Iteration Limit = 25 * (Default = 75)
  Print Level = 1 * (Default = 10)
End

*** E04NKF
*** Start of NAG Library implementation details ***

Implementation title: Generalised Base Version
Precision: FORTRAN double precision
Product Code: FLBAS18D
Mark: 18A

*** End of NAG Library implementation details ***

```

Parameters

```

-----
Frequencies.
Check frequency.....      10      Expand frequency.....    10000
Factorization frequency.  100

```

LP Parameters.

Scale tolerance.....	9.00E-01	Feasibility tolerance...	1.00E-06
Iteration limit.....	25	Scale option.....	2
Optimality tolerance....	1.00E-06	Partial price.....	10
Crash tolerance.....	5.00E-02	Pivot tolerance.....	2.04E-11

Crash option.....	2						
QP objective.							
Objective variables.....	7	Hessian columns.....	7				
Superbasics limit.....	7						
Miscellaneous.							
Variables.....	7	Linear constraints.....	8				
LU factor tolerance.....	1.00E+02	LU update tolerance.....	1.00E+01				
LU singularity tolerance	2.04E-11	Monitoring file.....	-1				
EPS (machine precision).	1.11E-16	Print level.....	1				
Infinite bound size.....	1.00E+25	Infinite step size.....	1.00E+25				
COLD start.....		MINIMIZE.....					
Workspace provided is		IZ(10000), Z(10000).					
To start solving the problem we need		IZ(428), Z(358).					

This is the E04NKF example. NCOLH = 7.

Variable	State	Value	Lower Bound	Upper Bound	Lagr Mult	Residual
...X1...	LL	0.000000E+00	.	200.00	2361.	.
...X2...	BS	349.399	.	2500.0	-3.6566E-12	349.4
...X3...	SBS	648.853	400.00	800.00	-5.9240E-12	151.1
...X4...	SBS	172.847	100.00	700.00	1.9491E-12	72.85
...X5...	BS	407.521	.	1500.0	.	407.5
...X6...	BS	271.356	.	None	-3.2802E-12	271.4
...X7...	BS	150.023	.	None	-1.4130E-12	150.0

Constrnt	State	Value	Lower Bound	Upper Bound	Lagr Mult	Residual
..ROW1..	EQ	2000.00	2000.0	2000.0	-1.2901E+04	.
..ROW2..	BS	49.2316	None	60.000	.	-10.77
..ROW3..	UL	100.000	None	100.00	-2325.	.
..ROW4..	BS	32.0719	None	40.000	.	-7.928
..ROW5..	BS	14.5572	None	30.000	.	-15.44
..ROW6..	LL	1500.00	1500.0	None	1.4455E+04	.
..ROW7..	LL	250.000	250.00	300.00	1.4581E+04	.
..COST..	BS	-2.988690E+06	None	None	-1.000	-2.9887E+06

Finished the E04NKF example.

Exit E04NKF - Optimal QP solution found.

Final QP objective value = -1847785.

Exit from QP problem after 10 iterations.