

NAG Fortran Library Routine Document

C06PCF

Note: before using this routine, please read the Users' Note for your implementation to check the interpretation of *bold italicised* terms and other implementation-dependent details.

1 Purpose

C06PCF calculates the discrete Fourier transform of a sequence of n complex data values (using complex data type).

2 Specification

```
SUBROUTINE C06PCF(DIRECT, X, N, WORK, IFAIL)
INTEGER          N, IFAIL
complex        X(N), WORK(2*N+15)
CHARACTER*1     DIRECT
```

3 Description

Given a sequence of n complex data values z_j , for $j = 0, 1, \dots, n - 1$, this routine calculates their (**forward** or **backward**) discrete Fourier transform defined by

$$\hat{z}_k = \frac{1}{\sqrt{n}} \sum_{j=0}^{n-1} z_j \times \exp\left(\pm i \frac{2\pi jk}{n}\right), \quad k = 0, 1, \dots, n - 1.$$

(Note the scale factor of $\frac{1}{\sqrt{n}}$ in this definition.) The minus sign is taken in the argument of the exponential within the summation when the forward transform is required, and the plus sign is taken when the backward transform is required. A call of the routine with `DIRECT = 'F'` followed by a call with `DIRECT = 'B'` will restore the original data.

The routine uses a variant of the fast Fourier transform (FFT) algorithm (Brigham (1974)) known as the Stockham self-sorting algorithm, which is described in Temperton (1983b).

4 References

Brigham E O (1974) *The Fast Fourier Transform* Prentice-Hall

Temperton C (1983b) Self-sorting mixed-radix fast Fourier transforms *J. Comput. Phys.* **52** 1–23

5 Parameters

1: DIRECT – CHARACTER*1 *Input*

On entry: if the **Forward** transform as defined in Section 3 is to be computed, then DIRECT must be set equal to 'F'. If the **Backward** transform is to be computed then DIRECT must be set equal to 'B'.

Constraint: DIRECT = 'F' or 'B'.

2: X(N) – **complex** array *Input/Output*

On entry: if X is declared with bounds (0 : N - 1) in the (sub)program from which C06PCF is called, then X(j) must contain z_j , for $j = 0, 1, \dots, n - 1$.

On exit: the components of the discrete Fourier transform. If X is declared with bounds (0 : N - 1) in the (sub)program from which C06PCF is called, then for $0 \leq k \leq n - 1$, \hat{z}_k is contained in X(k).

- 3: N – INTEGER *Input*
On entry: the number of data values, n . The total number of prime factors of N, counting repetitions, must not exceed 30.
Constraint: $N \geq 1$.
- 4: WORK(2*N+15) – *complex* array *Workspace*
- 5: IFAIL – INTEGER *Input/Output*
On entry: IFAIL must be set to 0, -1 or 1. Users who are unfamiliar with this parameter should refer to Chapter P01 for details.
On exit: IFAIL = 0 unless the routine detects an error (see Section 6).
 For environments where it might be inappropriate to halt program execution when an error is detected, the value -1 or 1 is recommended. If the output of error messages is undesirable, then the value 1 is recommended. Otherwise, for users not familiar with this parameter the recommended value is 0. **When the value -1 or 1 is used it is essential to test the value of IFAIL on exit.**

6 Error Indicators and Warnings

If on entry IFAIL = 0 or -1, explanatory error messages are output on the current error message unit (as defined by X04AAF).

Errors or warnings detected by the routine:

IFAIL = 1

IFAIL = 2

IFAIL = 3

IFAIL = 4

7 Accuracy

Some indication of accuracy can be obtained by performing a subsequent inverse transform and comparing the results with the original sequence (in exact arithmetic they would be identical).

8 Further Comments

The time taken by the routine is approximately proportional to $n \times \log n$, but also depends on the factorization of n . The routine is somewhat faster than average if the only prime factors of n are 2, 3 or 5; and fastest of all if n is a power of 2.

9 Example

This program reads in a sequence of complex data values and prints their discrete Fourier transform (as computed by C06PCF with DIRECT set to 'F').

It then performs an inverse transform, using C06PCF with DIRECT set to 'B', and prints the sequence obtained alongside the original data values.

9.1 Program Text

Note: the listing of the example program presented below uses *bold italicised* terms to denote precision-dependent details. Please read the Users' Note for your implementation to check the interpretation of these terms. As explained in the Essential Introduction to this manual, the results produced may not be identical for all implementations.

```

*      C06PCF Example Program Text.
*      Mark 19 Release. NAG Copyright 1999.
*      .. Parameters ..
INTEGER          NIN, NOUT
PARAMETER       (NIN=5,NOUT=6)
INTEGER          NMAX
PARAMETER       (NMAX=20)
*      .. Local Scalars ..
INTEGER          IFAIL, J, N
*      .. Local Arrays ..
complex        WORK(2*NMAX+15), X(0:NMAX-1), XX(0:NMAX-1)
*      .. External Subroutines ..
EXTERNAL        C06PCF
*      .. Intrinsic Functions ..
INTRINSIC       real, imag
*      .. Executable Statements ..
WRITE (NOUT,*) 'C06PCF Example Program Results'
*      Skip heading in data file
READ (NIN,*)
20  CONTINUE
READ (NIN,*,END=100) N
IF (N.GT.1 .AND. N.LE.NMAX) THEN
  DO 40 J = 0, N - 1
    READ (NIN,*) X(J)
    XX(J) = X(J)
40  CONTINUE
  IFAIL = 0
*
  CALL C06PCF('F',X,N,WORK,IFAIL)
*
  WRITE (NOUT,*)
  WRITE (NOUT,*) 'Components of discrete Fourier transform'
  WRITE (NOUT,*)
  WRITE (NOUT,*) '          Real          Imag'
  WRITE (NOUT,*)
  DO 60 J = 0, N - 1
    WRITE (NOUT,99999) J, real(X(J)), imag(X(J))
60  CONTINUE
*
  CALL C06PCF('B',X,N,WORK,IFAIL)
*
  WRITE (NOUT,*)
  WRITE (NOUT,*)
+   'Original sequence as restored by inverse transform'
  WRITE (NOUT,*)
  WRITE (NOUT,*)
+   '          Original          Restored'
+   '          Real          Imag          Real          Imag'
  WRITE (NOUT,*)
  DO 80 J = 0, N - 1
    WRITE (NOUT,99999) J, XX(J), X(J)
80  CONTINUE
  GO TO 20
ELSE
  WRITE (NOUT,*) 'Invalid value of N'
END IF
100 CONTINUE
STOP
*
99999 FORMAT (1X,I5,2(:5X,'(',F8.5,',',F8.5,')'))
END

```

9.2 Program Data

C06PCF Example Program Data

```

7
(0.34907, -0.37168)
(0.54890, -0.35669)
(0.74776, -0.31175)

```

```
(0.94459, -0.23702)
(1.13850, -0.13274)
(1.32850,  0.00074)
(1.51370,  0.16298)
```

9.3 Program Results

C06PCF Example Program Results

Components of discrete Fourier transform

	Real	Imag
0	(2.48361,	-0.47100)
1	(-0.55180,	0.49684)
2	(-0.36711,	0.09756)
3	(-0.28767,	-0.05865)
4	(-0.22506,	-0.17477)
5	(-0.14825,	-0.30840)
6	(0.01983,	-0.56496)

Original sequence as restored by inverse transform

	Original		Restored	
	Real	Imag	Real	Imag
0	(0.34907,	-0.37168)	(0.34907,	-0.37168)
1	(0.54890,	-0.35669)	(0.54890,	-0.35669)
2	(0.74776,	-0.31175)	(0.74776,	-0.31175)
3	(0.94459,	-0.23702)	(0.94459,	-0.23702)
4	(1.13850,	-0.13274)	(1.13850,	-0.13274)
5	(1.32850,	0.00074)	(1.32850,	0.00074)
6	(1.51370,	0.16298)	(1.51370,	0.16298)
