NAG Fortran Library Routine Document F04ADF

Note: before using this routine, please read the Users' Note for your implementation to check the interpretation of **bold italicised** terms and other implementation-dependent details.

1 Purpose

F04ADF calculates the approximate solution of a set of complex linear equations with multiple right-hand sides, using an LU factorization with partial pivoting.

2 Specification

```
SUBROUTINE F04ADF(A, IA, B, IB, N, M, C, IC, WKSPCE, IFAIL)

INTEGER IA, IB, N, M, IC, IFAIL

real WKSPCE(*)

complex A(IA,*), B(IB,*), C(IC,*)
```

3 Description

Given a set of complex linear equations AX = B, the routine first computes an LU factorization of A with partial pivoting, PA = LU, where P is a permutation matrix, L is lower triangular and U is unit upper triangular. The columns x of the solution X are found by forward and backward substitution in Ly = Pb and Ux = y, where b is a column of the right-hand side matrix B.

4 References

Wilkinson J H and Reinsch C (1971) Handbook for Automatic Computation II, Linear Algebra Springer-Verlag

5 Parameters

1: A(IA,*) - complex array

Input/Output

Note: the second dimension of the array A must be at least max(1, N).

On entry: the n by n matrix A.

On exit: A is overwritten by the lower triangular matrix L and the off-diagonal elements of the upper triangular matrix U. The unit diagonal elements of U are not stored.

2: IA – INTEGER

Input

On entry: the first dimension of the array A as declared in the (sub)program from which F04ADF is called.

Constraint: $IA \ge max(1, N)$.

3: B(IB,*) - complex array

Input

Note: the second dimension of the array B must be at least max(1, M).

On entry: the n by m right-hand side matrix B. See also Section 8.

4: IB – INTEGER

Input

On entry: the first dimension of the array B as declared in the (sub)program from which F04ADF is called.

Constraint: $IB \ge max(1, N)$.

[NP3546/20A] F04ADF.1

5: N – INTEGER Input

On entry: n, the order of the matrix A.

Constraint: N > 0.

6: M – INTEGER Input

On entry: m, the number of right-hand sides.

Constraint: $M \geq 0$.

7: C(IC,*) - complex array

Output

Note: the second dimension of the array C must be at least max(1, M).

On exit: the n by m solution matrix X. See also Section 8.

8: IC – INTEGER Input

On entry: the first dimension of the array C as declared in the (sub)program from which F04ADF is called.

Constraint: $IC \ge max(1, N)$.

9: WKSPCE(*) - *real* array

Workspace

Note: the dimension of the array WKSPCE must be at least max(1, N).

10: IFAIL – INTEGER

Input/Output

On entry: IFAIL must be set to 0, -1 or 1. Users who are unfamiliar with this parameter should refer to Chapter P01 for details.

On exit: IFAIL = 0 unless the routine detects an error (see Section 6).

For environments where it might be inappropriate to halt program execution when an error is detected, the value -1 or 1 is recommended. If the output of error messages is undesirable, then the value 1 is recommended. Otherwise, for users not familiar with this parameter the recommended value is 0. When the value -1 or 1 is used it is essential to test the value of IFAIL on exit.

6 Error Indicators and Warnings

If on entry IFAIL = 0 or -1, explanatory error messages are output on the current error message unit (as defined by X04AAF).

Errors or warnings detected by the routine:

IFAIL = 1

The matrix A is singular, possibly due to rounding errors.

IFAIL = 2

```
\begin{array}{lll} \text{On entry,} & N < 0, \\ \text{or} & M < 0, \\ \text{or} & IA < \max(1, N), \\ \text{or} & IB < \max(1, N), \\ \text{or} & IC < \max(1, N). \end{array}
```

7 Accuracy

The accuracy of the computed solution depends on the conditioning of the original matrix. For a detailed error analysis see page 106 of Wilkinson and Reinsch (1971).

F04ADF.2 [NP3546/20A]

8 Further Comments

The time taken by the routine is approximately proportional to n^3 .

Unless otherwise stated in the Users' Note for your implementation, the routine may be called with the same actual array supplied for parameters B and C, in which case the solution vectors will overwrite the right-hand sides. However this is not standard Fortran 77, and may not work on all systems.

9 Example

To solve the set of linear equations AX = B where

$$A = \begin{pmatrix} 1 & 1+2i & 2+10i \\ 1+i & 3i & -5+14i \\ 1+i & 5i & -8+20i \end{pmatrix}$$

and

$$B = \begin{pmatrix} 1 \\ 0 \\ 0 \end{pmatrix}.$$

9.1 Program Text

Note: the listing of the example program presented below uses **bold italicised** terms to denote precision-dependent details. Please read the Users' Note for your implementation to check the interpretation of these terms. As explained in the Essential Introduction to this manual, the results produced may not be identical for all implementations.

```
FO4ADF Example Program Text
      Mark 15 Revised. NAG Copyright 1991.
      .. Parameters ..
                       NMAX, IA, IB, IC
      TNTEGER
      PARAMETER
                        (NMAX=4, IA=NMAX, IB=NMAX, IC=NMAX)
                       NIN, NOUT
      INTEGER
                       (NIN=5,NOUT=6)
      PARAMETER
      .. Local Scalars ..
      INTEGER
                       I, IFAIL, J, M, N
      .. Local Arrays ..
      complex
                       A(IA,NMAX), B(IB,1), C(IC,1)
      real
                       WKSPCE (NMAX)
      .. External Subroutines ..
      EXTERNAL
                       F04ADF
      .. Executable Statements ..
      WRITE (NOUT,*) 'F04ADF Example Program Results'
      Skip heading in data Ûle
      READ (NIN, *)
      READ (NIN,*) N
      WRITE (NOUT, *)
      M = 1
      IF (N.GE.O .AND. N.LE.NMAX) THEN
         READ (NIN,*) ((A(I,J),J=1,N),I=1,N), (B(I,1),I=1,N)
         IFAIL = 0
         CALL FO4ADF(A, IA, B, IB, N, M, C, IC, WKSPCE, IFAIL)
         WRITE (NOUT,*) ' Solution'
         WRITE (NOUT, 99998) (C(I,1), I=1, N)
      ELSE
        WRITE (NOUT, 99999) 'N is out of range: N = ', N
      END IF
      STOP
99999 FORMAT (1X,A,I5)
99998 FORMAT (1X,'(',F7.4,',',F7.4,') ',:)
      END
```

[NP3546/20A] F04ADF.3

9.2 Program Data

```
F04ADF Example Program Data
3
( 1.0, 0.0 ) ( 1.0, 2.0 ) ( 2.0,10.0 )
( 1.0, 1.0 ) ( 0.0, 3.0 ) (-5.0,14.0 )
( 1.0, 1.0 ) ( 0.0, 5.0 ) (-8.0,20.0 )
( 1.0, 0.0 ) ( 0.0, 0.0 ) ( 0.0, 0.0 )
```

9.3 Program Results

```
F04ADF Example Program Results

Solution
(10.0000, 1.0000)
( 9.0000, -3.0000)
( -2.0000, 2.0000)
```

F04ADF.4 (last) [NP3546/20A]