

JAEGER ELEKTRONIK

SEMICON 1997

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International
BUK 427-600A,B	Phi	MOS-N-FET-e	VFET, 600/30V, 45W, 80/275ns(2,8A) A: 4,3/17A, <1Ω(6,5A), B: 3,9/16A, <1,2Ω(6,5A)	16c	SOT-199		BUK 727-600, 2SK1463, 2SK1684, 2SK1859
BUK 428-500A,B	Phi	MOS-N-FET-e	VFET, 500/30V, 45W, 120/410ns(2,9A) A: 6,8/27A, <0,4Ω(8A), B: 6,1/24A, <0,5Ω(8A)	16c	SOT-199		2SK1206, 2SK1523, 2SK1696, 2SK1832
BUK 428-800A,B	Phi	MOS-N-FET-e	VFET, 800/30V, 45W, 160/450ns(2,6A) A: 3,4/14A, <1,5Ω(4A), B: 3/12A, <2Ω(4A)	16c	SOT-199		2SK809A, 2SK1463, 2SK1684, 2SK1859
BUK 428-1000A,B	Phi	MOS-N-FET-e	VFET, 1000/30V, 45W, 160/450ns(2,5A) A: 2,9/12A, <2Ω(3,5A), B: 2,6/10A, <2,6Ω(3,5A)	16c	SOT-199		BUK 426-1000, 2SK1770
BUK 436-50A,B	Phi	MOS-N-FET-e	=BUK 426-50A, B: A=50/200A, B=46/184A, 125W	18p	TO-3P		BUZ 346, 2SK1297, 2SK1379, 2SK1514
BUK 436-60A,B	Phi	MOS-N-FET-e	=BUK 426-60A, B: A=50/200A, B=46/184A, 125W	18p	TO-3P		2SK1297, 2SK1379, 2SK1514, 2SK2096
BUK 436-100A,B	Phi	MOS-N-FET-e	=BUK 426-100A, B: A=33/132A, B=31/124A, 125W	18p	TO-3P		BUZ 345, 2SK850, 2SK906, 2SK1429, ++

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International
KSV 3100 ACN-....	Sam	A/D-D/A-IC	8-Bit A/D- + 10-Bit D/A-Converter		40-DIP		
KSV 3110(CN-....)	Sam	A/D-D/A-IC	8 Bit A/D- + 10 Bit D/A-Conv., Video, TTL In/Out		40-DIP		
KSV 3208(CN)	Sam	A/D-IC	8 Bit, hi-speed, TV, Video, 20MSPS, TTL In/Out		28-DIP		
KSV 3310	Sam	D/A-IC	10 Bit, TV, Video, 20MHz		28-DIP		
KSV 3404	Sam						
KSY 13	Sie						

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International
KT							
KT 208(A...V)	GUS	Si-N-Darl+Di	TV-HA, 400/200V, 8/15A, 60W, sat<1,5V(5A)	17j	TO-220	BU 806	17j
KT 209(A...V)	GUS	Si-N-Darl+Di	=BU 806 Iso	17c			
KT 814 A,B,G,V	GUS	Si-N-Darl+Di	=BU 806 Iso, 30W	17c	TO-220Iso		
KT 815 A,B,G,V	GUS	Si-N-Darl+Di	=BU 806 330/150V	17j	TO-220	BU 806	17j
KT 816 A,B,G,V	GUS	Si-N-Darl+Di	=BU 807 Iso, 30W	17c	TO-220Iso		
KT 817 A,B,G,V	GUS	Si-N-Darl	=BU 808FI integr. Damper-Diode	18c	TO-3P Iso		
KT 818 A,B,G,V	GUS	Si-N-Darl	CTV-HA, 1400/700V, 5/10A, 50W, hFE>25 sat<1,6V(5A)	18c	TO-3P Iso		
KT 819 A,B,G,V	GUS	Si-N-Darl	3Ph.-Motor Drv, 1500/700V, 12/20A, 160W, sat<1V(9V)	23a	TO-3		
KT 3030	Sam	Si-N-Darl+Di	S P, 600/400V, 7/10A, 75W, <0,6μs, sat<3V(7A)	17j	TO-220	2SD798	17j
KT 3031	Sam	Si-N-Darl+Di	S P, 650/375V, 0,5/1A, 12,5W, hFE>325, <1/2,5μs	13h	TO-202		
KT 3032	Sam	Si-N-Darl+Di	S P, 800/375V, 6/8A, 125W, <1,3/2,2μs, sat<2,5V(4A)	18j	TO-3P	BU 826	18j
KT 3033	Sam	Si-N-Darl+Di	=BU 826 1000/400V	18j	TO-3P		
KT 3040 J	Sam	Si-N-Darl	Tripletion, 650/400V, 8A, 70W, hFE>7000, sat<4V(3A)	17j	TO-220		
KT 3054 J	Sam	Si-N	El. Zündung/Ignition, Z-Diode				
KT 3064 J	Sam	Si-N	S P, TV-SMPS	18j	TO-3P	BU 908	18j
KT 3107(A...V)	GUS	Si-N	=BU 902			BU 508 AF	16c
KT 3170 J,N	Sam	Si-N				BU 903	18j
KT 5116 J	Sam	Si-N				BU 508 AF	16c
KT 8518	Sam	Si-N				BU 908	18j
KT 8520	Sam	Si-N				BU 508 AF	16c
KT 8521	Sam	Si-N				BU 806	17j
KT 8554(J)	Sam	Si-N				2SD7982	17j
KT 8555(J)	Sam	Si-N				2SD7982	17j
KT 8557(J)	Sam	Si-N					
KT 8592(N)	Sam	Si-N					
KT 8593(N)	Sam	Si-N					
KTA 200	Kec						
KTA 473	Kec						
KTA 940	Kec						
KTA 950	Kec						
KTA 968(A)	Kec						
KTA 1001	Kec						
KTA 1015	Kec						
KTA 1021	Kec						
KTA 1023	Kec						
KTA 1024	Kec						
KTA 1070	Kec						
KTA 1270	Kec						
KTA 1271	Kec						
KTA 1272	Kec						
KTA 1273	Kec						
KTA 1274	Kec						
KTA 1275	Kec						

80.000 types

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International	
BUW 66	Sgs	Si-N-Darl+Di	S P, 400/200V, 10/15A, 90W, <800/2200ns	23a			BU 920...922, BUW 29, 2SD685, 2S1	
BUW 67	Sgs	Si-N-Darl+Di	=BUW 66: 330/200V	23a			BU 920...922, BUW 29, 2SD685, 2SD	
BUW 70	Sie	Si-N	S P, SMPS, 150/100V, 10A, 80W, 1/4µs	23a			BUW 24, BUW 86...87, BUX 17(A...C)	
BUW 71	Sie	Si-N	S P, SMPS, 450/400V, 5A, 100W, 1.5/5.3µs	23a			BUW 24...25, BUX 17C, 2SC3046, 2SC	
BUW 72	Sie	Si-N	S P, SMPS, 450/400V, 10A, 100W, 2/5.2µs	23a			BUW 24...25, BUX 17C, 2SC3046, 2SC	
BUW 73	Sie	Si-N	S P, SMPS, 300/200V, 20/25A, 120W, <1.5/2µs	23a			BUW 51...52, BUW 12, BUX 12, 2N6322	
BUW 74	Mot,Sie	Si-N	S P, 400/250V, 12/17A, 120W, 20MHz, <700/3700ns	23a			BUX 13, BUY 50, MJ 15024, 2SC3043	
BUW 75	Mot,Sie	Si-N	=BUW 74: 600/300V	23a			BUS 13(A), BUW 45...46, BUX 48, 2SC4	
BUW 76	Mot,Sie	Si-N	=BUW 74: 750/350V	23a			BUS 13(A), BUW 45...46, BUX 48, 2SC47	
BUW 77	Mot,Sie	Si-N	=BUW 74: 800/400V	23a			BUS 13(A), BUW 45...46, BUX 48, 2SC47	
BUW 81	Tix	Si-N-Darl	S P, SMPS, 600/600V, 10/16A, 80W, hFE>200, -1.7µs	23a			BUV 90, MJ 10013...10014, 2SD685	
BUW 81 A		Si-N-Darl	=BUW 81: 800/800V	23a			BU 16, BUT 51P	
BUW 84	Phi	Si-N	P, 800/400V, 2/3A, 50W(Tc=45°), 20MHz, <500/2400ns	-14j	SOT-82	(BUX 85) ⁶	(BUV 36(A), BUX 84...85, 2SC3531) ⁶	
BUW 85	Phi	Si-N	=BUW 84: 1000/450V	-14j	SOT-82	(BUX 85) ⁶	(BUV 36A, BUX 85, 2SC3531) ⁶	
BUW 86	Phi	Si-N	S P, 240/120V, 10/15A, 62.5W, 50MHz, 200/720ns	23a			BUX 17(A...C), BUW 24, BUW 72, BUW 74, +	
BUW 87	Phi	Si-N	=BUW 86: 300/150V, 250/850ns	23a			BUX 17A...C, BUW 24, BUW 72, BUW 74, ++	
BUW 87 A		Si-N	=BUW 86: 400/200V, 300/1150ns	23a			BUX 17B...C, BUW 24, BUW 72, BUW 74, ++	
BUW 89	Tho	Si-N	=BUW 39:	18j	TO-3P		BUW 49...50, BUX 69...70	
BUW 90	Tho	Si-N	=BUW 40:	18j	TO-3P		BUW 50...52, BUX 70	
BUW 91	Tho	Si-N	=BUW 41:	18j	TO-3P		BUW 51...52	
BUW 92	Tho	Si-N	=BUW 42:	18j	TO-3P		BUW 52	
BUW 92 I		Si-N	=BUW 92: Iso, 75W	18c	TO-3P Iso		2SC4297, 2SC4423	
BUW 96	Tho	Si-P	S P, 200/150V, 15A, 150W, <-1.5µs	18j	TO-3P		BUW 42(A)P	
BUW 131(H)	Phi	Si-N	S P, 850/450V, 5/10A, 80W, 350/1300ns	18j	TO-3P	BUW 11 A	18j	BUV 82...83, BUW 11(A), 2SC3535...36, ++
BUW 131 A		Si-N	BUW 131: hFE>5(5A), BU 131H: hFE>7(5A), 400/1600ns	18j	TO-3P	BUW 11 A	18j	BUV 83, BUW 11A, 2SC3535...36, 2SC4236, ++
BUW 132(H)	Phi	Si-N	=BUW 131: 1000/450V	18j	TO-3P	2SC3466	18j	BUV 47(A), BUW 12(A), 2SC3637, 2SC4237, ++
BUW 132 A		Si-N	S P, 850/450V, 8/16A, 125W, 350/1600ns	18j	TO-3P	2SC3466	18j	BUV 47A, BUW 12A, 2SC4237
BUW 133(H)	Phi	Si-N	BUW 132: hFE>5(8A), BU 132H: hFE>7(8A), 400/1600ns	18j	TO-3P	BUW 13 A	18j	BUV 48(A), BUW 13(A), 2SC3638, 2SC4706, ++
BUW 133 A		Si-N	=BUW 133: 1000/450V	18j	TO-3P	BUW 13 A	18j	BUV 48A, BUW 13A, 2SC3552, 2SC3644
BUX								
BUX 10	Mot,Sgs	Si-N	S P, 160/125V, 25/30A, 150W, >8MHz, <1.5/1.5µs	23a	TO-3		BUV 10...11, BUW 39, BUW 58, 2N6322, ++	
BUX 10 A	Rca	Si-N	=BUX 10: 170/125V, >50MHz	23a	TO-3		BUV 10...11, BUW 39, BUW 58, 2N6322, ++	
BUX 10 P	Sgs	Si-N	=BUX 10: 106W	18j	TO-3P		BUW 49...50, BUX 69...70	
BUX 11	Mot,Rca,Sgs	Si-N	S P, 250/200V, 20/25A, 150W, >8MHz, <1/2,2µs	23a	TO-3		BUV 11...12, BUW 58, BUW 73, 2N6322	
BUX 11 A	Rca	Si-N	=BUX 11: 200W	23a	TO-3		2N6322	
BUX 11 N		Si-N	=BUX 11: 220/160V	23a	TO-3		BUV 11...12, BUW 58, BUW 73, 2N6322	
BUX 12	Mot,Rca,Sgs	Si-N	S P, 300/250V, 20/25A, 150W, >8MHz, <1/2,5µs	23a	TO-3		BUV 12, BUW 73, 2N6322	
BUX 13	Mot,Rca,Sgs	Si-N	S P, 400/325V, 15/20A, 150W, >8MHz, <1.2/3,5µs	23a	TO-3		BUV 25, BUW 44, BUX 25, MJ 15024	
BUX 14	Mot,Rca,Sgs	Si-N	S P, 450/400V, 10/15A, 150W, >8MHz, <1.4/4,2µs	23a	TO-3		BUW 34, BUW 75...77, BUX 17C, 2SC3046, ++	
BUX 15	Mot,Rca,Sgs	Si-N	S P, 500/500V, 8/10A, 150W, >8MHz, <1.6/6,4µs	23a	TO-3		BUW 25, BUW 34, BUW 75...77, 2SC3046, ++	
BUX 16	Rca	Si-N	S P, 250/200V, 5A, 100W, >5MHz	23a	TO-3		BUW 71, BUX 44...45, 2SC3840, 2SC4799, ++	
BUX 16 A		Si-N	=BUX 16: 325/250V	23a	TO-3		BUW 71, BUX 44...45, 2SC3040, 2SC3083, ++	
BUX 16 B		Si-N	=BUX 16: 375/300V	23a	TO-3		BUW 71, BUX 44...45, 2SC3040, 2SC3083, ++	
BUX 16 C		Si-N	=BUX 16: 425/350V	23a	TO-3		BUW 71, BUX 44...45, 2SC3040, 2SC3083, ++	
BUX 17	Rca	Si-N	S P, 250/150V, 10/30A, 150W, >2.5MHz, <2/4,5µs	23a	TO-3		BUW 87(A), BUW 24, BUW 74, BUX 14, ++	
BUX 17 A		Si-N	=BUX 17: 350/250V	23a	TO-3		BUW 87A, BUW 24, BUW 74, BUX 14, ++	
BUX 17 B		Si-N	=BUX 17: 400/300V	23a	TO-3		BUW 87A, BUW 24, BUW 74, BUX 14, ++	
BUX 17 C		Si-N	=BUX 17: 450/350V	23a	TO-3		BUW 34, BUW 44, BUW 75, BUX 14, ++	
BUX 18	Rca	Si-N	S P, 250/200V, 8/12A, 120W, <-2,6µs	23a	TO-3		BUW 87(A), BUW 24, BUW 72, BUX 14, ++	
BUX 18 A		Si-N	=BUX 18: 350/325V	23a	TO-3		BUW 87A, BUW 24, BUW 72, BUX 14, ++	
BUX 18 B		Si-N	=BUX 18: 400/375V	23a	TO-3		BUW 87A, BUW 24, BUW 72, BUX 14, ++	
BUX 18 C		Si-N	=BUX 18: 475/425V	23a	TO-3		BUW 25, BUW 34, BUW 72, BUX 14, ++	
X 20	Sgs	Si-N	S P, 160/125V, 50/80A, 350W, >8MHz, <1.5/1.5µs	23a	TO-3		BUR 50...52	
20 A		Si-N	=BUX 20: 40/50A, 140W, >50MHz, <0.7/1.7µs	23a	TO-3		BUR 21...22, BUW 21...22, BUW 60...62	
Bt21	Rca,Sgs	Si-N	S P, 250/200V, 40/50A, 350W, >8MHz, <1.2/2,2µs	23a	TO-3		BUR 51...52, 2N6323	
Bu22	Sgs	Si-N	S P, 300/250V, 40/50A, 350W, >10MHz, <1.3/2,5µs	23a	TO-3		BUR 51...52, 2N6323	
BUX3	Sgs	Si-N	S P, 400/325V, 30/40A, 350W, >8MHz, <1.3/3,7µs	23a	TO-3		2N6323	
BUX4	Sgs	Si-N	S P, 450/400V, 20A, 350W, >8MHz, <1.6/4,4µs	23a	TO-3		-	
BUX5	Sgs	Si-N	S P, 500/500V, 15/20A, 350W, >8MHz	23a	TO-3		-	
BUX 26	Sie	Si-N	S P, 750/350V, 6/10A, 60W(Tc=75°), 20MHz, tf<0.7ns	23a	TO-3		BUS 12(A), BUW 35...36, BUX 47, 2SC3092, ++	
BUX 27	Sie	Si-N	=BUX 26: 800/400V, tf<1µs	23a	TO-3		BUS 12(A), BUW 35...36, BUX 47, 2SC3092, ++	
BUX 28	Sie	Si-N-Darl	S P, 350/350V, 8/12A, 80W(Tc=55°), hFE>50, <-10µs	23a	TO-3		BUV 90, BUW 29, BUW 81(A), 2SD685, ++	
BUX 28 V		Si-N-Darl	=BUX 28: -400V	23a	TO-3		BUV 90, BUW 29, BUW 81(A), 2SD685, ++	
BUX 29	Sie	Si-N-Darl	=BUX 28: 400/400V, hFE>30	23a	TO-3		BU 920...922, BUW 90, BUW 66, BUW 81(A)	
BUX 30	Aeg	Si-N-Darl+Di	S P, -400V, 10/15A, 90W, hFE>150	23a	TO-3		BU 920...922, BUW 90, BUW 66, BUW 81(A)	
BUX 30 AV		Si-N-Darl+Di	=BUX 30: -350V, hFE>250	23a	TO-3		BU 920...922, BUW 90, BUW 66, BUW 81(A)	
BUX 30 AVA		Si-N-Darl+Di	=BUX 30: -250V, hFE>250	23a	TO-3		BU 920...922, BUW 90, BUW 66, BUW 81(A)	
BUX 30 AVB		Si-N-Darl+Di	=BUX 30: -300V, hFE>250	23a	TO-3		BU 920...922, BUW 90, BUW 66, BUW 81(A)	
BUX 30 AVC		Si-N-Darl+Di	=BUX 30: -350V, hFE>250	23a	TO-3		BU 920...922, BUW 90, BUW 66, BUW 81(A)	
BUX 31	Fer,Rca	Si-N	S P, 800/400V, 8/10A, 150W, >15MHz, <550/3400ns	23a	TO-3		BUS 12(A), BUW 35...36, MJ 8504, 2SC3061	
BUX 31 A		Si-N	=BUX 31: 900/450V	23a	TO-3		BUS 12A, BUW 36, MJ 8504, 2SC3061	
BUX 31 B		Si-N	=BUX 31: 1000/500V	23a	TO-3		BUS 12A, MJ 8504, 2SC3061, 2SC3215	
BUX 32	Fer,Rca	Si-N	S P, 800/400V, 8/10A, 150W, >15MHz, <550/3400ns	23a	TO-3		BUS 12(A), BUW 35...36, MJ 8504, 2SC3061	
BUX 32 A		Si-N	=BUX 32: 900/450V	23a	TO-3		BUS 12A, BUW 36, MJ 8504, 2SC3061	
BUX 32 B		Si-N	=BUX 32: 1000/500V	23a	TO-3		BUS 12A, MJ 8504, 2SC3061, 2SC3215	
BUX 33	Rca	Si-N	S P, 800/400V, 12/15A, 150W, >15MHz, <550/3400ns	23a	TO-3		BUS 13(A), BUW 45...46, BUX 48, 2SC3593	
BUX 33 A		Si-N	=BUX 33: 900/450V	23a	TO-3		BUS 13A, BUW 46, 2SC3593, 2SC3216	
BUX 33 B		Si-N	=BUX 33: 1000/500V	23a	TO-3		BUS 13A, 2SC3216	
BUX 34	Fer	Si-N	S P, 120/60V, 5A, 20W(Tc=25°) >70MHz, <600/1200ns	2a	TO-39		BU 125, BUY 47...48, BUY 68, BUY 80	
BUX 35	Sgs	Si-N	S P, 250/160V, 15A, 140W, >3MHz	23a	TO-3		BUV 11...12, BUW 73, BUX 11...12, BUX 41	
BUX 36	Sgs	Si-N	=BUX 35: 250/200V	23a	TO-3		BUV 11...12, BUW 73, BUX 11...12, BUX 41	
BUX 37	Aeg,Rca,Tho	Si-N-Darl+Di	S P, -400V, 15/20A, 50W(Tc=100°), hFE>100	23a	TO-3		BU 930...932, BUT 51P, 2SD1314, 2SD1466	
BUX 38	Tho	Si-N	S P, 500/400V, 40A, 250W, <2.5/µs	68a			2SC2366, 2SD642	
BUX 39	Mot,Phi,++	Si-N	S P, 120/90V, 30/40A, 120W, >8MHz, <1.5/1,3µs	23a	TO-3		BUV 21...22, BUW 39, BUX 21...22, 2N6322	
BUX 40(A)	Mot,Phi,++	Si-N	S P, 160/125V, 20/28A, 120W, >8MHz, <1.2/1,4µs	23a	TO-3		BUV 10...12, BUW 58, BUX 10...12, 2N6322, ++	
BUX 41	Mot,Phi,++	Si-N	S P, 250/200V, 15/20A, 120W, >8MHz, <1/2,5µs	23a	TO-3		BUV 11...12, BUW 58, BUW 73, BUX 11...12, ++	
BUX 41 N		Si-N	=BUX 41: 220/160V, 18/25A, <1.3/2,3µs	23a	TO-3		BUV 11...12, BUW 58, BUW 73, BUX 11...12, ++	
BUX 42	Mot,Rca,Sgs	Si-N	S P, 300/250V, 12/15A, 120W, >8MHz, <1/3,2µs	23a	TO-3		BUW 44, BUW 74...77, BUX 13, BUY 50, ++	
BUX 43	Mot,Rca,Sgs	Si-N	S P, 400/325V, 10/12A, 120W, >8MHz, <1/3,4µs	23a	TO-3		BUW 24...25, BUW 34, BUX 14, BUX 17C, ++	

JAEGER	Constr.	Info	Fig.	Compl.	
AA 119	Ge-Di	Dem, hi-ohm, 45V, 35mA	31a	DO-7	
AA 133	Ge-Di	Uni, 140V, 50mA	31a	DO-7	
AA 138	Ge-Di	TV-Dem, 25V, 20mA	31a	DO-7	
AC 151	Ge-P	LF Inp,Drv, (In), 32V, 0,2A	2a	TO-1	
AC 187 K	Ge-N	LF Drv,Out, 25V, 1A, 1W	3a	TO-1*	AC 188 K
AC 188 K	Ge-P	LF Drv,Out, 25V, 1A, 1W	3a	TO-1*	AC 187 K
AD 161	Ge-N	LF P, 32V, 1A, 4W(Tc=70°)	22a	SOT-9	AD 162
AD 162	Ge-P	LF P, 32V, 1A, 6W(Tc=63°)	22a	SOT-9	AD 161
AF 239 S	Ge-P	UHF Inp,Mx,Os, 700MHz	5g	TO-72	
AL 102	Ge-P	LF P, 130V, 6A, 30W	23a	TO-3	
AN 214(Q)*	LIN-IC	Audio Out, 18V, 1,2A, 4,4W(13V/4Ω)	9-SILP		
AN 217 P***	LIN-IC	AM Inp,Mx,Os, AM/FM IF	16-DIP		
AN 236***	LIN-IC	CTV, Hilfsträger/Sub-carrier	16-DIP		
AN 241 P***	LIN-IC	TV, Sound IF, Ucc=24V	14-DIP		
AN 246***	LIN-IC	TV, Signal IC	16-DIP		
AN 253(P)***	LIN-IC	AM/FM IF, LF Inp	16-DIP		
AN 260(P)***	LIN-IC	AM Mx,Os, AM/FM IF	14-DIP		
AN 303***	LIN-IC	VC Luminance, Noise Suppr.	18-DILP		
AN 304***	LIN-IC	VC, FM Limiter	14-DIP		
AN 316***	LIN-IC	VC, Drop-out Compensation	16-DIP		
AN 321***	LIN-IC	TV, AFT	9-SIP		
AN 340 P***	LIN-IC	TV, Sound IF, Demodulator	14-DIP		
AN 362***	LIN-IC	Stereo Decoder (Lämpchenanz./Lamp Driver), ...100mA	16-DIP		
AN 363 N***	LIN-IC	Stereo Decoder	16-DIP		
AN 370***	LIN-IC	LF Inp In, Ucc=35V	7-SIP		
AN 374***	LIN-IC	Audio Out, 16V, 1A, 1W(9V/8Ω)	TO-100		
AN 377***	LIN-IC	FM IF	16-DIP		
AN 608 P***	LIN-IC	TV, Video, Wide Band Amp.	4-SIP		
AN 610(P)***	LIN-IC	Modulator	14-DIP		
AN 5020***	LIN-IC	FB Empf.-Vorverst./Receiver Preamp.	9-SIP		
AN 5111***	LIN-IC	TV, Video IF, AFC, AGC	28-DIP		
AN 5265	LIN-IC	TV, Audio Out, DC Volume Ctrl., 2,3W(12V/16V)	9-SIL		
AN 5411***	LIN-IC	=AN 5410: X-Ray Protect (Pin 9)	24-DIP		
AN 5510***	LIN-IC	TV, VA Out	11-SILP		
AN 5512	LIN-IC	TV, VA Out	9-SIL		
AN 5515	LIN-IC	TV, VA Out	7-SIL		
AN 5521	LIN-IC	TV, VA Out	7-SIL		
AN 5601 K	LIN-IC	CTV, Chroma RGB & Sync. Processor (PAL/NTSC/SECAM)	42-SDIP		
AN 5610 N***	LIN-IC	CTV, PAL/SECAM Video & Chroma	16-DIP+g		
AN 5612	LIN-IC	CTV, PAL/SECAM Chroma	18-DIP		
AN 5620 X	LIN-IC	CTV, Chroma Signal Processor (PAL)	16-DIP+g		
AN 5700***	LIN-IC	TV, Tuner Bandumschaltung/Band Switch	9-SIP		
AN 5703***	LIN-IC	TV, Tuner Bandumschaltung/Band Switch	9-SIP		
AN 5730***	LIN-IC	TV, Sound IF, Ucc=5,5V	7-SIP		
AN 5732***	LIN-IC	TV, Sound IF, Ucc=12V	7-SIP		
AN 6136	LIN-IC	HiFi Pop-Noise Suppression	9-SIP		
AN 6250***	LIN-IC	Recorder, Autoreverse Control	7-SIP		
AN 6300***	LIN-IC	VC, Video Signal	24-DIP		
AN 6330***	LIN-IC	VC, Kopf-Verst./Head Amplifier	14-DIP		
AN 6332***	LIN-IC	VC, Video-Playback	28-DIP+g		
AN 6342(N)***	LIN-IC	VC, Frequenzteiler/Prescaler	7-SIP		
AN 6344***	LIN-IC	VC, Servo	28-DIP		
AN 6352***	LIN-IC	VC, Pitch-Control	12-SIP		
AN 6353***	LIN-IC	VC, Pitch-Control	12-SIP		
AN 6360	LIN-IC	VC, Color Signal	18-DIP		
AN 6551***	OP-IC	Dual, LF Equal., ±18V, -20...+75°	9-SIP		
AN 7116*	LIN-IC	Audio Out, 9V, 2A, 0,77W(6V/4Ω)	9-SIP		
AN 7140*	LIN-IC	Audio Out, 24V, 4A, 5W(13V/4Ω)	9-SIL		
AN 7145 M	LIN-IC	2x Audio Out, 24V, 4A, 2x4,5W(16V/8Ω)	18-DILP		
AN 7156(N)*	LIN-IC	2x Audio Out, 24V, 4A, 2x5,5W(13V/4Ω)	12-SILP		
AN 7158(N)***	LIN-IC	2x Audio Out, 24V, 4A, 2x7,5W(16V/4Ω)	12-SILP		
AN 7160***	LIN-IC	Audio Out, 24V, 4A, 17W(13V/4Ω)	12-SILP		
AN 7161 N	LIN-IC	2x Audio Out, 26V, 4A, 23W(15V/4Ω), BTL	12-SILP		
AN 7171 K	LIN-IC	2x Audio Out, 24V, 6A, 2x>9W(13V/4Ω), ON=+5V	16-SQL		
AN 7178	LIN-IC	2x Audio Out, 18V, 4A, 2x5,7W(12V/3Ω)	12-SIP		
AN 7222(N)	LIN-IC	AM/FM IF, AFC, AGC, Demodulator	18-DIP		
AN 7311***	LIN-IC	Auto-/Car Radio, 2x Audio Inp, 18V	9-SIP		
APU 2471	NMOS-IC	CTV, Audio Processor	24-DIP		
BA 159	Si-Di	S, TV Clamping, 1000V, 0,4/2A, Uf<1,5V(1A), <300ns	31a	DO-7	
BA 222***	LIN-IC	CR Timer, Ucc=4,5...16V, 0,2A, -20...+75°	7-SIP		
BA 401***	LIN-IC	TV, Sound IF, FM IF, Ucc=12V	5-SIP		
BA 402***	LIN-IC	TV, Sound IF, FM IF	7-SIP		
BA 514***	LIN-IC	Audio Inp+Out, 2W(9V/4Ω)	8-SIL		
BA 532	LIN-IC	Audio Out, 5,8W(13V/4Ω)	10-SIL		
BA 1310*	LIN-IC	FM Multiplex Stereo-Decoder	14-DIP		

JAEGER	Constr.	Info	Fig.	Compl.
BA 1320*	LIN-IC	FM Multiplex Stereo-Decoder, Ucc=12(5,4...14)V	16-DIP	
BA 1330*	LIN-IC	=BA 1320: Ucc=3,6...6V	16-DIP	
BA 5102 A	LIN-IC	VC, Audio Rec/Play Amp., Logic, 9 & 12V	18-DIP	
BA 5410	LIN-IC	2x Audio Out, 20V, 2x5,2W(12V/3Ω)	10-SIL	
BA 6109	LIN-IC	VC, Motor Drv (reversible), Ucc=6...18V, 0,8A	10-SIL	
BA 6209	LIN-IC	VC, Motor Drv (reversible), 6...18V, 1,6A	10-SIL	
BA 6222	LIN-IC	VC, Motor Drv (reversible), Ucc=8...18V, 2,2A	10-SIL	
BA 6247	LIN-IC	2x Motor Drv (reversible), Ucc=8...18V, 1A, 2W	10-SIL	
BA 7004***	LIN-IC	VC, Test Pattern Signal Generator	5-SIP	
BAT 42	Si-Di	Schottky, 30V, 0,2A, Uf<0,65V(50mA), <5ns	31a	DO-35
BC 141	Si-N	LF Drv,Out, 100/60V, 1A, 0,75W, >50MHz, <250/850ns	2a	TO-39
BC 161	Si-P	LF Drv,Out, 60/40V, 1A, 0,75W, >50MHz, <500/650ns	2a	TO-39
BC 327	Si-P	LF Drv, 50/45V, 0,8/1A, 0,625W, 100MHz	7a	TO-92
BC 337	Si-N	LF Drv, 50/45V, 0,8/1A, 0,625W, 100MHz	7a	TO-92
BC 546	Si-N	Uni, 80/65V, 0,1/0,2A, 0,5W, 300MHz	7a	TO-92
BC 550	Si-N	=BC 547: In, F<4dB(1kHz)	7a	TO-92
BC 556	Si-P	Uni, 80/65V, 0,1/0,2A, 0,5W, 150MHz	7a	TO-92
BC 560	Si-P	=BC 557: In, F<4dB(1kHz)	7a	TO-92
BC 639	Si-N	LF Drv,Out, 100/80V, 1/1,5A, 0,8W, 130MHz	7c	TO-92
BC 640	Si-P	LF Drv,Out, 100/80V, 1/1,5A, 0,8W, 50MHz	7c	TO-92
BC 807(SMD)	Si-P	=BC 327: SMD	35a	SOT-23
BC 817(SMD)	Si-N	=BC 337: SMD	35a	SOT-23
BC 846(SMD)	Si-N	=BC 546: SMD	35a	SOT-23
BC 850(SMD)	Si-N	=BC 550: SMD	35a	SOT-23
BC 856(SMD)	Si-P	=BC 556: SMD	35a	SOT-23
BC 860(SMD)	Si-P	=BC 560: SMD	35a	SOT-23
BC 879	Si-N-Darl+Di	L.F.S., 100/80V, 1/2A, 0,8W, 200MHz, hFE>2000	7c	TO-92
BC 880	Si-P-Darl+Di	L.F.S., 100/80V, 1/2A, 0,8W, 200MHz, hFE>2000	7c	TO-92
BD 139	Si-N	P, 100/80V, 1,5/2A, 12,5W(Tc=45°), >50MHz	14h	TO-126
BD 140	Si-P	P, 100/80V, 1,5/2A, 12,5W(Tc=45°), >50MHz	14h	TO-126
BD 189	Si-N	LF P, 70/60V, 4/8A, 40W, >2MHz	14h	TO-126
BD 190	Si-P	LF P, 70/60V, 4/8A, 40W, >2MHz	14h	TO-126
BD 237	Si-N	LF P, 100/80V, 2/6A, 25W, >3MHz, 300/1100ns	14h	TO-126
BD 238	Si-P	LF P, 100/80V, 2/6A, 25W, >3MHz, 300/1100ns	14h	TO-126
BD 243 C	Si-N	LF P, 115/100V, 6/10A, 65W, >3MHz, 300/1000ns	17j	TO-220
BD 244 C	Si-P	LF P, 115/100V, 6/10A, 65W, >3MHz, 200/800ns	17j	TO-220
BD 245 C	Si-N	LF P, 115/100V, 10/15A, 80W, >3MHz, 300/1000ns	18j	TO-3P
BD 246 C	Si-P	LF P, 115/100V, 10/15A, 80W, >3MHz, 200/800ns	18j	TO-3P
BD 249 C	Si-N	LF P, 115/100V, 25/40W, 125W, >3MHz, 300/700ns	18j	TO-3P
BD 250 C	Si-P	LF P, 115/100V, 25/40A, 125W, >3MHz, 200/400ns	18j	TO-3P
BD 317	Si-N	LF P, 100/100V, 16/20A, 200W, >1Hz	23a	TO-3
BD 318	Si-P	LF P, 100/100V, 16/20A, >1MHz	23a	TO-3
BD 679	Si-N-Darl+Di	LF P, 80/80V, 4/7A, 40W, >10MHz, hFE>750	14h	TO-126
BD 680	Si-P-Darl+Di	LF P, 80/80V, 4/7A, 40W, >10MHz, hFE>750	14h	TO-126
BD 683	Si-N-Darl+Di	=BD 679: 140/120V	14h	TO-126
BD 684	Si-P-Darl+Di	=BD 680: 120/120V	14h	TO-126
BD 809	Si-N	LF P, 80/80V, 10A, 90W, >1,5MHz	17j	TO-220
BD 810	Si-P	LF P, 80/80V, 10A, 90W, >1,5MHz	17j	TO-220
BD 901	Si-N-Darl+Di	LF P, 100/100V, 8A, 70W, >1MHz, hFE>750	17j	TO-220
BD 902	Si-P-Darl+Di	LF P, 100/100V, 8A, 70W, >1MHz, hFE>750	17j	TO-220
BDW 83 C	Si-N-Darl+Di	LF P, 100/100V, 15/40A, 150W, >1MHz, hFE>750	18j	TO-3P
BDW 84 C	Si-P-Darl+Di	LF P, 100/100V, 15/40A, 150W, >1MHz, hFE>750	18j	TO-3P
BDW 93 C	Si-N-Darl+Di	LF P, 100/100V, 12/15A, 80W, >20MHz, hFE>750	17j	TO-220
BDW 94 C	Si-P-Darl+Di	LF P, 100/100V, 12/15A, 80W, >20MHz, hFE>750	17j	TO-220
BF 198	Si-N	TV IF, agc, 40/30V, 400MHz, Gp=42dB(35MHz)	7d	TO-92
BF 199	Si-N	TV IF, 40/25V, 550MHz, Gp=43dB(35MHz)	7d	TO-92
BF 245 B	N-FET	LF,HF...VHF, 30V, Idss=6...15mA, Up=1,6...3,8V,700MHz	7f	SOT-30
BF 255	Si-N	FM Inp,Mx,Os, 30/20V, 200MHz, F=4dB(100MHz)	7d	TO-92
BF 259	Si-N	Vid, 300/300V, 0,1/0,2A, 0,8W, 90MHz	2a	TO-39
BF 324	Si-P	FM/VHF Inp, 30/30V, 450MHz, F=3dB(100MHz)	7a	TO-92
BF 420 A	Si-N	Vid, 300V, 0,5A, 0,8W, >60MHz	7c	TO-92
BF 421 A	Si-P	Vid, 300V, 0,5A, 0,8W, >60MHz	7c	TO-92
BF 459	Si-N	Vid P, 300/300V, 0,1/0,3A, 10W(Tc45°), 90MHz	14h	TO-126
BF 471(S)	Si-N	Vid P, 300V, 0,03A, 2W(Tc=110°), >60MHz	14h	TO-126
BF 472(S)	Si-P	Vid P, 300V, 0,03A, 2W(Tc=110°), >60MHz	14h	TO-126
BF 487	Si-N	Vid, 400/350V, 0,05/0,1A, 0,83W, >70MHz	7c	TO-92
BF 759	Si-N	Vid P, 350/350V, 0,5/0,7A, 10W, >45MHz	13h	TO-202
BF 762	Si-P	Vid P, 350/350V, 0,5/0,7A, 10W, >20MHz	13h	TO-202
BF 959	Si-N	VHF,TV IF(OFW/SAW-Filter), 30/20V, -/0,1A, 1100MHz	7d	TO-92
BF 960(S)	MOS-N-FET-d*	Dual-Gate, UHF, 20V, 30mA, Idss=2...20mA, Up<2,7V	25g	SOT-103
BF 979(S)	Si-P	UHF Inp, 20/20V, 30mA, 1350MHz, F<6dB(800MHz)	24e	SOT-37
BR 100(/03)	Diac	Ub=28...36V, Ib<0,1mA, Itsm=2A, BR100/03: DO-35	31a	DO-14
BRX 49	F-Thy	400V, 0,8A=, Igt/Ih<0,2/5mA, 8µs	7a	TO-92
BU 208 A	Si-N	CTV-HA, 1500/700V, 5/7,5A, 12,5W(Tc=95°), sat<5V	23a	TO-3
BU 208 D	Si-N+Di	=BU 208: + integr. Damper-Diode	23a	TO-3

JAEGER	Constr.	Info	Fig.	Compl.
BU 209*	Si-N	=BU 207: 1700/800V, 4A, sat<5V(3A)	23a	TO-3
BU 406	Si-N	TV-HA, 400/200V, 7/10A, 60W, <-/750ns, sat<1V(5A)	17j	TO-220
BU 406 D	Si-N+Di	=BU 406: + integr. Damper-Diode	17j	TO-220
BU 415 B	Si-N+Di	S P, TV-HA, 900/400V, 12A, 120W, sat<3V(8A)	23a	TO-3
BU 426 A	Si-N	TV-SMPS, 900/400V, 6/8A, 70W(Tc=73°), <600/4250ns	18j	TO-3P
BU 508 A	Si-N	CTV-HA, 1500/700V, 8/15A, 125W, sat<5V(4,5A)	18j	TO-3P
BU 508 AF	Si-N	=BU 508A: Iso, 34W	16c	SOT-199
BU 508 AT	Si-N	=BU 508A: 75W	17j	TO-220
BU 508 D	Si-N+Di	=BU 508A: + integr. Damper-Diode	18j	TO-3P
BU 508 DF	Si-N+Di	=BU 508D: Iso, 34W	16c	SOT-199
BU 508 DR	Si-N+Di	=BU 508D: + Rbe=25Ω	18j	TO-3P
BU 508 V	Si-N	=BU 508A		
BU 606 D	Si-N+Di	TV-HA, 400/200V, 7/10A, 90W, <-/750ns, sat<1V(5A)	23a	TO-3
BU 608	Si-N	=BU 606: <-/400ns, sat<1V(6A)	23a	TO-3
BU 705*	Si-N	TV-HA, 1500/700V, 2,5/4A, 75W, sat<1V(2A)	18j	TO-3P
BU 801	Si-N-Darl+Di	S P, 600/400V, 3A, 40W, hFE>100, <0,8/1,5μs	14h	TO-126
BU 806	Si-N-Darl+Di	TV-HA, 400/200V, 8/15A, 60W, sat<1,5V(5A)	17j	TO-220
BU 826	Si-N-Darl+Di	S P, 800/375V, 6/8A, 125W, <1,3/2,2μs, sat<2,5V(4A)	18j	TO-3P
BU 903	Si-N	S P, TV-SMPS, 1350/550V, 6/8A, 125W, sat<2V(3,2A)	18j	TO-3P
BU 908	Si-N	TV-HA/SMPS, 1500/700V, 8/15A, 125W, sat<2V(3,2A)	18j	TO-3P
BU 2508 A	Si-N	CTV-HA, 1500/700V, 8/15A, 125W, sat<5V(4,5A)	18j	TO-3P
BU 2508 AF	Si-N	=BU 2508A: Iso, 45W	16c	SOT-199
BUF 405 A	Si-N	S P, 1000/450V, 7,5/15A, 80W, sat<2V(5A)	17j	TO-220
BUH 517	Si-N	CRT-HA, hi-res, 1700/700V, 8/15A, 60W, sat<1,5V(5A)	18c	TO-3P Iso
BUK 444-800(A,B)	MOS-N-FET-e	VFET, 800/30V, 1,2...1,4A, 25W, <6...8Ω(1A), 40/80ns	17c	SOT-186
BUK 455-600(A,B)	MOS-N-FET-e	VFET, 600/30V, 4...4,5A, 100W, <2...2,5Ω(2,5A)	17p	TO-220
BUT 11 A	Si-N	S P, 1000/450V, 5/10A, 100W, <1/4,8μs	17j	TO-220
BUT 11 AF	Si-N	=BUT 11A: Iso, 20W	17c	SOT-186
BUT 12 A	Si-N	S P, 1000/450V, 8/20A, 125W, <1/4,8μs	17j	TO-220
BUT 12 AF	Si-N	=BUT 12A: Iso, 23W	17c	SOT-186
BUT 18 AF	Si-N	S P, Iso, 1000/450V, 6/12A, 33W, <1/4,8μs	17c	SOT-186
BUT 56 A	Si-N	S P, SMPS: 1000/450V, 8/10A, 100W, 10MHz, -/4μs	17j	TO-220
BUT 76 A	Si-N	S P, SMPS, 1000/450V, 10/20A, 100W, <1/3,8μs	17j	TO-220
BUV 70	Si-N	S P, 1300/550V, 10/15A, 140W, 9MHz, <0,5/4,6μs	18j	TO-3P
BUW 11 A	Si-N	S P, 1000/450V, 5/10A, 100W, <1/4,8μs	18j	TO-3P
BUW 13 A	Si-N	S P, 1000/450V, 15/30A, 175W, <1/4,8μs	18j	TO-3P
BUX 85	Si-N	P,1000/450V, 2/3A, 40W(Tc=50°), 20MHz, <500/3900ns	17j	TO-220
BY 133	Si-Di	Rr, 1300V, 1A, Uf<1,3V(2A)	31a	DO-27
BY 203/20	Si-Di	TV Rr, 2000V, 0,25A, Uf<2,4V(0,2A), <300ns	31a	DO-15
BY 228	Si-Di	TV Damper-Diode, 1500V, 3/10A, Uf<1,5V(5A)	31a	SOD-64
BY 255	Si-Di	Rr, 1300V, 3/20A, Uf<1,1V(3A)	31a	DO-27A
BY 329/1200	Si-Di	TV Damper-Di, 1000/1200V, 7/80A, Uf<1,85V, <150ns	17k	TO-220
BY 359/1500	Si-Di	TV FRr, 1300/1500V, 6,5/60A, <600ns	17k	TO-220
BY 500/800	Si-Di	TV Rr, 800V, 5A, Uf<1,35V(5A), <200ns	31a	DO-27A
BY 527	Si-Di	Rr, contr.av., 800/1250V, 0,8/12A, Uf<1V(1A), 2,5μs	31a	SOD-57
BY 713	Si-Di	TV kV-Rr, 20/24kV, 3mA, Uf<76V(0,05A), 200ns	31a(12mm)	=SOD-61
BYD 33 M	Si-Di	S, contr.av., 1000V, 1,3/12A, Uf<1,3V(1A), <300ns	31a	SOD-81
BYS 27-45	Si-Di	Schottky, 45V, 5A, Uf<0,55V(5A)	31a	(7,5x40)
BYV 27/200	Si-Di	FRr, contr.av., 200V, 2/15A, Uf<1,07V(3A), <50ns	31a	SOD-57
BYV 28/200	Si-Di	FRr, contr.av., 200V, 3,5/25A, Uf<1,1V(5A), <50ns	31a	SOD-64
BYW 95 C	Si-Di	FRr, contr.av., 600V, 3/15A, Uf<1,5V(5A), <250ns	31a	SOD-64
BYW 96 E	Si-Di	=BYW 95: 1000V, <300ns	31a	SOD-64
CNX 62 A	Opto	Optokoppler/Optocoupler, Riso>10GΩ	6-DIP	
CNX 83 A	Opto	Optokoppler/Optocoupler, Base Connect. (Pin6)	6-DIP	
DPU 2553	NMOS-IC	CTV, Ablenk-/Deflection Processor, normal-scan	40-DIP	
DTI 2223	NMOS-IC	CTV, digital Color Processor	40-DIP	
ESM 740*	Thy	asym. -5...300V, 10A, Igt<50mA, <15μs	30b	(TO-220MF)
HA 1197***	LIN-IC	AM Tuner, IF	16-DIP	
HA 1199***	LIN-IC	AM Tuner	16-DIP	
HA 1211***	LIN-IC	FM IF	8-SIP	
HA 1368*	LIN-IC	Audio Out, 18V, 4,5A, 5,3W(13V/4Ω)	10-SILP+a	
HA 1377	LIN-IC	Dual Audio Out, 18V, 4,5A, 2x5,8W(13V/4Ω)	12-SIL	
HA 1388	LIN-IC	Audio Out, 18V, 4A, 18W(13,2V/4Ω)	12-SIL	
HA 1392	LIN-IC	Dual Audio Out, 20V, 4A, 2x4,3W(12V/4Ω)	12-SIL	
HA 1394	LIN-IC	Dual Audio Out, 35V, 4,5A, 2x8,2W(25V/8Ω)	12-SIL	
HA 1396***	LIN-IC	Audio Out, 18V, 4A, 20W(13V/4Ω)	12-SIL	
HA 1398	LIN-IC	Audio Out	12-SIL	
HA 1406***	LIN-IC	Audio Inp	8-SIP	
HA 11215(A)***	LIN-IC	CTV, IF, Video Signal, AGC	24-DIP	
HA 11225	LIN-IC	FM IF	16-DIP	
HA 11229***	LIN-IC	TV, Sound IF	14-DIP	
HA 11244***	LIN-IC	TV, Sync. Signal	16-DIP	
HA 11401***	LIN-IC	TV, Video Signal	16-DIP	
HA 11423	LIN-IC	TV, Sync., VA Os, Blanking	16/20-DIP	
HA 11702***	LIN-IC	VC, Kopfvorverst./Head Preamp.	16/20-DIP	

JAEGER	Constr.	Info	Fig.	Compl.
HA 11706***	LIN-IC	VC, Color APC	16/20-DIP	
HA 11710***	LIN-IC	VC, Chroma	16/20-DIP	
HA 11716***	LIN-IC	VC, Luminance Signal	20-DIP	
HA 11717***	LIN-IC	VC, Color AFC	16/20-DIP	
HA 11718***	LIN-IC	VC, Luminance Signal	16-DIP	
HA 13001	LIN-IC	Dual LF Out, 18V, 4,5A, 2x5,5W(13V/4Ω), 17,5W(BTL)	12-SIL	
HA 13118	LIN-IC	Audio Out, 26V, 4A, 18W(13,2V/4Ω, BTL)	15-SQL	
HA 13119	LIN-IC	Dual, Audio Out, 18V, 4A, 2x5,5W(13,2V/4Ω)	15-SQL	
IRFBC 40	MOS-N-FET-e	VFET, 600/20V, 6,2/22A, 125W, <1,2Ω(3,7A), 31/75ns	17p	TO-220
IRFPC 50	MOS-N-FET-e	VFET, 600/20V, 11/44A, 180W, <0,6Ω(6A), 55/124ns	16p	TO-247
L 200 C	Z-IC	+2,85...36V, 2A	17/5Pin	TO-220/5V
LA 1111(A)P***	LIN-IC	TV, Sound IF, FM IF	8-DIP	
LA 1130	LIN-IC	AM Tuner, IF, AGC	16-SQP	
LA 1135	LIN-IC	AM Tuner, IF, AGC	20-DIP	
LA 1185	LIN-IC	FM Tuner/Front End, Ucc=1,5...8V	9-SIP	
LA 1201(FM)***	LIN-IC	AM/FM IF, AGC, AM Demodulator	14-DIP	
LA 1222***	LIN-IC	FM IF	8-DIP	
LA 1260	LIN-IC	AM Tuner, AM/FM IF, Ucc=3...8V	16-DIP	
LA 1266	LIN-IC	AM Tuner, AM/FM IF, Audio Inp, Ucc=6...14V	24-SDIP	
LA 1363***	LIN-IC	TV, Sound IF, Demodulator	14-DIP	
LA 1385***	LIN-IC	TV/CTV, VA Os, VA Out	10-SIL	
LA 1387***	LIN-IC	CTV, Sync. Signal (PAL)	16-DIP	
LA 2200*	LIN-IC	ARI Senderkennung/Station Code (SK)	16-DIP	
LA 2211***	LIN-IC	ARI Durchsagekennung/Information Code (DK)	22-DIP	
LA 2220	LIN-IC	ARI Senderkennung/Station Code (SK)	22-SQP	
LA 3120***	LIN-IC	LF Inp, Ucc=20V	8-SIP	
LA 3161	LIN-IC	Dual Audio Inp, Ucc=9V, integr. Stabi	8-SIP	
LA 3201***	LIN-IC	LF Inp, ALC	8-DIP	
LA 3210*	LIN-IC	LF Inp, ALC	9-SIP	
LA 3301***	LIN-IC	FM Dem, Stereo-Decoder	14-DIP	
LA 3350(B)***	LIN-IC	FM PLL MPX Stereo-Decoder	16-DIP	
LA 3600	LIN-IC	5-Band Graphic Equalizer, Ucc=8(5...15)V	16-DIP	
LA 4102***	LIN-IC	LF Out, 13V, 2,1W(9V/4Ω)	14-DIP+g	
LA 4112***	LIN-IC	LF Out, 2,3W(9V/4Ω)	14-DIP+g	
LA 4138	LIN-IC	Audio Out, 13V, 2,7W(9V/3,2Ω)	14-DIP+g	
LA 4140*	LIN-IC	LF Out, 0,5W(6V/8Ω)	9-SIP	
LA 4145	LIN-IC	LF Out, 9V, 0,5A, 0,9W(6V/4Ω), Icc0=10mA	9-SIP	
LA 4192	LIN-IC	Dual Audio Inp/Out, 11V, 2x2,3W(9V/4Ω)	12-DIP+b	
LA 4201***	LIN-IC	Audio Out, 20V, 2,5W(14V/8Ω)	14-DIP+g	
LA 4261	LIN-IC	Dual Audio Out, 25V, 2A, 2x 3,5W(16V/8Ω)	10-SIL	
LA 4270	LIN-IC	Dual Audio Out, 35V, 3,5A, 2x6W(25V/8Ω)	10-SILP	
LA 4280	LIN-IC	Dual Audio Out, 32V, 4A, 2x10W(32V/8Ω)	14-SILP	
LA 4282*	LIN-IC	Dual Audio Out, 32V, 2x10W(32V/8Ω)	12-SILP	
LA 4420***	LIN-IC	Audio Out, 18V, 5,5W(13V/4Ω)	10-SIL	
LA 4422	LIN-IC	Audio Out, 18V, 5,8W(13V/4Ω)	10-SIL	
LA 4440*	LIN-IC	Dual Audio Out, 18V, 2x6W, BTL=19W(13V/4Ω)	14-SILP	
LA 4445	LIN-IC	Dual Audio Out, 18V, 3,5A, 2x5,5W(13V/4Ω)	12-SILP	
LA 4446	LIN-IC	Dual Audio Out, 18V, 3,5A, 2x5,5W(13V/4Ω)	13-SIL	
LA 4460	LIN-IC	Audio Out, 18V, 4,5A, 12W(13V/4Ω)	10-SILP	
LA 4461	LIN-IC	=LA4460: spiegelb. Pinbelegung/Reverse Pinning	10-SILP	
LA 4495	LIN-IC	Audio Out, 18V, 4A, 12W(20V/4Ω), Standby (Pin9)	14-QILP	
LA 4498	LIN-IC	Audio Out, 18V, 4A, 12W(20V/4Ω), Standby	14-QILP	
LA 4500	LIN-IC	Dual Audio Out, 24V, 2,5A, 2x5,3W(12V/3Ω)	20-DILP	
LA 4505	LIN-IC	=LA 4500: 2x8,5W(15V/3Ω)	20-DILP	
LA 4508	LIN-IC	Dual Audio Out, 24V, 2,5A, 2x8,5W(15V/3Ω)	14-SILP	
LA 4520	LIN-IC	Recorder, Dual Verst./Amp., Ucc=4,5...6V	20-DIP	
LA 4555	LIN-IC	=LA 4500: 2x2,3W(9V/4Ω)	12-DIP+b	
LA 4570	LIN-IC	Kopfhörer-Vst./Headphone Amp., Ucc=3V	16-DIP	
LA 4700	LIN-IC	Dual Audio Out, 18V, 4A, 2x12W(13V/4Ω)	18-SILP	
LA 6510	OP-IC	Dual, hi-power, ±18V, 1A, -20...+75°	10-SIL	
LA 7116	LIN-IC	VC, Servo Interface	24-SDIP	
LA 7320	LIN-IC	VC, VHS Rec/Play Amp., Head Amp.	22-SDIP	
LA 7323	LIN-IC	VC, VHS-HQ, Luminance Signal Processor	30-SDIP	
LA 7520(N)	LIN-IC	CTV, Video IF, Sound IF	30-SDIP	
LA 7535	LIN-IC	TV, Video IF, Sound IF, pos. AGC, Ucc=9...13,2V	20-DIP	
LA 7800	LIN-IC	CTV, HA/VA Os, Sync. Signal	16-DIP	
LA 7820	LIN-IC	CTV, HA/VA Os, Sync. Signal	18-DIP	
LA 7830	LIN-IC	CTV, VA Drv, VA Out, Ucc=18...27V	7-SIL	
LA 7837	LIN-IC	TV, HA Drv, HA Out, max. Iq=1,8A	13-SIL	
LF 351/8-D	OP-IC	Serie 155, J-FET, ±18V, 13V/μs, 0...+70°	8-DIP	
LM 317 T	Z-IC	+1,2...37V, >1,5A, 0...+125°	17I	TO-220
LM 324 N	OP-IC	Quad, Serie 124, ±16V, 0...+70°	14-DIP	
LM 339 N	KOP-IC	Quad, Serie 139, ±18V, 0...+70°	14-DIP	
LM 380(N)	LIN-IC	Audio Out, Ucc=10...22V, 1,3A, >2,5W(18V/8Ω)	14-DIP	
LM 393/8-D	KOP-IC	Quad, lo-power, ±18V, 0...+70°	8-DIP	

JAEGER	Constr.	Info	Fig.	Compl.
LM 7000(N)	NMOS-IC	AM/FM Tuning PLL Frequ.-Synthesizer	20-DIP	
M 491 BB1	NMOS-IC	TV, Tuning, Memory(16Progr.), 7-Segment Display	40-DIP	
M 51102 L	LIN-IC	Dual Audio Out, 18V, 4A, 2x5,5W(13V/4Ω)	12-SIL	
M 51516 L*	LIN-IC	Audio Out, 18V, 4,5A, 12W(13V/4Ω)	9-SIL	
MB 3712	LIN-IC	Audio Out, 18V, 4,5A, 5,7W(13V/4Ω)	8-SIL	
MB 3713***	LIN-IC	=MB3712: spiegelb. Pinbelegung/Reverse Pinning	8-SIL	
MB 3731	LIN-IC	Audio Out, 18V, 4,5A, 18W(13,2V/4Ω)	12-SILP	
MB 3756 M	Z-IC	2x8,2V/0,1A + 1x8,3V/0,25A	8-SIL	
MC 14426(P)***	sRAM-IC	8x14 Bit (TV-Tuning)	16-DIP	
MDA 2062	EEPROM-IC	128x8 Bit, Tuning-Speicher/Memory	14-DIP	
MJ 3001*	Si-N-Darl+Di	LF, S P, 80V, 10A, 150W, hFE>1000	23a	TO-3
MJ 15015	Si-N	LF, S P, 200/120V, 15A, 180W, >0,8MHz	23a	TO-3
MJ 15016	Si-P	LF, S P, 200/120V, 15A, 180W, >2,2MHz	23a	TO-3
MJE 340	Si-N	LF P, -/300V, 0,5A, 20,8W, >10MHz	14h	TO-126
MPS-U 10	Si-N	Vid P, 300V, 0,5A, 10W, >60MHz	13m	(Uniwatt)
MPS-U 60	Si-P	Vid P, 300V, 0,5A, 10W, >60MHz	13m	(Uniwatt)
NE 555 N	LIN-IC	Zeitgeber/Timer, 4,5...16V, 0...+70°	8-DIP	
NE 556 N	LIN-IC	Dual, Zeitgeber/Timer, 4,5...16V, 0...+70°	14-DIP	
NE 592/8-D	LIN-IC	Diff. Video-Verst./Amp, 90MHz, Ucc=±3...8V, 0...+70°	8-DIP	
NE 592/14-D	LIN-IC	=NE 592/8-D:	14-DIP	
NE 645 N	LIN-IC	Dolby B + C	16-DIP	
NE 5532/8-D	OP-IC	Dual, ±22V, 10MHz, 9V/μs, 0...+70°	8-DIP	
PVPU 2204	NMOS-IC	CTV, Digital Video Processor	40-DIP	
RGP 30 M	Si-Di	FRr, 1000V, 3A, Uf<1,3V(3A), <500ns	31a	DO-27A
S 2000 A3*	Si-N	CTV-HA, SMPS, 1500V, 8/15A, 125W, sat<1V(4,5A)	16j	≈TOP-3L
S 2000 AF	Si-N	=S 2000A: 50W, Iso	18c	TO-3P Iso
S 2055 AF	Si-N+Di	=S 2000AF: int. Damper-Diode	18c	TO-3P Iso
S 2530 A	Si-N	TV SMPS, 1000/400V, 10A, 100W, <-/1μs, sat<3,3V	23a	TO-3
SAA 1024*	MOS-IC	US-FB Sender/Transmitter, 30 Codes	16-DIP	
SAA 1025	PMOS-IC	US-FB Empfänger/Receiver, 30 Codes	16-DIP	
SAA 1061***	NMOS-IC	LED Display Interface, 16 Segments	24-DIP	
SAA 1075	PMOS-IC	TV, Digital Tuning (Speicher/Memory)	18-DIP	
SAA 1124	CMOS-IC	US-FB Sender/Transmitter, 30 Codes	16-DIP	
SAA 1130*	PMOS-IC	US-FB Empfänger/Receiver, 30 Codes	18-DIP	
SAA 1250	CMOS-IC	IR-FB Sender/Transmitter, 64 Codes	24-DIP	
SAA 1251	PMOS-IC	IR-FB Empfänger/Receiver, 64 Codes	24-DIP	
SAA 1274*	PMOS-IC	TV, Digital Tuning Controller	24-DIP	
SAA 1276***	PMOS-IC	TV, Digital Tuning (Anzeige/Display)	18-DIP	
SAA 1293-3	NMOS-μC-IC	TV FB Empfänger/Receiver	40-DIP	
SAA 1293 A-03	NMOS-μC-IC	≈SAA 1293-3	40-DIP	
SAA 1350***	CMOS-IC	IR-FB Sender/Transmitter, 64 Codes	18-DIP	
SAA 3004(P)	CMOS-IC	IR-FB Sender/Transmitter, 7x64 Codes	20-DIP	
SAA 3010 P	MOS-IC	IR-FB Sender/Transmitter, 2048 Codes	28-DIP	
SAA 5030	LIN-IC	Tx, Video Signal	24-DIP	
SAA 5231	MOS-IC	Tx, Data Slicer f. Video Processor	28-DIP	
SAB 3013	NMOS-IC	6x D/A-Converter & Analog Memory	16-DIP	
SAB 3035	MOS-IC	TV Tuning, 8x Analog Signal, I ² C-Bus	28-DIP	
SAB 3037	LIN-IC	=SAB 3035: 4x Analog Signal, I ² C-Bus	24-DIP	
SAF 1039 P	CMOS-IC	IR-FB, Sender/Transmitter	16-DIP	
SAS 560 S	LIN-IC	Touch Sensor f. 4 Tasten/Keys	16-DIP	
SAS 570 S	LIN-IC	Touch Sensor f. 4 Tasten/Keys	16-DIP	
SAS 580	LIN-IC	Touch Sensor f. 4 Tasten/Keys	18-DIP	
SAS 590	LIN-IC	Sensor f. 4 Tasten/Keys	18-DIP	
SDA 2506(-5)*	EEPROM-IC	TV, 128x8 Bit, 3-Line-Bus	8-DIP	
SDA 2516(-5)	EEPROM-IC	TV, 128x8 Bit, I ² C-Bus	8-DIP	
SDA 2526(-5)	EEPROM-IC	TV, 256x8 Bit, I ² C-Bus	8-DIP	
SDA 2546(-5)	EEPROM-IC	TV, 512x8 Bit, I ² C-Bus	8-DIP	
SDA 3302(-2,-5)	LIN-IC	GHz-PLL f. VHF/UHF Tuner, I ² C-Bus	18-DIP	
SKE 4 F2/06*	Si-Di	FRr, 600V, 2A, <400ns	33	(17x15x7)
SKE 4 F2/10*	Si-Di	=SKE 4F2/06: 1000V	33	(17x15x7)
SONG 2***	IC	US-FB Empfänger/Receiver Control	14-DIP	
SPH 4690	Hybrid-IC	SMPS, =TDA 4605-3 + MOS-FET(600V/2Ω), ...250kHz	18-DIP	
STK 086*	Hybrid-IC	Audio Out, ±55V, 7A, >70W(±42V/8Ω)	HYB	
STK 459***	Hybrid-IC	2x Audio Out, ±31V, 2x >15W(±21V/8Ω)	HYB	
STK 465*	Hybrid-IC	2x Audio Out, ±41V, 2x >30W(±28/8Ω)	HYB	
STK 1070	Hybrid-IC	Audio Out, ±56V, 10A, >60W(±40V/8Ω)	HYB	
STK 2025	Hybrid-IC	Dual Audio Out, ±40V, 3A, 2x >20W(±24V/8Ω)	HYB	
STK 2028	Hybrid-IC	Dual Audio Out, ±43V, 5A, 2x >30W(±26V/4Ω)	HYB(78x44)	
STK 2038 II	Hybrid-IC	Dual Audio Out, ±55V, 7A, 2x >50W(±36V/8Ω)	HYB(78x44)	
STK 2129	Hybrid-IC	Dual Audio Out, ±43V, 5A, 2x >25W(±26,5V/8Ω)	HYB	
STK 2230	Hybrid-IC	Dual Audio Out, ±48V, 4A, 2x >30W(±30V/8Ω)	HYB	
STK 3042 III	Hybrid-IC	2x Audio Drv(Voltage Amp.), ±55V	HYB(44x30)	(4053A)
STK 3122 III	Hybrid-IC	=STK 3042: ±80V	HYB(44x30)	(4053A)
STK 4036 X	Hybrid-IC	Audio Out, ±52V, >50W(±36,5V/8Ω)	HYB(64x31)	(4062)
STK 4042 II	Hybrid-IC	Audio Out, ±65V, >80W(±45V/8Ω)	HYB(64x36)	(4075)

JAEGER	Constr.	Info	Fig.	Compl.
STK 4121 II	Hybrid-IC	Dual Audio Out, $\pm 30,5V$, $2 \times > 15W(\pm 20V/8\Omega)$	HYB(64x36)	(4040)
STK 4141 II*	Hybrid-IC	Dual Audio Out, $\pm 39V$, $2 \times > 25W(\pm 26V/8\Omega)$	HYB(64x36)	(4040)
STK 4142 II	Hybrid-IC	=STK 4141II	HYB(64x36)	(4040)
STK 4151 II	Hybrid-IC	Dual Audio Out, $\pm 42V$, $2 \times > 30W(\pm 27,5V/8\Omega)$	HYB(78x44)	(4042)
STK 4152 II	Hybrid-IC	=STK 4151II: Fig. \rightarrow	HYB(64x36)	(4040)
STK 4161 V	Hybrid-IC	Dual Audio Out, $\pm 46V$, $2 \times > 35W(\pm 30,5V/8\Omega)$	HYB(64x36)	(4040)
STK 4162 II	Hybrid-IC	Dual Audio Out, $\pm 45V$, $2 \times > 32W(\pm 30V/8\Omega)$	HYB(64x36)	(4040)
STK 4171 II	Hybrid-IC	Dual Audio Out, $\pm 48V$, $2 \times > 40W(\pm 32V/8\Omega)$	HYB(78x44)	(4042)
STK 4191 II	Hybrid-IC	Dual Audio Out, $\pm 52,5V$, $2 \times > 50W(\pm 35V/8\Omega)$	HYB(78x44)	(4042)
STK 4192 II	Hybrid-IC	=STK 4191II: Fig. \rightarrow	HYB(64x36)	(4040)
STK 4221 II	Hybrid-IC	Dual Audio Out, $\pm 65V$, $2 \times > 80W(\pm 45V/8\Omega)$	HYB(78x44)	(4086A)
STK 4241 V	Hybrid-IC	Dual Audio Out, $\pm 78V$, $2 \times > 120W(\pm 54V/8\Omega)$	HYB(78x44)	(4086A)
STK 4311	Hybrid-IC	Dual Audio Out, $52,5V$, $2 \times > 28W(35V/4\Omega)$	HYB	
STK 4332	Hybrid-IC	$2 \times$ Audio Out, $32V$, $2 \times > 5W(23V/8\Omega)$, THD=1%	HYB(59x25)	(4032A)
STK 4352	Hybrid-IC	=STK 4332: $39V$, $2 \times > 7W(27V/8\Omega)$	HYB(59x25)	(4032A)
STK 4362	Hybrid-IC	=STK 4332: $50V$, $2 \times > 10W(33V/8\Omega)$	HYB(59x31)	(4033)
STK 4432	Hybrid-IC	=STK 4332: $70V$, $2 \times > 25W(49V/8\Omega)$	HYB(59x31)	(4033)
STK 4833	Hybrid-IC	Dual Audio Out, $\pm 39V$, $2 \times > 25W(\pm 25,5V/8\Omega)$	HYB	
STK 4843	Hybrid-IC	Dual Audio Out, $\pm 43V$, $2 \times > 30W(\pm 27,5V/8\Omega)$	HYB	
STK 4863	Hybrid-IC	Dual Audio Out, $\pm 47V$, $2 \times > 35W(\pm 30V/8\Omega)$	HYB	
STK 4893	Hybrid-IC	Dual Audio Out, $\pm 46V$, $2 \times > 40W(\pm 32V/8\Omega)$	HYB	
STK 5322	Hybrid-Z-IC	VC, Dual, $+9,5V/1,6A$, $+15V/2,5A$	HYB	
STK 5325	Hybrid-Z-IC	VC, Dual, $+12V/1,6A$, $+14V/2,5A$	HYB	
STK 5326	Hybrid-Z-IC	VC, Dual, $+12V/1,6A$, $+13V/2,5A$	HYB	
STK 5331	Hybrid-Z-IC	VC, $+12V/1A$, $+6,05V/1A$, $+5,1V/0,5A$	HYB(39x25)	(4063)
STK 5332	Hybrid-Z-IC	VC, $+13V/1A$, $+6,05V/1A$, $+5,1V/0,5A$	HYB(39x25)	(4063)
STK 5337	Hybrid-Z-IC	VC, $+12,3V/1A$, $+6,1V/1A$, $+5,1V/1A$	HYB(44x25)	[8Pin]
STK 5338	Hybrid-Z-IC	VC, $+12,3V/1A$, $+5,8V/0,15A$, $+5,1V/1A$	HYB(44x25)	[8Pin]
STK 5339(A,B)	Hybrid-Z-IC	VC, $+12,3V/1A$, $+5,8V/1A$, $+5,1V/1A$	HYB(44x25)	[8Pin]
STK 5342	Hybrid-Z-IC	$12,3V/1A(2,5Ass)$, $6V/1A(2,5Ass)$, $5,25V/0,6A$	HYB(39x25)	
STK 5372 H	Hybrid-Z-IC	VC, $+12,1V/0,5A$, $+12V/0,8A$, $+5,3V/1A$	HYB(44x25)	[8Pin]
STK 5431 ST	Hybrid-Z-IC	VC, $+15V$, $+9,5V$, $+12V$, $+5,1V$	HYB	
STK 5461	Hybrid-Z-IC	VC, $+12V/1A$, $+12V/1A$, $+5,1V/0,5A$	HYB(59x25)	(4077)
STK 5467	Hybrid-Z-IC	VC, $+12V/1A$, $+12V/1A$, $+5,3V/1A$	HYB(59x25)	[12Pin]
STK 5471	Hybrid-Z-IC	VC, $+12V/1,5A$, $+12V/1,5A$, $+5,3V/0,5A$	HYB(44x25)	[10Pin]
STK 5476	Hybrid-Z-IC	VC, $+12V/1,5A$, $+12V/1,5A$, $+5,3V/1A$	HYB(59x25)	[12Pin]
STK 5481*	Hybrid-Z-IC	$+12V/1,5A$, $+12,2V/1A$, $+12,1V/1A$, $+5,3V/1A$	HYB(59x31)	[12Pin]
STK 5482*	Hybrid-Z-IC	$+15V/1A$, $+5,8V/0,5A$, $+12V/1A$, $+5,1V/1A$	HYB(59x31)	(4033)
STK 5490	Hybrid-IC			
STK 7226	Hybrid-Z-IC	VC, $+5,1V/1A$, $+13V/4A$	HYB(59x31)	(4033)
STK 7308	Hybrid-IC	CTV, Schaltregler/Switching Reg., $115V/0,7A$	HYB(59x25)	(4060)
STK 7309	Hybrid-IC	CTV, Schaltregler/Switching Reg., $115V/0,7A$	HYB(59x25)	(4060)
STK 7348	Hybrid-IC	CTV, S-Reg, $200V=$, $U_0=115V$, $0,3 \dots 0,7A$, $102W$	HYB(44x25)	[9Pin]
STK 7404	Hybrid-IC	Schaltregler/Switching Reg., offline	HYB	
STK 8250	Hybrid-IC	Audio Out, $\pm 56V$, $5A$, $> 50W(\pm 38V/8\Omega)$	HYB	
STR 450	Hybrid-Z-IC	Z-IC, $+115V$, $0,55A$	23/3Pin	\approx TO-3
STR 2012	Hybrid-Z-IC	S-Reg., $+5,1V$, $2A$, $75W$, $25kHz$	\approx 20/5Pin	
STR 5412	Hybrid-Z-IC		20/5Pin	
STR 40090	Hybrid-Z-IC		18/5Pin	\approx TO-3P
STR 41090	Hybrid-Z-IC	Schaltregler/Switching Reg., $+90V$	18/5Pin	\approx TO-3P
STR 54041	Hybrid-Z-IC	$U_{in}=900V$, $U_0=41,8V$	18/5Pin	\approx TO-3P
STR 58041	Hybrid-IC		18/5Pin	\approx TO-3P
TA 7060(A)P***	LIN-IC	TV, Sound IF, FM IF	7-SIP	
TA 7061(A)P***	LIN-IC	TV, Sound IF, FM IF	7-SIP	
TA 7070 P***	LIN-IC	TV, AFT	14-DIP	
TA 7073(A)P***	LIN-IC	TV, Sound IF	14-DIP	
TA 7075 P***	LIN-IC	TV,VC, Video IF, AGC	14-DIP	
TA 7120 P***	LIN-IC	Audio Inp In	7-SIP	
TA 7124 P***	LIN-IC	TV, Video IF	7-SIP	
TA 7129(A)P***	LIN-IC	Audio Inp In	7-SIP	
TA 7130 P	LIN-IC	FM IF, Demodulator	7-SIP	
TA 7145 P***	LIN-IC	TV, Video IF, AGC	16-DIP	
TA 7157(A)P***	LIN-IC	Stereo-Decoder	14-DIP	
TA 7205 AP	LIN-IC	Audio Out, $18V$, $2A$, $5,8W(13V/4\Omega)$	10-SIL	
TA 7217 AP	LIN-IC	Audio Out, $18V$, $4,5A$, $5,8W(13V/4\Omega)$	10-SIL	
TA 7222(A)P	LIN-IC	Audio Out, $25V$, $4,5A$, $5,8W(13V/4\Omega)$	10-SIL	
TA 7227 P	LIN-IC	Dual Audio Out, $25V$, $4,5A$, $2 \times 5,5W(13V/4\Omega)$	12-SILP	
TA 7230 P	LIN-IC	Dual Audio Out, $24V$, $1,5A$, $2 \times 4W(14V/4\Omega)$	10-SIL	
TA 7232 P	LIN-IC	Dual Audio Out, $16V$, $2A$, $2 \times 2,2W(9V/4\Omega)$	12-SIL	
TA 7233 P	LIN-IC	Dual Audio Out, $16V$, $2,5A$, $2 \times 4,5W(12V/4\Omega)$	12-SIL	
TA 7240 AP	LIN-IC	Dual Audio Out, $25V$, $4,5A$, $2 \times 5,8W(13V/4\Omega)$	12-SILP	
TA 7243 P	LIN-IC	TV, Sound IF, LF In/Out, $> 3W(30V/8-32\Omega)$	14-DIP+a	
TA 7250 BP	LIN-IC	HiFi Audio Out, $25V$, $9A$, $23W(13V/4\Omega)$	12-SQL	
TA 7251 BP	LIN-IC	=TA 7250: spiegelb. Pinbelegung/Reverse Pinning	12-SQL	
TA 7263 P	LIN-IC	Dual Audio Out, $25V$, $4,5A$, $2 \times 5,8W(13V/4\Omega)$	(12-SILP)	

JAEGER	Constr.	Info	Fig.	Compl.
TA 7270 P	LIN-IC	Dual Audio Out, 25V, 4,5A, 2x5,8W(13V/4Ω)	12-SQL	
TA 7271 P	LIN-IC	=TA 7241: spiegelb. Pinbelegung/Reverse Pinning	12-SQL	
TA 7273 P	LIN-IC	TV, Dual Audio Out, 37V, 2,5A, 2x13W(28V/8Ω)	12-SQL	
TA 7274 P	LIN-IC	Audio Out, 25V, 4,5A, 12W(13V/4Ω)	=7-SIL	
TA 7280 AP	LIN-IC	Dual Audio Out, 25V, 4,5A, 2x5,8W(13V/4Ω)	12-SQL	
TA 7281 P	LIN-IC	=TA 7280: spiegelb. Pinbelegung/Reverse Pinning	12-SQL	
TA 7282 AP	LIN-IC	Dual Audio Out, 16V, 2,5A, 2x4,6W(12V/4Ω)	12-SIL	
TA 7283 AP,P	LIN-IC	Dual Audio Out, 16V, 2x2,5A, 2x4,6W(12V/4Ω)	12-SIL	
TA 7288 P	LIN-IC	VC, Dual, Cassette/Tape Loading Motor Drv	10-SIL	
TA 7299 AP,P	LIN-IC	Dual HiFi Audio Out, 25V, 2x5,8W(13,2V/4Ω)	12-SQL	
TA 7303 P***	LIN-IC	FM IF	9-SIP	
TA 7324 P,S	LIN-IC	Stummuschaltung/Muting	9-SIP	
TA 7343 AP,P	LIN-IC	FM PLL MPX Stereo-Decoder, Ucc=3,5...12V	9-SIP	
TA 7604(A)P*	LIN-IC	Stereo-Decoder	16-DIP	
TA 7607(A)P	LIN-IC	TV, Video IF, AGC (MOSFET-Tuner)	16-DIP	
TA 7609(A)P	LIN-IC	TV, HA/VA Sync. Processor	16-DIP	
TA 7630 P	LIN-IC	Audio Reg./DC Volume & Tone Control, Ucc=8...14V	16-DIP	
TA 7640 AP,P	LIN-IC	AM Tuner, FM IF, Ucc=3...8V	16-DIP	
TA 7680 AP,P	LIN-IC	CTV, Video/Sound IF, AGC (FET-Tuner)	24-DIP	
TA 7698 AP,P	LIN-IC	CTV, PAL/NTSC Video, Chroma, Sync. Signal	42-DIP	
TA 7784 P	LIN-IC	Recorder, 2x Audio Inp f. Autoreverse, Ucc=3,5...15V	16-DIP	
TA 8205 AH	LIN-IC	Dual Audio Out, 25V, 9A, 2x15W(13,2V/4Ω), BTL	17-QILP	
TA 8207 K	LIN-IC	Dual Audio Out, 20V, 2,5A, 2x4,6W(12V/4Ω)	12-SIL	
TA 8210 H,AH	LIN-IC	Dual Audio Inp,Out, 25V, 9A, 2x19W(13,2V/4Ω)	17-QILP	
TA 8215 H	LIN-IC	Dual Audio Out, 25V, 9A, 2x18W(14,4V/4Ω)	17-QILP	
TA 8216 H	LIN-IC	TV, Dual Audio Out, 40V, 3A, 2x13W(28V/8Ω)	12-SQL	
TA 8221 H,AH	LIN-IC	Dual Audio Out, 25V, 9A, 2x30W(14,4V/2Ω)	17-QILP	
TA 8403 K	LIN-IC	CTV, 1,8Ap-p	=7-SIP	
TA 8659 AN	LIN-IC	CTV, Video & Chroma Signal (NTSC, PAL, SECAM)	64-SDIP	
TA 75902 P*	OP-IC	Quad, ±18V, -40...+85°	14-DIP	
TAA 550	Z-IC	Tuner Stabi, 33V	2g	TO-18
TAA 611 B12	LIN-IC	Audio Out, 15V, 1A, 2,1W(12V/8Ω)	14-QIP+c	
TAG 103 X	F-Thy	30V, 1A=, Igt/Ih<0,2/<2mA, 10µs	2a	TO-5
TAG 232-600	Triac	600V, 5A=(Tc=80°), Igt/Ih<10/<25mA	17j	TO-220
TAG 626-600	50Hz-Thy	600V, 3,5A(Tc=85°), 8A=, Igt/Ih<10/<25mA	17e	TO-220
TBA 120 S	LIN-IC	TV, Sound IF, LF Inp	14-DIP	
TBA 120 T	LIN-IC	TV, Sound IF f. Keramikfilter	14-DIP	
TBA 120 U	LIN-IC	TV, Sound IF, VC Signal	14-DIP	
TBA 510***	LIN-IC	CTV, PAL Chroma Signal	16-DIP/QIP	
TBA 520*	LIN-IC	CTV, PAL Sync. Demodulator	16-DIP/QIP	
TBA 530*	LIN-IC	CTV, PAL RGB Matrix Preamp.	16-DIP/QIP	
TBA 540	LIN-IC	CTV, PAL Reference Os	16-DIP/QIP	
TBA 560 C*	LIN-IC	CTV, PAL Luminance & Chrominance Control	16-DIP/QIP	
TBA 800	LIN-IC	TV, VA Out, Audio Out, 30V, 1,5A, 5W(24V/16Ω)	12-QIP+b	
TBA 810 AS	LIN-IC	Audio Out, 20V, 2,5A, 6W(14V/4Ω)	12-QIP+a	
TBA 810 AT	LIN-IC	Audio Out, 25V, 3A, 6W(14V/4Ω)	12-QIP+a	
TBA 810 S	LIN-IC	=TBA 810 AS: Fig. →	12-QIP+b	
TBA 820	LIN-IC	Audio Out, 16V, 1,5A, 2W(12V/8Ω)	14-QIP	
TBA 820 M	LIN-IC	=TBA 820: Fig. →	8-DIP	
TBA 920 S	LIN-IC	TV, HA-Kombination/Line Osc. Combination	16-DIP	
TBA 940 A***	LIN-IC	TV, HA Sync. Signal f. Thyristor Out	14-DIP	
TBA 950 :2(X)	LIN-IC	TV, HA Sync. Signal f. Transistor Out	14-DIP	
TBA 1441***	LIN-IC	TV, Video IF, AGC (NPN-Tuner)	16-DIP	
TBA 2800	LIN-IC	IR-Vorverst./Preamp.	14-DIP	
TCA 650***	LIN-IC	CTV, PAL/SECAM Sync. Demodulator	16-DIP/QIP	
TCA 660(B)*	LIN-IC	CTV, Einstellkombi/Adjust Control	16-DIP/QIP	
TCA 910*	LIN-IC	Motorregler/Speed Control, Uq=5,6V	14b	TO-126
TCA 4500(A)	LIN-IC	PLL Stereo-Decoder, Blend, o. Spulen/wo. Inductors	16-DIP	
TD 3 FP 800 H*	F-Thy+Di	TV-HA, Hinlauf/Trace, 800V, 3,4A, Igt/Ih<50/<100mA	17f	TO-220
TD 3 FP 800 R*	F-Thy+Di	TV-HA,Rückl./Retrace, 800V, 3,4A, Igt/Ih<50/<100mA	17f	TO-220
TDA 440 S	LIN-IC	TV, Video IF, AGC (PNP Tuner), int. Stabi	16-DIP	
TDA 1002(A)*	LIN-IC	Recorder, Rec/Play Amp., ALC	16-DIP/QIP	
TDA 1005(A)*	LIN-IC	PLL, Stereo-Decoder	16-DIP	
TDA 1010(A)	LIN-IC	Audio Inp,Out, 24V, 3A, 6,2W(14V/4Ω)	9-SIL	
TDA 1013 B	LIN-IC	Audio Inp,Out, 40V, 1,5A, 4,2W(18V/8Ω)	9-SIL	
TDA 1015	LIN-IC	Audio Out, 18V, 2,5A, 4,2W(12V/4Ω)	9-SIL	
TDA 1020*	LIN-IC	Audio Out, 18V, 4A, 12W(14V,2Ω)	9-SIL	
TDA 1023(N,N3)	LIN-IC	Thyristor-, Triac-Ansteuerung/Trigger Ctrl.	16-DIP	
TDA 1034(BN)	OP-IC	hi-speed, ±3...20V, =...+70°, N=lo-noise	8-DIP	
TDA 1044	LIN-IC	TV, VA Os, Sync. Signal	12-QIP+b	
TDA 1046***	LIN-IC	AM Radio, Audio Inp	16-DIP	
TDA 1047***	LIN-IC	FM IF, Dem, AFC	18-DIP	
TDA 1054(M)	LIN-IC	Recorder, Rec/Play Amp., ALC	16-DIP	
TDA 1059(B)	LIN-IC	Motorregler/Speed Control	14b	TO-126
TDA 1060	LIN-IC	TV, SMPS Controller, -25...+125°	16-DIP	

JAEGER	Constr.	Info	Fig.	Compl.
TDA 1072(A)	LIN-IC	AM Radio, Audio Inp	16-DIP	
TDA 1074(A)	LIN-IC	Dual El. Stereo-Potentiometer/DC Controlled Pot.	18-DIP	
TDA 1082	LIN-IC	CTV, Ost-West-Korrektur/East-West Correction	16-DIP	
TDA 1083	LIN-IC	AM Inp, AM/FM IF, Audio Out, >0,3W(5,5V/8Ω)	16-DIP	
TDA 1151	LIN-IC	Motorregler/Speed Control, 20V, 1,2A	14b	TO-126
TDA 1170 S	LIN-IC	TV, VA System, VA Out	12-QIP+b	
TDA 1180 P	LIN-IC	TV,CTV, HA Processor, Ucc=12V, P: PAL	16-DIP	
TDA 1510	LIN-IC	Dual Audio Out, 18V, 6A, 2x12W(14V/2Ω)	13-QILP	
TDA 1512(A)	LIN-IC	HiFi Audio Out, 35V, 3,2A, 25W(32V/4Ω)	9-SILP	
TDA 1514 A	LIN-IC	HiFi Audio Out, ±30V, ±4A, 40W(±27,5V/8Ω)	9-SILP	
TDA 1515 A,AQ	LIN-IC	Dual Audio Out, 28V, 6A, 2x12W(14V/2Ω)	13-QILP	
TDA 1516 Q	LIN-IC	Dual Audio Out, 18V, 4A, 2x11W(14V/4Ω), 20dB	13-QILP	
TDA 1518 Q,BQ	LIN-IC	=TDA 1516Q,BQ: 40dB	13-QILP	
TDA 1520 A,B	LIN-IC	HiFi Audio Out, 50V, 4A, 22W(33V/4Ω)	9-SILP	
TDA 1521	LIN-IC	Dual HiFi Audio Out, ±20V, 4A, 2x15W(±16V/8Ω)	9-SILP	
TDA 1522	LIN-IC	Recorder, Dual Audio Inp	9-SIL	
TDA 1524 A	LIN-IC	Stereo Potentiometer f. Tone+Volume+Balance Ctrl.	18-DIP	
TDA 1541 A,AN	D/A-IC	CD, Dual, 16 Bit, Digital Audio	28-DIP	
TDA 1578(A)	LIN-IC	PLL Stereo-Decoder	18-DIP	
TDA 1675 A	LIN-IC	TV, VA System, VA Out	15-SQL	
TDA 1701	LIN-IC	TV, Sound IF, Audio Inp,Out	12-DIP+b	
TDA 1904	LIN-IC	Audio Out, 4...20V, 2A, 4,5W(14V/4Ω)	16-DIP	
TDA 1905	LIN-IC	Audio Out, 4...30V, 2,5A, 5,5W(14V/4Ω)	16-DIP	
TDA 1908	LIN-IC	Audio Out, 30V, 3A, 8W(22V/8Ω)	12-QIP+b	
TDA 1940	LIN-IC	TV, HA System	18-DIP	
TDA 2003	LIN-IC	Audio Out, 28V, 3,5A, 10W(14V/2Ω)	17/5Pin	TO-220/5
TDA 2004	LIN-IC	Dual Audio Out, 28V, 3,5A, 2x6,5W(14V/4Ω)	11-SQL	
TDA 2005(M,S)	LIN-IC	Dual Audio Out, 28V, 3,5A, 2x10W(14V/2Ω)	11-SQL	
TDA 2008(V)	LIN-IC	Audio Out, 28V, 3A, 12W(22V/4Ω)	17/5Pin	TO-220/5
TDA 2009(A,S)	LIN-IC	Dual Audio Out, 28V, 3,5A, 2x11W(23V/4Ω)	11-SQL	
TDA 2030(H,V)	LIN-IC	HiFi Audio Out, ±18V, 3,5A, 18W(±14V/4Ω)	17/5Pin	TO-220/5
TDA 2030 A(AV,AH)	LIN-IC	=TDA 2030: ±22V, 3,5A, 18W(±16V/4Ω)	17/5Pin	TO-220/5
TDA 2040(H,V)	LIN-IC	HiFi Audio Out, ±20V, 4A, 22W(±16V/4Ω)	17/5Pin	TO-220/5
TDA 2050(H,V)	LIN-IC	Hi-Fi Audio Out, ±25V, 5A, 32W(±22V/8Ω)	17/5Pin	TO-220/5
TDA 2320 A	LIN-IC	IR-FB, Vorverstärker/Preamp, 36V, In (f.HiFi Inp)	8-DIP	
TDA 2532 *	LIN-IC	CTV, RGB Matrix	16-DIP/QIP	
TDA 2541	LIN-IC	CTV, Video IF, AGC (PNP-Tuner)	16-DIP	
TDA 2543	LIN-IC	TV, AM Sound IF (L-Norm/French Standard)	18-DIP	
TDA 2545(A,Q)	LIN-IC	TV, Quasi-Parallelton/Split-sound	16-QIP	
TDA 2546(A)	LIN-IC	TV, Quasi-Parallelton/Split-sound, 5,5MHz Demod.	18-DIP	
TDA 2555	LIN-IC	TV, Stereo FM Dem.(IF: 8 Stufen/Stages)	18-DIP	
TDA 2556	LIN-IC	TV, Quasi-Parallelton/Split-sound	24-DIP	
TDA 2557	LIN-IC	=TDA 2555: IF= 5 Stufen/5 Stages	18-DIP	
TDA 2578 A	LIN-IC	TV, HA/VA Os, Sync. Signal	18-DIP	
TDA 2579 A	LIN-IC	TV, HA/VA Os, Sync. Signal	18-DIP	
TDA 2581 *	LIN-IC	TV, SMPS Controller	16-DIP	
TDA 2582	LIN-IC	=TDA 2581: verbessert/improved	16-DIP	
TDA 2593	LIN-IC	TV, HA/VA Sync. Combination	16-DIP	
TDA 2594	LIN-IC	=TDA 2593: Sender-,Transmitter Identification	18-DIP	
TDA 2595	LIN-IC	TV, HA Os, Sync. Signal f. pos. FBAS-Signal	18-DIP	
TDA 2611 A	LIN-IC	Audio Out, 35V, ±1,5A, 5W(25V/15Ω)	9-SIL	
TDA 2640 *	LIN-IC	TV, SMPS Controller	16-DIP	
TDA 2653 A	LIN-IC	CTV, VA Os, VA Out, f. 30AX-System	13-SQL	
TDA 2654 S	LIN-IC	TV 110°, CTV 90°, VA Os, VA Out	9-SIL	
TDA 2791 *	LIN-IC	TV, FM Dem, Tonsteurg./DC Volume & Tone Control	16-DIP	
TDA 2795	LIN-IC	TV, Stereo Identification	18-DIP	
TDA 2822	LIN-IC	Dual Audio Out, 15V, 1,5A, 2x1,7W(9V/4Ω)	16-DIP	
TDA 2822 M	LIN-IC	Dual Audio Out, 15V, 1A, 2x0,65W(6V/4Ω)	8-DIP	
TDA 3048(P)	LIN-IC	IR-FB Empfänger/Receiver	16-DIP	
TDA 3190	LIN-IC	TV, Sound IF, Audio Out, 4,2W(24V/16Ω)	16-DIP	
TDA 3301 B *	LIN-IC	CTV, PAL/NTSC Color Processor	40-DIP	
TDA 3420	LIN-IC	Recorder, Dual Audio Inp, In	16-DIP	
TDA 3501 *	LIN-IC	CTV, RGB Chroma Processor, Video Out	28-DIP	
TDA 3505	LIN-IC	CTV, RGB Signal(neg. B-Y,R-Y), Video Out	28-DIP	
TDA 3506	LIN-IC	=TDA 3505: pos. B-Y,R-Y	28-DIP	
TDA 3510	LIN-IC	CTV, PAL Decoder	24-DIP	
TDA 3541	LIN-IC	TV, Video IF, AGC (PNP-Tuner)	16-DIP	
TDA 3561 A	LIN-IC	CTV, PAL Decoder	28-DIP	
TDA 3562 A	LIN-IC	CTV, PAL/NTSC Decoder	28-DIP	
TDA 3565	LIN-IC	CTV, PAL Decoder	18-DIP	
TDA 3566	LIN-IC	CTV, PAL/NTSC Decoder	28-DIP	
TDA 3576 B *	LIN-IC	CTV, HA/VA Os, Sync. Signal	18-DIP	
TDA 3580	LIN-IC		28-DIP	
TDA 3590(A)	LIN-IC	CTV, SECAM/PAL Transcoder	24-DIP	
TDA 3592 A	LIN-IC	CTV, SECAM/PAL Transcoder	24-DIP	

JAEGER	Constr.	Info	Fig.	Compl.
TDA 3640	LIN-IC	CTV, SMPS Controller	18-DIP	
TDA 3645	LIN-IC		18-DIP	
TDA 3650*	LIN-IC	CTV, VA Os, VA Out	13-SQL	
TDA 3653 C	LIN-IC	CTV, VA Out, 90°, =TDA 3651	9-SILP	
TDA 3654	LIN-IC	CTV, VA Out, 110°, =TDA 3652	9-SILP	
TDA 3803 A	LIN-IC	CTV, VC, Stereo-Decoder	28-DIP	
TDA 3810	LIN-IC	Audio Stereo, Pseudo Stereo	18-DIP	
TDA 3840	LIN-IC	TV, IF Amp., Demodulator, Signal Identification	20-DIP	
TDA 4190	LIN-IC	TV, Sound IF, Audio Out, 4,1W(24V/16Ω)	20-DIP	
TDA 4260*	LIN-IC	TV, AFC	8-DIP	
TDA 4282 T	LIN-IC	TV, Quasi-Parallelton/Split-sound, FM IF	22-DIP	
TDA 4290(V)	LIN-IC	El. Tonsteuerung/DC Audio Signal Control	14-DIP	
TDA 4420	LIN-IC	TV, Video IF, AFC, AGC (PNP-Tuner)	18-DIP	
TDA 4431***	LIN-IC	TV, AFC Control, Signal Identification	14-DIP	
TDA 4432***	LIN-IC	TV, Suchlauf-Stop/Station Searching Stop Pulse	8-DIP	
TDA 4433	LIN-IC	TV, AFC Control, Signal Identification	14-DIP	
TDA 4439	LIN-IC	TV, Video IF, Multistandard	18-DIP	
TDA 4440	LIN-IC	TV, Video IF, AGC (PNP-Tuner)	16-DIP	
TDA 4442	LIN-IC	TV, Video IF, AGC, VCR Connector	16-DIP	
TDA 4443	LIN-IC	TV, CTV, Video IF, Multistandard	16-DIP	
TDA 4445	LIN-IC	TV, Quasi-Parallelton/Split-sound	14-DIP	
TDA 4445 B	LIN-IC	TV, Quasi-Parallelton/Split-sound, AM/FM Dem	16-DIP	
TDA 4480-2	LIN-IC	TV, Quasi-Parallelton/Split-sound, Multistandard	20-DIP	
TDA 4501	LIN-IC	CTV, Signal Processor (NPN/PNP-Tuner)	28-DIP	
TDA 4502(A)	LIN-IC	CTV, Signal Processor(NPN/PNP-Tuner)	28-DIP	
TDA 4505 E	LIN-IC	CTV, Signal Processor (neg. AGC), 50/60Hz	28-DIP	
TDA 4510	LIN-IC	CTV, PAL Decoder	16-DIP	
TDA 4555	LIN-IC	CTV, PAL/SECAM/NTSC(3,58/4,43)Dec. -(R-Y)/-(B-Y)	28-DIP	
TDA 4556	LIN-IC	=TDA 4555: Ausg.-Signal/Output: +(R-Y)/+(B-Y)	28-DIP	
TDA 4557	LIN-IC	CTV, PAL/SECAM/NTSC-3,58/4,43 Decoder	28-DIP	
TDA 4565	LIN-IC	CTV, Y-Verzögerung/Delay, 690...1005ns	18-DIP	
TDA 4580	LIN-IC	CTV, Video Controller (Multistandard)	28-DIP	
TDA 4600-2	LIN-IC	TV, SMPS Controller	9-SIL	
TDA 4601	LIN-IC	=TDA 4600: verbessert/improved	9-SIL	
TDA 4601 B,D	LIN-IC	=TDA 4600-2D: verbessert/improved	18-DIP	
TDA 4605	LIN-IC	TV, SMPS Controller f. MOS-FET, ...165kHz	8-DIP	
TDA 4305-3	LIN-IC	=TDA 4605: verbessert/improved Version, ...250kHz	8-DIP	
TDA 4650	LIN-IC	CTV, Color Decoder, Multistandard	28-DIP	
TDA 4660	LIN-IC	CTV, 64µs Verzögerung/Delay Line	16-DIP	
TDA 4661	LIN-IC	CTV, Verzögerungsleitung/Delay Line	16-DIP	
TDA 4680	LIN-IC	CTV, Video Processor, I ² C-Bus	28-DIP	
TDA 4935	LIN-IC	Dual Audio Out, 32V, 2,8A, 2x15W(24V/4Ω)	9-SIL	
TDA 4944	LIN-IC	TV, Stereo Matrix, VC Anschluss/Connection	14-DIP	
TDA 4950	LIN-IC	TV, Ost-West-Korrektur/East-West Correction	8-DIP	
TDA 5030(A)	LIN-IC	TV, VC, VHF Tuner Os,Mx, UHF Inp	18-DIP	
TDA 5631 T(SMD)	LIN-IC	SMD, TV,VC, VHF/UHF/Hyperband Mx,Os, 48...860MHz	20-(S)MDIP	
TDA 5850	LIN-IC	Video-Verst./Amplifier, Multistandard f. SCART	8-DIP	
TDA 6100 Q	LIN-IC	CRT, 8MHz Video Out	9-SQL	
TDA 6610-5	LIN-IC	TV, Stereo Processor, Multistand., SCART, I ² C-Bus	28-DIP	
TDA 7000	LIN-IC	FM Mono Radio	18-DIP	
TDA 7040 T(SMD)	LIN-IC	PLL Stereo-Decoder, Ucc=3V	8-MDIP	
TDA 7050	LIN-IC	Dual Audio Out, 6V, 0,15A, 2x75mW(4,5V/32Ω)	8-DIP	
TDA 7052	LIN-IC	Audio Out, 18V, 1,2W(6V/8Ω)	8-DIP	
TDA 7240 A	LIN-IC	Audio Out, 28V, 3,5A, 20W(14V/4Ω, BTL)	TO-220/7	
TDA 7250	LIN-IC	Dual HiFi Audio Out, 100V, 2x50W(±35V/4Ω)	20-DIP	
TDA 7275(A)	LIN-IC	Motorregler/Motor Speed Control, 19V, 1,5A	8-DIP	
TDA 7350(A)	LIN-IC	Dual Audio Out, 28V, 4A, 2x11W(14,4V/2Ω)	11-SQL	
TDA 8115	LIN-IC	Dual Motor-Treiber/Motor Driver	TO-220/7	
TDA 8120(B)	LIN-IC	Multistandard Video IF, Sound IF	24-DIP	
TDA 8138 A	Z-IC	VC, Disable, ±2%, +5,1V/1A, 12V/1A	17/7Pin	TO-220/7
TDA 8140	LIN-IC	TV, HA Drv, Pin6: Special Remote Standby	16-DIP	
TDA 8143	LIN-IC	TV, HA Drv, Pin7: Special Remote Standby	9-SIL	
TDA 8145	LIN-IC	TV, Ost-West-Korrektur/East-West Correction	8-DIP	
TDA 8160	LIN-IC	IR-FB Empfänger/Receiver	8-DIP	
TDA 8170	LIN-IC	TV,CTV, Flyback Gen., VA Out, Ucc=35V, Io=3A	17/7Pin	TO-220/7
TDA 8172	LIN-IC	TV,CTV, Flyback Gen., VA Out, Ucc=35V, Io=3A	17/7Pin	TO-220/7
TDA 8173	LIN-IC	=TDA 8172: →	16-DIP	
TDA 8175	LIN-IC	TV,CTV, VA System, VA Out, Ucc=35V, Io=3A	17/7Pin	TO-220/7
TDA 8185(I)	LIN-IC	TV, HA/VA Processor, 50/60Hz	24-DIP	
TDA 8190	LIN-IC	TV, Sound IF, Audio Out, 4,1W(24V/16Ω), DC Ctrl.	20-DIP	
TDA 8196	LIN-IC	TV, Audio Switch, DC Volume Control, Ucc=16V	8-DIP	
TDA 8214 B	LIN-IC	CTV, HA/VA Processor f. Darl Line Out, PAL	20-DIP	
TDA 8305 A	LIN-IC	CTV, IF, Signal Prozessor	28-DIP	
TDA 8341	LIN-IC	TV IF, AGC f. PNP-Tuner	16-DIP	
TDA 8391	LIN-IC	CTV, PAL Decoder, RGB Matrix	32-DIP	

JAEGER	Constr.	Info	Fig.	Compl.	
TDA 8405	LIN-IC	TV,VC, Stereosound Processor, I ² C-Bus	28-DIP		
TDA 8415	LIN-IC	TV,VC, Stereosound Processor, I ² C-Bus	20-DIP		
TDA 8421	LIN-IC	HiFi Audio Processor, I ² C-Bus	28-DIP		
TDA 8432	LIN-IC	TV, HA/VA Processor	28-DIP		
TDA 8442(N)	D/A-IC	CTV, I ² C Interface, Quad, 6 Bit, -20...+70°	16-DIP		
TDA 8443(A)	LIN-IC	Video Signal Selector, I ² C-Bus	24-DIP		
TDA 8444(N)	D/A-IC	8x 6 Bit, I ² C-Bus, -20...+70°	16-DIP		
TDA 8490	LIN-IC	CTV, SECAM Decoder	18-DIP		
TDA 8702(P)	D/A-IC	TV,VC, 8 Bit, Video, ...30MHz	16-DIP		
TDA 8708	A/D-IC	8 Bit, Video analog Input(0,5V) Interface	28-DIP		
TDA 9403***	LIN-IC	TV, HA System, f. Thyristor Out	16-DIP		
TEA 1009	LIN-IC	IR Empfänger-Vst./Receiver Amplifier	14-DIP		
TEA 1039	LIN-IC	SMPS Controller, -25...+125°	9-SIL		
TEA 2014	LIN-IC	Video Signal Switch, >6MHz, Ucc=18V	8-DIP		
TEA 2025(B)	LIN-IC	Dual Audio Out, 15V, 1,5A, 2x2,3W(9V/4Ω)	16-DIP		
TEA 2029 C	LIN-IC	CTV, SMPS, Scan-Processor, pos. AGC Key Pulse	28-DIP		
TEA 2031 A	LIN-IC	CTV, Ost-West-Korrektur/East-West Correction	8-DIP		
TEA 2164	LIN-IC	TV, SMPS Controller	16-DIP		
TEA 2164 G,N*	LIN-IC	=TEA 2164	16-DIP		
TEA 2261	LIN-IC	CTV, SMPS Controller, I _o <0,6A, <100kHz	16-DIP		
TEA 5101 A,B	LIN-IC	CTV, RGB Out, A=ESD-Schutz/Protection	15-SQL		
TEA 8170	LIN-IC	TV, VA Out	17/7Pin	TO-220/7	
TIC 106 M	50Hz-Thy	600V, 3,2A(Tc=80°), 5A _{avg} , I _{gt} /I _h <0,2/5mA	17e	TO-220	
U 2829 B	LIN-IC	TV, 2x Sound IF, Demodulator, f. Keramik-Filter	16-DIP		
U 6202 B	LIN-IC	VC,TV, PLL Tuning, Freq.-Teiler/Prescaler	18-DIP		
VCU 2133 A	LIN-IC	CTV, Video Codec	40-DIP		
VCU 2136 A	LIN-IC	CTV, Digital Video Codec	40-DIP		
ZTK 33	Z-IC	Tuner-Stab., 33V	31h	DO-35	
1 N 4007	Si-Di	Rr, Uni, 1000V, 1A, U _f <1,1V(1A)	31a	SOD-22	
1 N 4148	Si-Di	SS, 75/100V, 0,2A, U _f <1V(10mA), <4ns, <4pF(0V)	31a	DO-35	
1 N 4148(SMD)	Si-Di	=1N4148: SMD	72a(3,4mm)	SOD-80	
1 N 5822	Si-Di	Schottky Rr, 40V, 3A, U _f <0,525V(3A)	31a	DO-27A	
2 N 3055	Si-N	LFS P, 100/60V, 15A, 115W, >2,5MHz, hFE=20...70	23a	TO-3	
2 SA 748	Si-P	LFS P, 70/50V, 2/3A, 15W, 120MHz	17j	TO-220	2SC1398
2 SA 1077*	Si-P	DC-DC-Converter, 120/120V, 10/12A, 60W, 60MHz	17j	TO-220	
2 SA 1112	Si-P	LFS P, 180/180V, 1/1,5A, 20W, 200MHz	17j	TO-220	2SC2592
2 SA 1124	Si-P	Uni, In, 150/150V, 50/100mA, 1W, 200MHz	7c(9mm)	TO-92L	2SC2632
2 SA 1156	Si-P	S P, 400/400V, 0,5/1A, 10W, <1/5μs	14h	TO-126	2SC2752
2 SA 1186	Si-P	P, 150/150V, 10A, 100W, 60MHz, 250/1000ns	18j	TO-3P	2SC2837
2 SA 1248	Si-P	TV Audio Out, 180/160V, 0,7/1,5A, 10W, 120MHz	14h	TO-126	2SC3116
2 SA 1249	Si-P	TV Audio Out, 180/160V, 1,5/2,5A, 10W, 120MHz	14h	TO-126	2SC3117
2 SA 1294	Si-P	P, 230/230V, 15A, 130W, 35MHz, -/1800ns	18j	TO-3P	2SC3263
2 SA 1295	Si-P	P, 230/230V, 17A, 200W, 35MHz, -/1800ns	20j	TO-3P	2SC3264
2 SA 1302	Si-P	HiFi-LF Out, 200/200V, 15A, 150W, 30MHz	77j	TOP-3L	2SC3281
2 SA 1307	Si-P	P, 60/50V, 5A, 20W, 60MHz, lo-sat<0,4V(3A)	17c	SOT-186	2SC3299
2 SA 1329	Si-P	P, 80/60V, 12A, 40W, 50MHz, sat<0,4V(6A)	17j	TO-220	2SC3346
2 SA 1357	Si-P	35/20V, 5/8A, 10W, 170MHz, lo-sat<1V(4A)	14b	TO-126Iso	2SC3420
2 SA 1359	Si-P	LF, HF/S P, 40/40V, 3A, 10W, 100MHz	14b	TO-126Iso	2SC3422
2 SA 1371	Si-P	Vid, hi-def, 300/300V, 0,1/0,2A, 1W, 150MHz	7c(9mm)	TO-92L	2SC3468
2 SA 1381	Si-P	Vid P, hi-def, 300/300V, 0,1/0,2A, 7W, 150MHz	14h	TO-126	2SC3503
2 SA 1403	Si-P	Vid, hi-def, 80/60V, 0,5/1A, 10W, 800MHz	14h	TO-126	2SC3597
2 SA 1405	Si-P	Vid, hi-def, 120/120V, 0,3/0,6A, 8W, 500MHz	14h	TO-126	2SC3599
2 SA 1407	Si-P	Vid, hi-def, 200/200V, 0,15/0,3A, 7W, 400MHz	14h	TO-126	2SC3601
2 SA 1535 A	Si-P	HF, LF P, 180/180V, 1/1,5A, 15W, 200MHz	17c	SOT-186	2SC3944A
2 SA 1593	Si-P	S P, 120/100V, 2/3A, 15W, 120MHz, 80/790ns	30j	TO-251/252	2SC4135
2 SA 1606	Si-P	LF P, 180/160V, 1,5/3A, 15W, 100MHz	17c	TO-220 Iso	2SC4159
2 SB 754	Si-P	P, 50/50V, 7A, 60W, 10MHz, sat<0,4V(4A)	18j	TO-3P	2SD844
2 SB 772	Si-P	P, 40/30V, 3/7A, 10W, 80MHz, sat<0,5V(2A)	14h	TO-126	2SD882
2 SB 817	Si-P	P, 160/140V, 12/15A, 100W, 15MHz, 250/1140ns	18j	TO-3P	2SD1047
2 SB 826	Si-P	S P, 60/50V, 12/15A, 40W, 10MHz, lo-sat<0,5V(6A)	17j	TO-220	2SD1062
2 SB 829	Si-P	S P, 60/50V, 15/20A, 90W, 20MHz, lo-sat<0,5V(8A)	18j	TO-3P	2SD1065
2 SB 861	Si-P	LF P, TV-VA, 200/150V, 2/5A, 30W	17j	TO-220	2SD1138
2 SB 865	Si-P-Darl	80/50V, 1,5/3A, 0,9W, 120MHz, hFE=23k>4k	7c(9mm)	TO-92L	2SD1153
2 SB 892	Si-P	60/50V, 2/4A, 1W, 150MHz, sat<0,7V(1A)	7c(9mm)	TO-92L	2SD1207
2 SB 985	Si-P	Drv, 60/50V, 3/6A, 1W, 150MHz	7c(9mm)	TO-92L	2SD1347
2 SB 986	Si-P	=2SB985: 4/6A, 10W	14h	TO-126	2SD1348
2 SB 1018	Si-P	P, 100/80V, 7A, 30W, 10MHz, sat<0,5V(4A)	17c	SOT-186	2SD1411
2 SB 1020	Si-P-Darl+Di	P, 100/100V, 7/10A, 30W, hFE>2k, 0,8/4,5μs	17c	SOT-186	2SD1415
2 SB 1142	Si-P	P, 60/50V, 2,5/5A, 10W, 140MHz, lo-sat<0,5V(1A)	14b	TO-126 Iso	2SD1682
2 SB 1212	Si-P	LF, 160/160V, 1,5/3A, 0,9W, 50MHz	7c(9mm)	TO-92L	2SD1812
2 SB 1446	Si-P	Uni, 50/50V, 5/7A, 1W, 70MHz	9c		2SD2179
2 SC 1398	Si-N	P, 70/50(A=70/70)V, 2/3A, 15W, 120MHz	17j	TO-220	2SA748
2 SC 1413 A*	Si-N	TV-HA, 1500/500V, 5/16A, 50W, 4MHz, sat<10V(5A)	23a	TO-3	
2 SC 1505	Si-N	Vid P, 300/300V, 0,2/0,3A, 15W, 80MHz	17j	TO-220AB	
2 SC 1969	Si-N	AM P, 60/25V, 6A, 150MHz, PQ=16W(27MHz/12V)	17j	TO-220	

JAEGER	Constr.	Info	Fig.	Compl.
2 SC 1970	Si-N	VHF Drv,Out, 40/17V, 0,6A, PQ=1,3W(175MHz/13,5V)	17j	TO-220
2 SC 2078	Si-N	AM P, 80/75V, 3/5A, 150MHz, PQ>4W(27MHz/12V)	17j	TO-220
2 SC 2166	Si-N	HF P, 75V, 4A, PQ>6W(27MHz/12V)	17j	TO-220
2 SC 2334	Si-N	S P, 150/100V, 7/15A, 40W, <0,5/2µs	{2SA1010 17j	TO-220
2 SC 2466	Si-N	TV UHF Mx, 30/20V, 50mA, 2,2GHz, Gp=18dB(900MHz)	25p	≈SOT-103
2 SC 2570 A	Si-N	UHF, 25/12V, 0,07A, 5GHz, Gp=11,5dB(1GHz)	7f	TO-92
2 SC 2592	Si-N	P, 180/180V, 1/1,5A, 20W, 200MHz	17j	TO-220 2SA1112
2 SC 2632	Si-N	Uni, In, 150/150V, 50/100mA, 1W, 160MHz	{2SA1124 7c(9mm)	TO-92L 2SA1124
2 SC 2814(SMD)	Si-N	SMD, HF, 30/20V, 30mA, 320MHz, F=3/Gp=25dB(100MHz)	35a	SOT-23
2 SC 2834 A	Si-N	S-P, 900/500V, 7/15A, 100W, 3,5MHz, <1/3,5µs	18j	TO-3P
2 SC 2837	Si-N	P, 150/150V, 10A, 100W, 70MHz, 200/1750ns	18j	TO-3P 2SA1186
2 SC 3026	Si-N	TV-HA, 1700/800V, 6/16A, 50W, 1,5/5,5µs,sat<2V(5A)	23a	TO-3
2 SC 3071	Si-N	120/100V, hi-Ueb=15V, 0,2/0,3A, 150MHz	7c(9mm)	TO-92L
2 SC 3116	Si-N	TV Audio Out, 180/160V, 0,7/1,5A, 10W, 120MHz	14h	TO-126 2SA1248
2 SC 3117	Si-N	TV Audio Out, 180/160V, 1,5/2,5A, 10W, 120MHz	14h	TO-126 2SA1249
2 SC 3225	Si-N	40/40V, 2A, 220MHz, hi-hFE>500, lo-sat<0,5V(0,3A)	7c(9mm)	TO-92L
2 SC 3263	Si-N	LFS P, 230/230V, 15A, 130W, 60MHz	18j	TO-3P 2SA1294
2 SC 3264	Si-N	LFS P, 230/230V, 17A, 200W, 60MHz	20j	(MT-200) 2SA1295
2 SC 3281	Si-N	HiFi LF Out, 200/200V, 15A, 150W, 30MHz	77j	TOP-3L 2SA1302
2 SC 3299	Si-N	DC-DC Con., 60/50V, 5A, 20W, 120MHz, sat<0,4V(3A)	17c	SOT-186 2SA1307
2 SC 3303	Si-N	100/80V, 5/8A, 20W, 120MHz,200/1100ns,sat<0,4V(3A)	30j	TO-251/252
2 SC 3346	Si-N	P,80/80V, 12A, 40W, 80MHz, sat<0,4V(6A),200/1200ns	17j	TO-220 2SA1329
2 SC 3355	Si-N	UHF, 20/12V, 0,1A, 0,6W, 6,5GHz, F<3dB(1GHz)	7f	TO-92
2 SC 3356(SMD)	Si-N	SMD, UHF, 20/12V, 0,1A, 7GHz, F<2dB(1GHz)	35a	SOT-23
2 SC 3420	Si-N	50/20V, 5/8A, 10W, 100MHz, sat<1V(4A)	14b	TO-126 Iso 2SA1357
2 SC 3422	Si-N	LF,HF/S P, 40/40V, 3A, 10W, 100MHz	14b	TO-126 Iso 2SA1359
2 SC 3457	Si-N	S P, 1100/800V, 3/10A, 50W, 15MHz, <0,5/3,3µs	17j	TO-220
2 SC 3459	Si-N	S P, 1100/800V, 4,5/15A, 90W, 15MHz, <0,5/3,3µs	18j	TO-3P
2 SC 3461	Si-N	S P, 1100/800V, 8/25A, 140W, 15MHz, <0,5/3,3µs	18j	TO-3P
2 SC 3466	Si-N	S P, 1200/650V, 8/20A, 120W, 5MHz, <1/4,7µs	18j	TO-3P
2 SC 3468	Si-N	Vid, hi-def, 300/300V, 0,1/0,2A, 1W, 150MHz	7c(9mm)	TO-92L 2SA1371
2 SC 3503	Si-N	Vid-L, hi-def, 300/300V, 0,1/0,2A, 7W, 150MHz	14h	TO-126 2SA1381
2 SC 3504	Si-N	Vid,hi-def, 70/60V, 50/100mA, 0,9W, 500MHz	{2SA1433 7c(9mm)	TO-92L
2 SC 3597	Si-N	S-L, 900/500V, 5/10A, 40W, 8MHz, <1,2/4,2µs	14h	TO-126 2SA1403
2 SC 3599	Si-N	Vid,hi-def, 120/120V, 0,3/0,6A, 8W, 500MHz	14h	TO-126 2SA1405
2 SC 3601	Si-N	Vid, hi-def, 200/200V, 0,15/0,3A, 7W, 400MHz	14h	TO-126 2SA1407
2 SC 3688	Si-N	TV-HA, hi-def, 1500/800V, 10/25A, 150W, sat<5V(8A)	18j	TO-3P
2 SC 3752	Si-N	S P, 1100/800V, 3/10A, 30W, 15MHz, <500/3300ns	17c	TO-220 Iso
2 SC 3782	Si-N	Vid,hi-def,200/200V, 0,2/0,3A, 15W, 400MHz	{2SA1476 17j	TO-220
2 SC 3795 A	Si-N	S-L, 900/500V, 5/10A, 40W, 8MHz, <1,2/4,2µs	17c	SOT-186
2 SC 3808	Si-N	80/60V, hi-Ueb=15V, 2/4A, 15W, 170MHz,sat<0,5V(1A)	≈14h	(TO-126LP)
2 SC 3944(A)	Si-N	LF,HF P, 180/180V, 1/1,5A, 15W, 200MHz	17c	SOT-186 2SA1535A
2 SC 4135	Si-N	P, 120/100V, 2/3A, 15W, 120MHz, 80/1050ns	30j	TO-251/252 2SA1593
2 SC 4159	Si-N	P, 180/160V, 1,5/3A, 15W, 100MHz	17c	TO-220 Iso 2SA1606
2 SC 4237	Si-N	S P, 1200/800V, 10A, 150W, 8MHz, <0,5/3,8µs	16j	(MTO-3P)
2 SC 4924	Si-N	Display-HA, 1500/800V, 10/25A, 70W, sat<5V(8A)	18c	TO-3P Iso
2 SD 350 A*	Si-N	TV-HA, 1500/700V, 5/11A, 22W(Tc=90°), sat<7V(4,5A)	23a	TO-3
2 SD 725	Si-N	TV-HA, 1500/600V, 6A, 50W, sat<5V(5A)	23a	TO-3
2 SD 774	Si-N	Uni, 100/50V, 1A, 1W, 95MHz	{2SB734 9b	
2 SD 798	Si-N-Darl	S P, 600/300V, 6A, 30W, hFE>1500, 1/13µs	17j	TO-220
2 SD 844	Si-N	P, 50/50V, 7A, 60W, 15MHz, sat<0,4V(4A)	18j	TO-3P 2SB754
2 SD 882	Si-N	P, 40/30V, 3/7A, 10W, 90MHz, sat<0,5V(2A)	14h	TO-126 2SB772
2 SD 947	Si-N-Darl	P, 40V, 2A, 5W, 150MHz, hFE>4000	14b	TO-126 Iso
2 SD 986	Si-N-Darl+Di	P, 150/80V, ±1,5/3A, 10W, hFE=2k...30k	{2SB795 14h	TO-126
2 SD 1047	Si-N	P,160/140V, 12/15A, 100W, 15MHz, 200/7560ns	18j	TO-3P 2SB817
2 SD 1062	Si-N	S P, 60/50V, 12/15A, 40W, 10MHz, lo-sat<0,4V(6A)	17j	TO-220 2SB826
2 SD 1065	Si-N	S P, 60/50V, 15/20A, 90W, 10MHz, lo-sat<0,4V(8A)	18j	TO-3P 2SB829
2 SD 1138	Si-N	LF P, TV-VA, 200/150V, 2/5A, 30W	17j	TO-220 2SB861
2 SD 1153	Si-N-Darl	80/50V, 1,5/3A, 0,9W, hFE>4000, 120MHz	7c(9mm)	TO-92L 2SB865
2 SD 1207	Si-N	60/50V, 2/4A, 1W, 150MHz, sat<0,4V(1A)	7c(9mm)	TO-92L 2SB892
2 SD 1273	Si-N	80/60V, 3/6A, 40W, 50MHz, hi-hFE=500...2500	17c	SOT-186
2 SD 1279	Si-N	TV-HA, 1400/600V, 10A, 50W, 3MHz, sat<5V(8A)	23a	TO-3
2 SD 1347	Si-N	60/50V, 3/6A, 1W, 150MHz, sat<0,5V(2A)	7c(9mm)	TO-92L 2SB985
2 SD 1348	Si-N	=2SD1347: 4/6A, 10W	14h	TO-126 2SB986
2 SD 1409	Si-N-Darl+Di	S P, 600/400V, 6A, 25W, hFE=1000>600, 1/13µs	17c	SOT-186
2 SD 1411	Si-N	P, 100/80V, 7A, 30W, 10MHz, sat<0,5V(4A), 0,4/3µs	17c	SOT-186 2SB1018
2 SD 1415	Si-N-Darl+Di	P, 100/100V, 7A, 30W, hFE=2k...15k, 0,8/5,5µs	17c	SOT-186 2SB1020
2 SD 1555	Si-N+Di	TV-HA, 1500/600V, 5A, 50W, 3MHz, sat<5V(5A)	18c	TO-3P Iso
2 SD 1577	Si-N	TV-HA, 1500/700V, 5/17A, 100W, 2MHz, sat<2V(4,5A)	16c	(TOP-3F)
2 SD 1680	Si-N	TV-HA,S P, 330/200V, 7/10A, 70W, 30MHz, sat<1V(5A)	16c	(TOP-3F)
2 SD 1682	Si-N	S P, 60/50V, 2,5/5A, 10W, 140MHz, lo-sat<0,3V(1A)	14b	TO-126 Iso 2SB1142
2 SD 1756	Si-N-Darl	P, 200/200V, 10/15A, 40W, hFE>1500, 0,9/11,5µs	17j	TO-220
2 SD 1812	Si-N	LF Drv,Out, 160/160V, 1,5/3A, 0,9W, 80MHz	7c(9mm)	TO-92L 2SB1212
2 SD 2179	Si-N	Uni, 50/50V, 5/7A, 1W, 80MHz	9c	2SB1446
2 SK 727	MOS-N-FET-e	VFET, 900/20V, 5A, 125W, on<2,5Ω(2,5A), 110/420ns	18p	TO-3P

JAEGER	Constr.	Info	Fig.	Compl.
78L05/TO-92	Z-IC	+5V, 0,1A	7b	TO-92
78L08/TO-92	Z-IC	+8V, 0,1A	7b	TO-92
78L12/TO-92	Z-IC	+12V, 0,1A	7b	TO-92
78L15/TO-92	Z-IC	+15V, 0,1A	7b	TO-92
79L05/TO-92	Z-IC	-5V, 0,1A	7a	TO-92
79L12/TO-92	Z-IC	-12V, 0,1A	7a	TO-92
318/8-D*	OP-IC	hi-speed, Serie 118, ±20V, 0...+70°	8-DIP	
723/14-D	Z-IC	=723/TO: Fig. →	14-DIP	
723/TO	Z-IC	+2...+37V, 0,15A	TO-100	
741/8-D	OP-IC	=741/TO: Fig. →	8-DIP	
741/TO	OP-IC	Uni, Serie 741, ±18V, 0...+70°	TO-99	
747/14-D	OP-IC	=747/TO: Fig. →	14-DIP	
747/TO	OP-IC	Dual, Serie 747, ±18V, 0...+70°	TO-100	
748/14-D	OP-IC	=748/TO: Fig. →	14-DIP	
748/8-D	OP-IC	=748/TO: Fig. →	8-DIP	
748/TO	OP-IC	Uni, Serie 748, ±18V, 0...+70°	TO-99	
4001 (C-MOS)	CMOS-Logic	4x NOR, 2 Eing./2 Inputs	14-DIP	
4002 (C-MOS)	CMOS-Logic	2x NOR, 4 Eing./4 Inputs	14-DIP	
4011 (C-MOS)	CMOS-Logic	4x NAND, 2 Eing./2 Inputs	14-DIP	
4013 (C-MOS)	CMOS-Logic	2x D-Flipflop	14-DIP	
4015 (C-MOS)	CMOS-Logic	2x 4Bit-Schieberegister/Shift Register	16-DIP	
4017 (C-MOS)	CMOS-Logic	5stuf. Johnson-Zähler/Counter	16-DIP	
4021 (C-MOS)	CMOS-Logic	8Bit-Schieberegister/Shift Register, static	16-DIP	
4023 (C-MOS)	CMOS-Logic	3x NAND, 3 Eing./3 Inputs	14-DIP	
4024 (C-MOS)	CMOS-Logic	7 Bit Binärzähler/Ripple Counter	14-DIP	
4025 (C-MOS)	CMOS-Logic	3x NOR, 3 Eing./3 Inputs	14-DIP	
4027 (C-MOS)	CMOS-Logic	Dual JK-Flipflop	16-DIP	
4028 (C-MOS)	CMOS-Logic	BCD/Dezimal-Decoder	16-DIP	
4029 (C-MOS)	CMOS-Logic	Up/down Counter	16-DIP	
4030 (C-MOS)	CMOS-Logic	4x EXOR	14-DIP	
4040 (C-MOS)	CMOS-Logic	12stuf. Binär-Zähler/Binary Counter	16-DIP	
4049 (C-MOS)	CMOS-Logic	Hex Inverter Buffer	16-DIP	
4050 (C-MOS)	CMOS-Logic	Hex non-inverting Buffer	16-DIP	
4052 (C-MOS)	CMOS-Logic	Dual-Multiplexer	16-DIP	
4053 (C-MOS)	CMOS-Logic	3x 2-Kanal/Channel Analog Multiplexer	16-DIP	
4060 (C-MOS)	CMOS-Logic	14stuf. Zähler/Counter	16-DIP	
4066 (C-MOS)	CMOS-Logic	4x Analogschalter/Analog Switch	14-DIP	
4069 (C-MOS)	CMOS-Logic	Hex-Inverter	14-DIP	
4070 (C-MOS)	CMOS-Logic	4x EXOR, 2 Eing./2 Inputs	14-DIP	
4071 (C-MOS)	CMOS-Logic	4x OR, 2 Eing./2 Inputs	14-DIP	
4081 (C-MOS)	CMOS-Logic	4x AND, 2 Eing./2 Inputs	14-DIP	
4093 (C-MOS)	CMOS-Logic	4x NAND-Schmitt-Trigger	14-DIP	
4094 (C-MOS)	CMOS-Logic	8-Bit Universal-Busregister	16-DIP	
4098 (C-MOS)	CMOS-Logic	2x monostab. Multivibrator	16-DIP	
4503 (C-MOS)	CMOS-Logic	6x Puffer/Buffer (3-state)	16-DIP	
4512 (C-MOS)	CMOS-Logic	8-Kanal Datenselektor/8-Channel Selector	16-DIP	
4516 (C-MOS)	CMOS-Logic	Up/down Zähler/Counter	16-DIP	
4518 (C-MOS)	CMOS-Logic	Dual BCD-Zähler/Counter	16-DIP	
4539 (C-MOS)	CMOS-Logic	2x 4 → 1 Multiplexer	16-DIP	
4541 (C-MOS)	CMOS-Logic	Programmable Osc./Timer	14-DIP	
4558/8-D	OP-IC	Dual, Serie 158, ±18V, 0...+70°	8-DIP	
4584 (C-MOS)	CMOS-Logic	6x Schmitt-Trigger	14-DIP	
7805/TO-3	Z-IC	+5V, 2,2A	23a	TO-3
7805/TO-220	Z-IC	+5V, 1,5A	17b	TO-220
7805/Iso TO-220	Z-IC	Iso, +5V, 1A	17b	TO-220 Iso
7806/TO-220	Z-IC	+6V, 1,5A	17b	TO-220
7808/TO-220	Z-IC	+8V, 1,5A	17b	TO-220
7809/TO-220	Z-IC	+9V, 1,5A	17b	TO-220
7810/TO-220	Z-IC	+10V, 1,5A	17b	TO-220
7812/TO-3	Z-IC	+12V, 2,2A	23a	TO-3
7812/TO-220	Z-IC	+12V, 1,5A	17b	TO-220
7812/Iso TO-220	Z-IC	Iso, +12V, 1A	17b	TO-220 Iso
7815/TO-220	Z-IC	+15V, 1,5A	17b	TO-220
7815/Iso TO-220	Z-IC	Iso, +15V, 1A	17b	TO-220 Iso
7818/TO-220	Z-IC	+18V, 1,5A	17b	TO-220
7818/Iso TO-220	Z-IC	Iso, +18V, 1A	17b	TO-220 Iso
7820/TO-220	Z-IC	+20V, 1,5A	17b	TO-220
7824/TO-220	Z-IC	+24V, 1,5A	17b	TO-220
7824/Iso TO-220	Z-IC	Iso, +24V, 1A	17b	TO-220 Iso
7905/TO-220	Z-IC	-5V, 1,5A	17c	TO-220
7912/TO-220	Z-IC	-12V, 1,5A	17c	TO-220
7915/TO-220	Z-IC	-15V, 1,5A	17c	TO-220
17088(H)*	F-Thy+Di	TV-HA, Hinlauf/Trace, 900V; 5A	17f	TO-220
17089(R)*	F-Thy+Di	TV-HA, Rücklauf/Retrace, 900V, 5A	17f	TO-220
17127*	Thy		17e	TO-220

JAEGER	Constr.	Info	Fig.	Compl.
μPC 555(H)***	LIN-IC	HF, IF, 10....150MHz, Ucc=12V	7-SIP	
μPC 575 C2*	LIN-IC	LF Out, 20V, 1A, 2W(13,2V/8Ω)	8-DIP+h	
μPC 577(H)***	LIN-IC	FM IF, Ucc=10V	7-SIP	
μPC 1024(H)*	LIN-IC	NF Inp, In, Ucc=35V, >87dB(1kHz)	7-SIP	
μPC 1025(H)***	LIN-IC	LF Out, 17V, 2,5A, 4,8W(13,2V/4Ω)	10-SIL	
μPC 1032(H)*	LIN-IC	2x LF Inp In, Ucc=13,2V	8-SIP	
μPC 1183(H)***	LIN-IC			
μPC 1212(C)*	LIN-IC	LF Out, Ucc=3,5...V, 1W(6V/4Ω)	8-DIP+g	
μPC 1213(C)	LIN-IC	LF Out, Ucc=4,5...11V, 2,4W(9V/4Ω)	8-DIP+g	
μPC 1277 H	LIN-IC		12-SIL	
μPC 1350(C)*	LIN-IC	LF In/Out, ALC, 0,45W(6V/8Ω)	14-DIP+g	
μPC 1353(C)***	LIN-IC	TV, Sound IF, LF In/Out, 2,4W	14-DIP+g	
μPC 1363(C)***	LIN-IC	TV, 16x Touch Sensor, LED Drv	24-SDIP	
μPC 1365(C)	LIN-IC	CTV, PAL Decoder, Chroma, RGB Out	28-DIP	
μPC 1377	LIN-IC	CTV, Sync. Combination, Stabi, AFC, Ucc=12V	22-DIP	
μPC 1391(H)*	LIN-IC	TV, Sound IF	8-SIP	
μPC 1488	IC	TV-VA		