

Errata for MIPS R4000/R4400 Microprocessor User's Manual, 2nd. Edition

This errata supplements the "MIPS R4000/R4400 User's Manual, 2nd Edition" by
Joe Heinrich

November 8, 1994

MIPS Technologies Inc.
1225 Charleston Road

Mountain View, CA 94043-1353

This document contains information that is proprietary to MIPS Technologies, Inc.

MIPS Technologies, Inc. reserves the right to change any products described herein to improve the function or design. MIPS Technologies, Inc. does not assume any liability arising out of the application or use of any product or circuit described herein; neither does it convey any license under patent rights nor imply the rights of others.

Copyright 1994 by MIPS Technologies, Inc. All rights reserved.

Page 229

At the end of the section titled SyncIn/SyncOut, add the following:

The delay allowed between the SyncOut and SyncIn must be no more than $[1/2 * \text{MasterClock cycle} - 2\text{nS}]$

Page 319

In Table 12-3, for Page Attribute "Exclusive" the Processor Configuration should be only R4000MC (remove "R4000SC")

Page 338

At the end of the sentence in the ninth line: "Figures 12-24 through 12-27 illustrate below. Add the following sentence: "All the waveforms are shown with zero delay from the SClock's rising edge; i.e. outputs are driven by the processor at the corresponding rising edge and inputs are driven by the external logic at the corresponding rising edge of the SClock.

Also at the end of the paragraph describing Figure 12-24: "Figure 12-24 illustrates WrRdy*. Add the following sentence: "In this example, the WrRdy* must be deasserted in cycle 5 (sampled by the processor at the rising edge of cycle 6) to delay the issue cycle that would have occurred in cycle 7. Assertion of WrRdy* in cycle 8 (sampled by the processor at the rising edge of cycle 9) will cause the Write Request to be issued in cycle 10.