



ON Semiconductor®

<http://onsemi.com>

Power-Up and Power-Down Characteristics for Digitally Programmable Potentiometers (DPP™)

Prepared by: Chuck Wojslaw,
Director of Applications Engineering
ON Semiconductor

ABSTRACT: This design note discusses what happens when power (V_{CC}) is applied or removed from a digitally programmable potentiometer in an application circuit.

Turn-on and Power-on-Recall (POR): CAT 5111-5114

Power-up means a bias supply voltage is applied to the DPP's V_{CC} pin and it rises from 0 V to a final value. The range of operating values for V_{CC} is 2.5 V to 6 V. During power-up, an internal power on recall (POR) circuit transfers the stored wiper setting from nonvolatile memory to the wiper control register. Some of the industry's electronic potentiometers are designed such that their power on recall (POR) function will only be initiated if the slope of the applied V_{CC} voltage is linear, continuous, and falls between a certain minimum and maximum value. The POR circuit for ON Semiconductor's potentiometers (CAT5111-5114) will trip at a fixed voltage (1.2 V maximum) and is not rate/slope dependent.

For a successful turn-on operation, V_{CC} MUST start below 100 mV. When V_{CC} rises to 1.2 V, a power on reset

condition (1 msec) is initiated in the DPP during which time the contents of nonvolatile memory are transferred to the wiper control register.

The DPP is fully functional and will meet all data sheet specifications when V_{CC} is at 2.5 V AND 1msec has elapsed after V_{CC} reached 1.2 V.

During power-up, $V_W, V_L, V_H < V_{CC}$.

Turn-off and Brown-out: CAT 5111-5114

(a) If V_{CC} drops below its nominal value (2.5 V-6 V) but stays above 1.2 V and then returns back to its nominal value, the device is fully functional and meets all specs. (b) If V_{CC} drops below its nominal value to a value between 0.1 V and 1.2 V, and then returns to its nominal value, the DPP wiper will, more than likely, NOT return to its previous condition/state.

(c) To ensure a successful re-start or a new power-up case, V_{CC} MUST be driven below 100mV and then brought up again.

APPLICATION NOTE

DPP is a trademark of Semiconductor Components Industries, LLC (SCILLC).

ON Semiconductor and **ON** are registered trademarks of Semiconductor Components Industries, LLC (SCILLC). SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the SCILLC product could create a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application, Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor
P.O. Box 5163, Denver, Colorado 80217 USA
Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada
Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada
Email: orderlit@onsemi.com

N. American Technical Support: 800-282-9855 Toll Free
USA/Canada
Europe, Middle East and Africa Technical Support:
Phone: 421 33 790 2910
Japan Customer Focus Center
Phone: 81-3-5773-3850

ON Semiconductor Website: www.onsemi.com
Order Literature: <http://www.onsemi.com/orderlit>

For additional information, please contact your local
Sales Representative