

Series 2000 Micro Reader

Description

The Series 2000 Micro Reader is an intelligent module that provides all RF and control functions in order to communicate with 134.2 kHz HDX/FSK transponders and a host application. It is designed as a 30-pin Dual-in-line printed circuit board. The Series 2000 Micro Reader is equipped with a serial communication interface and works together with a 47 μ H low-Q antenna that eliminates the need to tune the system to resonance.



Specifications:

Part Number	RI-STU-MRD1
Operating Temperature	-20° to +50°C
Storage Temperature	-40° to +85°C
Relative Humidity	<97% non-condensing, IEC 68-2-30 Test Db, 21 cycles
RF Transmit Frequency	134.2 kHz
Power Supply	5 Vdc, regulated
Typical Current Consumption	Active mode: 100 mA Idle mode: 5 mA
Host Communication	Point-to-Point
Communications Parameters	9600 baud, 8 data bits, no parity, 1 start bit, 1 stop bit
Communications Protocol	Micro Reader specific communications protocol with Xon / Xoff handshake
Communications Interface	Serial Communications Interface (SCI), TTL voltage level
Reader Interference Protection	Wireless and wired synchronization
Antenna	47 μ H, Q 10 – 20
Typical Read Time	Without synchronization: 100 ms With synchronization: 120 ms
Transponder Types	134.2 kHz HDX/FSK
Package	30-pin Dual-in-line for plug- or to solder-in
Reference Documentation	11-06-21-027 Reference Guide S2000 Reader System Micro Reader RI-STU-MRD1
Dimensions	(38.3 mm x 29.3 mm x 13.5 mm) \pm 0.5 mm
Weight	approx. 5 g
Approval	CE, FCC

For more information, contact the sales office or distributor nearest you. This contact information can be found on our web site at: <http://www.ti-rfid.com>

Texas Instruments reserves the right to change its products and services at any time without notice. TI provides customer assistance in various technical areas, but does not have full access to data concerning the uses and applications of customers products. Therefore, TI assumes no responsibility for customer product design or for infringement of patents and/or the rights of third parties, which may result from assistance provided by TI.