



Si7114ADN vs. Si7114DN

Description: N-Channel, 30-V (D-S) MOSFET

Package: PowerPAK® 1212-8

Pin Out: Identical

Part Number Replacements: Si7114DN-T1-GE3 replaces Si7114ADN-T1-E3
Si7114DN-T1-GE3 replaces Si7114ADN-T1-GE3

ABSOLUTE MAXIMUM RATINGS $T_A = 25\text{ }^\circ\text{C}$, unless otherwise noted					
PARAMETER	SYMBOL	Si7114ADN	Si7114DN	UNIT	
Drain-Source Voltage	V_{DS}	30	30	V	
Gate-Source Voltage	V_{GS}	± 20	± 20		
Continuous Drain Current	I_D	$T_A = 25\text{ }^\circ\text{C}$	18	18.3	A
		$T_A = 70\text{ }^\circ\text{C}$	16	14.7	
Pulsed Drain Current	I_{DM}	60	60		
Continuous Source Current (MOSFET Diode Conduction)	I_S	3.2	3.2		
Power Dissipation	P_D	$T_A = 25\text{ }^\circ\text{C}$	3.7	3.8	W
		$T_A = 70\text{ }^\circ\text{C}$	2.4	2.0	
Operating Junction and Storage Temperature Range	T_J and T_{stg}	- 55 to 150	- 55 to 150	$^\circ\text{C}$	
Maximum Junction-to-Ambient	R_{thJA}	34	33	$^\circ\text{C/W}$	

SPECIFICATIONS $T_J = 25\text{ }^\circ\text{C}$, unless otherwise noted								
PARAMETER	SYMBOL	Si7114ADN			Si7114DN			UNIT
		MIN.	TYP.	MAX.	MIN.	TYP.	MAX.	
Static								
Gate-Threshold Voltage	$V_{GS(th)}$	1.0		2.5	1.0		3.0	V
Gate-Body Leakage	I_{GSS}			± 100			± 100	nA
Zero Gate Voltage Drain Current	I_{DSS}			1			1	μA
On-State Drain Current	$V_{GS} = 10\text{ V}$ $I_{D(on)}$	20			40			A
Drain-Source On-Resistance	$V_{GS} = 10\text{ V}$ $R_{DS(on)}$		0.0062	0.0075		0.0062	0.0075	Ω
	$V_{GS} = 4.5\text{ V}$		0.0081	0.0100		0.0081	0.0100	
Forward Transconductance	g_{fs}		50			77		S
Diode Forward Voltage	V_{SD}		0.8	1.2		0.7	1.2	V
Dynamic								
Total Gate Charge	Q_g		10.2	20		12.5	19	nC
Gate-Source Charge	Q_{gs}		3.9			6.3		
Gate-Drain Charge	Q_{gd}		3.2			3.6		
Gate Resistance	R_g	0.3	1.6	3.2	0.7	1.4	2.1	Ω

Specification comparisons are supplied as a courtesy to compare two devices and do not constitute a commercial product datasheet or any guarantee of identical performance. Designers should refer to the appropriate datasheets of the same number for guaranteed specification limits.