

ICOM COMMUNICATION INTERFACE CI-IV/CI-V CONVERTER

UX-14

INSTRUCTION MANUAL

この取扱説明書は英文と共用です。 日本語については18ページからご覧 ください。

INTRODUCTION


The UX-14 CI-IV/CI-V CONVERTER is designed for converting an ICOM communication I/O port from a CI-IV (Parallel I/O port) to the advanced CI-V (Serial I/O port).

The ICOM COMMUNICATION INTERFACE-V (CI-V) SYSTEM is a remote control local area network with CSMA/CD (Carrier Sense Multiple Access with Collision Detection) standard, allowing easy computer control of a variety of modern ICOM equipment.

TABLE OF CONTENTS

•	BLC	OCK	DIA	٦GF	RAM						•			1
•	INS	TAL	LAT	ΓΙΟΙ	N									2
•	SET	TIN	G D)IP	SWI	ТСН	ES.							8
	(1)	SE.	TTIN	١G	THE	S1	SV	VITC	. H					10
	(2)	SE'	TTIN	١G	THE	S2	SV	VITO	. H					12
•	OPE	RA	TIOI	V E	XAN	/IPLE	ES .		•					13
	(1)	CO	NTF	ROL	US	ING	Α	CO	MP	U-	ΓΕ	R.		13
	(2)	TR	ANS	SCE	IVE	OPE	ERA	ATIC	N(14
	(3)	SA	TEL	LIT	E O	PER	AT	ION						14
	(4)	АН	-2 <i>F</i>	TNA	ENN	IA 1	run	NER						
		OP	ERA	TIC	ON.				•				• .	15

BLOCK DIAGRAM




INSTALLATION

The following radios are equipped with a CI-IV I/O port and can be converted for CI-V use with the UX-14:

- ① IC-R71A, IC-R71E, IC-R71D
- ② IC-271A, IC-271E, IC-271H
- ③ IC-471A, IC-471E, IC-471H
- 4 IC-751, IC-751A
- ⑤ IC-1271A, IC-1271E

CAUTION: Unplug the power cable before performing any work on the radio.




- 1) Set the S1 and S2 SWITCHES according to your particular radio requirements. See section SETTING DIP SWITCHES below.
- 2) Remove the bottom cover of the radio.
- 3) Orient the unit correctly and use the supplied screws.
- 4) Remove the metal plate or rubber cover attached to the rear panel and pass the connector inward onto the bottom side.

 The metal plate with a remote jack (ACC plate) should be attached with screws. (Install the ACC plate with the supplied screws and nuts if the rear panel holes are not threaded.)


Refer to the diagrams for proper installation.

5) Connect two plugs from the unit to connectors on the radio as shown in each diagram.


- Connection with IC-R71A/E/D receivers.
- ●接続方法 IC-R71
- UX-14 J10 (9-pin) LILLILLIL ACC plate LOGIC UNIT
- Connection with IC-271A/E, IC-471A/E and IC-1271A/E transceivers.
- ●接続方法 IC-271, IC-371, IC-1271




- Connection with IC-471H and IC-271H transceivers.
- ●接続方法 IC-271D, IC-371D



- Connection with IC-751 and IC-751A transceivers.
- ●接続方法 IC-750/S, IC-750A/AS



SETTING DIP SWITCHES




CAUTION: All dip switches MUST be set before installing the UX-14

 The following are example switch positions for \$1 and \$2.


S1: Baud rate is 1200bps, transceive function is ON for IC-1271A/E.

S2: Address is set at 24H (36) for IC-1271A/E.





S2 SWITCH



DIP SV	WITCH	FUNCTION		
	1 2	These switches can select baud rate (data transfer rate). See Table 3.		
S1 SWITCH	3	This switch turns ON and OFF the transceive operation. See Table 4.		
	4	These switches set the band		
	5	for each radio and MUST be set before turning ON power		
	6	to the radio.		

Table 1 S1 SWITCH designation.

• Bracketed figures () are decimals and figures marked with an H are hexadecimals.

DIP SWI	ТСН	FUNCTION
S2 SWITCH	1~6	These switches are designated for CI-V addresses. An address can be selected from 01H \sim 3FH (01 \sim 63). For your convenience we recommend setting the radios to the ICOM standards shown in Table 6.

Table 2 S2 SWITCH designation.

(1) SETTING THE S1 SWITCH

• DIP SWITCHES 1 AND 2

NOTE: The standard ICOM CI-V baud rate is 1200bps.

S1 SV	VITCH	BAUD RATE
1	2	(bps)
OFF	OFF	
ON	OFF	9600
OFF	ON	1200
ON	ON	300

Table 3 Baud rate setting.

• DIP SWITCH 3

S1 SWITCH	FUNCTION
ON	Activates transceive operation. Data are sent out when each parameter is changed.
OFF	For independent control using a personal computer. Data are sent out when commands are received.

Table 4 Transceive operation ON-OFF.

9
AND
ro
HES 4
TCHI
SWI
OPP

	S1	S1 SWITCH	I	TYPE OF RADIO	
	4	5	9	RADIO	BAND
*	OFF	OFF	*(1) OFF OFF	IC-751, IC-751A	
8	*(2) OFF ON	NO	OFF	IC-R71A, IC-R71E, IC-R71D	! :
(O)	OFF	OFF OFF ON	NO	IC-751, IC-751A	÷
4	4 OFF ON	NO	NO	IC-R71A, IC-R71E, IC-R71D	
2	ON OFF ON	OFF	NO	IC-271A, IC-271E, IC-271H	144MHz
9	NO	NO	OFF	IC-471A, IC-471E, IC-471H	430MHz
0	ON	NO	NO	IC-1271A, IC-1271E	1.2GHz

300000			
		₩	
1000		7	
		*	Tusing the transceive operation
)	U .	
1000		~	0
1000		<u> </u>	
			ш
		—	-
I		U	•••
		"	•
U	•	•	വ
	Ħ.	41	
	•	u	
		<u></u>	
	•	m .	U
- C	•	•	
			വ
	•	~	
		n	7
	٠.	×	-
7			ധ
	2	O	7
l		•	•
		•	ഗ
			•
	1	(7) ···	a.
		1)	
L.			
l L			
l 💮			
.,,		35)	ധ
)	7	-
	2000 <u>u</u>		
W 6	1 V		
	2 ×		m
C			*
) L	L	
		•	10
		A	
LL.) 🔍	<i>-</i>	
	2		
()			
		60000000000000000000000000000000000000	· ·
88 Y		<u></u>	
N		7 4	
7	Ö) 4	-
7	. () 4 	_
7 3	, (_ L	n n
7 30	` (20-
7 301	E 1) 	しいり
hes 2	751	10 k 0 k	L C つ /
7 says	754	727.5	100/-
7 sayu	754	0 10/-	100/-
tches 4	751	0 10/7	165/-0
iitches 2	751		こ・/ らり
witches 2	10.754	コーラインコード・コーラー・コーラー・コーラー・ファイン・ファイン・ファイン・コード・コード・コード・コード・コード・コード・コード・コード・コード・コード	105/-01
witches 2	10.754	0 10/51	105/-21
switches 2	10 764	0 10/-51-	105/-21 a
switches 2	10 764		1007-01 at
Switches 4	n 10 751 c.		TC57-21 all
n switches 4	on 10 751 c.	10-701 O	TCSY-OL alli
in switches 2	hop IC 7Et al	161 15-73T U	100/-01 am
in switches 2	hop IC 7E1	ALERI 10-73F C	Test-or am c
Din switches 2	when 10 7Et al	Mileti 10-731 0	.o une IC-735 T
Din switches 2	whom 10 7Et al	Witch 10-73F 0	10 the 10-733 th
Din switches 2	whom IC 7E1 c.	Wileli 10-73F C	U une 10-735 TC
: Din switches 4	whom IC 751 c.	Wileli IC-73F 0	to the IC-735T
: Din switches	whom IC 751 co		Tee/-21 am of
T: Din switches	whom IP 7E1 a	WHEN IC-73F O	no me IC-/35 T
IT: Din switches 2	whom IC 751	0 167-51 USHW	10 me 10-733 T
VT: Din switches	whom IC 7E1	0 167-51 1545 t	10 the 10-735 t
NT: Dip switches 4	whom IC 751	0 167-51 Hallw	106/-01 am o
ANT: Dip switches	whom IC 751	0 107-01 House	to the IC-735T
ANT: Din switches 4	whom IC 751	O 167-01 IONA	166/-21 am oi
"ANT: Dip switches 4	100 100 100 100 100 100 100 100 100 100	O 167-OI Hallw	100 me 10-733 T
TANT: Dip switches 4	whom 10 751	O 167-21 Olivers	to the IC-733 t
TANT: Din switches	(C)		1667-21 am 01
STANT: Dip switches	"Show IC 7E4"	O 167-OI Hallw	TCC/-22 I
BTANT : Dip switches 2	whom IC 754	O 167-OL Hallow	10 the 16-735 T
ORTANT: Dip switches 2	whom IC 7E4	O TEXTOT HELIAM	TCS/-OLBIN OL
ORTANT: Dip switches	whom IC 751	0 167-01 Hallw	10 the 10-735 t
OBTANT: Dip switches	whom IC 751 c.	O IG/-OI HAHM	1 GS/-21 am 01
PORTANT: Dip switches 2	whom IC 751 a	0 167-01 Hallon	166/-21 am 01
PORTANT: Din switches 4	whom IC 751 c.	O 167-01 Hallw	1 CS/-31 am 01
MPORTANT: Dip switches 4	whom IC 7E1 an IC D74 contact of the	0 167-01 Hallw	1 CS/-51 all 01

2 pa

able 5 Radio type setting.

(2) SETTING THE S2 SWITCH

The S2 SWITCH consists of six dip switches. These switches are designated for CI-V addresses which can be selected from $01H \sim 3FH (1 \sim 63)$.

The following addresses in Table 6 are ICOM standard addresses. Set the addresses for each radio as shown in the diagrams.

NOTE: Address 00H (00) is inhibited since it is already reserved for another function.


RADIO	ADDRESS	SWITCH SETTING
IC-751/A	1CH (28)	ON
IC-R71A/E/D	1AH (26)	ON
IC-271A/E/H	20H (32)	ON
IC-471A/E/H	22H (34)	ON
IC-1271A/E	24H (36)	ON

Table 6 CI-V addresses recommended.

(1) CONTROL USING A COMPUTER

The radios listed above can be controlled by using an optional CT-17 CI-V LEVEL CONVERTER with a computer equipped with an RS-232C I/O port. CT-17 can be connected to a maximum of 4 radios.


• Frequency, mode and memory channels can be controlled.



Controlling a radio using a personal computer through the CT-17.

(2) TRANSCEIVE OPERATION


Each radio frequency can track another when two or more of the same band transceivers in series are connected using the CI-V R'EMOTE JACK. Dip switch 3 on S1 must be placed in the ON position.



(3) SATELLITE OPERATION

The 144MHz and 430MHz transceivers listed in Table 5 can be adapted for satellite operation using the optional CT-16 SATELLITE INTERFACE UNIT from ICOM.

* Dip switch 3 on the S1 SWITCH **MUST BE OFF** when using satellite operation.





(4) AH-2 ANTENNA TUNER OPERATION

The AH-2 HF ALL BAND ANTENNA TUNER can be automatically operated with the IC-751 or IC-751A. By pushing the [TUNE] SWITCH on the AH-2, the tuner can create a good matching condition without manually changing mode or RF power.

An optional OPC-137 cable must be purchased separately for connecting the AH-2.

The S2 SWITCH **MUST** be set as shown at right when using the AH-2:







ICOM INCORPORATED

1-6-19, KAMIKURATSUKURI, HIRANO-KU, OSAKA 547, JAPAN

A-0981 Printed in Japan