

Fig. 2 Microphone plug wiring

Referring to Fig. 2 above,

3. Remove the retaining screw.
4. Unscrew the housing.
5. Loosen cable clamp screws.
6. Thread cable through the housing, knurled ring and washer.
7. Solder the wires to the pins in accordance with the microphone wiring table above and figure 3 below. Before soldering, the washer must be placed on the threaded portion of the pin receptacle body.

- 15 -




Fig. 3. Microphone pin numbers

8. Once all soldering is complete, you may re-assemble the unit. When assembling, make sure that the wires do not touch each other or any other metal parts. Check for excessive solder which could cause a short. To re-assemble, screw the housing onto the pin receptacle body. Make sure the screw hole and threaded hole line up, and then replace the retaining screws.

Your microphone should now be ready to use with your radio.

- 16 -