



IC706 Transceiver  
Low Power ADSP<sup>2</sup> Installation  
Catalog Number 70-11

This document describes procedures that could result in voiding of the warranty of your radio.

If these procedures are not precisely and properly carried out, it could result in a radio that does not work or is damaged.

Furthermore, while reasonable efforts have been made to assure the accuracy of this information, it is possible that there are some errors, or that your radio is of a slightly different version than the one used for testing and thus, differences may exist. You are expected to take total responsibility for your own actions.

It is assumed that anyone following suggestions made in this document is already thoroughly familiar with the technologies and techniques involved and possesses the necessary skill and knowledge to make their own judgment as to the appropriateness and validity of the information.

*If you choose to do the installation outlined, you do so at your own risk. You are solely responsible for any damage, voiding of warranty, or other harm that may come about by following these procedures. It is very strongly recommended that, if you maintain your own radio, you thoroughly familiarize yourself with the transceiver service manual. If you don't have one, get one!*

CAUTION: Soldering and desoldering of very small Surface Mount Components may be required to perform this installation

**IMPORTANT NOTE: Support for the ADSP<sup>2</sup> board will be provided by SGC exclusively by email. Please write to [sgc@sgcworld.com](mailto:sgc@sgcworld.com) for assistance if needed.**

## 1. Technical Specifications

Specification	Low Audio	High Audio
Size	1.7 X 1.475"	2.645 X 1.475"
Weight	0.6 oz	1.1 oz
<b>Audio Limits</b>		
Min Input	10 mv RMS	100 mv RMS
Max Input	150 mv RMS	5 volt RMS
Max Output	.5 v RMS	9 v RMS
Power Output		5 Watts RMS
<b>Current Consumption</b>		
idle	80 mA	110 mA
full out	80 mA	500 mA
	X1	X2
Noise Reduction	13 dB	26 dB
Time Delay	6.5 ms	13 ms
Tone Rejection	-50 dB	-65 dB
<b>Filters (3dB Bandwidth)</b>		
Voice	300-2100 Hz	
CW Wide	400-900 Hz	
CW Narrow	600-700 Hz	
Out of Band Rejection	-45 dB	

SGC Inc. SGC Building, 13737 SE 26th St. Box 3526 Bellevue, WA. 98009 USA

Fax: 425-746-6384, Tel: 425-746-6310 or 1-800-259-7331

E-mail: [sgc@sgcworld.com](mailto:sgc@sgcworld.com) • World Wide Web: [www.sgcworld.com](http://www.sgcworld.com)

©April 2003, SGC Inc.



IC706 Transceiver  
Low Power ADSP<sup>2</sup> Installation  
Catalog Number 70-11

## 2. Preparation

The ADSP<sup>2</sup> installation provides you with an unprecedented ADSP capability, far beyond what you can find on most amateur radio transceivers.

Every possible effort has been made to provide you with a simple, easy to use product. One where you can concentrate on your communication and not on fiddling with knobs. SGC's ADSP<sup>2</sup> will give you years of service improving your ability to communicate.

- ***Prepare your work area***
  
- ***Assemble your tools and parts***

- ADSP<sup>2</sup> board
- ADSP<sup>2</sup> switch assembly
- Double-stick tape for mounting the board
- Tools for disassembling your transceiver
- soldering iron suitable for working with Surface Mount Devices

## 3. Install the ADSP<sup>2</sup> Board

- ***Open your transceiver***
  
- ***Remove the backing from the double-stick foam tape and attach the ADSP<sup>2</sup> assembly into a convenient location***

We placed the board in the 706 as shown in the picture.



IC706 Transceiver  
Low Power ADSP<sup>2</sup> Installation  
Catalog Number 70-11



□ ***Connect the ADSP<sup>2</sup> into the signal path***

The following connections will be made between the ADSP<sup>2</sup> board and the transceiver:

- Pin 7 to 12V DC, White wire
- Pin 9 to DC ground, Black wire
- Pin 8 to audio in to the ADSP<sup>2</sup>, Gray wire
- Pin 10 to the audio out from the ADSP<sup>2</sup>, Brown wire



You will also need to make the following connections to the board from the momentary switches provided for switching ADSP modes and Filters:

- Pin 4 to the Yellow Wire
- Pin 5 to the Red Wire
- Pin 6 to the Black Wire



IC706 Transceiver  
Low Power ADSP<sup>2</sup> Installation  
Catalog Number 70-11

The picture below shows these connections:




The audio path should be broken at the input to the audio amplifier just before the volume control. The only requirement at this point is that a minimum of 10 millivolts RMS and a maximum of 150 millivolts RMS will appear at this point when using the Low Power version of the ADSP<sup>2</sup>. Normally, there is a capacitor at this point (0.1 uf is a typical value) to couple the stages together. Remove this capacitor and connect the ADSP<sup>2</sup> board in its place. The board has coupling capacitors on its input and output.






IC706 Transceiver  
Low Power ADSP<sup>2</sup> Installation  
Catalog Number 70-11




In the IC706, this is at capacitor C47 as shown below.





IC706 Transceiver  
Low Power ADSP<sup>2</sup> Installation  
Catalog Number 70-11

The schematic shows it like this:



12 VDC can be taken from any point where it is convenient and the ground can be connected to any convenient point that is connected to the chassis ground. On the 706, the Q45 Emitter (shown above) turns out to be a convenient place to tap for 12 VDC power and there are a number of caps in the vicinity with one side connected to chassis ground.

- **Route the ADSP<sup>2</sup> switch assembly out of the transceiver body**




IC706 Transceiver  
Low Power ADSP<sup>2</sup> Installation  
Catalog Number 70-11

- **Connect the switch assembly to the switch wire connector**
  
- **Reassemble the transceiver**

#### **4. Test your transceiver**

The switch buttons are assigned to their functions according to the diagram below:



Each switch steps through its functions in order as shown below under testing.

- **Testing the ADSP Functions**
  - Press & Release the ADSP<sup>2</sup> Pushbutton for Noise Reduction X1
  - Press & Release the ADSP<sup>2</sup> Pushbutton for Noise Reduction X2
  - Press & Release the ADSP<sup>2</sup> Pushbutton for No Reduction
  - Repeat several times to verify operation
  
- **Testing the Filter Functions**
  - Press & Release the Filter Pushbutton for the Voice Filter
  - Press & Release the Filter Pushbutton for the Wide CW Filter
  - Press & Release the Filter Pushbutton for the Narrow CW Filter
  - Press & Release the Filter Pushbutton for No Filter
  - Repeat several times to verify operation

**SGC**  
IC706 Transceiver  
Low Power ADSP<sup>2</sup> Installation  
Catalog Number 70-11

## 5. Installing the Switches

The switches may be installed in any convenient location. The specific choice of switches was made to make it easy to mount on nearly any transceiver. Some people have chosen to install their switches on the side of the unit, others have preferred the top, and some on the front. Your specific installation will determine what the best location is. We brought the switch out through the Compression Gain control on the right side when looking at the front.



SGC welcomes any suggestions regarding these switches to improve installation and operation.

**CAUTION:** Overdriving the ADSP2 module may cause distortion. Backing off the level of the input signal will avoid it.