



SERVICE BULLETIN

PRODUCT: Computer Monitor
BULLETIN: MON00-005
MODEL: PG19LS9U, PG19HS9U,
 PG19RS9T, PG19SS9T, PG19PS9L,
 PG19LT9U,
 Samtron 95PT

SUBJECT: Improve the High Voltage Electrical Charge for all Pegasus 19" monitors.

BACKGROUND: When power is initially turned on, a high voltage arcing sound can be heard because of a charge from anode to bracket or TCO tape.

SOLUTION: Improve the isolation between anode and ground. Change capacitor C539 from a 2.2uf 50V C-Elec. Non-Polar to a 1uf 63V C-MP. This should be applied to monitors produced from March 2000 to May 2000.

PARTS LIST:

ORIGINAL			NEW	
Location No.	Part No.	Description	Part No.	Description
C539	2401-000649	C-Elec NP 50V, 2.2uF	2305-000237	C-MP 63V, 1uF

Disclaimer: This information is provided "as is" without warranty of any kind either expressed or implied, including, but not limited to, the implied warranties of merchantability and fitness for a particular purpose.