

# SERVICE BULLETIN

**PRODUCT:** Computer Monitor  
**BULLETIN:** MON 97-010  
**MODEL:** CQA4147, CQB4147

**SUBJECT:** No Raster

---

**BACKGROUND:** D618, which is the rectifier diode for the 166V line, burns due to a reverse peak voltage that occurs when power is turned off.

**SOLUTION:** A snubbing capacitor must be added in parallel with D618 in order to prevent this from occurring. This capacitor should be added to all CQB and CQA chassis as a preventative maintenance.

## PARTS LIST:

ORIGINAL			NEW	
Location No.	Part No.	Description	Part No.	Description
C643	NA	NA	2201-000012	C-CERAMIC DISK, 220pf, 10%, 1KV

Disclaimer: This information is provided "as is" without warranty of any kind either expressed or implied, including, but not limited to, the implied warranties of merchantability and fitness for a particular purpose.