

**SONY**

Car Stereo  
Service Bulletin

Sony Service Company Technical Services  
A Division of Sony Corporation of America  
Sony Drive, Park Ridge, New Jersey 07656

**Model:** RM-X2001

**No. 162**

**Subject:** Output Level Is Low

**Date:** February 16, 1990

**Symptom:**  
(52)

The maximum volume cannot be obtained at the output.

**Solution:** Please change the following resistors:

Ref. No.	Description		Part Number
	Former	New	
R132 R232	0.47 Ohm Resistor	220 Ohm Resistor	1-216-033-00
R133 R233	82 Ohm Resistor	330 Ohm Resistor	1-216-037-00
R134 R234	150 Ohm Resistor	560 Ohm Resistor	1-216-043-00
R135 R235	270 Ohm Resistor	1k Ohm Resistor	1-216-049-00
R136 R236	470 Ohm Resistor	1.8k Ohm Resistor	1-216-055-00
R137 R237	1k Ohm Resistor	3.3k Ohm Resistor	1-216-061-00

Compact Disc  
CSA-14

Reference:

PRINTED IN U.S.A.  
JA-14290-2