
Model: CDP-XA7ES

No. 476

Subject: Unstable Display

Date: May 29, 1996

Symptom:

(13)

The unit exhibits an unstable display.

Solution:

Perform the following:

- 1.) Cut a pattern between Q955 C, E and the negative side of C963.
- 2.) Connect the collector of Q956 to the negative side of C963 via a jumper wire.
- 3.) Change the location of the 1K resistor lead mounted to the emitter of Q956 (foil side of the board) to the emitter of Q955 (See diagram below).