

19 18 17 15  
New One Tube Reflex; How to Assemble Miloplex

# Radio Digest

EVERY WEEK

## Illustrated

TEN CENTS

REG. U. S. PAT. OFF. & DOM. OF CANADA

Vol. VII

Copyright, 1923  
R. D. P. Co. Inc.

SATURDAY, NOVEMBER 10, 1923

No. 5

## OPERA SEASON STARTS



### 1000-WATT POWER NOW USED AT WBZ

#### SPRINGFIELD PLANT INHERITS OLD VOICE OF WJZ

##### Studio and Equipment Rivals Best in Country—Use Old WBZ Set for Telegraph

SPRINGFIELD, MASS.—Recent additions to the Radio equipment at the Westinghouse station here, WBZ, have made it one of the best 1000-watt stations in the country. The Radio room rivals the best and provides ample space for the operators, while at the same time it makes the equipment easily accessible.

Chief Operator H. E. Hiller was formerly Announcer OHN of Station WJZ at Newark. He is well acquainted with the transmitter, which formerly was the "voice" of WJZ. The transmitting set consists of four 250-watt oscillator and five 250-watt modulator tubes. This is the main part of the

### TELLS BEETHOVEN'S GENIUS IN RECITAL

#### Walter Damrosch, Famous Symphony Conductor, Delivers Lecture from WEAF

NEW YORK.—Walter Damrosch, the famous conductor of the New York Symphony Orchestra and one of the greatest symphony orchestra leaders in the world, broadcast a lecture recital through Station WEAF recently. The recital was picked up by microphones placed in Carnegie Hall here. It was Mr. Damrosch's first appearance before any Radio audience, and was appreciated greatly as indicated by the many letters from listeners in.

Mr. Damrosch's recital, in which he played the piano, was on the subject of Beethoven. It was given in order to satisfy the tremendous interest which has been stimulated in the Beethoven Cycle to be given at Carnegie Hall this season by the New York Symphony Orchestra, with Mr. Damrosch conducting.

The subject of Mr. Damrosch's lecture was Beethoven's First Symphony and the Eroica or Third Symphony.

### 'LUCIA' FIRST ON AIR FROM STATION KYW

#### Music Lovers Welcome Tidings—Chicago Station Prepares for Big Feature

#### November 10 Is Date Set

#### Will Give Two Operas Each Week—Synopsis between Acts—Metropolitan Refuses

CHICAGO.—Grand Opera on the air again! Music lovers all over the country welcome the news that KYW, Westinghouse station here, will resume its most popular feature on the evening of November 10 with the opera "Lucia di Lammermoor," sung by the Chicago Civic Opera Company at the Auditorium Theater, and picked up there by the Radio microphones.

For two years already KYW, the pioneer opera broadcaster, has enjoyed a tremendous success with its broadcasting of several performances each week of the civic opera during its season, and the announcement that the Chicago station will again play its part in promoting an appreciation of the better things musical, is hailed

(Continued on page 2)



Opera stars in the premier opera broadcast this season, "Lucia Di Lammermoor," by the Chicago Civic Opera, and on the air Saturday, November 10, at 8 p. m., Central time. Left to right they are: Jose Mojica as "Lord Arthur Bucklaw"; Florence Macbeth, who sings the role of "Lucia"; Giacomo Rimini as "Lord Henry Ashton"; and Elizabeth Kerr, who will sing the role of "Alice"



### Judge Talks on World Court

SCHENECTADY, N. Y.—John Bassett Moore, judge of the Permanent Court of International Justice at The Hague, addressed the Radio audience of Station WGY here, the General Electric Company, recently on the subject of the international court and some illusions concerning it. Judge Moore's address was delivered at a session of the fifty-ninth convocation of the University of the State of New York, held at Chancellor's Hall, Albany, New York.

### UNITED CIGAR STORES TAKE UP AIRPHONES

NEW YORK.—The United Cigar Company have entered the Radio field, at least in this city, with five of their stores stocked with a representative stock. Harold Bergman, in charge of Radio sales for the company, states that, according to present plans, Radio equipment will eventually be stocked in Philadelphia and Chicago stores.

transmitting station and is the equipment that carries the voice and music into the air.

#### Old WBZ Set for Telegraph

The apparatus used for broadcasting at WBZ before the WJZ set was installed has a rating of 500 watts and at the present time is used for Radiotelegraph purposes. The telegraph service is maintained between KDKA at East Pittsburgh and WBZ for inter-plant communication.

An addition to the station is the line amplifying equipment for wire lines from the downtown WBZ studio, the Springfield Auditorium and local churches.

A modulation meter and control rheostat has also been added so that the operator can listen to the programs and gauge the modulation.

# BAR GOES UP ON COUPONS NOV. 24

## COLDER WEATHER CLOSES REWARD OFFER

All Letters Must Reach Digest Office Before December 1 to Be Eligible

### SPECIAL REWARD OFFER

#### Coupon Number 24

This Special Reward Coupon appears each issue in Radio Digest until November 24. When sent in, accompanied by necessary remittance, according to the rules governing same, apparatus can be secured. See rules of offer below.

Save Me—I Am Valuable

The Special Reward Offer will be discontinued for the present season with the publication of Coupon Number 26 in the issue of November 24. This action has been deemed necessary as a result of the increased rush in business coming with the colder (and more favorable for Radio) weather.

All Radiophans contemplating taking advantage of the special offer must do so before December 1. All letters containing coupons and remittances for parts must reach the office of Radio Digest on or before that date. Such letters arriving after December 1 will be returned to the writer.

Lack of space requires the omission of the list of Radio parts obtainable. See issue of October 27 or November 3 for this list. One change, however, is to be noted. Articles in Class H must be accompanied by sixteen consecutively numbered coupons and \$3.40, instead of \$3.00 as given previously in the list.

Readers contemplating taking advantage of the special offer must remember that the coupons turned in for any item must be numbered consecutively, as for example, 16, 17, 18 and 19, or 18, 19, 20, 21, 22 and 23. The number of coupons necessary and the cash remittance, of course, depend on the item sought by the reader. There is no limit to the number of series turned in by any one reader.

Another point to be remembered by readers taking advantage of the offer is that checks and money orders will be accepted, but no cash or postage stamps.

## OPERA SEASON STARTS

(Continued from page 1)

with delight by countless listeners in. The opera season opens on Thursday night, November 8, but the first performance to be microphoned will be the famous score of Gaetano Donizetti, "Lucia."

### KYW to Give Synopses of Acts

While the opera performance will not begin until 8 p. m., Central Standard Time, Station KYW will come on the air about fifteen minutes earlier, at 7:45 p. m. Announcer A. W. "Sen" Kaney, famous for his clear enunciation and expression, will then give a short history of the opera to be broadcast, together with a synopsis of the first act. Between acts he will give the synopsis of the act to follow.

The synopses for all the operas to go on the air are being prepared and written by Mrs. George B. Foster, prominent in Chicago society. Mr. Kaney will do the opera announcing for the entire season.

Preceding the first opera broadcast, on November 9, KYW will devote a part of its evening program to a talk by Mr. Kaney on "How Grand Opera Broadcasting Is Done."

### Cast of "Lucia"

The principals who will sing Donizetti's beautiful score and their rôles are: Giacomo Rimini, baritone, as "Lord Henry Ashton"; Florence Macbeth, soprano, as "Lucia"; Giulio Crimi, tenor, as "Sir Edgar of Ravenswood"; Jose Mojica, tenor, as "Lord Arthur Bucklaw"; Elizabeth Kerr, mezzo-soprano, as "Alice," the companion to Lucia; Virgilio Lazzari, tenor, as "Raymond"; and Lodovico Oliviero, tenor, as "Norman," captain of the guard at Ravenswood. Pietro Cimini will conduct.

All of the stars, with the exception of Macbeth and Kerr have been heard on the air by Radiophans who tuned in the opera broadcasts of KYW last year. The two sopranos are newcomers this year to the Chicago Civic Opera Company.

Elsewhere in this issue appears a synopsis of the opera.

As was the plan last year, KYW will broadcast the two most suitable operas each week during the season. The music and periods of waiting of all operas are

(Continued top third column)

## FINDS AIRPHONE AID TO BOX OFFICE TILL



Marcus Loew, owner of Loew's Theaters, well-known vaudeville houses, has found that broadcasting his acts helps to increase the box office receipts. His station, WHN, New York City, has proven a profitable enterprise; so much so in fact that he is planning to install another plant at Boston

not adapted to good broadcasting, so that the ones better fitted to the needs of Radio are selected.

For those unacquainted with the Chicago station, KYW transmits on a 536-meter wave length, having made this change from 345 meters when some improvements were made several months ago.

### Metropolitan Still Refuses

When queried recently by a representative of Radio Digest, the management of the Metropolitan Opera Company of New York City, again stated as final its decision that the Metropolitan opera would not be broadcast. Readers of the Digest last year will recall the efforts made to no avail to convince the Metropolitan management that their performances should be broadcast as are those of the Chicago Civic Opera Company. The management of the Metropolitan is still of the opinion that broadcasting would be a detriment and is prejudiced against giving the public the benefit of their interpretations of the masters.

It remains therefore, that the East must listen to the West to hear the supreme of music, but in so doing the East will lose nothing, for music critics agree that the Chicago Civic Opera is in some respects more progressive and better than Metropolitan.

## Mormons Put Conference on Air for First Time

SALT LAKE CITY.—The proceedings of the big semi-annual conference of the Mormon or Latter-day Saint Church, just held, were broadcast for the first time in the history of the church. The benediction of Chas. W. Penrose, the 92-year-old counsellor to President Heber J. Grant, could be distinctly heard in many sections of the country, it was reported.

# CONTENTS

Radio Digest, Illustrated, Volume VIII, Number 5, published Chicago, Illinois, November 10, 1923. Published weekly by Radio Digest Publishing Company, 123 West Madison Street, Chicago, Illinois. Subscription rates, yearly, Five Dollars; Foreign Postage One Dollar additional; single copies, Ten Cents. Entered as second-class matter at the postoffice at Chicago, Illinois, under the Act of March 3, 1879.

"All the Live News of Radio".....	1 to 9
An Evening at Home with the Listener In.....	5
Double Tube Circuit in Simplex Picture Form.....	10
Further Details of Miloplex Hook-Up.....	11
Advance Programs.....	12
Simple Explanation of Radio for Everybody, Chapter IV, Part III—Inductances—Fixed and Variable, by M. W. Thompson.....	15
Editorials; Indi-gest; Condensed, by Dielectric.....	16
How to Build a Miloplex Receiver, by H. J. Marx.....	17
Another Single Tube Reflex, RD-102.....	18
Simple Coil Increases Range of Old Set.....	19
Review of Books.....	20
Audio Amplification for the Flewelling Set, Part III, by E. T. Flewelling.....	21
Inside Mounting for Honeycomb Coils.....	21
Questions and Answers.....	22
Broadcasting Stations, Part IV—Station Schedules.....	23
Radio Illustrated, a Page of Pictures.....	24

## Looking Ahead

When You Wire Your Three-Tube Miloplex III—Use either one of the two hook-ups H. J. Marx will give you next week. He will tell how to wire the famous "Plexy" to get the most out of it. Anyone building the popular new circuit would be foolish to miss reading this article.

Copyrighted Music, the A. S. of C. A. and P., and the Story of the National Broadcaster's Association—Beginning next issue, a serial exposé of the obstacles thrown in the way of but surmounted by the spunky stations who banded together and are now laughing at the "music trust" that threatened to throttle all popular song broadcasting.

Capacities, Fixed and Variable—The title of M. W. Thompson's next chapter in his series on the principles of Radio. Read this interesting explanation of variable and fixed condensers so that you'll know why a condenser "percolates."

The Mysterious Inventor of the Miloplex says that he will devote his article next week to the "interesting-if-true" analyses of what makes a Plexy plex. Not being confirmed to his own theories, he will give a few proposed by well-known engineer friends.

Build a Multiple Phone Jack Box according to the instructions to be given next issue, and then you can hook on several loud speakers and headsets at the same time. Handy to have around when company drops in to hear the concert.

Much Ado About Four-Circuit Tuners—But wait till you see the one H. J. Marx is building. Tests so far have proven it superior to anything of its kind, and it is worth describing, and waiting for. Watch for the next few issues for the start of the series describing the construction.

Newsstands Don't Always Have One Left

WHEN YOU WANT

# Radio Digest

YOU WANT IT!

BE SURE OF YOUR WEEKLY COPY BY SUBSCRIBING NOW

SEND IN THE BLANK TODAY

Publisher Radio Digest, 123 West Madison St., Chicago, Illinois.


Please find enclosed check M. O. for Five Dollars (Six, Foreign) for One Year's Subscription to Radio Digest, Illustrated.

Name .....

Address .....

City..... State.....

## KELLOGG RHEOSTATS




Very accurate! for sharp tuning for simplicity

Now stand by men and let me tell you something about this Kellogg Rheostat that you have been hearing about. FIRSTLY—the long contact surfaces gives you a perfect contact under all conditions. SECONDLY—to assure perfect current to the most critical tube this baby gets into action on the half turn of the resistance element. THIRDLY—you can look it over carefully and you will find only one moving part—that's for simplicity.

If you want your little outfit to be the "Pride of the Neighborhood" just remember that good rheostating has a whole lot to do with good receiving. We have a price, yes. It's \$1.50.

Use is the test

KELLOGG SWITCHBOARD & SUPPLY COMPANY CHICAGO



# This RADIO BOOK will save you money!

Compiled by HARRY F. DART, B.S.E.E. Formerly with the Western Electric Co., and U. S. Army Instructor of Radio Technically edited by F. H. DOANE

JUST off the press! The greatest book on radio ever written. Price only \$1. Filled with sound, practical, tested information for every radio fan, from beginner to hard-boiled owl. Written, compiled and edited by radio experts of national reputation.

Every page tells you something useful. And there are 514 pages! More than 150 illustrations and diagrams!

You may dip into this I. C. S. Radio Handbook at random, or hunt up special information you want, or read it right through. Different types of receiving and sending hook-ups are explained; proposed insurance regulations; lists of broadcasting stations; radio compass stations; interesting experiments; definitions; codes and symbols; technical data and thousands of suggestions for getting more pleasure out of radio. Will save you from wasting money on things that won't work.

Send \$1 to-day and get this 514-page I. C. S. Radio Handbook before you spend another cent on parts. Money back if not satisfied.

TEAR OUT HERE

INTERNATIONAL CORRESPONDENCE SCHOOLS Box 8277-C, Scranton, Penna.

I enclose One Dollar. Please send me—postpaid—the 514-page I. C. S. Radio Handbook. It is understood that if I am not entirely satisfied I may return this book within five days and you will refund my money.

Name.....

Address.....

# EQUITY'S BAN STOPS COMEDY BROADCAST

## ORGANIZATION DEMANDS ACTORS BE PAID

### Volunteer Performance of "Thank-U" Called Off When Union Steps In

BOSTON.—Theatrical managers, especially those heading musical comedy companies, have begun to sit up and take notice of Radio as a means of publicity for their shows. Instead of forbidding the broadcasting stations from making use of their song hits, they are now coming to the stations voluntarily and with their entire choruses and cast of stars, to broadcast excerpts from their productions. But now comes a new obstacle, the Actors' Equity Association.

Recently the "Thank-U" company, which has been playing at the Hollis Street theater for six weeks, after a run of 300 nights at the Longacre Theater in New York and 200 nights at the Cort Theater in Chicago, planned to give excerpts from the comedy from WNAC, with the entire cast volunteering.

#### Equity Blocks Broadcast

The plans, however, were upset at the last minute by the action of the Actors' Equity Association, who demanded that those performers who took part in the broadcasting be paid one-eighth of their proportional salaries for one day, for performing in the broadcasting studio. This came as a surprise, not only to the management of WNAC, but to the management of the company and the performers themselves.

The latter said they had no knowledge of anything in the union rules that prevented them from volunteering for such a performance. Rather than start any controversy, the management of Station WNAC called off the program, broadcasting an announcement to that effect, and leaving the question to be possibly threshed out at some future date.

## Trace Annoying "Hum" with Antenna on Auto

### Leaky High Voltage Transformer Blamed for Disturbance

CINCINNATI.—Radio is being put to a novel use in this city, that of tracing a leaky high voltage transformer supposedly belonging to the Union Gas and Electric Company, which organization supplies the city with gas and current.

For the past few weeks, broadcast listeners in northern suburbs of the city have been greatly disturbed by what they at first thought to be some new form of static. Old time Radio men, however, quickly diagnosed the true cause of the trouble, and notified the Union Gas and Electric Company to repair its transformer. As there are a number of transformers in this section, however, it was found impossible to locate the source of the disturbance, hence the hum persisted to such an extent that for many it virtually drowned out even the two local broadcasting stations.

A Radio set with a loop antenna was mounted on an automobile and the car was driven through every street in the district, an operator in the machine listening in and turning the loop continually. While the defective transformer has not yet been located, due to the fact that only a few such pilgrimages have been made to date, the district is being constantly restricted, and it is a matter of days only until the source of trouble will be found.

### Russ-Franco Pact Ratified

WASHINGTON.—Ratification has been made of the contract between the French Compagnie General de Telegraphie Sans Fil and the Russian Radio Electric Trust, according to cable advices from Paris. The agreement provides for the installation of stations and the manufacture of apparatus in Russia.

## BISHOP'S TIMEPIECE SPOILS HIS SERMON

CHICAGO.—Bishop Wm. F. McDowell recently talked against time at the Sunday Evening club's meeting, broadcast by direct wire through Station KYW here, and time evidently won the contest. Radiophans protested that the ticking of the bishop's watch placed too close to the microphone on the pulpit, made enough noise almost to drown out the sermon.

## HARVARD GAMES TO GO ON AIR AT WNAC

BOSTON.—Three of the Harvard games at the stadium have been broadcast by WNAC, the Shepard Stores station here, and two more will be. The ones yet to go on the air are Harvard vs. Brown, November 17, and Harvard vs. Yale, November 24. Paul Waittee, well-known sports and feature writer, announces the games play by play.

# ELECTRICAL WIZARD, STEINMETZ, PASSES

## WORLD-FAMOUS ENGINEER DIES UNEXPECTEDLY

### Keen Brain Predicted Transmission of Power by Radio—Death Great Loss to World

SCHENECTADY, N. Y.—Dr. Charles P. Steinmetz, wizard of the electrical world, died at his home here on the morning of October 26. Physical breakdown of the man, whose great loss to the world is that of the greatest electrical engineer, was given as the cause of his death. A recent trip he had made to the Pacific coast had greatly sapped his strength and confined him to his bed two weeks previously with a heavy cold.

Not even his doctors had any indication that the end was near. He had seemed to be recovering from the exhaustion of his western tour. When the trip was planned and made, his physicians knew the condition of his heart and arranged everything for a minimum of exertion, but as it was his first trip to the West, the electrical wizard was very active.

#### Passes without Warning

On the morning of his death he awakened cheerful and made a remark that he was feeling fine and expected soon to have the liberty of the house. When asked by his nurse how he felt he responded, "I'm feeling fine."

When he was about to be served with breakfast he said that he felt a little tired and a few minutes later turned over on his side and passed away without sign or warning.

The funeral of Dr. Steinmetz was impressive for the eminent scientists who rushed to attend. It was strictly private, but thousands of his friends came to his house to pay homage. The brilliant man who was consulting engineer for a great factory employing 20,000 men, had never married. He was fifty-eight years old.

#### Was Born in Germany

Dr. Steinmetz was born at Breslau, Germany, April 9, 1865. He came to this country thirty-four years ago.

He was educated in Germany and Switzerland. He arrived in America in 1889, penniless, and started at the bottom of the ladder. He was employed first by a firm in Yonkers, N. Y., which later was absorbed by the General Electric Works, the company for which Dr. Steinmetz was working when he died.

In 1902 he was awarded a degree of A. M. by Harvard and the following year Union College at Schenectady conferred upon him the degree of Ph. D. In 1902 he taught the science of electricity in Union College.

It was the life dream of Dr. Steinmetz to make electricity the universal power of America. He was constantly experimenting with this end in view.

#### Wrote Many Books

Dr. Steinmetz was the author of many books, including "Theory and Calculation of Alternating Current Phenomena," "Theoretical Elements of Electrical Engineering" and "General Lectures on Electrical Engineering."

Among Dr. Steinmetz' accomplishments were the invention of more than one hundred devices, the development of the practical electric automobile, and the making of artificial lightning of 1,000,000 volts' pressure.

The deceased scientist foresaw the future world different from the present. He predicted that this planet would communicate with Mars some day, traversing the distance of 30,000,000 miles. He also foretold the coming of the four-hour workday, and called work a curse. He foresaw the breaking up of big cities, the sending of power by Radio, a world living on microbes, and control of all industry by the people.

In New York City an undertaker operates a hearse equipped with a Radio amplifier and loud speaker. As the vehicle enters the cemetery, chimes, hymns and funeral music are played.

## CHARLES P. STEINMETZ DIES



A surprised world was recently shocked by the news of the death of Charles P. Steinmetz. Photo shows the famous electrical engineer in one of his characteristic poses P. & A. Photo

## Syncopators Demonstrated and "Sold" by Broadcast

NEW YORK.—J. E. Horn, of this city, has perfected a novel method of demonstrating concert and dance orchestras to clients via Radio.

Heretofore a cafe, hotel or club in need of the services of an orchestra has insisted upon a demonstration of the musical organization with the result that considerable expense has been involved. Now

it has been arranged with leading stations all over the United States to demonstrate the various orchestras via broadcasting.



### \$1,400 Radio Job Open

WASHINGTON, D. C.—The Civil Service commission has announced a vacancy in the Bureau of Agricultural Economics, Department of Agriculture for a Radio operator. Announcement is made that receipt of applications will close on November 20. The position will pay \$1,400 a year with a \$20 a month bonus.

## THE ANTENNA BROTHERS

Spir L. and Lew P.

## Romance vs. QRM



# "JAZZ" TUBE KEEPS IN STEP TO BLUES

## WCAP'S TRIODE DEVELOPS SYNCOPATED LIGHTS

### Engineers Rise to Defense of Tired Vacuum Container, Saying It's Caused by Gas Remaining

WASHINGTON.—The national craze for jazz may affect vacuum tubes. This is the latest development in broadcasting news. When a Radio transmitting tube shows unmistakable signs of becoming converted to jazz music and develops a blue light which dances in perfect cadence and absolute abandon to the "blue" notes of a moaning saxophone, "what chance has the advocate of grand opera broadcasting?" Radio engineers and operators ask.

Such is the situation at the Chesapeake and Potomac Telephone broadcasting station, WCAP, every time it broadcasts the music of Le Paradis Orchestra or the Metropolitan Theater. On all other occasions the tube maintains a solemn dignity befitting the occasion, and performs in a highly efficient manner, it is said.


#### Rise to Defense of Tube

The engineers who carefully avoid discussing the ethics of the equipment, rise to the defense of the tube to say that the blue light is probably caused by a small amount of gas which is present in some quantity in all vacuum tubes. When the tube is working, the gas becomes ionized, and if present in sufficient quantity, gives off a bluish light. The vividness of this light, it is explained, is increased with the modulation and with the changes in volume of the music. When a heavy chord is struck, the light visibly brightens, with the result that during a jazz piece the blue light keeps absolute time with the music, bringing out the beats, thus emphasizing the syncopation.

"That's as it should be," say the lovers of jazz. "Even a Radio tube gets a thrill out of popular music." The students of Wagner, Beethoven and Liszt, however, scoff at the idea, claiming "that jazz gives the tube the blues."

Radio receiving sets are installed on coaches of several railway lines in England.

# ELECTED PRESIDENT OF BROADCAST BODY



Eugene F. McDonald, Jr., of the Zenith-Edge-water Beach Hotel broadcasting station, WJAZ, who was elected president of the National Association of Broadcasters at their recent annual meeting. This organization is doing much good in providing broadcasting stations with popular music, the copyrights for which are not controlled by the "music trust"

#### Successful Girl Talks to Fans

NEWARK, N. J.—Continuing in the interesting series of "Half Hours with Successful Women," which is being featured in the WOR programs, Mrs. Edith Ellis Furniss, playwright, recently talked from the L. Bamberger and Company station. She related her experiences of the theater, which are diversified and interesting and cover years.

# Twenty-Kilowatt Tubes at Six Big New Code Stations

NEW ORLEANS.—Six transmitters, to be the most powerful on the American continent, operating from vacuum tubes and first to make use of the recently developed twenty-kilowatt Radiotron, are being installed by the United Fruit Com-

pany and the Tropical Radio Telegraph Company at points in Central America and the United States for the purpose of completing the links of an adequate communications system between the Americas.

The transmitters will be located at New Orleans, La.; Miami, Fla.; Puerto Barrios, Guatemala; Tegucigalpa, Honduras; Managua, Nicaragua, and Almirante, Panama.

# Thrills from Radio

No. 2 of a Series Featuring Experiences of "ALL-AMERICAN" Users


## They're "There" in Selectivity

By R. Disheroon, Hot Springs, Ark.

"Out of four makes of transformers, I have found the 'All-American' best either in a straight radio frequency or a reflex circuit. Don't spend time and money experimenting — over 300,000 radio enthusiasts, like Mr. Disheroon, have already proved that 'All-Americans' are best. And they are standard equipment on the better sets.

"In selectivity they are certainly there. I have never had two stations together or in other words 'jamming' each other.

"Using two 3-1 ratio 'All-American' Audio Frequency and two 'All-American' Radio Frequency Transformers in the Grimes Reflex, by careful placing of the transformers and the



All-American Audio Frequency Transformer — comes in three ratios.

#### FREE

All-American Book of Tested Hook-ups for getting new thrills out of your present radio outfit. Send 2c stamp for postage.

All the better dealers sell "ALL-AMERICAN"

RAULAND MFG. CO., 200 N. Jefferson St., CHICAGO PIONEERS IN THE INDUSTRY

AUDIO FREQUENCY




RADIO FREQUENCY

# ALL-AMERICAN AMPLIFYING TRANSFORMERS


Largest selling Transformers in the world

# THE AUDIOPHONE

Quality of reproduction such as only the original itself can equal. Speech that is so distinct that the voice heard is the actual voice of the speaker. Music that requires no tolerant imagination to be recognized as music of the finest type.



# Bristol's Single Stage Power Amplifier



gives additional VOLUME with any two stage amplifier. No separate batteries required. It provides the additional volume necessary to bring in very distant stations on the loud speaker.

Write for bulletin and address of the nearest dealer handling our instruments

# THE BRISTOL COMPANY WATERBURY, CONN.

Boston New York Philadelphia Pittsburgh Detroit Chicago St. Louis San Francisco

# REAL BARGAINS ON SETS AND PARTS

## Complete Parts for Miloplex Circuit—Cabinet Free

1 .0005 Variable Condenser, Vernier	\$6.00	3 3/4-inch Dials, each	\$2.25	1 B Battery, Burgess, 22 1/2 volt	\$3.00
1 Estru Variometer	5.00	1 Potentiometer, 1850 ohm	2.20	3 Dry Cells	1.35
1 .00025 Variable Condenser	2.00	1 Rheostat	1.00	12 ft. sq. brass bus wire	.30
1 Variable Grid Leak	.75	1 Socket Bakelite Base	.90	1 Set Readem Bind. Posts	.75
1 .00025 Mica Fixed Condenser	.40	1 Bakelite Panel 9x14x 3/8	2.50		
2 .002 Phone Condensers	.80	1 DeForest D.V. 6 Tube	6.50		
				<b>TOTAL</b>	<b>\$35.70</b>

Blue print FREE only with order for complete parts

## Our Price Only \$28.50

3 Tube Sockets, Bakelite Bases	\$2.70	<b>SPECIAL PRICE ITEMS</b>	
2 Radiometers, \$3.00 each	6.00	<b>SPECIAL Tri-Coil Reflex Radio Frequency Transformer</b>	
1 .0005 Condenser, Variable Vernier	6.00	.....\$2.00	
1 Honeycomb, 75 turn	1.20	<b>PHONES</b>	
1 Single Coil Mounting	.50	Mico Double Phones "Sealed—Guaranteed" List Price	
1 Variable Grid Leak and Condenser	1.00	with Head Bands.....\$7.00	
2 Transformers, Audio Frequency	8.00	Double Phone Cord.....\$.75	
3 Rheostats	3.00	Genuine Master-Baldwin Type C Unit.....6.00 4.39	
1 .00025 Mfd. Fixed Mica Condenser	.40	Genuine Master-Baldwin Type C Double.....12.00 7.95	
1 .005 Mfd. Fixed Mica Condenser	.75	Loud Speaker Cord, 20 ft., 4 tips, our price ... 1.00	
1 Set Readem Binding Posts	.75	<b>WIRE</b>	
12 feet of Bus Wire	.30	All kinds of wire put up in 1/4 pound spools. No. 18 to No. 28, silk, cotton and enamel, double or single .....45 cents a spool	
2 Double Circuit Jacks	1.80	Same wire as above on 1/2 pound spools.75 cents a spool	
1 Open Circuit Jack	.75	Hook-up Wire, No. 14 square brass, cut in 6 foot lengths.....15c	
1 3" Dial	1.00	<b>RHEOSTATS AND SOCKETS</b>	
1 Panel, Bakelite, 9x14x 3/8	2.50	MARVEL Rheostat, 6 ohms.....\$.35	
1 Baseboard, 9x14x 3/8	.25	MARVEL Rheostat, 20, 25 and 30 ohms......45	
1 Cabinet, 9x14x8", fine mahog. finish	6.50	MARVEL Rheostat, 40 ohms......55	
Including blue print with panel layout. OUR PRICE	\$39.75	MARVEL Rheostat, 50 ohms......65	
<b>TOTAL</b>	<b>\$44.15</b>	Potentiometer, 200 ohms......55	

## Complete Parts RD 99 Long Distance Receiving Set

3 Bakelite Base Sockets	\$2.25	<b>GRID-LEAKS</b>	
3 Rheostats	3.00	List Price	
2 A. F. Transformers	8.00	Freshman Grid-Leak with Condenser.....\$1.00 .79	
2 Double Circuit Jacks	1.80	Freshman Grid-Leak......75 .59	
1 Open Circuit Jack	.75	<b>VARIOMETERS</b>	
1 Estru Variometer	5.00	Moulded Variometer.....\$6.00 \$4.39	
1 Variable Grid Leak and Condenser	1.00	Estru Split Variometer.....4.50	
1 .0005 Variable Condenser with Vernier	6.00	Variometer, All Circuits.....5.50	
1 .005 Fixed Condenser	.75	Readem Binding Posts. Set composed of 1 antenna, 1 ground, 1 A Battery +, 1 A Battery -, 2 telephones, 1 B Battery +, 1 B Battery -.....\$.75	
1 75-turn Honeycomb Coil, mounted	1.20	<b>VARIABLE CONDENSERS</b>	
1 Single Coil Mounting	.50	List Price	
1 Set Readem Binding Post	.75	Variable Condenser, .0005 (Same as 23 plate).....\$5.50 \$3.00	
1 Panel Bakelite, 7x16x 3/8	2.25	Variable Condenser with Vernier, .0005.....6.50 4.50	
1 Cabinet, 7x16x8, fine mahogany finish	6.00	Variable Condenser, .001 (Same as 45 plate).....6.00 3.50	
Our price complete with panel drawing and blue print. ONLY	\$30.25	Variable Condenser, with Vernier, .001.....7.50 5.00	
<b>TOTAL</b>	<b>\$39.25</b>	Walnut Variable Condenser, .00025.....1.75	

## Complete Parts for One Tube Reflex

1 Radiometer	\$3.00	<b>CABINETS</b>	
1 23 Plate Condenser	3.00	List Price	
1 Tricoil Transformer	2.00	9x14x8, mahogany finish.....\$3.25	
1 Audio Transformer	4.00	7x9x8, mahogany finish.....2.75	
1 199 Socket	.99	7x21x8, mahogany finish.....3.50	
1 199 Tube	6.50	<b>MUST SEND POSTAGE</b>	
1 Baseboard, 7x9	.25	H. C. Coil Mounting.....\$5.00	
1 7x9x 3/8 Bakelite Panel	1.25		
1 Set Readem Binding Post	.75		
2 .002 Micon Fixed Condensers	.80		
1 Type B. B. Metal Detector	1.50		
1 Cabinet, 7x9x8	2.50		
Complete			
OUR PRICE ONLY	\$22.45	<b>TOTAL \$28.45</b>	

We Are Responsible Folks. Money Promptly and Cheerfully Refunded If You Are Not Satisfied

Every-thing in Radio Write Us


All Orders Mailed Promptly. Parcel Post Prepaid on \$5.00 or Over. No Stamps Accepted. Send Money Orders. Quality Merchandise at Low Prices

## Economical Radio House

4600 Lincoln Avenue, Chicago

We Personally Guarantee All Goods

# WTAM, BATTERY FED, HAS NO HUM



Many fans undoubtedly have heard a new call recently, WTAM. Above are a few pictures from the station, which is owned and operated by the Willard Storage Battery Company of Cleveland. No generator hum can possibly be in WTAM's carrier wave as it is operated entirely from storage batteries. Center is a view of the studio. Left is A. R. Herske, announcer, and right is S. E. Leonard, operator. Mr. Leonard designed and personally supervised the installing of Station WTAM.  
Photos specially posed for Radio Digest

## WNAC Gets a Home of Its Own in Boston

"Frank's Place" Famous in "Wet" Days Is Remodeled

BOSTON, MASS.—Station WNAC, The Shepard Stores here, now has a home of its own. The Winter Place Hotel, famous in pre-Volstead days as "Frank Locke's place," has been remodeled for the purpose, and work is fast being completed to have the new studio ready for occupancy. The broadcasting and entertainment will be on the third floor of the building, the second floor being reserved for a big employes' lunch room for the clerks of the Shepard Stores. There will be two separate studios with a spacious reception room, for the station, with an announcer's booth, which will be located in a sound-proof room opening into both studios, so that programs can go on continuously.

## Duck for Apples by Radio at WOR "Hallowe'en Party"

NEWARK, N. J.—A recent novelty on the WOR program was the broadcast of an old-fashioned "Hallowe'en Party" held in the studio. The party was held from 8:45 to 11 p. m., eastern time, and consisted of ducking for apples, ghost stories and thrilling tales of Hallowe'en superstitions. The program included dance music furnished by the Elite Orchestra and several numbers sung by the Royal Male Quartette of New York. The usual announcing was dispensed with and the microphone was left open continuously throughout the evening.

According to Dr. Lee De Forest, pioneer Radio inventor, in less than five years there will be a Radio audience of 20,000,000 persons in the United States.

## CAPETOWN, S. AFRICA, PONDER'S BROADCASTS

Plant Will Be Controlled by City Instead of Individuals

CAPETOWN, S. AFRICA.—As the result of an offer made by Sir David Graff here to present this city with a Marconi broadcasting station, a special committee of the city council is now considering a scheme of municipal broadcasting. The council is anxious to reserve for itself the privilege of broadcasting for

a period of fifteen years since it believes that broadcasting in the hands of private enterprise might be misused. Their report continues:

"The equipment of this station will be furnished by the Marconi Company of England, which will also supply the technical assistance to supervise its operations. With the exception of several experiments made by the South African newspapers, the Cape Town broadcasting station will be the first permanent venture of its kind in South Africa."

Radio experiments are being conducted at the Hudson County Hospital, at Secaucus, N. J., for patients suffering from mental ailments. Various entertainments are given for the treatment of the insane.

# The "A" Battery's Power in Your Radio Receiving Set

THIS IS NUMBER TWO OF A SERIES

THE sole purpose of the "A" Battery in your Radio Receiving Set is to furnish current to heat the filaments of the tubes.

And this can be done satisfactorily only by an "A" Battery that supplies an adequate steady current.

Anticipating the popularity of the dry cell tube in Radio, and realizing that it required a Dry Cell capable of standing up under service conditions differing from what dry cells are called upon to meet in other fields, the National Carbon Company developed the Eveready Radio Dry Cell specifically for this new use.

A dry cell gives its maximum service only when designed especially for the work it is intended to perform. There are for dry cells several uses which are so alike that one type of cell serves for all. This is the field covered by the ignition or general purpose dry cell.

The conditions encountered in Radio are different from the conditions grouped together under the term "general purpose." And while the general purpose dry cell performs well as an "A" Battery, it was found possible to produce a Dry Cell "A" Battery capable of delivering more service on Radio loads.

Thirty years of dry cell experience and an immense research organization resulted in the superior Eveready Radio Dry Cell. One of the outstanding features of this special cell is that while it will last much longer when used as an "A" Battery, it is no larger than the standard dry cell.

The increased service life of the Eveready Dry Cell "A" Battery greatly offsets the slight increase in cost; so this battery is not only the best, but it is the most economical you can buy. "The Story of Eveready Dry Cell Radio 'A' Batteries," which tells how to use Dry Cells to the greatest advantage with the various dry cell tubes now available, will be sent to you free on request.

Note: This is number 2 of a series of informative advertisements which will appear in this magazine. They are designed to help users get the most out of their Batteries and their Radio Sets. If you have any battery problem, write to G. C. Furness, Manager Radio Division, National Carbon Company, Inc., Thompson Avenue and Orton Street, Long Island City, N. Y.



**POWER**  
for Your Radio Set  
Eveready Dry Cell  
Radio "A" Battery  
(No. 7111)

Directions and wiring diagrams on the jacket tell just how to use this battery with the different dry cell tubes.

This special Radio Cell is also available in two and four cell multiple batteries for receiving sets employing from two to four WD-11 or WD-12 tubes.

### Other Radio Batteries

Eveready Storage "A" Batteries—best suited for filament heating of all Radio Tubes not especially designed for dry cells. The quality storage battery with the long life plates, \$15 to \$20.

Eveready "B" Batteries—the life of your Radio.

Eveready "Three" Battery—3 cells, 3 purposes.

Manufactured and guaranteed by

NATIONAL CARBON COMPANY, Inc.

# EVEREADY

## Radio Batteries

—they last longer

## AN EVENING AT HOME WITH THE LISTENER IN (SEE INSTRUCTIONS FOR USE BELOW)

Station and City	Mot.	Monday	Tuesday	Wednesday	Thursday	Friday	Saturday	Sunday
CFCN, Calgary, Alta.	440	12:00-1:00		11:00-2:00			11:00-1:00	
CKAC, Montreal, Que.	430		6:00-8:30		6:00-8:30		6:00-8:30	8:30-4:30
KDKA, E. Pittsburgh, Pa.	326	5:00-9:00	4:00-8:00	5:00-9:00	5:00-9:00	5:00-9:00	5:00-9:00	6:30-7:30
KDZE, Seattle, Wash.	455	10:30-12:30		10:30-12:30			10:30-12:30	
KFAF, Denver, Colo.	360	9:00-10:00	9:00-10:00		8:30-9:00	9:00-10:00	9:00-10:00	
KFL, Los Angeles, Calif.	469	8:45-1:00	8:45-1:00	8:45-2:00	8:45-1:00	8:45-2:00	8:45-2:00	10:00-1:00
KGW, Portland, Ore.	492	10:00-12:30	10:00-1:00	10:00-1:00	10:00-1:00	10:00-1:30	10:00-1:00	8:00-10:00
KHJ, Los Angeles, Calif.	395	8:45-12:00	8:45-12:00	8:45-12:00	8:45-12:00	8:45-12:00	8:45-12:00	10:00-12:00
KPO, San Francisco, Calif.	423	10:00-12:00	10:00-12:00		10:00-12:00		10:00-12:00	10:00-12:00
KSD, St. Louis, Mo.	546	8:00-10:00	8:00-1:00	8:00-1:00		8:00-10:00	8:00-10:00	
KYW, Chicago, Ill.	536		8:00-9:00	8:00-9:00	8:00-9:00	8:00-9:00	8:00-9:00	
NAA, Radio, Va.	435	5:45-7:20	6:05-7:20		6:25-7:40	5:45-7:40		
PWX, Havana, Cuba	400			8:00-10:30			8:00-10:30	
WBAP, Fort Worth, Texas	476	7:30-10:30	7:30-10:30	7:30-10:30	7:30-10:30	7:30-10:30	7:00-7:30	5:00-6:00
WBAV, Columbus, O.	390	7:00-9:00						
WBZ, Springfield, Mass.	337	6:30-8:00	6:30-8:00	6:00-8:00	6:30-8:00	6:30-8:00	6:30-8:30	7:30-8:30
WCAP, Washington, D. C.	469		5:30-6:30		8:45-11:00		5:30-11:00	5:20-8:00
WCBD, Zion, Ill.	345	8:00-10:00				8:00-10:00		2:30-5:30
WCX, Detroit, Mich.	517	7:30-9:00	7:30-11:00	7:30-9:00	7:30-9:00	7:30-9:00		6:15-7:15
WDAF, Kansas City, Mo.	411	8:00-1:00	11:45-1:00	8:00-1:00	11:45-1:00	8:00-1:00	11:45-1:00	4:00-5:00
WDAJ, College Park, Ga.	258	7:30-11:30	7:30-11:30	10:30-11:30	7:30-11:30	7:30-11:30	7:30-11:30	7:30-11:30
WDAP, Chicago, Ill.	360		7:00-1:00	7:00-1:00	7:00-1:00	7:00-1:00	7:00-1:00	9:15-11:15
WDAZ, Philadelphia, Pa.	395	6:30-9:55	6:30-7:00	6:30-10:00	6:30-7:00	6:30-12:00	6:30-7:00	
WDT, New York, N. Y.	405			6:00-7:00		10:00-11:00		
WEAF, New York, N. Y.	492	6:30-9:00	6:30-9:00	6:30-9:00	6:30-9:00	6:30-9:00	6:30-10:00	6:30-9:00
WFAA, Dallas, Tex.	476	8:30-9:30	8:30-12:00		8:30-9:30	8:30-9:30	8:30-12:00	8:30-11:00
WFI, Philadelphia, Pa.	395	6:00-6:30	6:00-8:00	6:00-6:30	6:00-8:00	6:00-6:30	6:00-6:30	6:30-7:30
WGI, Medford, Mass.	319		6:00-7:30	6:30-8:00	6:00-7:30	6:30-8:00	6:30-8:00	7:30-10:00
WGR, Buffalo, N. Y.	360	5:30-9:00	5:30-7:45	5:30-9:00	5:30-7:45	5:30-9:00	5:30-7:45	
WGY, Schenectady, N. Y.	380	6:45-9:00	6:45-9:00		6:45-9:00	6:45-10:30		5:30-6:30
WHA, Madison, Wis.	360	7:30-8:30		7:30-8:30		7:30-8:30		
WHAS, Louisville, Ky.	400		7:30-9:00	7:30-9:00	7:30-9:00	7:30-9:00	7:30-9:00	4:00-5:00
WHAZ, Troy, N. Y.	380	8:00-9:30						
WHB, Kansas City, Mo.	411		8:00-10:00		8:00-10:00			8:00-10:00
WHK, Cleveland, O.	360	5:00-5:30	5:00-5:30	5:00-8:55	5:00-5:30	5:00-5:30	5:00-5:30	7:00-8:55
WHN, New York, N. Y.	360	6:30-11:00	8:30-11:00	6:30-11:00	8:30-11:00	8:30-11:00	6:30-11:00	8:30-11:00
WIP, Philadelphia, Pa.	509	5:00-6:30	5:00-11:00	5:00-6:30	5:00-11:00	5:00-6:30	5:00-11:00	3:30-4:30
WJAX, Cleveland, O.	390		6:30-8:30		7:00-9:30			
WJZ, Chicago, Ill.	448		10:00-2:00	10:00-2:00	10:00-2:00	10:00-2:00	10:00-2:00	6:00-9:00
WJZ, New York, N. Y.	455	6:30-10:30	6:30-10:30	6:00-10:30	6:30-10:30	6:30-10:30	6:30-10:30	7:00-9:30
WKAQ, San Juan, P. R.	360		7:00-8:30				7:00-8:30	
WLAG, Minneapolis, Minn.	417	7:30-10:00	7:30-10:00	7:30-12:30	7:30-10:00	7:30-10:00	7:30-12:30	7:45-8:45
WLW, Cincinnati, O.	309	8:00-10:00	10:00-12:00	8:00-10:00	10:00-12:00			
WMAQ, Chicago, Ill.	448		7:00-10:00	7:00-10:00	7:00-10:00	7:00-10:00	7:00-10:00	4:30-5:00
WMC, Memphis, Tenn.	500	8:30-9:30			8:30-9:30	8:30-12:00	8:30-9:30	
WNAC, Boston, Mass.	278		7:00-9:00	8:00-10:00	7:00-9:00	7:00-9:00	8:00-10:00	5:30-7:30
WOAI, San Antonio, Texas	385		9:30-10:30		7:30-8:30		9:30-10:30	9:30-10:30
WOAW, Omaha, Neb.	526	9:00-10:00	9:00-10:00		9:00-10:00	9:00-10:00	9:00-10:00	9:00-10:00
WOC, Davenport, Ia.	484	8:00-10:00		8:00-11:00		8:00-9:00	9:00-10:00	7:30-10:00
WOO, Philadelphia, Pa.	509	6:45-10:00				6:45-10:00		
WOR, Newark, N. J.	405	5:15-10:00	5:15-6:30	5:15-10:00	5:15-6:30	5:15-6:30	5:15-10:00	
WOS, Jefferson City, Mo.	441	8:00-9:30		8:00-9:30		8:00-9:30		
WRC, Washington, D. C.	469	7:00-9:30		7:00-9:00		7:00-9:00		
WSAI, Cincinnati, O.	309		8:00-10:00		8:00-10:00		10:00-12:00	
WSB, Atlanta, Ga.	429	8:00-12:00	8:00-12:00	8:00-12:00	8:00-12:00	8:00-12:00	8:00-12:00	7:30-9:15
WSY, Birmingham, Ala.	360	8:00-8:45		8:00-8:45		8:00-8:45		8:00-9:00
WTAM, Cleveland, Ohio	390						8:00-10:00	
WWJ, Detroit, Mich.	517	7:30-9:00	7:30-9:00	7:30-9:00	7:30-11:00	7:30-9:00		4:30-5:30

Instructions for Use.—All the hours above are given in Central Standard Time. If your city uses Eastern Time, add one hour to each of the periods stated; if your city uses Mountain Time, subtract one hour; if your city uses Pacific Time, subtract two hours. This table includes only the evening broadcasts, and on Sunday, the late afternoon program.

The "A" Battery gives power to your Radio Receiving Set. Eveready Batteries—especially made for Radio—serve better, last longer, give better results.

# 'RADIO EAR' IS NEW PAIN FOR LISTENER

## TIGHT HEAD PHONES BRING ON AFFECTION

Sharp, Shooting Sensation in Head Symptom; Doctor Tells How to Bring About Cure

By Carl H. Buttman

WASHINGTON.—A new affection of the ear is being reported by some Radiophans, who sit for long periods at their receiving sets. It is called "Radio Ear" and is accompanied by noticeable pains in the auditory appendages even when not listening in. Sometimes it takes the form of sharp shooting pains in the head near the ears which cause thoughts of possible abscesses or other serious afflictions.


Upon consultation, ear specialists usually say that the remedy is easy and fairly sure. "You are a Radiophan?" they ask. "You spend a good portion of your time with your head phones on?" Upon receiving your replies in the affirmative, they say, "Well, when you go home loosen up on your head phones. The spring is too tight and presses on some of the nerves of your ear. Just like some forms of spectacles," they will tell you. "Your head set is undoubtedly causing the pains. Relieve the excessive pressure and it will disappear."

One assurance is given of a benefit from Radio head sets, however: Youths of this generation will never have as protruding ears as some of their older brothers. All youngsters who sit for as much as three hours a day with their head phones clamped over their ears will grow up with close-fitting ears, most experts believe. Mothers who formerly tied back their offspring's ears to prevent their protruding will be saved that worry and trouble if they provide their children with Radio receiving sets and head phones.

**Boston to Continue Air Sermons**  
MEDFORD HILLSIDE, MASS.—The airphone pulpit conducted every Sunday evening by the Greater Boston Federation of Churches from WGI will be continued throughout the winter. Each month one night will be devoted to interests covered by the general committees of the federation, and an authority on each line of civic and religious activity will talk for fifteen minutes on Sunday nights.

# RETAIL FIELD TAKES PIONEER ANNOUNCER

Major J. Andrew White, former editor of an eastern Radio paper and well-known broadcaster, has associated himself with a retail Radio house. He will continue to broadcast sporting events, and is here seen announcing the recent World's Series over WJZ, New York



## Royal Order of Wouff Hong Plans to Initiate at Atlanta

ATLANTA, GA.—The Royal Order of the Wouff Hong, a secret organization of amateur Radio men, will once more predominate as the feature of an American Radio League convention when amateurs of the fourth district meet in this city for three days, December 27, 28 and 29, for a great "hamfest," according to the announcement of a tentative program today by H. L. Reid, manager of the League's East Gulf Division. An initiation into the weird order will take place on the last night of the convention.



Used by Radio Experts Because They're Federal Standard

Knowing the vital importance of the head set in their work, professional radio men demand the best. This undoubtedly accounts for the tremendous call for Federal Standard Head Sets among these experts.

A good Radio Set is frequently made poor by a cheaper head set.

130 Federal Standard Radio parts offer the radio enthusiast a complete line of guaranteed parts of one quality—the best.

List price 2200 OHMS

**\$7.00**

# Federal

Standard RADIO Products



## Tame The Wild Waves

with a Service Type 212 Receiver. Will tune through local phone and telegraph interference and get the distant stations. 30 inches loop antenna furnished with set.

Price **\$150.00**


Why take our word for what "Service" will do. Ask your dealer.

This is a TELEFORCE product.

Dealers, Jobbers, Write for Terms and Complete Information.

# SERVICE RADIO CO.

4749 Montgomery Ave., Norwood, O.




## WILLARD

WILLARD RADIO COMPANY

291 BROADWAY, New York City

"THE BEST FOR LESS"



### REINARTZ CIRCUIT EVERY PART COMPLETE

1 Reinartz wound coil, 1 tube socket, 1 rheostat, 1 23-plate .0005 MFD. variable condenser, 1 13-plate .00025 MFD. variable condenser, 3 inductance switches, 23 switch points and nuts, 6 switch stops and nuts, 8 binding posts, 2 3" dials, 1 variable grid leak, 1 .002 MFD. phone condenser, 23 feet bus bar wire, 1 high-grade panel ALREADY DRILLED AS PER DIAGRAM and complete instructions. **\$10.95**

Two-Stage Audio Frequency Amplifier—Parts complete in every detail for this Circuit—\$11.00 Specify type of tubes you intend using

#### CONDENSERS

3 Plate Variable; value, \$1.75	.....	\$1.05
11 Plate Variable; value, \$2.50	.....	1.20
13 Plate Variable; value, \$2.50	.....	1.20
17 Plate Variable; value, \$3.50	.....	1.35
23 Plate Variable; value, \$3.50	.....	1.35
43 Plate Variable; value, \$4.50	.....	1.95
13 Plate VERNIER; value, \$5.50	.....	\$3.75
23 Plate VERNIER; value, \$6.00	.....	4.00
43 Plate VERNIER; value, \$6.50	.....	4.25

Honeycomb Coils, 50 turns mounted	..	\$.95
Honeycomb Coils, 75 turns mounted	..	1.00
Double Coil Mountings	.....	2.45
Triple Coil Mountings	.....	3.35
Reinartz Coils, increased wave-length and mounting	.....	1.95

VARIOCOUPLER—Celeron Condensite and Litz Wire Wound Secondary; Value \$4.50. Special.....\$2.25

AUDIO FREQUENCY TRANSFORMER—Designed for use with W. D. 11 Tubes, list, \$4.50; price.....\$2.75

BALL BEARING INDUCTANCE SWITCH—value, 75c; special.....\$.25

V. T. SOCKETS—Nickel-plated, brass sleeve, composition base; value, \$1.00; special at......40

EXTRA SPECIAL—Telephone 3000 Ohms Headsets; \$9.00 value; reduced to.....3.50

Vernier Dial Adjuster. List, 35c; special......25

### FLEWELLING CIRCUIT EVERY PART COMPLETE

2 honeycomb coils, 1 2-coil mounting, 2 coil plugs, 3 .005 condensers, 1 variable grid leak, 1 grid leak, 1 23-plate .0005 MFD. variable condenser, 1 Vernier rheostat, 1 tube socket, 8 binding posts, 20 feet bus bar wire, 1 3" dial and 1 high grade panel ALREADY DRILLED as per Diagram in Booklet of instruction sent free. **\$11.95**

Two-Stage Audio Frequency Amplifier—Parts complete in every detail for this Circuit—\$11.00 Specify type of tubes you intend using

BEST QUALITY JACKS, Single Circuit; value, 65c; special at.....\$.30 Double Circuit; value, 90c; special at......45

MULTIPLE POINT INDUCTANCE SWITCH with Knob and Dial (15 Switch Points).....\$1.25

LIGHTNING ARRESTERS approved by underwriters......90

THREE-INCH DIALS—Unbreakable—heat resisting composition—high finish; special.. .30

TWO-INCH DIALS—Same design—for rheostats and potentiometer; special at.....\$.25


Filament Rheostat, 6 ohm......65

Filament Rheostat, 20 ohm......80

Filament Rheostat, 50 ohm......80 With 2" Dial, 15c extra.


TELEPHONE PLUGS......60

FRESHMAN VARIABLE RESISTANCE LEAK and MICA CONDENSER Combined. 75



Half the pleasure of Radio is in building your own sets. Many pleasurable and profitable hours can be passed in this way. Our service department will be glad to give you any information you need. Just drop us a line.

Every article advertised above is guaranteed by the manufacturer and by us—Mail orders filled immediately—transportation PREPAID on all orders of \$5.00 or over east of the Mississippi River. Send cash, check or money order—absolutely no goods sent C. O. D.



# INDICATIONS INSURE SUCCESS OF "WEEK"

## PLAN TO FOLLOW CHICAGO RADIO SHOW

November 25 to December 1 Set Aside as Period to Educate Public to Best in Radiophony

CHICAGO.—Immediately following the Radio show in Chicago, the week of November 25 to December 1, will be known throughout the world as National Radio Week. For the first time in the short and exciting history of the Radio industry, every faction and party in the business is aligned behind a common purpose, Powell Crosley, Jr., chairman of the executive committee for National Radio Week, announced recently.

National Radio Week proposes to present to the public the very best in Radio in the very best possible manner. To insure the success of such a movement, the co-operation of practically every branch of this great industry, which is barely old enough to be recognized in some quarters, and yet, which extends to every part of the nation and into far distant quarters of the globe, had to be obtained.

### Success of Week Assured

The thousands of Radio men who are backing the movement and the interest upon the part of the Radio public, assures the success of the week. Only in an industry of young men could this complete co-operation have been secured with so little delay. The younger generation has placed the Radio industry on its present high plane and the stabilization of the business has been accomplished more quickly than was the case in the automobile or talking machine trades.

A hearty response is reported from all the broadcasting stations, and they have indicated their willingness to follow the National Radio Week schedule of programs. Nearly five hundred firms and hundreds of publications are already behind the great movement for the Radio week.

## HOT SPRINGS TO TELL IT TO WORLD BY AIR

### Will Seek Speakers among the Celebrities at Resort

HOT SPRINGS, ARK.—N. H. R., the Nation's Health Resort, Hot Springs National Park, is to take the air! The Junior Chamber of Commerce here is behind the movement and will launch the biggest and most popular drive in the history of the resort this month. The entire proceeds will go toward providing Hot Springs with one of the best broadcasting stations in the United States.

After the station is put into service a message will be broadcast each evening at a definite hour to tell the world about Hot Springs. A special effort will also be put forth to have national celebrities who frequent the resort to send out messages. Concerts and other forms of entertainment at the hotels will be among the attractions offered Radiophans.

Hot Springs, when its plan goes through, will have established a precedent in having the first municipally owned broadcasting station in Arkansas and the only one owned by a Junior Chamber of Commerce in the United States.

## YELLOW TIP

MICROMETER ADJUSTING CRYSTAL DETECTOR Increases the Efficiency of Your Crystal Set



FINER tuning, clearest possible reception, constant adjustment until you wish to change, then—"A Twist of the Wrist—It's Set." Excellent for reflex and other circuits. Write for folder and name of your nearest dealer.

Dealers and Jobbers—Write for Attractive Proposition  
**WHOLESALE RADIO EQUIPMENT CO.**  
Exclusive Factory Representatives  
35 William Street, NEWARK, N. J.

## GIANTS-YANKEE SCORE HEARD AT WOODPILE




This "feller" doesn't need a friend, even though the woodpile kept him busy and he couldn't see the "world's serious" between the New York Giants and Yankees. You see the reason why, don't you? Fotograms Photo

### Urges Pan-American Policy

WASHINGTON.—The Pan-Americas are planning to take a prominent place in world communication in the near future. The United States has led in organizing an Inter-American Communications Commission, and is now urging the adoption of a continental policy on all matters of electrical communication, including Radiotelegraph and Radiophone operation. The next session of the body will probably be held next spring in Mexico City.

## Morrison



Loud Speaker IF YOU ARE CRITICAL

ASK the man who is proud of his receiving set—who boasts of the wonderful reproduction free from long distance stations—ask him what Loud Speaker he uses and he will say, "Morrison." Today people want to hear their opera and their dance orchestra in clear, full tones entirely free of harsh noises. Attach Morrison Loud Speaker to the tone arm of your

### PHONOGRAPH

or use it with your

### HORN

and you will be proud to entertain your friends with a real radio concert. Tones adjusted soft or loud by a turn of a little dial—no other adjustment necessary.

Sold under an absolute money-back guarantee. Order from your dealer or send direct to factory.

**\$10.00**

NICKEL PLATED MODEL Complete with 5 foot cord

**\$15.00**

GOLD PLATED MODEL

Illustrated Catalog will be sent free on request

### DEALERS

Morrison Loud Speaker is Radio's most popular merchandising unit. We have a plan to help you sell that many of the best dealers in the country are finding quite profitable. Wire us today.

**Morrison Laboratories, Inc.**  
343 Jefferson Avenue, East, Detroit, Mich.

## Cotton Pickers Stay on Job to Hear Radio

### Plantation Community Center Has Complete Airphone Set

CLARKSDALE, MISS.—The typical Southern plantation has modernized itself as inventions and electric developments have brought improvements which could make even better the carefree life of the South. The latest development is the addition of complete Radio equipment on the plantation owned by John Bell Hood, near Jonestown, Miss. The plantation owner has erected a community center to house the Radio and provided a stage, dance floor and gallery.

A six-piece orchestra made up of negroes from the plantation takes turns with the Radio in the community meets held there. Every worker on the plantation is free to attend the Radio concerts and the plantation motion picture show which takes place in the same building. Out of 1,400 negroes employed on the plantation, known as "Matagorda" and consisting of 7,000 acres, not one has joined the hegrira of negroes to the North.

Washington Dealers Organize  
WASHINGTON, D. C.—Radio dealers here have recently formed an organization known as the Reliable Radio Dealers of Washington.



## SPECIAL (IMPROVED MODEL) Direct From Manufacturer to Consumer LOUD SPEAKER

Genuine Wood Fiber Horn (With Unit and Cord) Entirely eliminates that annoying metallic sound. Positively the only WOOD FIBER HORN on the market today. 10-inch Bell with Standard Attachment; Complete. Height 24 inches. Colors, Black, Mahogany and Olive Green.

Price **\$8.00**

(For a limited time only.)

Delivered to any part of the United States and Canada

**EMIL DECLYNE**

15 Park Row, Room 2525, NEW YORK CITY  
Send M. O. or C. O. D. Dept. R. D., Barclay 6298

## The New Grebe Broadcast Receiver



Point No. 2 A FOUR-TUBE RECEIVER in which you may use all kinds of tubes—in any desired combination.


No storage battery unless you desire it.

Just One of its Seven Points of Satisfaction

Licensed under Armstrong U.S. Pat. No. 1,113,149

Ask Your Dealer

A. H. GREBE & CO., Inc.  
Richmond Hill, N. Y.



## RADIO AT N.Y. PRICES Daily Parcel Post

The Prices Quoted Below Deliver Goods to Your Door  
REFERENCES: R. G. Dun, Bradstreet, Coal and Iron National Bank, Corn Exchange Bank, New York City. No salvaged goods handled. Only standard brands in original packing, which bears our and the manufacturers' guarantee. Due to our tremendous output we can undersell any of our competitors. Send your order in today and insure prompt delivery.

HOW TO ORDER—Write your order plainly; state number, description and price of items wanted. Send Post Office or Express Money Order, personal check or bank draft.

- WOOD CABINETS**  
Highest grade Mahogany finish Cabinets. Hinged top. These cabinets are being sold at less than one-half regular value.  
C57 Wood Cabinet; panel size 7"x10". Each.....\$2.50  
C58 Wood Cabinet; panel size 7"x12"..... 2.75  
C59 Wood Cabinet; panel size 7"x14"..... 3.00  
C60 Wood Cabinet; panel size 7"x18"..... 3.50  
C61 Wood Cabinet; panel size 7"x21"..... 3.75  
C62 Wood Cabinet; panel size 7"x24"..... 4.00
- R.A.U. FREQUENCY TRANSFORMERS**  
C70 Tri-coil for 201A or 301A tubes.....\$1.95  
C71 For 199, 299 or W.D.11 and 12 tubes..... 1.95  
C72 Eria AB1..... 3.75  
C73 Eria AB2..... 3.75  
C74 Eria AB3..... 3.75  
C75 Eria Reflex..... 4.65

- VARIOCOUPLER**  
C77 High Grade 180 Degree Coupler made of Bakelite tubing wound with green silk wire. Special.....\$2.65  
C78 Variometer, same specifications..... 2.65

- MISCELLANEOUS**  
C163 Spaghetti Tubing per yd.....\$.09  
C164 Synthetic Crystal......30  
C165 Ground Clamps......17  
C166 Black Rubber Binding Posts......05  
C167 Nickel Plated Binding Posts, 2 for......05  
C168 No. 18 Annunciator Wire, half pound coil......79  
C169 6 ft. Phone Cord with Tips..... 1.95  
C170 20 ft. Extension Cord with Tips......05  
C171 Wall Insulators, Porcelain......10  
C172 Tubular Porcelain Lead-in Insulators, 6-in..... 1.45  
C173 Reinartz Coil..... 2.42  
C174 Cockaday Coil......25  
C175 2 in. Dial and Knob......35  
C176 3 in. Dial and Knob......49  
C177 4 in. Dial and Knob......49

- 1 1/2 VOLT DIETZEN TUBE**  
Two-element Fleming valve effect; operates on one dry cell with or without "B" Battery; wiring diagram free with each tube.  
C95 Dietzen Tube.....\$1.00  
C96 Socket for Dietzen Tube......40

- BAKELITE TUBE SOCKETS**  
Moulded of brown bakelite; Binding Post Connections.  
C99 Standard Type for 201A, 301A, W. D. 12..... 39c  
C100 For U. V. 199, U. V. 299, Socket..... 39c  
C101 For W. D. 11, C11..... 39c

- Audio Frequency Transformers**  
The following transformers are guaranteed standard makes, and will produce very efficient results.  
C63 Dietzen 3 to 1 Ratio.....\$3.95  
C64 Dietzen 5 to 1 Ratio..... 3.95  
C65 Dietzen 10 to 1 Ratio..... 3.95  
C66 Acme Audio..... 4.25  
C67 Amertran..... 5.95  
C68 U. V. 712 R.C.A..... 5.75  
C69 U. V. 714 R.C.A..... 5.75

- Loop Aerial**  
C76. Can be assembled by anyone in five minutes; all wood parts, wire and binding posts included, complete.....\$1.00

- Standard Brand Head Phones**  
C134 Brandes Superior.....\$5.25  
C135 Dictograph.....\$6.75  
C136 Baldwin Type "C" Double.....\$9.85  
C137 Baldwin Type "C" Single.....\$4.95  
C138 Western Electric.....\$10.50  
C139 Dietzen 2000 ohms extra special.....\$3.95

- VARIABLE AIR CONDENSERS**  
These condensers are made of heavy aluminum plates, high grade bakelite ends.  
C110 21 Plate .0005 Mfd.....\$1.75  
C111 11 Plate .0025 Mfd..... 1.25  
C112 3 Plate .0095 Mfd......95  
C113 43 Plate .001 Mfd..... 2.25

**Modell's**  
ESTABLISHED 1895

**71 Cortlandt Street**  
NEW YORK, N. Y.  
America's Greatest Radio Mail Order House  
ELEVEN NEW YORK STORES

# WOR, WJAX AND KGW THEMSELVES



The popularity of a broadcasting station is not due exclusively to the performers; up-to-date equipment has its share and so has the announcer. Above is Joseph Barnett, familiar to listeners in on WOR, the Newark, N. J., station, as "J. B." In the circle is E. J. Johnson, who has won deserved recognition for the efficient manner in which he has worked out the broadcasting of "The Wave from Lake Erie" from WJAX, the Union Trust Company's station at Cleveland. Above Photo © K. & H.

Above is presented another announcer, Richard W. Haller, who is also director of The Oregonian's station KGW, at Portland. His popularity is in part due to his being "Keeper of the Grand Goat" of the "Keep Growing Wiser Order of Hoot Owls," the famous burlesque club of KGW. Whether or not there actually is a goat to be kept is uncertain and doesn't matter, but natural "baa-as" are often heard and listeners in have presented him with enough goat bells to make a fair set of chimes.

## U. S. TAKES DAILY TESTS OF LENGTHS

### KEEPS BROADCASTERS ON LICENSED WAVES

Prompt Readjustment of Plant by Radio Supervisors Follows Disclosure of Inaccuracy

WASHINGTON, D. C.—In order to assist the Radio Inspection Service in maintaining broadcasters on their licensed wave lengths, the Bureau of Standards now makes daily measurements of the waves radiated from various stations. The measurements to date have been mainly on Class B broadcasting stations, and also on the high wave length, high-power transoceanic stations.

The measurements show in general a close degree of adherence to the assigned frequencies. In a few cases where the tests showed stations to be seriously off the assigned wave, the supervisors of Radio have readjusted the stations to bring them within the required tolerance.

In only a few cases are the stations maintaining without exception the assigned frequencies so closely that the wave can be used as a frequency standard.

#### To Use Waves to Calibrate

Special attention is being given by the bureau to the stations which do maintain such standards, and an announcement will be made later in the Radio Service Bulletin, stating the degree of constancy that has been observed, so that persons may utilize the transmissions from these sta-

tions as a standard for the calibration of apparatus.

The method used by the bureau in measuring the waves of distant stations involves the use of a local Radio frequency generator. This is adjusted to the same frequency as the wave received from the transmitting station, the adjustment being determined by receiving both frequencies in a receiving set and varying the local Radio frequency generator until a zero beat note is obtained. The frequency of the local generator is then measured with a wavemeter.

## New Firm Organizing in Italy Will Make Outfits

WASHINGTON, D. C.—Reports from the American commercial attaché at Rome state that a firm has just been organized in Italy for broadcasting and for the manufacture of Radio apparatus. While information in regard to the new company is somewhat limited at present, the enterprise has every indication of being an attempt to provide Italy with a huge Radio manufacturing and operating organization similar to the Marconi Company of England and the Radio Corporation of America. Up to the present time Radio activities in Italy have been almost solely confined to the government.

## Names New Seattle Inspector


WASHINGTON.—The Department of Commerce has designated Harold D. Hayes, of San Francisco, as assistant Radio inspector to succeed Louis E. Richwein, of the Seattle office, who died recently. Mr. Richwein, who was transferred from Baltimore in 1922, served until recently at the headquarters of the seventh district at Seattle, as assistant to Supervisor of Radio O. R. Redfern.

## Floodbound "Gadders" Get Late News by Air Bulletin

FT. WORTH, TEX.—WBAP, Star-Telegram here, came to the rescue of a party of one hundred marooned traveling and business men at the Oriental Hotel, Altus, Okla., recently, by furnishing them with a special bulletin of the news, the only word they had received in some hours. A flood had cut off the one hundred men from communication and the hotel man-

agement wired asking a special news bulletin for the benefit of the floodbound travelers. Accordingly, WBAP broadcast a condensed news bulletin before the usual 7:30 program.

Congress will be asked at the next session for increased appropriations, amounting to more than \$100,000, to meet the department of commerce needs in Radio control.



# E. J. Flewelling Sockets

The action of your tube is greatly dependent upon the socket that holds it. Mr. Flewelling has shown the gains possible through careful design in this important part of the Radio set and now you are offered the benefits of his experience and research—a socket as near perfect as we can make it. Losses due to faulty contacts, capacity between terminals etc., are entirely eliminated. Order a set today.

**BUELL MANUFACTURING COMPANY**  
2977 COTTAGE GROVE AVE.  
CHICAGO

**\$1.00**  
At your dealers or post paid.

#### RADIO TALKS

So called tube noises are most often caused by poor contacts, dampness, soldering paste and many small condenser effects caused by crossing, touching and parallel wires throughout the set. Clean up these defects and then listen-in for "tube noises." You will be surprised to find how quiet your tubes really are.

*E. J. Flewelling*

## The New Grebe Broadcast Receiver


THE 20-foot silk-covered wire supplied with this Receiver is the only antenna required. This wire may be concealed behind the picture moulding or run along the baseboard.

Write for "Grebe Radio in the Well-Appointed Home."

Licensed under Armstrong U.S. Pat. No. 1,113,149

Ask Your Dealer

A. H. GREBE & CO., Inc.  
Richmond Hill, N. Y.





## WOMAN RUNS CO-OP PLANT FOR 2 CITIES

IN HEART OF "LAND OF 10,000 LAKES"

Minneapolis and St. Paul Join Hands in Reopening WLAG with a New Slogan

By Vera Brady Shipman

A visitor from WDAP, Chicago, announced the other night over Station WLAG. He opened with "The Land of a Thousand Lakes" and when he was corrected, he said he didn't think there could be ten thousand lakes in the world. But there really are—not only in the world, or in the Northwest, but right within the borders of Minnesota. There are actually ten thousand lakes counted and named besides numerous too small for consideration. The WDAP visitor stands corrected and probably much abashed.

A visit to WLAG with its able woman director, Eleanor Poehler, was an interesting climax to a hundred-and-fifty-mile motor trip from my country place in upper Wisconsin.

With so many stations financed by newspapers, electric companies and a few individuals and colleges, a station with the co-operation of two cities is unique. It is a great advertising enterprise and with the Twin Cities co-operating for success, its publicity gains authority in the combine.

Reopen with New Slogan

WLAG opened September 14, 1922, as "The Call of the North" and was financed by Minneapolis concerns only. On August 1, 1923, St. Paul concerns took their places with the withdrawal and combining of certain Minneapolis subscriptions and the station, on 417 meters wave length, adopted the combined slogan of the ten thousand lakes. With equipment owned and operated by the Cutting and Washington Radio Corporation, a number of organizations subscribed for WLAG's financial support. Those from Minneapolis were the Minneapolis Loan and Trust and Northwest National Bank, L. S. Donaldson, Benzo Gas Company, Munsingwear Corporation, and from St. Paul, the retailers' and jobbers' organizations, Brown and Bigelow Advertising Agency, and the Purity Baking Company.

The Northwest Farmstead, a Minnesota farm journal whose editor James Kelley

## TWIN CITIES HAVE JOINT BROADCASTING PLANT



The Twin Cities get along nicely at their new co-operative broadcasting plant, WLAG. There is a studio in each city, from which programs are alternated. The managing director, Eleanor Poehler,

(in the circle) is an accomplished musician and is assisted by an able staff. The chief operating engineer is R. R. Sweet, and his first assistant C. W. Tuttle, shown at the right and left of the circle

and managers W. C. and H. H. Allen are progressive in ideas of Northwest publicity, each evening gives an hour of lectures for farm improvement. Some of these are given by the University of Minnesota faculty or under the university supervision.

### Plan to Make New Orleans Radio Center of South

NEW ORLEANS.—The New Orleans Radio Association held a meeting at the Grunewald hotel recently, electing the following officers: Valdemar Jensen, president; C. E. Ammen, vice-president; H. E. Faller, secretary-treasurer, and Edward T. Jones, publicity chairman. Plans to make New Orleans the Radio center of the South were discussed, and resolutions to bring better and more frequent musical programs to fans listening in on the 1923-24 offerings from Crescent City broadcasting stations were passed.

Constant improvements are being made in the operating rooms. Chief operator R. R. Sweet and his assistant C. W. Tuttle are shown in the picture. Paul Johnson is chief announcer with frequent announcements by Eleanor Poehler, the director. The Minneapolis station is operated at the Oak Grove Hotel, in Minneapolis' residence section. Operating rooms, studio and office are on the sixth floor of the hotel.

The combining of the Twin Cities for one broadcasting station with studios in each city, from which they alternate programs, has found a happy solution for local rivalry. The broad spirit of both cities sponsors programs of varied inter-

est. Each subscriber has a part of the daily schedule. Musical programs are divided according to the time allotted each organization.


The managing director, Eleanor Poehler, is an accomplished musician and on the evening I visited WLAG, it was my good fortune to hear her sing on the midnight program.\*

A prize of \$500 is being awarded by Station WGY for the best Radio drama submitted during the three months' period ending December 1. The winning play will be sent into the air during the winter, when transmitting conditions are ideal for a large audience to hear it.

**T**HE De Forest name has been in the forefront of radio research for twenty-three years. De Forest invented the three-electrode vacuum tube which makes present-day radio possible. The sets and parts made today by the De Forest Company are worthy of the De Forest name.

DE FOREST RADIO TEL. & TEL. CO.  
Dept. R. D. 3 JERSEY CITY, N. J.

If Located West of Pennsylvania, Address  
DE FOREST RADIO TEL. & TEL. CO.  
Western Sales Division  
Dept. R. D. 3 5680 12th St., DETROIT, MICH.



## Cotogrip


"Built First to Last"

This little beauty was approved by our engineers only when convinced that they had produced the one socket that combines all the essential features of a good socket.

1. Positive Cotogrip Contacts.
2. Hard Rubber Insulation.
3. Rugged Construction.
4. Compact Design.
5. Concealed Mounting.


It is impossible to show the unique mechanical action of Cotogrip contacts in a photograph. It is different from any other socket you have ever seen. This socket will interest you in every way.

You ought to have one.  
Ask Your Dealer



PACIFIC COAST BRANCH:  
329 Union League Bldg.  
LOS ANGELES

## COTO-COIL CO PROVIDENCE



## UV-199

Radiotron UV-199 is a small tube—but 3½ inches high. But it is a tube of big performance—an excellent detector, audio and radio frequency amplifier.

It means economy—lives longer than other tubes—and draws but .06 ampere, filament current. Nothing like it for portable sets, because it can be used with little flashlight batteries.

Price  
**\$6.50**

Radio Corporation of America

Sales Offices: Dept., 3002

233 Broadway, New York

10 So. La Salle Street,  
Chicago, Ill.


433 California Street,  
San Francisco, Cal.

Be sure the vacuum tubes you buy are marked Radiotron.

# Radiotrons

REG. U. S. PAT. OFF.

**DOUBLE TUBE CIRCUIT IN SIMPLEX PICTURE FORM**



THERE have been innumerable single-tube Reflex diagrams shown, but double-tube circuits have not been quite so numerous. The circuit shown is exceptionally simple for one of this type. In fact, if it wasn't for the crystal detector, we'd be accused of palming off a slight modification of a regeneration

type. It only goes to show the little difference that actually exists between regeneration and some of the Reflex type of circuits.

A variocoupler and two variable condensers make up the tuning control and give very good selectivity. The condenser across the coupler rotor should be of the

vernier type. A by-pass condenser of .005 mfd. capacity is shunted across the A and B batteries. The plate batteries consist of four 22 1/2-volt units or their equivalent. A hard tube is required. The circuit gives good volume, and will give good distance results, but good aerial and ground connections are required.

**Condenser Capacity Rating**

The rating of variable condensers by the number of plates is not a satisfactory method of determining the capacity. This is apparent when we consider that the electrical capacity of two different commercial types of condensers having the same number of fixed and movable plates will differ considerably.

The proper method of rating any condenser is by its capacity in microfarads, as determined by actual laboratory tests. —Peter J. M. Clute, Schenectady, N. Y.



**Unequaled Clearness Thru a New Magnetic Principle of Construction**

Distant and local broadcasting reproduced without distortion. Endorsed by Radio Experts—Lieut. Commander Raison, U. S. Navy says: "I use your headset in preference to others in experimental work."

**Trial Offer** If your dealer is out of "Repeaters" send \$5.00 and dealer's name for complete set subject to refund in full within 10 days if not perfectly satisfactory.

**Moss-Schury Mfg. Co., Inc.**  
Radio Division  
2011-2015 Franklin Street, Detroit, U. S. A.  
Manufacturers of precision electrical devices

**Semi-Indoor Aerial**

There are many Radiophans who live in apartment houses and other places where an outdoor aerial cannot very well be employed. A very good way to overcome this difficulty is to replace the window screens with copper screening. At the corners of a screen frame tack a strip of rubber inner tubing for insulation. If more than one screen is used, connect them together and take the lead-in off the screen that is nearest the Radio set.

Fifty assorted flathead solid brass machine screws, nuts, washers, copper lugs, 50c. Eight initialed binding posts, set, 60c. Twelve nicked binding posts, 50c. All three items, \$1.50. RADIO LIST for stamp. All prepaid. Stamps accepted. Kladag Radio Laboratories, Kent, O.

A vacuum tube regenerative set, using only one tube, will bring in signals from nearly the same distance as a set having an audio frequency amplifier. The ampli-

fier only serves to increase the strength of signals brought in by the detector tube.

**FREE with every Purchase of \$10.00 and over, a small 22 1/2 V. B. Battery**

- \$18.00 Westinghouse Rectigon Charger.....\$14.63
- 30.00 Music Master Loud Speaker..... 27.00
- 5.00 U. B. 199 Transformer, 6-1 ratio..... 3.25
- 2.00 Tri-Coil Reflex Transformer. (Specify tube used)..... 1.72
- Thordarson Transformer, low ratio..... 3.25
- High ratio..... 3.75
- 3/16" Dilecto XX Bakelite Panels at 2c square inch.....
- 1/8" Dilecto XX Bakelite Panels at 1/2c square inch.....
- 1/4" Dilecto XX Bakelite Panels at 3c square inch.....
- Ritter K. D. Portable Loop, complete.. 1.00
- ADVANCE B BATTERIES**
- 1.75 22 1/2 V., Small..... .75
- 3.00 22 1/2 V., Large..... 1.45
- 4.25 45 V., Small..... 2.00
- 5.50 45 V., Large..... 2.90
- Aerial Wire, 7 Strand, Tinned Copper, 100 ft. Coils..... .60
- 5.00 13 Plate Vernier Condenser..... 2.65
- 6.00 23 Plate Vernier Condenser..... 3.50
- 6.50 43 Plate Vernier Condenser..... 4.00
- 7.00 Pioneer Moulded Bakelite Variocoupler 4.95
- 6.50 Pioneer Moulded Bakelite Variometer.. 4.85

Only money orders accepted; must include postage. Our merchandise is guaranteed by the manufacturer and is of the highest quality.

Send for monthly price list.  
**MARVEL RADIO SPECIALTY CO.**  
132 Nassau Street New York City, Dept. R. D.


**FREE RADIO VACUUM TUBE SET**



**NAZELEY'S**

**PORLENA FOLDING LOOP**  
(PATENT PENDING)

SPREAD, 28 INCHES  
GENUINE BAKELITE FACINGS  
85 FT. GREEN COVERED WIRE  
MOROCCO FINISHED CASE



*Practical—Efficient—Perfect*


RICH MAHOGANY FINISH

FOLDS UP LIKE AN UMBRELLA; WORKS LIKE A CHARM

In individual Morocco covered Tube **List \$7.00 Each** One dozen to a Case

**J. NAZELEY CO., 571 Hudson St., New York City**

**ACOUSTICALLY CORRECT!**



The Trimm extra large Loud Speaker unit with its wonderful ADJUSTO instantly regulating loud speaker to signal strength insures greatest volume without flaws or distortion. At three prices:

**Acousticola** STANDARD MODEL  
With non-metallic horn, 21 1/2" high; bell 10" diam. **\$22.50**

**Acousticola Grand**  
with solid cast aluminum horn the world's finest loud speaker **\$35.00**

**ACOUSTICOLA** Phonograph Attachment **\$10.00**

**TRIMM HIGH GRADE HEADSETS**

"PROFESSIONAL"  
model-3000 ohms  
**\$7.65**

"DEPENDABLE"  
model-2400 ohms  
**\$5.00**

Any Trimm product shipped and sold on approval and Guaranteed FOR LIFE. Write for descriptive folders. Mention your dealer's name.

**TRIMM RADIO MFG. COMPANY**  
Dept. 54, 24-30 S. Clinton St. CHICAGO, ILL.

# Further Details of the Famous Miloplex Hook-Up

## Part VII—One Theory on the Operation of the Set

By the Mystery Man

**F**EAR be it from me to criticize cooks, and to that I add Radio engineers; both are as temperamental, as fussy about their calculus and trigonometry, their B. T. L.'s and what's what, as a tin soldier with a rusty gun. They just won't agree or positively say, and yet out of the swarm of theories relative to the Plexy that have reached me, there is a sameness in thought that clearly indi-

would bring my cook back. Stretch—say, I've now stretched it until I'm afraid it will rip the casing. Mercy, if I stretch it any more I'll have to touch the editor for a rubber hat.

But way back among the records in the archives of Radio comes quite a plausible theory from my good friend and counsel Harry Marx, Radio Digest's Technical Editor, who most modestly asks me to distinctly understand his version as but a theory, sort of f. o. b. as it were, subject to change without notice. Just like a shirt, you know, one is supposed to ask permission before publication, but his phone was busy. No, that wasn't the reason; the true story is I got the wrong number and Mabel answered—curses, I always did get house, car license and telephone numbers mixed up and besides one shouldn't park more than an hour on a phone line.

Now get this, it's a thinker. Mr. Marx, says "A circuit consisting of an inductance and capacity, will, when energized from a source, oscillate at a particular frequency dependent upon the values of such inductance and capacity; if either of the two are variable, then the value of the frequency is variable." That's what he said, but read it again and note particularly that Mr. Marx specifically states "when energized from a source," because he carries on amplifying this basic thought through introducing another most interesting statement, which follows as his second assumption, his first being omitted temporarily.

"The second assumption is that as the separate oscillating circuit is capable of adjustment to a distinctly lower or higher frequency than that of the primary, it is well within reason to believe that a heterodyning effect can be and possibly is produced, the altered frequency being superimposed upon the incoming wave, and as the oscillating circuit is totally flexible both in capacitance and inductive relation to the stator, then through proper adjustment the highest efficiency of circuit adjustment is possible, resulting in a volume and selectivity far surpassing that of a normally controlled circuit." And I'm going to be just tattle-tale enough to let him read that "them's my sentiments" until proved otherwise; besides haven't three of those research fellows told me the same thing.

But what does it all mean? Not a varying frequency, although the circuit does

vary and start "souping" if one's adjustments slip into low gear, but you can't—neither can I—hold it on a varying frequency. If we could we would have a true super-regenerator, and never having met a varying frequency "face to face," I hesitate to tell it to "be good" when it sticks its nose into the Plex. Well, I ask again, what is it all about? You get an inch or two nearer to true resonance, the greatest atomic active force existent for space annihilation.

It's that wonder of wonders, the invisible power which caused you and me as "kids" to get an immediate answer when we hollered down the well, four letters long, wide and high, and yet to each of us whether we be six or sixty, ever mysterious, "an echo."

If you or I know how to listen when it's going or coming; if we can but arrange a device that will synchronize perfectly with the incoming wave, or should I say, the passing wave, I would hesitate to assume how very little power it would require to transmit and receive a signal across the continent. You among my readers who understand the theory of operation of the synchronous motor quite appreciate the goal I have been striving for in King Miloplex, fully realizing that this so-called fourth or oscillating circuit is not far from being related to the basic theory of the synchronous motor, and while it is my intention to present the views of others, ever searching for a theory that can be substantiated by proof positive, not accepting either Mr. Marx' explanation or others which will follow, yet most appreciative to him and glad to say that it possesses much of logical reasoning, I cannot pass without notice those who have offered criticism. It may

interest them to learn that such letters interest me most, as it is from constructive criticism only that any good can be derived, destructive criticism being mostly ignored because the critics often write first and think afterward. But to you—who number so many—that are offering suggestions for improvement I am indeed grateful.

Many are asking, can they use this or that tube, this or that battery. Use anything you like, the Miloplex isn't fussy; in fact, its outstanding feature is that an eight-year-old boy can build it and it will at least say "Hello, Kid!" for him. But it is a stickler for good parts. "As ye sow, so shall ye reap"; if you want better, build better. Good, yes, excellent parts are made, but you have to find for them.

However, let us drop back into a further discussion of Mr. Marx' theory by going a step farther. Many ask me if my oscillating circuit is not in reality a rejector circuit, an acceptor circuit, or a wave trap? I am believing all these questions are asked because, in principle, it is identical mechanically with the above, and it's somewhat like the girl who "was what she was dressed." Technically, and omitting its location relative to the balance of the Miloplex, it is in reality a tuned Radio frequency circuit, that and nothing more. Then visualize, if you will, your primary with its condenser and aerial with ground completing another with the broadcasting station eliminated from consideration. In practice, if it is possible to adjust each of these circuits to synchronism with closely allied frequencies, then the product of the two will produce a third; or to pos-

(Continued on page 20)

### THE MYSTERY MAN

Dear Sir:

In the September 29 issue of Radio Digest you gave a hook-up of the Miloplex circuit. I didn't pay any attention to it at the time, but when you came out with the October 6 article I sat up and took notice. Then I started to work and to say I got results is putting it rather mildly—but more about that later.

I used a fiber panel, a home-wound variometer, a B battery nine months old, and started in; couldn't get anything at first but a lot of humming and laid it to a 33,000-volt line across the street. After about 10 minutes of this I started looking around for trouble in the set, and I found out it will not work if the B— is connected to the A—. After this change it started to cut up something awful; don't know what it did, but it did anyway.

You can't make a "bug" quit, so I kept right on. Last night I put one stage of amplification with it and got— you say what! Oh, yes, the following: KSD, WFAA, WQAW, KYW, WDAP, WOS, WLAG, WMAQ, WGY, WHB and Zion City, Ill., some of them so loud I could hear them 10 feet away.

What we need in the set is a tuner that is not so critical, the variometer works so fast I can't catch them fast enough to hold them. Now, Mr. Editor, please see that he does this, let's make him work. Respectfully,

J. W. Lickiss.

icates few if any care to digress from precedent. But their unusual interest still remains; all are "cutting and trying," so I guess the soldering iron and pliers will win. The harmonics of a "pin stuck" baby cannot be defined or expressed in equations. I opine, then, that the gentleman who addressed me in perfect German script with an 800-word thesis on the Miloplex theory will pardon my not having received but a marking of 40 in German; therefore, I can only unknowingly admit that his theory is unquestionably correct, if he said what I think he said. The Bureau of Scriptology is now dissecting it, the patient may die, but I hope the operation will prove a success.

Another very considerate fan frankly tells me that I only need to stretch my imagination in order to get the correct Miloplex theory; that's what I thought



ON APPROVAL FOR 30¢  
ZOBEL-STEIN LABORATORIES  
322 9TH ST. BROOKLYN, N.Y. SOUTH 2650

### LOUD SPEAKER

Large. Scientifically correct. Non-metal prevents tinny sounds. Complete..... **\$8.00**

Single Control Distant Receiving Tube Set. Easily assembled, mahogany cabinet, drilled panel, vernier condenser and vernier rheostat, tube, batteries and phones with directions. Complete..... **\$19.00**

Signal Corps Phones..... 3.00

Our catalogue with attractive discounts, latest diagrams and other valuable radio information..... 10c

Fremont Radio Sales Corp.

227-229 FULTON ST., NEW YORK CITY

### SUPER VALUES

#### NEUTRODYNE PARTS

Workrite Neutrodyne Kit  
Consisting of 3 Neutroformers  
and Variable Condensers with 2  
Neutrodons. Our Price..... **\$16.00**

FADA Neutrodyne  
Parts ..... **\$18.75**

WORKRITE Neutroformers  
only (Set of three)..... **\$5.00**

#### LOUD SPEAKERS

List Price	Our Price	\$30.00 Music Master	Our Price
\$161.00 Western Electric 10-A.....	\$125.75	25.00 Atlas Amplifier.....	19.50
55.00 Western Electric 10-D.....	44.00	25.00 Trinity Type A-1.....	19.50
60.00 Magnavox Type E-3.....	51.00	22.50 Belcanto.....	18.00
35.00 Magnavox Type R-2.....	29.50	28.50 Dictogrand.....	23.50

List Price	Our Price	List Price	Our Price
<b>\$7.00 FEDERAL</b> .....	<b>\$5.50</b>	1.80 3 PLATE VERNIER.....	.90
\$6.00 BRANDES.....	\$5.25	5.00 23 PLATE VERNIER.....	2.50
8.00 N&K GERMAN.....	5.75	5.50 43 PLATE VERNIER.....	2.75

List Price	Our Price	List Price	Our Price
5.00 RADIOTRON U. V. 200.....	\$3.95	4.50 ALL AMERICAN, 3 to 1 Ratio.....	\$3.95
5.00 CUNNINGHAM C. 300.....	3.95	4.75 ALL AMERICAN, 5 to 1 Ratio.....	4.10
6.50 RADIOTRON U. V. 201-A.....	5.75	4.75 ALL AMERICAN, 10 to 1 Ratio.....	4.10
6.50 CUNNINGHAM C. 301-A.....	5.75	7.00 AMERICAN.....	5.55
6.50 RADIOTRON W. D. 11.....	5.75	7.00 FEDERAL No. 65.....	5.55
6.50 RADIOTRON W. D. 12.....	5.75		
6.50 CUNNINGHAM C. 11.....	5.75		
6.50 RADIOTRON U. V. 199.....	5.75		
6.50 CUNNINGHAM C. 299.....	5.75		

List Price	Our Price	List Price	Our Price
1.80 3 PLATE VERNIER.....	.90		
5.00 23 PLATE VERNIER.....	2.50		
5.50 43 PLATE VERNIER.....	2.75		
3.00 23 PLATE PLAIN.....	1.50		
2.80 43 PLATE PLAIN.....	1.90		

#### AUDIO TRANSFORMERS

List Price	Our Price
4.50 ALL AMERICAN, 3 to 1 Ratio.....	\$3.95
4.75 ALL AMERICAN, 5 to 1 Ratio.....	4.10
4.75 ALL AMERICAN, 10 to 1 Ratio.....	4.10
7.00 AMERICAN.....	5.55
7.00 FEDERAL No. 65.....	5.55

ALL Mail Orders Shipped Promptly Send Money Order, including Postage

Write for Our Catalogue B

The RADIO MAIL ORDER HOUSE—Known for Low Prices

# HANES-ZENER

3 WEST 29TH STREET, NEW YORK CITY

# Learn Radio At Home

## Earn \$2,400 to \$10,000 a Year

The man who would be a success in business today must be a specialist. The market is already crowded with clerks, stenographers, accountants and detail men of every description. That is why

the chances are so strongly against their getting big pay. But look at the men who are earning real big money today. In practically every case we find them to be specialists!

### RADIO NEEDS TRAINED MEN

There is probably no other field today where specialists are needed more than in Radio. Trained men are needed in every branch of this fascinating, profitable profession. And the opportunities for trained men are great—almost without limit. Even in this field, the men who stand the best chance of landing big are those who enter this field NOW while Radio is growing so rapidly.

and see the world if you care to, or to establish a business of your own. It will make you a specialist with the unlimited opportunities that are open to a specialist in this tremendous uncrowded field of Radio.

#### FREE BOOK Describes Opportunities

To any man who is eager to better his condition, and is interested in the remarkable opportunities in Radio, we will gladly send a copy of our newly published book on Radio—absolutely free. You assume no obligation whatever in sending for this interesting, helpful book. It is yours for the asking.

Send for your copy of "How to Learn Radio at Home" and learn all about the wonderful opportunities that are opening in Radio, how we train men for them and help them to the best positions. Read actual experiences of many of our students since we have trained them. "Tune in" on a real job. Mail the coupon for this interesting Free Book today. It will pay you!



National Radio Institute, Dept. 55-L, Washington, D. C.

### You Can Qualify at Home Easily and Quickly

If YOU are sick of plodding along in the daily grind of monotonous office routine—held down by thousands of men doing the same work you are—get out of the rut into a big paying profession. Learn Radio at home. A short course of training will quickly enable you to be independent, to travel

Without any obligation on my part, please send me a FREE copy of your book, "How to Learn Radio at Home." Also tell me how your Free Employment Service will help me to a position and send details of your special short-time offer.

Name.....

Street.....

City..... State.....

# GRAND OPERA OPENING AT KYW FEAT

## Story of "Lucia" on KYW November 10

THE theme of this opera, written by Salvatore Cammerano, was taken from Sir Walter Scott's novel, "The Bride of Lammermoor," and became a great Italian opera through the genius of an Italian, Gaetano Donizetti, who was himself of remote Scottish ancestry. The opera was first produced in Naples, almost a hundred years ago.

The scene is laid in Scotland during the seventeenth century. Briefly, it is the story of a cruel brother, Henry Ashton of Lammermoor, who plans to marry his sister, Lucia, to a man she does not love, in order to repair his fortune and better his political position. To gain his end he forges a letter from the lover, Sir Edgar of Ravenswood, in which he insinuates that the latter has married while in France. Just as Lucia, goaded to despair, has signed the marriage contract with Lord Arthur Bucklaw, Edgar appears and denounces her. Overcome with grief Lucia kills her husband while the wedding guests are still making merry. When she recovers her mind, the horror of her deed overwhelms her and she soon dies. Edgar wandering in the graveyard of his ancestors, hears the death bell tolling, and knowing that Lucia has remained faithful to her love, falls on his sword and dies.

## Tuesday, November 6

**CKAC, Montreal, Canada (Eastern, 430), 7:00 p. m.** - Kiddies' stories in French and English; 7:30, Popular selections, La Presse Orchestra; 8:15, French concert, Paul Vennart, director.

**KDKA, E. Pittsburgh, Pa. (Eastern, 326), 6:15 p. m.** - Dinner concert, Grand Symphony Orchestra; 7:30, "See with the Eyes of Youth," Dr. A. Goldstein; 7:45, "With the Deep Woods Lady," 8:00, Special service, Shady Side Presbyterian Church, Tenth Anniversary of the Pastorate of Dr. Hugh T. Kerr; Dr. Charles R. Brown; Mrs. Christine M. Clemons, soloist; 9:15, Concert, pupils of Joseph H. Moore, Margaret Waring, pianist; Marion White, pianist; Prof. W. Trinks; Mrs. W. Trinks, soprano; Harold Trinks, violinist; Mrs. Albert Young, soprano; Blanche Ahlstrom, violinist; Robert J. Dods, violinist; Richard J. Boxel, Jr., saxophonist; Margaret Drynan, pianist.

**KFI, Los Angeles, Calif. (Pacific, 469), 6:45-7:30 p. m.** - Dinner concert, Grand Symphony Orchestra; 7:30, Children's program; 8:00-10:00, Matinee musicale, organ recital, Stanley Theater; Piano solos, Edna Finestone; 2:00-3:00, Concert, Arcadia Cafe Concert Orchestra; 4:45-5:00, Song recital; 7:30-7:45, Bedtime stories, Dream Daddy; 7:45-8:00, Dramatic Review, Walter Greenough.

**WDT, New York, N. Y. (Eastern, 405), 12:00-12:45 p. m.** - Fred Whitehouse Song Revue, All Star Broadway attraction.

**WFAA, Dallas, Texas (Central, 476), 12:30-1:00 p. m.** - Address, DeWitt McMurray; 8:30-9:30, Mozart Choral Club, Earle D. Behrends; 11:00-12:00, Hedley Cooper and assisting musicians.

**WFI, Philadelphia, Pa. (Eastern, 395), 1:00 p. m.** - Dinner music, Meyer Davis Bellevue Stratford Concert Orchestra; 3:00, Short talk; 6:30, Dinner music, Meyer Davis Bellevue Stratford Concert Orchestra; 7:00-7:30, Children's Own Half Hour Stories, Cousin Sue; 9:00, Radio play by WFI players.

**WGR, Buffalo, N. Y. (Eastern, 319), 12:30-1:00 p. m.** - George Albert Bouchard, organist; 6:30-7:00, Vincent Lopez Hotel Statler Dance Orchestra; 7:00, Digest of the day's news; Topics of scientific interest.

**WGY, Schenectady, N. Y. (Eastern, 380), 2:00 p. m.** - "Reducing the High Cost of Dinner Parties," 7:45, Program, auspices of Y. Perrin & Co., "A Few Moments with New Books," L. L. Hopkins; Olive Wentworth, soprano; Harry Arnold, baritone; Elizabeth Weatherly, violinist; Arch Batty, tenor; "The Story of Glove Making," J. E. Shill; Lelah Abrahams, harpist; Hazel Scoville, contralto.

**WHAS, Louisville, Ky. (Central, 400), 4:00-5:00 p. m.** - Selections, Strand Theater Orchestra; "Just Among Home Folks," Selections, Alamo Theater organ; 7:30-9:00, Ray Pfaff and his orchestra; Reading: An Interesting Historical Episode.

**WHN, New York, N. Y. (Eastern, 360), 2:15-2:30 p. m.** - Anna Stump, classical pianist; 9:45-10:15, Charles Hathaway's Orchestra; 10:30-10:45, Ruth and Janet Meyer, jazz pianist and jazz singer; 11:00-11:30, Shapiro Bernstein Music Co.; 11:45-12:00, Charles Bourne, jazz pianist.

**WIP, Philadelphia, Pa. (Eastern, 509), 1:00 p. m.** - Organ recital, Karl Bonawitz; 3:30, Song recital; 7:00-7:30, Bedtime stories, Uncle Wip; 8:00, Dramatic review; 8:15, Song recital.

**WJAX, Cleveland, Ohio (Eastern, 390), 7:30 p. m.** - Concert, Cleveland News-Leader; 7:30-7:45, Bedtime story, E. C. Johnson; 7:45-10:30, Popular dance program, Wiggins Orchestra.

**WJAZ, Chicago, Ill. (Central, 447.7), 10:00 p. m.-2:10 a. m.** - Barbara Sands, soprano; Alfred Heath, baritone; Frank Aulback, pianist; Amanda C. Burhop, pianist; Jennie M. Navigator, soprano; Esther Spalding, soprano.



Miss Eunice R. Randall sends thousands of WGI's youngsters to the Land of Nod. Hear her Tuesday and Thursday nights



Miss Anna Ludmila, premiere danseuse for the Chicago Civic Opera, will dance but won't be heard Saturday night over KYW

Left is A. W. "Sen" Kaney who will read the synopsis of the opera "Lucia." He will act in this capacity as Virgilio Lazzari, tenor "Raymond"

**WJZ, New York, N. Y. (Eastern, 455), 3:00-3:50 p. m.** - Wanamaker Concert; 3:50-4:00, "Home Beautiful," Dorothy Walsh, interior decorator; 4:00-4:15, Irving Schiff, boy soprano; 4:15-4:40, Recital and Poems, Clyde Monroe; 4:40-5:40, "Revue," by Irvin Ghee; 6:00-6:30 p. m., The Macmillan Co.; 7:30-7:45, Herbert Clair, popular pianist; 7:45-8:00, University of the Air, Advertising; Elton G. Pratt; 8:00-8:15, "Broadcasting Broadway," Bertha Brainerd; 8:15-8:50, Margaret Manierre Brown, soprano; Room 9-90, "Etiquette," Doubleday Page Co.; 9:00-9:35, Phyllis Krauter, cellist; 9:35-9:55, "Harding's Last Day in Alaska," Jos. M. Chapelle; 10:00-10:30, Darl Bethman, baritone; 10:30-11:30, Hotel Astor Grill Orchestra.

**WLW, Cincinnati, Ohio (Central, 309), 3:00 p. m.** - Music, Jennie Kehrt; 10:00, Artistic program; Rose Boden, soprano, director; Edythe Tolken, Bessie Muldoon, violinists; Neta H. Strietman, contralto; Arnold Schroeder, baritone; Constance Cochnover, accompanist.

**WMAA, Chicago, Ill. (Central, 447.5), 4:30 p. m.** - Program, Mrs. Glenn Dillard Gunn School of Music; 7:00, "Jamie," Hevon-Robert W. Servo; program; Program, Chicago Consulate of Norway; 9:15, Weekly program, Lyon & Healy.

**WOC, Davenport, Iowa (Central, 484), 12:00 m.** - Chimes concert; 3:30 p. m., A. G. Hinrichs, lecturer; 5:45, Chimes concert.

**WOO, Philadelphia, Pa. (Eastern, 509), 11:00-11:30 a. m.** - Organ recital, Marie E. Vogt; 12:00-12:55 p. m., Luncheon music, Wanamaker Crystal Tea Room Orchestra; 4:45-5:00, Organ recital, Mary E. Vogt.

**WOR, Newark, N. J. (Eastern, 405), 3:00-3:30 p. m.** - "Half Hours with Successful Women," Baroness Katherine von Klennert will speak on "Women in Opera," 6:30, "The Man in Moon Story for Children"; 7:15-7:30, Arthur Fischer playing 1 string violin.

**WWJ, Detroit, Mich. (Eastern, 517), 9:30 a. m.** - "Tonight's Dinner," Woman's Editor; 9:45, "Ironing Day" program, Fred Shaw, Margery Richmond; 3:00 p. m., Detroit News Orchestra; 8:30, Detroit News Orchestra; Madame Homer Dubard.

## Wednesday, November 7

**KDKA, E. Pittsburgh, Pa. (Eastern, 326), 7:00 p. m.** - Dinner concert, Pittsburgh Athletic Association Orchestra; 7:30, Literary period; Children's period; 8:15, Testimonial dinner, Turtle Creek Valley Post American Legion; Addresses, Judge Landis, Hon. M. Clyde Kelly, Mayor Magee.

**KFI, Los Angeles, Calif. (Pacific, 469), 6:45-7:30 p. m.** - Nick Harris concert; 10:00-11:00, Agnes Woodward, Director California Whistling School.

**KGW, Portland, Ore. (Pacific, 492), 5:30 p. m.** - Children's program, Inez Caplan, pianist; Aunt Nell; 8:00, Rybka string orchestra; 9:00, Business talks; Alexander Hamilton Institute; 10:00, Dance music, George Olsen's Metropolitan Orchestra.

**KHJ, Los Angeles, Calif. (Pacific, 395), 12:30-1:15 p. m.** - Dinner concert, 2:30-3:30, Matinee musicale, 6:45-7:30, Children's program, Master Louis Pelta, age 14 years, accompanist; 8:00-10:00, Virginia Flohr, soprano; 10:00-12:00, Art Hickman's Orchestra; Ethel R. Brown, lyric soprano.

**KSD, St. Louis, Mo. (Central, 546), 8:00 p. m.** - Aberg's Concert Ensemble; Arne Arnesen, violinist; 11:00, Dance music, Rodemich's Orchestra.

**KYW, Chicago, Ill. (Central, 536), 11:35 a. m.** - Table Talk, Mrs. Anna J. Peterson; 6:50 p. m., Children's bedtime story; 8:01, Farm program; "Orderly Marketing of Live Stock," John G. Brown; "A Bottle of Milk," E. B. Heaton; 8:30, Chicago Musical College; 9:50, Herbie Mintz, pianist; A. W. "Sen" Kaney, specialty act.

**WBAP, Fort Worth, Texas (Central, 476), 7:30-8:30 p. m.** - Wylbert Brown, violinist; 9:30-10:45, Casino Novelty Four Quartet.

**WBZ, Springfield, Mass. (Eastern, 337), 7:30 p. m.** - Twilight tales for the Kiddies; Household Management Course, Agnes H. Craig; 8:00, Alfred Troemel, violinist; Ruby Kingley, pianist; Pupils of the Springfield Conservatory of Music; 9:00, Bedtime Story for Grown-ups, Orison S. Marden.

**WDAP, Chicago, Ill. (Central, 360), 1:40 p. m.** - Concert, Drake Concert Ensemble and Blackstone String Quintet; 7:00, Drake Concert Ensemble and Blackstone String Quintet; 10:00, Frederick W. Agard, tenor; Bob Conley, pianist; Jack Chapman's Orchestra.

**WDAR, Philadelphia, Pa. (Eastern, 395), 12:00-12:54 p. m.** - Organ recital, Stanley Theater; Piano solos, Edna Finestone; 2:00-3:00, Concert, Arcadia Cafe Concert Orchestra; 4:45-5:00, Song recital; 7:30-7:45, Bedtime stories, Dream Daddy; 7:45-8:00, Dramatic Review, Walter Greenough.

**WDT, New York, N. Y. (Eastern, 405), 12:00-12:45 p. m.** - Fred Whitehouse Song Revue, All Star Broadway attraction.

**WFAA, Dallas, Texas (Central, 476), 12:30-1:00 p. m.** - Address, DeWitt McMurray; 8:30-9:30, Mozart Choral Club, Earle D. Behrends; 11:00-12:00, Hedley Cooper and assisting musicians.

**WFI, Philadelphia, Pa. (Eastern, 395), 1:00 p. m.** - Dinner music, Meyer Davis Bellevue Stratford Concert Orchestra; 3:00, Short talk; 6:30, Dinner music, Meyer Davis Bellevue Stratford Concert Orchestra; 7:00-7:30, Children's Own Half Hour Stories, Cousin Sue; 9:00, Radio play by WFI players.

**WGR, Buffalo, N. Y. (Eastern, 319), 12:30-1:00 p. m.** - George Albert Bouchard, organist; 6:30-7:00, Vincent Lopez Hotel Statler Dance Orchestra; 7:00, Digest of the day's news; Topics of scientific interest.

**WGY, Schenectady, N. Y. (Eastern, 380), 2:00 p. m.** - "Reducing the High Cost of Dinner Parties," 7:45, Program, auspices of Y. Perrin & Co., "A Few Moments with New Books," L. L. Hopkins; Olive Wentworth, soprano; Harry Arnold, baritone; Elizabeth Weatherly, violinist; Arch Batty, tenor; "The Story of Glove Making," J. E. Shill; Lelah Abrahams, harpist; Hazel Scoville, contralto.

**WHAS, Louisville, Ky. (Central, 400), 4:00-5:00 p. m.** - Selections, Strand Theater Orchestra; "Just Among Home Folks," Selections, Alamo Theater organ; 7:30-9:00, Ray Pfaff and his orchestra; Reading: An Interesting Historical Episode.

**WHN, New York, N. Y. (Eastern, 360), 2:15-2:30 p. m.** - Anna Stump, classical pianist; 9:45-10:15, Charles Hathaway's Orchestra; 10:30-10:45, Ruth and Janet Meyer, jazz pianist and jazz singer; 11:00-11:30, Shapiro Bernstein Music Co.; 11:45-12:00, Charles Bourne, jazz pianist.

**WIP, Philadelphia, Pa. (Eastern, 509), 1:00 p. m.** - Organ recital, Karl Bonawitz; 3:30, Song recital; 7:00-7:30, Bedtime stories, Uncle Wip; 8:00, Dramatic review; 8:15, Song recital.

**WJAX, Cleveland, Ohio (Eastern, 390), 7:30 p. m.** - Concert, Cleveland News-Leader; 7:30-7:45, Bedtime story, E. C. Johnson; 7:45-10:30, Popular dance program, Wiggins Orchestra.

**WJAZ, Chicago, Ill. (Central, 447.7), 10:00 p. m.-2:10 a. m.** - Barbara Sands, soprano; Alfred Heath, baritone; Frank Aulback, pianist; Amanda C. Burhop, pianist; Jennie M. Navigator, soprano; Esther Spalding, soprano.

**WJZ, New York, N. Y. (Eastern, 455), 3:00-3:50 p. m.** - Wanamaker Concert; 3:50-4:00, "Home Beautiful," Dorothy Walsh, interior decorator; 4:00-4:15, Irving Schiff, boy soprano; 4:15-4:40, Recital and Poems, Clyde Monroe; 4:40-5:40, "Revue," by Irvin Ghee; 6:00-6:30 p. m., The Macmillan Co.; 7:30-7:45, Herbert Clair, popular pianist; 7:45-8:00, University of the Air, Advertising; Elton G. Pratt; 8:00-8:15, "Broadcasting Broadway," Bertha Brainerd; 8:15-8:50, Margaret Manierre Brown, soprano; Room 9-90, "Etiquette," Doubleday Page Co.; 9:00-9:35, Phyllis Krauter, cellist; 9:35-9:55, "Harding's Last Day in Alaska," Jos. M. Chapelle; 10:00-10:30, Darl Bethman, baritone; 10:30-11:30, Hotel Astor Grill Orchestra.

**WMAA, Chicago, Ill. (Central, 447.5), 4:30 p. m.** - Program, Mrs. Glenn Dillard Gunn School of Music; 7:00, "Jamie," Hevon-Robert W. Servo; program; Program, Chicago Consulate of Norway; 9:15, Weekly program, Lyon & Healy.

**WOC, Davenport, Iowa (Central, 484), 12:00 m.** - Chimes concert; 3:30 p. m., A. G. Hinrichs, lecturer; 5:45, Chimes concert.

**WOO, Philadelphia, Pa. (Eastern, 509), 11:00-11:30 a. m.** - Organ recital, Marie E. Vogt; 12:00-12:55 p. m., Luncheon music, Wanamaker Crystal Tea Room Orchestra; 4:45-5:00, Organ recital, Mary E. Vogt.

**WOR, Newark, N. J. (Eastern, 405), 3:00-3:30 p. m.** - "Half Hours with Successful Women," Baroness Katherine von Klennert will speak on "Women in Opera," 6:30, "The Man in Moon Story for Children"; 7:15-7:30, Arthur Fischer playing 1 string violin.

**WWJ, Detroit, Mich. (Eastern, 517), 9:30 a. m.** - "Tonight's Dinner," Woman's Editor; 9:45, "Ironing Day" program, Fred Shaw, Margery Richmond; 3:00 p. m., Detroit News Orchestra; 8:30, Detroit News Orchestra; Madame Homer Dubard.

**WJZ, New York, N. Y. (Eastern, 455), 3:00-3:50 p. m.** - Wanamaker Concert; 3:50-4:00, "Home Beautiful," Dorothy Walsh, interior decorator; 4:00-4:15, Irving Schiff, boy soprano; 4:15-4:40, Recital and Poems, Clyde Monroe; 4:40-5:40, "Revue," by Irvin Ghee; 6:00-6:30 p. m., The Macmillan Co.; 7:30-7:45, Herbert Clair, popular pianist; 7:45-8:00, University of the Air, Advertising; Elton G. Pratt; 8:00-8:15, "Broadcasting Broadway," Bertha Brainerd; 8:15-8:50, Margaret Manierre Brown, soprano; Room 9-90, "Etiquette," Doubleday Page Co.; 9:00-9:35, Phyllis Krauter, cellist; 9:35-9:55, "Harding's Last Day in Alaska," Jos. M. Chapelle; 10:00-10:30, Darl Bethman, baritone; 10:30-11:30, Hotel Astor Grill Orchestra.

**WMAA, Chicago, Ill. (Central, 447.5), 4:30 p. m.** - Program, Mrs. Glenn Dillard Gunn School of Music; 7:00, "Jamie," Hevon-Robert W. Servo; program; Program, Chicago Consulate of Norway; 9:15, Weekly program, Lyon & Healy.

**WOC, Davenport, Iowa (Central, 484), 12:00 m.** - Chimes concert; 3:30 p. m., A. G. Hinrichs, lecturer; 5:45, Chimes concert.

**WOO, Philadelphia, Pa. (Eastern, 509), 11:00-11:30 a. m.** - Organ recital, Marie E. Vogt; 12:00-12:55 p. m., Luncheon music, Wanamaker Crystal Tea Room Orchestra; 4:45-5:00, Organ recital, Mary E. Vogt.

**WOR, Newark, N. J. (Eastern, 405), 3:00-3:30 p. m.** - "Half Hours with Successful Women," Baroness Katherine von Klennert will speak on "Women in Opera," 6:30, "The Man in Moon Story for Children"; 7:15-7:30, Arthur Fischer playing 1 string violin.

**WWJ, Detroit, Mich. (Eastern, 517), 9:30 a. m.** - "Tonight's Dinner," Woman's Editor; 9:45, "Ironing Day" program, Fred Shaw, Margery Richmond; 3:00 p. m., Detroit News Orchestra; 8:30, Detroit News Orchestra; Madame Homer Dubard.

## Thursday, November 8

**CKAC, Montreal, Canada (Eastern, 430), 7:00 p. m.** - Kiddies' stories in French and English; 7:30, Concert, Knights of Columbus entertainers and orchestra; Lafontaine Lodge, Armand Renaud, director.

**KDKA, E. Pittsburgh, Pa. (Eastern, 326), 6:15 p. m.** - Dinner concert, Grand Symphony Orchestra; 7:15, "Famous Violins in America and Abroad," G. M. Francois, violin maker; 7:45, "Uncle Remus" has a story for the children; 8:15, Farm program, Frank E. Mullen; 8:30, Concert, KDKA Little Symphony Orchestra; Clara Huhn, soprano; Rose Leader Chislett, contralto; Roy Strayer, tenor; George Wahl, baritone; 11:00 Midnight Frolic.

**KFI, Los Angeles, Calif. (Pacific, 469), 6:45-7:30 p. m.** - Courtesy Y. M. C. A.; 10:00-11:00, Courtesy John Smallman, baritone.

**KGW, Portland, Ore. (Pacific, 492), 12:30-1:15 p. m.** - Child Training program; 8:00 Dramatic program, J. Adison Hunter; 10:00, Dance music, George Olsen's Metropolitan Orchestra.

**KHJ, Los Angeles, Calif. (Pacific, 395), 12:30-1:15 p. m.** - Concert; 2:30-3:30, Matinee musicale; 6:45-7:30, "Uncle John," 8:00-10:00, Fuhrer String Quartet; "Methods of Science," Professor John C. Shedd; 10:00-12:00, Art Hickman's Orchestra.

**WJZ, New York, N. Y. (Eastern, 455), 3:00-3:50 p. m.** - Wanamaker Concert; 3:50-4:00, "Home Beautiful," Dorothy Walsh, interior decorator; 4:00-4:15, Irving Schiff, boy soprano; 4:15-4:40, Recital and Poems, Clyde Monroe; 4:40-5:40, "Revue," by Irvin Ghee; 6:00-6:30 p. m., The Macmillan Co.; 7:30-7:45, Herbert Clair, popular pianist; 7:45-8:00, University of the Air, Advertising; Elton G. Pratt; 8:00-8:15, "Broadcasting Broadway," Bertha Brainerd; 8:15-8:50, Margaret Manierre Brown, soprano; Room 9-90, "Etiquette," Doubleday Page Co.; 9:00-9:35, Phyllis Krauter, cellist; 9:35-9:55, "Harding's Last Day in Alaska," Jos. M. Chapelle; 10:00-10:30, Darl Bethman, baritone; 10:30-11:30, Hotel Astor Grill Orchestra.

**WMAA, Chicago, Ill. (Central, 447.5), 4:30 p. m.** - Program, Mrs. Glenn Dillard Gunn School of Music; 7:00, "Jamie," Hevon-Robert W. Servo; program; Program, Chicago Consulate of Norway; 9:15, Weekly program, Lyon & Healy.

**WOC, Davenport, Iowa (Central, 484), 12:00 m.** - Chimes concert; 3:30 p. m., A. G. Hinrichs, lecturer; 5:45, Chimes concert.

**WOO, Philadelphia, Pa. (Eastern, 509), 11:00-11:30 a. m.** - Organ recital, Marie E. Vogt; 12:00-12:55 p. m., Luncheon music, Wanamaker Crystal Tea Room Orchestra; 4:45-5:00, Organ recital, Mary E. Vogt.

**WOR, Newark, N. J. (Eastern, 405), 3:00-3:30 p. m.** - "Half Hours with Successful Women," Baroness Katherine von Klennert will speak on "Women in Opera," 6:30, "The Man in Moon Story for Children"; 7:15-7:30, Arthur Fischer playing 1 string violin.

**WWJ, Detroit, Mich. (Eastern, 517), 9:30 a. m.** - "Tonight's Dinner," Woman's Editor; 9:45, "Ironing Day" program, Fred Shaw, Margery Richmond; 3:00 p. m., Detroit News Orchestra; 8:30, Detroit News Orchestra; Madame Homer Dubard.

**WJZ, New York, N. Y. (Eastern, 455), 3:00-3:50 p. m.** - Wanamaker Concert; 3:50-4:00, "Home Beautiful," Dorothy Walsh, interior decorator; 4:00-4:15, Irving Schiff, boy soprano; 4:15-4:40, Recital and Poems, Clyde Monroe; 4:40-5:40, "Revue," by Irvin Ghee; 6:00-6:30 p. m., The Macmillan Co.; 7:30-7:45, Herbert Clair, popular pianist; 7:45-8:00, University of the Air, Advertising; Elton G. Pratt; 8:00-8:15, "Broadcasting Broadway," Bertha Brainerd; 8:15-8:50, Margaret Manierre Brown, soprano; Room 9-90, "Etiquette," Doubleday Page Co.; 9:00-9:35, Phyllis Krauter, cellist; 9:35-9:55, "Harding's Last Day in Alaska," Jos. M. Chapelle; 10:00-10:30, Darl Bethman, baritone; 10:30-11:30, Hotel Astor Grill Orchestra.

**WMAA, Chicago, Ill. (Central, 447.5), 4:30 p. m.** - Program, Mrs. Glenn Dillard Gunn School of Music; 7:00, "Jamie," Hevon-Robert W. Servo; program; Program, Chicago Consulate of Norway; 9:15, Weekly program, Lyon & Healy.

**WOC, Davenport, Iowa (Central, 484), 12:00 m.** - Chimes concert; 3:30 p. m., A. G. Hinrichs, lecturer; 5:45, Chimes concert.

**WOO, Philadelphia, Pa. (Eastern, 509), 11:00-11:30 a. m.** - Organ recital, Marie E. Vogt; 12:00-12:55 p. m., Luncheon music, Wanamaker Crystal Tea Room Orchestra; 4:45-5:00, Organ recital, Mary E. Vogt.

**WOR, Newark, N. J. (Eastern, 405), 3:00-3:30 p. m.** - "Half Hours with Successful Women," Baroness Katherine von Klennert will speak on "Women in Opera," 6:30, "The Man in Moon Story for Children"; 7:15-7:30, Arthur Fischer playing 1 string violin.

**WWJ, Detroit, Mich. (Eastern, 517), 9:30 a. m.** - "Tonight's Dinner," Woman's Editor; 9:45, "Ironing Day" program, Fred Shaw, Margery Richmond; 3:00 p. m., Detroit News Orchestra; 8:30, Detroit News Orchestra; Madame Homer Dubard.

**KYW, Chicago, Ill. (Central, 536), 11:35 a. m.** - Table Talk, Mrs. Anna J. Peterson; 6:50 p. m., Children's bedtime story; 8:00, Twenty Minutes of Good Reading, Rev. C. J. Ferrin; 8:20-9:20, Herbie Mintz, pianist; Sallie Meukes, pianist; A. W. "Sen" Kaney, specialty act; Lucille O'Brien, soprano; Hilda Butler Farr, pianist.

**PWX, Havana, Cuba (Eastern, 400), 8:30-11:00 p. m.** - Dance program, Antonio M. Romeu's Orchestra.

**WBAP, Fort Worth, Texas (Central, 476), 7:30-8:30 p. m.** - Concert, Fort Worth artists; 9:30-10:45, True's True Tones Orchestra.

**WBZ, Springfield, Mass. (Eastern, 337), 7:00 p. m.** - Letter from the New England Homestead; 7:30, Twilight tales for the Kiddies; "Story Openings and Endings," Dr. J. Berg Esenwein; 8:00, Concert, Mrs. C. D. Root, soprano; Mrs. Howard A. King, accompanist; 9:00, Bedtime story for Grown-ups, Orison S. Marden.

**WDAP, Chicago, Ill. (Central, 360), 1:40 p. m.** - Concert, Drake Concert Ensemble and Blackstone String Quintet; 7:00 Drake Concert Ensemble and Blackstone String Quintet; 10:00, Hugh E. Marshall, tenor; Jack Chapman's Orchestra.

**WDAR, Philadelphia, Pa. (Eastern, 395), 12:00-12:54 p. m.** - Organ recital, Stanley Theater, dinner music; 2:00-3:00, Concert, Arcadia Cafe Concert Orchestra; 4:45-5:05, Piano recital, Edna Finestone; 7:30-7:45, Bedtime stories, Dream Daddy.

**WDT, New York, N. Y. (Eastern, 405), 12:00-12:45 p. m.** - Dave White; 12:15-12:45 p. m., Frank Goodman, Willie White, Billie Frish, Will Donaldson.

**WFAA, Dallas, Texas (Central, 476), 12:30-1:00 p. m.** - "Facts About Dallas," representative of Dallas Chamber of Commerce; 8:30-9:30, Aida Choral Club.

**WFI, Philadelphia, Pa. (Eastern, 395), 1:00 p. m.** - Dinner music, Meyer Davis Bellevue Stratford Concert Orchestra; 3:00, Short talks; 6:30, Dinner music, Meyer Davis Bellevue Stratford Concert Orchestra; 7:00, Bedtime stories, Cousin Sue; 8:00, Boy Scouts Radio; 9:00, Piano solos, Loretta Kerk; Dance music, Meyer Davis Bellevue Stratford Dance Orchestra.

**WGR, Buffalo, N. Y. (Eastern, 319), 12:30-1:00 p. m.** - George Albert Bouchard, organist; 6:30-7:00, Vincent Lopez Hotel Statler Dance Orchestra; 7:00 Digest of the day's news; Boy Scout Radiogram; Employment Bulletin; Story from "The American Boy" magazine; 9:00, Musical program, Greater Buffalo Drug Club.

**WGY, Schenectady, N. Y. (Eastern, 380), 2:00 p. m.** - "Law Enforcement," Mrs. Samuel; 7:45, Radio drama, "The Green Goddess," The Rajah of Rukh, Edward H. Smith; Watkins, his valet, Frank Oliver; Major Anthony Crespin, Jerome Lovenheim; Lucilla, his wife, Rose Cohn; Doctor Basil Traherne, Ed. E. St. Louis; Lieut. Denis Cardew, John Loftus; WGY Orchestra.

**WHAS, Louisville, Ky. (Central, 400), 4:00-5:00 p. m.** - Selections, Strand Theater Orchestra; "Just Among Home Folks," Selections, Rialto Theater organ; 7:30-9:00, Concert, Louisville Normal School; Reading: An Interesting Historical Episode.

**WHN, New York, N. Y. (Eastern, 360), 2:15-3:00 p. m.** - Shapiro Bernstein Music Co.; 3:45-4:15, Irving Berlin Music Co.; 9:30-9:45 p. m., Saroff and His Wigwag Orchestra; 9:45-9:50, Benny Leonard; 9:50-9:55, Harry Richmond; 9:55-10:00, Belle Bart, astrologist; 10:00-10:15, Milton Miller, Avery Nesbit, piano duets; 10:15-10:30, Robert Becker, baritone; 10:30-11:00, Fred Fischer Music Company.

**WIP, Philadelphia, Pa. (Eastern, 509), 1:00 p. m.** - Organ recital, Karl Bonawitz; 3:30, Song recital; 7:00-7:30, Bedtime stories, Uncle Wip; 8:00, Eugene D. Hogle; 8:15, Dance music, Ace Brigade and His Ten Virginians; 9:00, Organ recital, Karl Bonawitz.

**WJAX, Cleveland, Ohio (Eastern, 390), 7:30 p. m.** - Concert, Cleveland News-Leader; 7:30-7:45, Bedtime story, E. C. Johnson; 7:45-10:30, Popular dance program, Wiggins Orchestra.

**WJZ, New York, N. Y. (Eastern, 455), 3:00-3:50 p. m.** - Wanamaker Concert; 3:50-4:45, The Threshold Players; 4:45-5:05, Beatrice Nelson, soprano; 5:05-5:25, William F. Hirschman, soprano; 5:25-5:40, Nathan Kroil, violinist; 6:00-6:30, Jack Rabbit Stories, David Cory; 7:30-7:45, World's Work; 7:45-8:05, Fred Tangeman, pianist; 8:15-9:00, Wanamaker Organ Concert; 9:00-9:15, The Sterling Quartet; 9:15-9:30, E. M. Young, Financial World magazine; 9:30-9:45, The Sterling Quartet; 9:45-10:00, "How to Finance a Home," David B. Hutton; 10:00-10:30, Marghee


**JUST LINES THIS OPERA** should listen in Tuesday noon, to Katherine Klenner men in Opera," the Spanish and oper day after WJY. Violinists enjoy Evening films," at Wednesday, and very in C. M. talk on Violins in ica and Thurs KDKA. Fischer is gymnast crates string in at WOR. I know you have feeling no ing how and get this w dance mu the Rad Arthur begins his ing des WOR. We Drama Tuesday Radio pla Players. Wedn WOR. French Grand Players. Thursda the 29 T Players; "The Gre des's"; Scenes Shakesp Friday: one a c "P i e e r Mother"; Radio pla ters Gr Players. —THE PROC



# BUILD THOSE SETS NOW!

## Western Electric VT-2 TUBES


One of the big features of these brand new genuine Western Electric VT-2 Tubes that we bought from the U. S. Signal Corps is that they have a higher amplification factor than any other 5-watt tube made! And almost half of our purchase consisting of 10,000 tubes have been sold. Radio men know that a genuine VT-2 Tube for \$7.45 is an unusual opportunity—a real "find"! These tubes may be used for both RF and AF Amplification and for CW and phone transmitting. They are not Navy defects—have been sold only as a surplus.



**\$7.45**

## Electric Soldering Iron

Specially adapted to Radio work. Simply attach to your light socket. Complete, with 6-foot cord and attaching plug. Lasts a lifetime for ordinary home or light shop work.



**\$2.45**



## Automatic Electric LONG RANGE HEAD SETS


Formerly sold by the Automatic Electric Co., makers of telephone exchanges, at \$10 each. We bought their entire stock—40,000 phones—paid spot cash and because of this unequalled buying power, we are able to offer you a \$10 headset for \$3.65.

30 years of experience have produced the Automatic headset. Coil is wound with about 6500 turns of No. 40 enamel coated copper wire. DC resistance 1600 ohms. Impedance, at average music and voice frequency (800 cycles) 21,000 ohms. (Effective impedance rather than DC resistance is the big factor in a good headset.)

**\$10.00 VALUE \$3.65**


## FORMICA

Made from Anhydrous Redmanol Resins  
SHEETS TUBES RODS



We are prepared to furnish promptly and saw Formica panels of any dimensions. Cutting charge is included in the following prices:  
 1/8" Formica, sq. in. .... 2c  
 1/4" Formica, sq. in. .... 1 1/2c  
 Tubing (up to 3/4" diameter), per running inch ..... 10c


## COCKADAY COMPLETE CIRCUIT



Regular Price	Our Price Each
\$3.00	1 Cockaday Coil ..... \$1.95
1.00	2 Bakelite Dials ..... .25
1.00	1 John Firth Socket ..... .45
1.00	1 Freshman Grid Leak and Condenser ..... .65
1.50	1 Howard Vernier Rheostat ..... 1.35
1.00	1 Patent Double Circuit Jack ..... .50
.80	8 Binding Posts ..... .05
.02	7 Switch Points ..... .01
.10	1 Switch Lever ..... .25
.50	1 Switch Lever ..... .25
1.75	1 7x14 1/2 Formica Panel, Blueprint and Wire ..... 1.00
1.00	1 Baseboard ..... .25
3.30	2 23 Plate Condensers ..... 1.45

**Our Price \$11.95**

## HAZELTINE NEUTRODYNE




ALL PARTS LICENSED UNDER HAZELTINE PATENTS

- 1 7x21 1/2 drilled formica panel.
- 1 Howard rheostat.
- 3 4" Radion Dials.
- 3 John Firth bakelite sockets.
- 8 Binding posts.
- 23 plate variable condensers.
- 1 Wave control neutroformer.
- 2 Radio frequency amplifying neutroformers.
- 2 Grid neutralizing condensers.
- 1 .00025 micron grid condenser.
- 1 Marco variable grid leak.
- 1 Baseboard for mounting.
- 25 feet tinned copper bus bar wire and complete instructions for assembling and wiring.

3 TUBE  
**OUR PRICE \$28.60**

4 Tube \$44.65  
5 " \$46.25  
(Freed Eisenman or Fada Neutroformers)

## 2 and 3 Coil Mountings



Completely moulded of bakelite in which all metal parts are moulded. Mounts on four screws threaded in back, nickel plated. Highly finished in black. Moulded bakelite spaces the coil plugs. Silk flexible leads with provision for rear or base outlet. Spring contacts insure positive connection. Eliminates body capacity. Any standard plugs will fit. Size 3" deep, 2 1/4" high, 4" long.


2 Coil \$2.45  
3 " \$3.45

## Moulded Variometers and Variocouplers \$3.65

## Rubicon Transformers

TYPE C	AF (ratio 3 to 1) ... \$6.00
TYPE D	AF (ratio 5 to 1) ... 6.00
TYPE E	AF (ratio 10 to 1) .. 6.50
TYPE R	RF (range 250 to 650M) ..... 6.00
RUBICON DUPLEX (Push-Pull)	Set of two transformers ..... 15.00

## Knocked-Down Short Wave Receiver



Reg. Price	Consisting of	Our Price
\$10.00	2 Mahogany Variometers...	\$3.90
5.00	1 Mahogany Variocoupler...	1.75
3.00	3 Bakelite Dials ....	.75
1.00	1 John Firth Socket. ....	.45
1.10	1 Howard Rheostat... ..	1.00
4.50	1 Mahogany Cabinet. ....	2.95
2.25	1 Genuine Formica Panel .....	1.75
.80	8 Binding Posts ....	.40
.50	1 Switch Lever .....	.25
.40	12 Switch Points .....	.20
1.00	1 Freshman Grid Leak and Condenser Combined .....	.65
1.00	1 Complete Drawing for Assembly and Wiring.....	.50

**\$25.85 Value \$13.45**  
**OUR PRICE**

## Bradleystat UNIVERSAL


**NEW TYPE \$1.25**



**\$25.00**

Very Special

## REINARTZ DETECTOR AND 2-STEP



Reg. Price Each	Our Price Each	Reg. Price	Our Price
\$8.00	1 Drilled Panel, 7x23 1/2" ..	\$2.00	1 Variable Grid Leak and Condenser (cartridge type) \$1.40
2.50	1 Reinartz Spider Web Coil. 1.95	4.75	2 Transformers (All American 10-1 and 3-1 or new type high and low ratio Thoradson) ..... 3.95
6.00	1 23 Plate Vernier Condenser 3.45	.10	7 Binding Posts ..... .05
5.00	1 11 Plate Vernier Condenser 2.95	.40	2 Dozen switch points..... .20
1.50	1 Howard Vernier Rheostat. 1.35	.02	6 Switch Stops ..... .01
1.10	2 Howard Plain Rheostat..... 1.00	.50	3 Switch Levers ..... .25
.75	3 Firth Sockets ..... .45	1.00	2 Bakelite Dials ..... .25
		1.00	2 Jacks, Double Circuit..... .50
		.65	1 Jack, Single Circuit..... .35
		1.00	1 Baseboard ..... .50
		.75	1 Blueprint for assembly.... .50
		.50	25 feet tinned wire..... .25

**\$46.97 \$29.95**  
**OUR SPECIAL PRICE**

## Important

Any individual part in any of the four outfits above may be purchased separately at the special reduced prices listed under column headed "Our Price."

### PANELS DRILLED

Specially drilled panels are included with each outfit. No additional charge for drilling.

### COMPLETE INSTRUCTIONS

for assembling, and blueprints for wiring are included with each outfit. Instructions written so everyone can understand them. No special skill or technical knowledge required—a few hours and you're ready to tune-in New York, Los Angeles—any of 'em!

"THE LARGEST RADIO STORE IN AMERICA"



ALL MDSE. GUARANTEED BY US TO BE OF FIRST QUALITY

ALL MAIL ORDERS, LARGE OR SMALL, SHIPPED TO YOU PROMPTLY

509 SOUTH STATE ST., Dept. 6, CHICAGO, ILL.

# Simple Explanation of Radio for Everybody

## Chapter IV, Part III—Inductances—Fixed and Variable

By M. W. Thompson

THE following article is the seventh of a series for Radio beginners, written by Marvin W. Thompson, well known in air-phone circles for his understandable style of approaching his subject, and his ability as a Radio engineer. Mr. Thompson is now an associate editor on the staff of Radio Digest. A preliminary outline of the Chapters to follow is:

- Chapter V—Condensers—Fixed and Variable.
- Chapter VI—Vacuum Tubes.
- Chapter VII—Antennas and Grounds.
- Chapter VIII—Regeneration.
- Chapter IX—Audio Frequency Amplification.
- Chapter X—Loud Speakers.

A VARIOMETER being similar in construction to a variocoupler, we will take it up next. It is the purpose of a variometer, primarily, not to transfer energy but to change the amount of inductance in a circuit and so alter the circuit to respond to various wave lengths. The two coils in Figures 28 and 29 are connected as shown in Figure 31. When




Figure 31—Showing how two coils are connected in series to form a variometer

current is passing through these coils, each creates within itself a magnetic field with N and S poles. If the inner coil is turned so that its turns are wound in the same direction as those on the outer coil (see Figure 28), the two fields will build together and aid each other, and the inductance of the coil is high. If the inner coil is rotated as shown by Figure 29, the fields do not aid each other and the inductance value is but one-half what it was previously. If we continue turning the rotor to the point where the two groups of turns are wound in opposite directions, the fields will oppose each other and the inductance becomes zero.

The two coils shown in our sketches are closely wound single-layer coils, which, as explained in the first half of this chapter, have small distributed capacity losses. For use as a variocoupler or to secure "variometer effect," the manufacturers of honeycomb, Giblin-Remler and spider-web coils supply stands which permit one to vary the relationship between such coils

(see Figure 32). While the drawing shows honeycomb coils, the other types of winding are also thus arranged.

Another type of variocoupler, which we do not show, consists of an outer sta-




Figure 32—Top view of two honeycomb coils so mounted that their relationship can be varied

tionary coil with an inner rotor similar to Figure 28, but both windings are honeycomb and thus the compactness of the inner-outer-coil variocoupler is combined with the efficiency of the air spaced honeycomb type of winding.

### Radio Frequency Transformers

There are uses to which the large diameter air-core type of inductance can be put in which the varying of coupling is not required, as in the neutroformers of the neutrodyne circuit. A neutroformer consists only of two single-layer coils, with one placed permanently within and tightly coupled to the other. This forms a transformer to handle current alternating at Radio frequencies and differs from the variocoupler in that there can be no varying of the relationship between the coils, and no taps are taken from it to permit different numbers of turns.

The unit now on the market and known as a Radio frequency transformer is another example of the use of two unconnected coils, whose positions cannot be varied and which are to handle current at Radio frequencies. At this point it might be well to explain the action of iron placed within a transformer. Inserting an iron core within the two coils of a transformer enables one coil to transfer more energy

to the other as stronger lines of force are created, but these stronger lines of force cannot be built up and dissipated as rapidly as might be desired. If there is no iron, the magnetic field will rise and fall as rapidly as the Radio frequency currents alternate; if there is too much solid iron the magnetic fields lag behind the current and choke it. Some makers of Radio frequency transformers prefer to use no iron and avoid lag; others use considerable iron and believe the slight loss due to its presence to be offset by the greater transfer of energy, while a third group compromises and uses a mixture of iron filings and some compound such as beeswax as a core.

### Audio Frequency Inductances

To handle currents varying at audible frequencies and to be used between the detector and an amplifier tube or between two successive amplifier tubes, there are two units that may be used. One is termed an impedance coil, the other an audio frequency transformer. The impedance coil is used as shown in Figure 33 and its action is just what its name suggests. While it permits the direct current of the B battery to reach the plate of the tube and keep it positive, it impedes the passage of the currents varying at voice frequencies to such an extent that they travel on to




Figure 33—A single coil with iron core used for impedance coupling

the condenser in the grid lead of the following tube and create audible variations of voltage on the next grid.

The audio frequency transformer consists of two windings on an iron core connected as shown in Figure 34. The iron core can be used here without fear of

trouble, as its lag is not such that the magnetic field cannot change at audible frequencies. When two windings are placed in close relationship to each other, the ratio of the varying voltages in them




Figure 34—An audio frequency transformer connecting the detector and amplifier tubes

is as the ratio of the turns in the coils. In speaking of transformers, we always refer to the winding connected to a source of current as the "primary" and to the winding in which current is induced as the "secondary." In Figure 34 the left winding is the primary, the parallel lines the core, and the right coil the secondary.

### "Transformer Action"

In the preceding paragraph it should be (Continued on page 20)

## Cockaday Coil Set \$2.50

Including full size blue prints of panel layout, complete picture hookup, and fully illustrated instructions for construction and operation.

Coils are fully assembled, made exactly as specified by Mr. Cockaday, D coil bank wound. Far more efficient than any home made coils.

Standard parts for this sensational circuit—panel, coils, condensers, verniers, variable resistance, vernier rheostat, socket, double jack, dials, switch, contact points, posts, busbar wire, sphagetti, etc. (no tubes or phones).

### Complete for \$11.65

Postage additional on all shipments. Send No Money. PAY THE POSTMAN. All Goods Shipped Parcel Post C. O. D.

**RADIO SURPLUS STORES**  
HELENA, MONTANA

## SAVE ON RADIO

Stop paying exorbitant prices for radio apparatus. We can supply you any standard parts at greatly reduced prices.

- WD11 TUBES, SPECIAL PRICE.....\$5.75
- UV201A and C301A TUBES.....\$5.75
- BRANDES SUPERIOR PHONES.....\$4.95
- 2 1/2 VOLT B BATTERY.....\$1.30

You can save money on the latest and best in radio at our rock-bottom prices. Orders shipped same day received, C. O. D., under absolute money-back guarantee.

We pay postage on orders accompanied by check. Write today for our Price-Slashing bargain list. **STANDARD RADIO CO.** Dept. 6, 1233 Walnut St., Kansas City, Mo.

## RUSONITE

CRYSTAL RECTIFIER (Patent Pending)

THE PERFECT SYNTHETIC CRYSTAL DETECTOR, SENSITIVE OVER ENTIRE SURFACE. No Hunting for "Spots." Loud and Clear. Endorsed by thousands of satisfied users. Sensitiveness Guaranteed. Price, Mounted..... 50c

14 K. GOLD SUPERSENSITIVE RUSONITE CATWHISKER. Permanent. Will Not Oxidize. Price..... 25c

RUSONITE REFLEX CRYSTAL. Manufactured Expressly for Reflex Circuits. Will Stand Up Under Heavy Plate Voltage. Guaranteed. Price, Mounted..... \$1.00

Order from your dealer or direct from **RUSONITE PRODUCTS CORP.** 15 Park Row New York, N. Y.

## SAVE MONEY ON SETS!

These Specials Cut the Cost of Building a Set Almost in Half

The parts listed in these groups are of the best standard manufacture, and only our large buying power makes these low prices possible.

Drilled Panels with Each Set of Parts! And of course, we pay all parcel post charges—and send C. O. D. without deposit!

### SHACKDX SPECIAL

With Drilled Panel

One tube wonder. All the parts, including Variometer, Socket, Rheostat, Jack, Variable Condenser, Dials, Binding Posts, Bus Wire, etc.

Reg. Price \$15.00

OUR PRICE \$7.29

### TWO STEP AUDIO

With Drilled Panel

Works with any set. The parts include Sockets, Rheostats, Transformers, Jacks, Binding Posts, Bus Wire, etc.

Reg. Price \$20.00

Our Price \$11.59

### AUTO- PLEX

The very latest in radio! All Parts,

Reg. \$23.00

Our Price \$11.39

### 3-CIRCUIT SET

With Drilled Panel

Nothing tunes finer. We supply the Variometers, Variocoupler, Condensers, Socket, Rheostat, Jack, Binding Posts, etc.

Reg. Price \$25.00

Our Price \$9.95

### REFLEX SETS


Nothing like the Reflex for results with a minimum of tubes. Even the One Tube Reflex will operate a loud speaker! The parts are complete—Transformers, both audio and radio, and all other parts included.

One Tube \$14.29 Two Tube \$19.29 Three Tube \$24.59

## THE RADIO SHACK

58 DEY STREET

NEW YORK CITY



## World Storage Batteries Save You 50% And You Get A Written 2-Yr. Guarantee

No better battery than the "World" can be built. That is why we can back it with the strongest guarantee written. We maintain the quality of our product. Our batteries have to be "right." And they are "right." Our tremendous steady increase in sales prove it. World Battery Owners "tell their friends." This is our best proof of performance.

- Special 2 Volt Storage Battery...\$5.00
- For W.D. 11 and W.D. 12 tubes. Will run 200 hours on one charge. Rechargeable.
- Special 4 Volt Storage Battery...\$8.00
- For U.V. 199 tubes. Same features as 2 Volt.
- 6 Volt, 60 Amp.....\$ 8.50
- 6 Volt, 80 Amp..... 10.00
- 6 Volt, 100 Amp..... 12.50
- 6 Volt, 120 Amp..... 14.50
- 6 Volt, 140 Amp..... 16.00

Send No Money. Just your name and address. We ship C. O. D. subject to inspection or will allow 5% discount for cash with order. When the battery arrives C. O. D., read the 2-year written guarantee before you pay one penny. You are protected from every angle. Save 50% by acting while these prices hold.

## WORLD BATTERY CO.

60 E. Roosevelt Road

Dept. L

Chicago, Illinois

# Radio Digest Illustrated

REG. U. S. PAT. OFF. AND DOM. OF CANADA

Published by the Radio Digest Publishing Company, Inc.  
123 West Madison Street  
Telephone: State 4843, 4844, 4845  
Chicago, Illinois

E. C. RAYNER, Publisher

Chas. F. Smisor, Editor Evans E. Plummer, Managing Editor  
H. J. Marx, Technical Editor M. W. Thompson, Associate Editor

Eastern Representative, Jacob Miller, Times Bldg., Times Square,  
New York; Telephone Bryant 4909

Pacific Coast Representatives

E. J. Wood, 251 Kearney St., San Francisco  
Telephone Kearney 1472

H. M. Morris, 417 Western Mutual Life Building, Los Angeles  
Telephone 12811

Member of the Audit Bureau of Circulations

58  
PUBLISHED WEEKLY

SUBSCRIPTION RATES

Yearly in U. S. and Possessions and Canada, \$5.00.  
Foreign postage, \$1.00 additional. Single copies, 10 cents.

Vol. VII Chicago, Saturday, November 10, 1923 No. 5

## Cold Days Revive Interest

Jack Frost Is a Welcome Visitor

SHORTER days and chilly evenings are doing much to revive interest in Radio. Practically all of the big broadcasting stations are going back to the daily winter programs. All these stations curtailed their schedules during the summer months on account of lack of interest. Within a few weeks the greatest of all indoor sports will again hold the center of the stage.

## Seeing Is Believing

Just a Little Glimpse Into the Future for Radio

AN EDITORIAL appearing in a New York paper says: "The next great invention will be the Radioscope. It will reproduce by the Radio waves transient events within 10 to 15 seconds after they happen. It will develop its film direct from the receiving reel and the record will be made by the simple application of Radio tone and vibration to kin tones of light and shade. Wizards are now working to win first place with this wonderful next invention. Yet, some poor and unknown youngster may be the one to succeed. You never can tell!"

Talk about "eye openers"; some of the wielders of the quill try to make you see things you never saw before. For years and years the visionary writers have tried to dip far into the future, bringing to the mind's eye just what is going to happen in the year 1950. Perhaps this sort of a chap will get a chance to peep into the year 1950—if he lives long enough; and through Radio at that, who knows?

We are traveling fast. Just the other day a few naval officers took an evening's jaunt of 2,000 miles, started from New Jersey, looked in on St. Louis and Chicago, never stopped to shake hands with us, and returned by night so that they had rolls and coffee at home the next morning. A little slower than the Radio wave but nevertheless fast compared to what it used to be. Soon we will not need to take that jaunt in a big blimp, just switch on the Radio periscope and direct it toward the city, old home site, the school-house where we spelled out our education and see it in actuality—by Radio.

## Two Groups of Listeners

Building Your Own Sets and Buying Them Complete

RADIO has divided itself into two distinct groups of broadcast listeners, those who buy a complete set and those who purchase the parts and put them together in the way that suits their fancy and according to circuits which seem to them to give the best results.

The class who build their own sets are in the majority because of the fun they get out of receiving distant broadcasting stations on a set designed, built, installed and operated by themselves, and their ability to change, rearrange and experiment with new developments in Radio.

When Radio came, the man on the street found that he could make his own apparatus at a saving in cost and have a lot of fun doing it. Today hundreds of thousands in various vocations throughout the country are building their own receiving sets and amplifiers. Progressive Radio companies and Radio publications are showing them how. They are getting results and learning something of science and mechanics. Radio is developing the people of this country into a more self-reliant race.

To trace theoretical circuits and to build a set an amateur must think. The process develops the mental powers of youth and it broadens the mind of the middle-aged bank president or professional man who a few short years ago had not the slightest idea of theoretical electricity, but who is now a bear for amperes, resistance and amplification.

It may be possible that complete Radio sets will largely replace the home-made, but today the average fan is not only having a lot of fun and getting good results with his own set, but is contributing by his experiments with circuits and apparatus to more satisfactory results in the use of Radio.

## RADIO INDI-GEST

### Interducing Kink Miloplex Hissself!

Responding to the terrific onslaught, rush and riot of readers of Indi-Gest and other foolish Radiophans, and, as was predicted last week, Indi herewith presents the



first and only picture of that now famous personage, The Mystery Man of the Miloplex, sometimes known as King Miloplex. He and Indi are great sidekicks, both being old scouts who never drank water before July, 1919. The portrait presented herewith was stolen from the Isle of Walla Walla during the war but was returned by the Germans when they found out that it wasn't worth anything. It has never been published before and probably never will be again. We don't know who else would have the nerve to publish it. The King has been crowned time and time again by his wife, alias the cook, alias Maggie. Just what is under the crown no one knows. Indi hesitates to say what, after analyzing the three circuits he has peddled off to the great American public. Photos of Maggie are still being made, after fourteen unsuccessful attempts in which the camera went into self-oscillation and paralyzed itself.

### A-B-C Lessons for Indigest Beginners

Chapter XXI—Milo Is It Now

BY GOSH

U IS for the ultimate,  
The last word in sets,  
And when you think you have it  
A new one calls your bets.

### Our Staff Photographer's a Wonder

Dear Indi-Gest: In interpreting the "boy milking cow" picture on the last page, upper right, September 29, you misunderstood cow language. The cow is not at all interested in Radio, but is looking for the best position to register a center kick to the boy who is attempting to milk her on the wrong side. Better try again. E. F. C.

### Send Us the Last; Keep the Rest

Dear Indi: I have been putting the Capitol Theater on the air here in N. Y. C. for almost long enough to furnish a house. Reason for that statement? Ah, that's easy. My worldly goods have been enriched by the following tokens of esteem, presented by admiring Radiophans:

- Fresh flowers.
- Fresh fruit.
- Fresh fish.
- 2 pair of pink sleeve garters.
- 1 book of poetry with the compliments of the author.
- 1 oil painting with the compliments of the artist.
- 141 ballads with the compliments of the composers.
- 7 original cartoons.
- 1 Airedale.
- 1 Police Dog.
- 238 Souvenir postcards from Radiophans on vacation.
- 17 ditto from honeymoon couples at Niagara Falls.
- 92 ditto from ditto at Washington, D. C.
- 1 hand-embroidered whiskbroom holder.
- 1 quart bottle of what-have-you. S. L. ROTHAFEL.

### Now We Know Who Is Doing the Dirty Work

Hear me laugh and chuckle with glee,  
'Tis such a funny thing to see,  
The way I violate the laws,  
And all the troubles I can cause.

I broadcast when I please,  
Come pounding in with ease;  
I crackle, snap and boil,  
Caring not what I spoil.

Why fight you, simple fools?  
'Tis his Satanic Majesty who rules,  
And does so many things erratic,  
To which you've given the name Static. H. K. C.

### Using That Junk? We Doubt It

Dear Indi-Gest-able: Please look carelessly over the enclosed diagram of my new set and try to explain why it won't work. In place of a detector tube I am trying out a special .002 Radio Corporation "Patent" in series with the transverse process of the seventh dorsal vertebra. Tuning is thru a 13-plate Music Trust invaluable condenser. Should it work? GRID LEAK.

P. S. I guess I won't send the diagram, you couldn't understand it nohow. G. L.

### See King Tut Proof; Page 4 Last Week

Dear Indi: Who said Radio is a new thing? Why long ago they named places after spare parts. Frinstance take Galena and Crystal City, both in Illinois. MIKE ROFARADS.

### It Might Be Anything

Dear Indi: I got the following song over the Radio last night. What might its name be:

Darling I am growing bananas,  
We have no string beans among the gold,  
Cabbages shine upon my brow today,  
Old fashioned tomatoes are fading fast away. E. SA. P.

To Indi-Gest Contributors and Prospective Helpers: Indi-Gest wants to thank each and every one of you for your prompt acknowledgment of the recent invitation to help. Still paging Spider Web, Le Moquer, Rotor E. Cap. Where are you? Indi.

## He Must Have Been Wrong



## Condensed

By DIELECTRIC

If you manufactured a phonograph to sell the gullible public, the tones of which were not perfectly free from a scratching noise, would you predict its certain removal from the market unless the unpleasant sound was eliminated quickly? I think so, too. No talking machine is free from mechanical sounds; nor is there a Radio receiving set made that is impervious to static's annoying spluttering. But to say, as Mr. Edison is quoted as saying, that unless the frying noises in Radio sets are prevented the interest in broadcast reception will quickly die—well, we shall see. A great inventor may fail as a prophet.

The football season is on with a vengeance. Many college graduates are so located as to be unable to attend a single game in which their alma mater takes part. To them the broadcasting of each play is an invaluable gift and far more stirring than to read about it. WNAC will continue to broadcast games from the Harvard stadium until the end of the football season. WEAF gave to a multitude of interested ones the contest between Syracuse and Pittsburgh, describing each incident in and out of the game, when those two teams met on the field of the Yankee stadium in New York. WJZ fed the Princeton-Notre Dame listeners in on the same day. There is really little missed with Radio in your home.

No more useful agency in the advancement of Radio (including Radiophony) exists than the amateur operator of a code station. He has contributed bountifully to the good of the science, incidentally to every broadcast listener in the world. Governmental regulations have safeguarded his continuance and at the same time provided for the happiness of concert fans. A certain owner of a receiving set near Chicago has a grievance against an amateur, located in the same town of Dwight, complaining of being unable to enjoy his concerts via Radio because of the code messages emanating from 9CA. By all means let's have every high powered commercial station in the land shut down while we listen to our favorite studios broadcast. What constitutes "profit"? McWilliams vs. QRM.

A new Radio station is under way at Wilmington, Calif., adding one more to the great transmitting stations owned by the R. C. A. Within a few months this station will be on the air, sending and receiving messages from a maximum distance of 15,000 miles. To the shipping through the Panama Canal this will be a great boon, though that is but one of its many points of advantage.

A feature that will no doubt find much favor among ship owners is the proposed use of a Radiophone equipment, by which speech may be had between ships at sea and Los Angeles offices, with the aid of land wires.

I trust broadcast announcers will take a minute to read the next few lines; the rest of you skip it. Several hundred miles from one of the great broadcasting stations a dealer tuned it in and entertained the crowd with its program. Seldom did the announcer state where he was, giving only the call letters. It may seem strange, but many among the listeners that evening were unfamiliar with the call, hence little realized how far away was the orchestra. Think it over!

Speaking of grand opera and musical broadcasts in general, I was interested to see that Musical America contains a column, under the captious title of Mephisto, supporting the stand taken by one of the publishers of operatic music compelling payment of a fancy sum before allowing certain scores to be broadcast. My sympathies are not at all with this position, for I still contend that attendance at grand opera performances will increase in proportion to the number of folks educated to its beauties.



# How to Build a Three-Tube Miloplex Receiver

## Part II—Assembly of Apparatus


By H. J. Marx

AFTER the apparatus has been purchased, the panel layout finished and the panels drilled, the troubles are by no means over. The proper arrangement of the parts on the baseboard in the rear of the panel is too often overlooked. There is a vague idea that leads should be kept as short as possible, yet nine times out of ten the fan thinks of it, but doesn't take it into consideration when laying out the parts in the rear.

The use of jacks for plugging in at various stages is very convenient, but the amount of wiring is increased thereby, and unless the apparatus is arranged with regard to these extra wires, it becomes difficult to make the connections without recrossing wires and running all around the various pieces of apparatus. Filament control jacks are even worse in this respect. Since three rheostats are used, there is no need for the filament control, however.

### Position of Transformers

The detector tube, plate terminal and primary of the first audio transformer are connected to the first jack, so their positions in the rear should be in close proximity to this jack. Then, the grid terminal



with and next to the one on the second unit.

The brass angles were purchased in a five and ten-cent store, but can be made at home if not available.

Binding posts can be substituted for the connection jacks if desired, the selection of these parts being entirely optional.

### Plan View of Second Unit.

No dimensions are given in the plan view of the base layout of the second panel. Dimensions will be determined entirely by the apparatus used, but the layout suggests the most efficient arrangement of parts for short wiring.

Particular attention should be paid to the relative position of the transformers and tube socket terminals. This arrangement permits short wiring and at the same time the transformers are far enough apart to avoid interference between their magnetic fields.

Improvements in the hook-up diagram has necessitated the postponing of this illustration until the next issue. The circuit will then be shown and the wiring will be discussed in detail.

(TO BE CONTINUED.)

**GENUINE EDISON ELEMENTS** (new) for making "B" Batteries, obtained from U. S. Government. A positive and negative element—6c; glass tube—3c; all other parts at reasonable prices. Postage, etc., 50c extra per order. Free instructions. **TODD ELECTRIC COMPANY**, 109 West 23rd Street, New York.

### Special Sets Made to Order


Let us quote you on any circuit.

### Send for Miloplex Price List

FORBES RADIO CO.

127 N. Dearborn St.

Chicago, Ill.



the second jack, so this must be equally considered in the arrangement. Again, the grid terminal of the secondary of this transformer must be connected to the grid of the third tube, so this, too, must be provided for in the planning. The plate terminal of this third tube must be convenient for connection to the third jack.

### Inter-Panel Connections

The connections between the two panels must be made convenient for external connections, and at the same time the leads to the apparatus must be considered.

Details are given of the drilling of the three small connection blocks. The one shown on top is for the battery binding posts and is mounted, by means of one of the brass angles, at the outer end of the base of the second unit.

The other two blocks are shown at the bottom, and consist of right and left-hand

pieces. The same angle is used for mounting them. The exact position on the base of the second unit is shown in the plan view layout.

Since all the apparatus of the first unit is mounted on the panel, no further plan view is given. The position of the connection block is on the right side in line



### Distributors for

### Radio Corporation of America

- |                  |          |
|------------------|----------|
| Grebe            | Magnavox |
| Atwater Kent     | Burgess  |
| Brandes          | Gould    |
| Murdock          | Eveready |
| Nath. Baldwin    | Frost    |
| Western Electric | Carter   |
| Acme             | Dubilier |
| All American     | Howard   |
| Signal           | Eby      |
| Chelsea          | Bradley  |
| Cutler-Hammer    | Jewell   |
| Western Coil     |          |

and other manufacturers of high standing

We carry a comprehensive stock of the latest receiving sets, parts and supplies of the leading manufacturers, and ship from stock promptly.

### FREE CATALOG

Illustrated, Sent on Request

Dealers: Buy reliable equipment from a house of established reputation. Send for catalog of tested and approved apparatus and our discount sheet.


**JULIUS ANDRAE & SONS COMPANY**  
113 Michigan Street, Milwaukee, Wis.

terminal on the secondary of the first transformer should be connected to the grid terminal of the second tube. This lead should be as short as possible. Therefore these two parts should be arranged so these terminals are close together.

The plate terminal of the second tube and the primary of the second audio frequency transformer must be connected to

## Cold Winter Nights

Won't find you on the roof fixing the aerial—removing snow and sleet, exposing yourself to sickness, if you use



### ANTENNELLA

(No aerial or antenna needed.)

A light socket plug that eliminates all outside wiring, lightning arresters and other inconveniences. Merely plug Antenella in any light socket and you can enjoy the best in radio in any room in the house.

NOW ONLY \$1.25

At your dealers—otherwise send purchase price and you will be supplied postpaid.

**Chas. Freshman Co. Inc.**  
Radio Condenser Products  
106 Seventh Ave., NEW YORK

# PERFECTION

MAKE PERFECTION YOUR SELECTION

<b>RADIOLA SPECIAL</b> —We are offering this remarkable Radio Corporation Set complete with Brandes Phones and U. V. 199 tube at the special price of.....	<b>\$44.50</b>	<b>FADA NEUTRODYNE</b> —One Sixty four-tube set. List \$120. Special.....	<b>\$94.50</b>
(The greatest radio value ever offered)		<b>STORAGE BATTERIES</b>	
<b>N &amp; K PHONES</b> —These are the new type N & K phones made in Germany. They are, without question, the world's best phones. A limited quantity at special price.....	<b>\$5.90</b>	Eveready, 90 amp.....	List \$18.00 Our Price \$14.90
<b>BRANDES PHONES</b> , Superior.....	<b>\$4.95</b>	Eveready, 110 amp.....	20.00 16.90
<b>ALL-AMERICAN</b> Transformers, all ratios.....	<b>\$3.95</b>	Marko, 50 amp.....	12.50 10.50
		Marko, 80 amp.....	16.00 13.50
		Marko, 110 amp.....	20.00 16.50
		<b>ATLAS LOUD SPEAKER, NEW TYPE.</b> A loud speaker beyond compare. Adjustable tone. List \$25. Special.....	<b>\$18.50</b>
		<b>AMERTRON TRANSFORMERS.</b> List \$7. None better made.....	<b>\$5.75</b>

**PERFECTION RADIO CORP.**  
Mail Order Dept. 59 CORTLAND ST., NEW YORK CITY Add Parcel Post  
Do Not Send Stamps  
N. Y. Retail Stores: 78 Cortland St., 119 West 23rd St., 128 Chambers  
208 page complete Radio catalogue free with order of \$5.00 on request. Otherwise prepaid for 25 cents

## Natural Re-PRODUCTION

# Atlas AMPLITONE


## LOUD SPEAKER

Atlas Loud Speaker re-PRODUCTIONS are absolutely true to the original. The patented "double diaphragm" responds in perfect harmony to every change of vibration intensity. Adjustable to your set and particular receiving conditions as accurately as though built expressly for you. Ask the nearest Atlas dealer to demonstrate the ATLAS Loud Speaker for you.

**WRITE FOR BOOKLET "R"** \$25  
What have you accomplished with your Atlas Amplitone? Tell us about it!

**Multiple Electric Products Co. Inc.**  
ORANGE ST. RADIO DIVISION NEWARK, N. J.

### ANOTHER SINGLE TUBE REFLEX



FANS very often fail to get due credit for their efforts in developing little alterations in circuits that are really distinct improvements. Mr. J. P. Flaherty, Rialto Theater Bldg., Louisville, Ky., has sent us his development of a single tube reflex and asks us to offer it to the fans.

His circuit is shown in the illustration as hook-up R.D.-102 and his letter follows:

"After experimenting for the past six months with every reflex circuit known, I have decided the following one is the best, and hereby ask you to publish it for the benefit of the many reflex amateurs.

"The circuit, with exception of the variometer regeneration and fixed condenser across primaries of both transformers, was originally presented by Mr. Harry J. Marx of Radio Digest.

"I am covering the whole United States with this one tube circuit, with any amount of volume and clarity desired. Briefly there is no end of encouraging surprises in this circuit. I have heard

### THE UNOTROL (One Control) Broadcast Receiver

A Real One Tube Set. Made of best material throughout. In a Real Cabinet, with hinged top. High grade mahogany finish, hand rubbed. At a Real price. Will ship C. O. D.

Postage paid east of Rocky Mountains ..... \$11.90

Set is Fully Guaranteed. Wonderful Distance Reported by Enthusiastic Users.

Dealers: Write for our proposition. Some good territories still open for bona fide Radio Dealers.

To the Experimenter and the Man Who Builds His Own: Write for Our Bulletin of Parts at Bargain Prices. Standard Merchandise Only.

Abalene Radio 105 Audubon Ave. New York, N. Y.

### The B-T Vernier Tuning Unit

owes its wonderful popularity, gained within a comparatively short time, to the fact that its designers knew what they were about.

Vernier control of inductance is secured by the rotor, the adjustment of which makes it possible to widen the range of wave lengths that can be covered without taps.

For those who want something less expensive we can recommend our 4 to 1 Fixed Coupler as being excellent in design and workmanship, but we do not make any claims about its being a Vernier Tuner. It's fixed. The condenser must do the tuning.

If you want to know more about close tuning, send 10c and dealer's name for our booklet.

Bremer Tully Mfg. Company  
532 South Canal Street CHICAGO




### Ask your Dealer about "HEGEHOG"

(Trade Mark) AUDIO TRANSFORMER \$3.50

This little wonder is the surprise and talk of Radio Engineers everywhere. Fix in your mind's eye an AUDIO Transformer about the size of an English walnut and you have the "HEGEHOG" for size. Then recall the best Radio amplifier you ever heard, and you have the "HEGEHOG" for volume and tone quality. Our new patented design and construction (100% shielded) makes this possible. It's a real bit of engineering, and we would like to have YOU try one.

Ratios 1 to 3, 1 to 4 and 1 to 5.....\$3.50  
1 to 10..... 4.50  
Write for Bulletin No. 92

Premier Electric Company  
3810 Ravenswood Avenue, CHICAGO, ILL.



### WE REPAIR YOUR VACUUM TUBES

- WD-11-12, UV-199, UV-201-A C-301-A .....\$3.50 each
- UV-200, C-300..... 2.75 each
- UV-201, C-301..... 3.00 each
- DV-6, DV-6-A ..... 3.50 each


All Work Fully Guaranteed  
Quick Service—Repaired Tubes shipped C. O. D. unless accompanied by remittance plus postage.

- #### NEW TUBES
- A-399 (Type UV-199) \$4.10
  - A-401-A (Type UV-201-A) EACH
  - A-12 (Type WD-12)

All the above Tubes guaranteed amplifiers and detectors. Shipped C. O. D., postage prepaid.

ABALENE RADIO 14 Vesey Street NEW YORK CITY

### EASTERN COIL SETS for the COCKADAY CIRCUIT



are now a standard, and in universal use, due to their efficiency in this wonder circuit. Made as per specifications of Mr. Cockaday, using No. 18 wire with D coil bank-wound.

Complete Assembled Set of B, C and D Coils..... \$2.75

Hook-up directions and material list furnished free with each set of coils.

Mail Orders Filled. Dealers Communicate  
EASTERN RADIO MFG. CO.  
22 Warren Street, Dept. R. D., NEW YORK, N. Y.

stations at Kansas City, Omaha and others at equal distances, with no aerial other than 15 ft. of wire thrown upon the floor. I can hear WHAS, a distance of six miles with no aerial or ground.

"I would like to hear from other amateurs concerning this circuit."

### The Reader's View

**Consideration for the Broadcasters**  
There has been a decided tendency on the part of some fans to belittle the programs given out by various broadcasting stations throughout the country. Many seem to forget that the broadcasters are handicapped at times, as well as the fellow on the receiving end. They seem to think that a great deal of the music, lectures, concerts, etc., broadcast evening after evening, is executed by poor talent and is too much of a repetition of the same thing. These fans do not consider the fact that they receive all of this free, and that, besides, they have a choice of several stations and may select the one they like best. Tastes are not alike; some

like jazz, some classical music, some lectures, some sports, etc., and it is hard to please everybody.

Have some consideration for the broadcasting station. Don't expect too much, especially when the Radio business is still in its infancy. If we lived in Europe and had to pay a license on our receiving sets, and then have only a comparative few stations to listen to, we might have some real cause for complaint.

I am not in favor of a government license on a receiving set. This is in answer to an article by W. R. Spangle, in "The Reader's View" of your September 22 issue.—R. A. Pauly, Springfield, Ohio.

It is estimated by engineers that the current picked up by the antenna is about three trillionths of the energy broadcast from the transmitting station's aerial.

### METALECTRIC SOLDERING IRON

"The All-Metal Quality Instrument—GUARANTEED"

A Solution to the Small Soldering Problem of the Discriminating Assembler. Unbreakable Construction — Economical Operation on any Electrical Circuit—Interchangeable Tip.


\$5.50

From your dealer or write

Post Electric Co., Mfrs.  
Dept. 509, 30 East 42nd St.  
New York City



### CARTER Automatic Control Rheostat



Six Ohms \$2.25 20 or 30 Ohms \$2.50

Rheostat and Jack in one. Eliminates necessity for Jacks in amplifier circuit. Attach head phones or loud speaker to binding posts or Detector Jack and each stage of amplification can be brought in by simply turning the knob of Rheostat. Original Carter design. Positive in action, easy to mount and install.

Send for illustrated catalog giving interesting and unusually efficient hook-up.

Carter Radio Co.  
209 S. STATE STREET CHICAGO

### What About It?

Isn't it about time to stop experimenting with multiple control circuits and build one that, combining ease of assembly and operation, loudness, clarity and selectivity of signals, as well as beautiful appearance, is excelled by none?

### THE ELGIN SUPER-REINARTZ RADIO RECEIVING SET


Embodies all the advantages of the well known Elgin Reinartz (the set which was largely responsible for the popularity of this wonderful circuit) and many others. It is much louder, more selective, requires no storage battery, and can be used with excellent results on a short or loop aerial.

It has brought in California stations two thousand miles from Elgin, clearly and without interference on a loud speaker with only one tube, and that while our powerful local station was broadcasting three miles away.

Could you ask for more?  
Write for circular giving one, two and three bulb hook-ups of this remarkable circuit. IT IS FREE.

ELGIN RADIO SUPPLY CO.  
207 East Chicago Street ELGIN, ILLINOIS

### "Service that is certain"



- Langbein & Kaufman Variometers and Variocouplers .....\$6 ea.
- Finest instruments in the world.
- Myers Hi-Mu Tubes.....\$4.35
- Amperite-Automatic Filament, eliminates Rheostat.....Unmounted, 70c; mounted, \$1.10
- All merchandise absolutely guaranteed.
- Shipped immediately on receipt of purchase price.

Radio & Mechanical Trade Corp.  
23 Warren St. NEW YORK

### REAL RADIO PERFORMANCE! New Principle of Tuned Radio-Frequency Gives Remarkable Results

### WITH THE MELCO-SUPREME

The Radio-Frequency Amplifying Receiver that— Operates with merely a 10 Ft. Wire—not even a ground necessary. Offers exceptional Clarity without the slightest loss of tone quality. Assures unusual program Selectivity through its single tuning adjustment.


Affords real Long Distance by covering all Broadcasting ranges from 180 to 610 Meters.

We also manufacture a complete line of parts under the Amsco Brand. Write for our complete literature.

AMSCO PRODUCTS, Inc.  
Broome & Lafayette Sts. Dept. DT. NEW YORK CITY

Price Only \$140

Complete knock-down parts for Melco-Supreme, including drilled engraved Bakelite panel and solid mahogany cabinet. Price \$90



# Simple Coil Increases Range of Old Set

## Distance Accomplished on Single Circuit Set

Having a single circuit receiver that would tune to only about 425 meters and using a variocoupler with 65 turns on the primary and 60 on the tickler, I found that when the broadcasting wave lengths

### WORKSHOP KINKS? EARN A DOLLAR—

**T**HERE are many little kinks worked out at home that would aid your fellow Radio worker if only he knew about them. There are new hook-ups, new ways of making parts and various unique ways of operating sets that are discovered every day. Radio Digest is very much interested in obtaining such material. Send them in with full details, including stamped envelope, so rejected copy may be returned. The work must be entirely original, not copied.

RADIO KINKS DEPARTMENT,  
Radio Digest,  
123 W. Madison St., Chicago

were changed, some alterations were necessary to receive the longer waves. However, as I did not wish to rebuild the set nor to purchase a larger condenser (the one in use being 23 plate) the following plan was decided upon, and gave good results:


A cardboard tube, 3 1/4 inches in diameter, was wound with 70 turns of 24 dcc. wire and tapped every ten turns. The cabinet was not large enough to accommodate this coil and a special one was built 6 by 6 by 5 inches, the coil being mounted in a horizontal position. A 6 by 6 bakelite panel was used and holes were drilled to mount switch, switch points and binding posts as shown in the diagram. Leads were run from the taps on the coil to the switch points. One end of the coil was connected to the lower binding post, the switch being connected to the other.

The loading coil was then mounted on top of the set and connections made through 1/8-inch hollow fiber tubing run through the top. It was found to work best connected between the condenser and the switch of the variocoupler.

The use of this coil seemed to increase the volume of reception, as 360 and 400 meter stations that were hard to bring in before, came in very plainly. The following stations have been heard frequently this summer, with this arrangement: KSD, WOAW, WMC, WOS, WEAY and WOAI. —R. Lewis Rockett, Ft. Worth, Texas.

Efficient operation of a Radio receiving or transmitting set depends on the proper adjustments of inductance and capacity.

## VOLUME OF RECEPTION ENLARGED



### Levers for Dial Turning

Many fans have wondered how they can eliminate body capacity effects without shielding the panel. The arm or handle shown in the illustration, eliminates body capacity effects and also acts as a vernier for condensers, couplers and variometers. It helps greatly in picking up outside stations and does not take up any panel space. After a station is tuned in, the arm may be removed from the dial and put out of the way.

The parts required may be found in any Radiophan's "junk box."




FIG. 1




FIG. 2

The parts needed are: One strip formica 6 by 1/2 by 1/8 inches, one small rubber knob, two upholstery nails 1/2 inch long, and one flat head machine screw 3/8 inch long.

The strip of formica, cut down on one end to 5 1/2 inch and the ends rounded, is shown in Figure 1. At the narrow end drill two holes 1/2 inch apart and slightly smaller than the diameter of the nails so that they will fit tightly. At the other end

drill a 1/8-inch hole and countersink it for the head of the machine screw. Push the nails through the holes at the narrow end, as far as the heads, and cut off the points so that 1/4 inch of the body will project from the strip. With the machine screw fasten the small knob on the other end. In the knob of each dial to be used drill two holes 1/2 inch apart and slightly larger than the diameter of the nails (Figure 2). In some sets the knobs and dials are placed close together. Where this happens to be the case the strip will need to be shorter, to avoid striking the other knobs. —Robert Shimek, Chicago, Ill.

## Neat Way of Mounting Condenser on the Panel

Many variable condensers, when mounted directly on the panel, allow the screw heads to show on the outside of the dial, thus detracting from the appearance of the finished set. As the shafts on these instruments are usually a trifle longer than necessary, this is easily overcome by first mounting the condenser on a piece of bakelite or wood, and then mounting the whole on panel with flat-head screws, countersunk under the dial.

This kink can also be applied to variocouplers, variometers and tuning coils, and the finished appearance will well repay one for his trouble. —Neil E. Henry, Lynchburg, Va.

## FORMICA A Laminated Phenolic Condensation Product SHEETS TUBES RODS RADIO PANELS POLISHED BLACK FINISH

CUT PERFECTLY SQUARE TO ANY SIZE

1/32" THICK	1/2¢ PER SQ. INCH
1/16" THICK	3/4¢ PER SQ. INCH
3/32" THICK	1¢ PER SQ. INCH
1/8" THICK	1 1/2¢ PER SQ. INCH
3/16" THICK	2¢ PER SQ. INCH
1/4" THICK	2 1/2¢ PER SQ. INCH
5/16" THICK	4¢ PER SQ. INCH
3/8" THICK	5 1/4¢ PER SQ. INCH

SEND FOR COMPLETE PRICE LIST PROMPT ATTENTION TO MAIL ORDERS DEALERS PRICES ON APPLICATION

STARRETT MFG. CO.  
519 SOUTH GREEN ST. CHICAGO

## WD11 and WD12 REPAIRED


ALSO OTHER TYPES OF TUBES for \$3.00

and guarantee them to work like new. We prepay parcel post back to you.

QUICK SERVICE

THOMAS BROWN CO.

511-519 ORANGE ST. NEWARK, N. J.



## Crosley Model X-J \$65

DISPEL dull care during the fall and winter evenings with a Crosley Model X-J radio receiver. Enjoy, nightly, the concerts, speeches and other amusements that are sent out from New York, Honolulu, Cuba, Cincinnati and hundreds of other places.

For bringing in distant stations clearly and distinctly, no set can excel a Crosley Model X-J. It is a 4 tube radio frequency set, combining one stage of tuned radio frequency amplification, detector and two stages of audio frequency amplification.

Actual tests have proven it the most remarkable radio receiver ever offered regardless of price. See this beautiful instrument at your dealers. Complete catalog describing the entire Crosley line of instruments and parts will be sent free upon request.

Write for It Today.

Crosley Manufacturing Company

POWEL CROSLY, Jr., President

11492 Alfred St., Cincinnati, Ohio

## B-METAL

The Crystal That Brought Joy to 100,000 Radio Users Last Season.

Sent on approval. Pay us when you are satisfied. That's how sure we are that it will please you. Just pass the good news on to a dealer so others may enjoy B-Metals too. Just send us the name of dealer who hasn't heard of B-Metal when remitting.

**50c**

## RADIO CRYSTAL

B-Metal Refining Co., 3134 Trumbull Ave. Bellevue, Pa., Sept. 4th, 1923. Detroit, Mich.


Gentlemen:—Your crystal is simply fine. I've been using "....." a crystal manufactured and widely advertised throughout Pennsylvania and they claim it is used by people in 15 states, but your crystal has it all over theirs. I thought "....." was good myself, but yours wins 1st prize.

Kindly send me the type "B" tube detector and if it is anything like your crystal it must be a wonder. You will hear again from me or my friends. Best wishes for your success. I am very truly yours,

EDWIN RICHARDSON

**\$2.50**

## REFLEX DETECTOR



## W W

### Variable Grid Leak and Condenser

Brings in those stations you have been trying to get

FOR SALE BY PROGRESSIVE DEALERS

**Hansen Sales Co.**


4607 West Madison Street Chicago, Ill.

Dealers: Write for Discounts

Sample Postpaid  
**75 cts**

## DUPONT PYRALIN SHELSTONE

Loud Speaker With Nath. Baldwin Head Set Type C Perfect Results



Sheltone is made of Dupont's Pyralin, is transparent and one of the most attractive Loud Speakers on the market.

It is built differently to take advantage of the most correct acoustic principles and reproduces music and speech with a clear tone.

Loud Speaker with phones .. \$15.00


Loud Speaker postpaid ..... 3.00

Satisfaction guaranteed. C. O. D. or cash with order. Dealers write for discounts.

THE SHELSTONE COMPANY  
185 Clinton Avenue NEWARK, N. J.

## WALNART

### Variable Grid Resistance



Complete with knob and pointer ..... **\$1.00**

Clears up signals. Gives longer life to batteries. Simple to operate and install. Will last indefinitely without deterioration or loss in efficiency. Can be used with or without a fixed condenser.

The one Variable Grid Resistance that has given entire satisfaction.

We also manufacture variable condensers, plain and vernier, tube sockets, standard and UV. 199, vernier adjusters, inductance switches, etc., of highest quality. Ask to see them at your dealers.

WALNART ELECTRIC MFG. CO.

Dept. 408—1249 W. Van Buren St. CHICAGO

WRITE FOR FOLDER OF COMPLETE LINE OF WALNART RADIO PARTS

### RADIO FOR EVERYBODY

(Continued from page 15)

noted we said "the ratio of the varying voltages is as the ratio of the turns." Because there are 22 volts in the primary of our audio frequency transformer, it does not mean there will be 110 volts on the grid of the amplifier tube if the ratio of the number of turns in our windings is 5 to 1. The voltage in the primary of the transformer will have a maximum of 22 volts, but it may vary below that figure 2, 3, or 4 volts. Thus, if our incoming signals vary the potential on the grid of our detector tube so that it varies the voltage in the plate circuit between 18 and 22 volts, there will be voltages on the grid of our amplifier tube varying between zero and 20. The maximum variation in our primary is 4 volts, the ratio is 5 to 1; therefore, the maximum voltage on our next grid is 20. It should be understood that in "transformer action," while we triple or quadruple the voltage, we divide the current or amperage by three or four. Energy cannot be created in a transformer—energy is figured in watts—watts are the result of multiplying volts by amperes—as the voltage is raised, the amperage is lowered. As it is large voltage changes that we desire, the lessening in amperage does not matter.

So much for our inductances. In the next chapter we will see how capacity is provided in the form of condensers both fixed and variable.

(TO BE CONTINUED.)

### NEW MILOPLEX CIRCUIT

(Continued from page 11)

sibly make it even more understandable, if you should sound the key of C and E simultaneously upon a piano, the resultant note would not be either C or E but that produced by their combination. It is this third tone which we are desirous of using in the Miloplex, or as Mr. Marx says, the result of a heterodyne effect, it being sharper and more easily handled. Many will question, a few dispute the possibility of producing such a tuning result. Frankly, I am not positive that I do, yet it still holds true that some such action is taking place, as at times when the settings of such tuning is correct, a varying frequency is produced indicating super-regeneration. To those who have amplified circuit three, or the final circuit, and have apparently by so doing lost some of the circuit's selectivity, may I suggest as a remedy the insertion of a .006 fixed condenser in the plate-to-antenna connection? It sometimes occurs, when amplifying, that the impedance of the first audio windings, which connected became a high impedance by-pass through the B battery to A, inserts too much resistance coupled to the primary and hinders selectivity. By inserting a fixed condenser as suggested, this impedance is eliminated, and we at once secure our original primary selectivity, thus retaining a balance that is very desirable. It should be understood that the total circuit of the Miloplex, excepting the tuned Radio frequency oscillating rotor circuit, is the well-known Colpitt's modification of the ultra-audio with a slight alteration. In all, or in practically all, such modifications, regeneration is controlled through filament adjustment with

the result that the selection of a detector tube is very essential, some such tubes functioning very poorly. Hence I suggest that one try several detector tubes if possible, retaining that which appears best. Again, when amplifying either a straight ultra-audio on the Miloplex, one should use a rheostat for each tube. You have no doubt noticed a very pronounced ground hum in the circuit until the filament of both the detector and each amplifier is adjusted. When this balance is had, the hum disappears and she starts hitting on all six. If when set the volume is too great, leave the rheostats alone, but reduce your volume by slightly changing the inductive coupling of the oscillator. To tell each of you the exact method for proper tuning of Plexy is a difficult job indeed; in fact better results are obtained if you learn to shift the gears without aid. You will, however, as you gain in experience, discover that just a hair line away is another station ready to hop in and that's when the fun begins.


Radio Digest has mentioned, also published some of the DX results secured with the Miloplex, while I have a bushel basket of letters containing reports which are most pleasing. I have deliberately refrained from mentioning DX work, being content to leave this to the fans, yet you may be interested in knowing that I seek primarily DX during daylight as I consider daylight reception as the supreme test. In my work along this line the greatest distance on loud speaker has been Detroit, which is about 300 miles, while with phones I have heard WGR at Buffalo, WGY at Schenectady and WSB at Atlanta many times. Only yesterday I ploughed through KYW and brought in Omaha at 2:30 p. m., Omaha being 422 miles from Chicago. Please understand each of these are daylight DX results and are not consistent, yet have been accomplished several times, which leads me to believe the Miloplex will travel some in a pinch. Reports received seem to indicate that those centrally located get most of the principal stations, while the usual freak coast to coast results are reported here and there. I say "freak results" for I question very much those circuits that refuse to listen to any station short of Los Angeles every night; they always remind me of the sweet young thing who "wouldn't marry the best man on earth" and finally didn't. Seems to me they are always singing "I hear you calling me," and next day have all their friends "call them."

Cuba will say "Hello" to you on the Plex, but if you expect to hear Cuba every night, build a Spanish circuit, the Miloplex just won't—and that's that. And now, I come "to the end of a perfect day."

Beginning the day (Sunday) by reading a host of fan letters, friend wife said, "Forget Radio and go to church"; so robbing the kid's bank of all its pennies, off

### You Don't Need Tubes

to get out of town. If you want new stations on your crystal set WRITE ME TODAY. Mine works 400 to 1,000 miles without tubes or batteries! Thousands have bought my plans and now get results like mine. CHANGES OFTEN COST LESS THAN A DOLLAR. Send self-addressed envelope for further information. Leon Lambert, 501 South Volusia, Wichita, Kansas.



FREE! Send for Circuit

### New Cockaday Circuit --with the DIODE

A revelation in reflex work. The Diode replaces the crystal and overcomes all former difficulties with reflex circuits. Requires no adjustments for change of wave lengths. Gives you the clear reproductions of a crystal with the sturdiness and reliability of a tube. No "B" batteries required. Operates on less than 1/2 ampere from single dry cell. Easily adapted to Erla circuits. At your dealers or send purchase price and you will be supplied postpaid.

ELECTRAD, Inc.

428 Broadway NEW YORK



to the meeting house we go—I secure in the knowledge that as yet I remain "The Mystery Man" but you cannot fool a preacher, for no sooner had the "soft hand" usher seated us than the choir began singing "Listen and ye shall hear," and just to rub it in the minister constantly referred to "A voice in the wilderness." Then, apparently thinking my one minded brain had not grasped the full meaning of their effort, they hammered out the pipe organ encore entitled "Softly a voice is calling." The next time I go to church—well, I don't know what they will place on the Christmas tree for me—I'm going to have them cut out all of those Radio songs; 'taint fair—you know what I mean.

The cook is back. How do I know? Well, I know how well I know; didn't the gas company just call up and say, "please pay" for the sake of the maker of the universe. Gas companies and cooks certainly have a closed union. Let's eat! (TO BE CONTINUED.)

### Modulation Transformer

Most of us who have small transmitting sets are not troubled with an overload of ready cash and wish to make most of our own parts. I was unable to locate data on a modulation transformer except such that it would be impossible for the average amateur to build, and therefore used my own ideas with the result that in half an hour and without any expense whatever except for 2 feet of Litz wire, I produced a transformer that gives excellent results.

Some amateurs use a Ford unit and get fair results but the secondary has entirely too much winding, which increases the resistance and ratio out of proportion, so I cut it down as follows:

Take the coil from the case and remove the wax by sharp taps with a light ham-

mer. Then, take the two secondaries off the primary, and unwind the primary, saving the wire. Cut the core off to 3 1/2 inches in length. Wind the primary back on in four layers, 45 turns to the layer. You will have just enough wire. Tape it well and lay it aside. Next, take one of the secondaries which contains 35 layers, 250 turns to the layer, of Number 36 enameled wire. With a knife remove the paper from the inside and start unwinding from the inside end. Remove six layers and solder a piece of Litz to the end for the connection. Remove nine layers from the outside, soldering on a Litz wire connection. Tape carefully to protect the fine wire. The core with primary wound on will fit snugly into the secondary. Tape all together solidly, leaving the connections projecting. It can be mounted in any manner you desire.

This transformer will have a ratio of about 27 to 1, primary resistance 3 ohms, secondary direct current resistance 700 to 800 ohms, and works best with a .00025 condenser across the secondary.—Chas. Middleton, La Porte, Ind.

If you put the third step of audio on your set, fixed condensers across the windings of the last transformer will help stop howling if any occurs.

### ROOT FOR RADIO!!

LOUD SPEAKERS	
Western Electric 10D.....	\$48.50
Mercury.....	7.50
PHONES	
Brands.....	\$5.25
Western Electric.....	8.25
Nerco (1-year guarantee).....	2.75
TRANSFORMERS	
All American (all ratios).....	\$4.25
Erla Reflex.....	3.95
Acme.....	3.75
PANELS (High Grade) CABINETS (Mah. Fin.)	
7x10.....	\$ .75
7x18.....	1.35
7x24.....	1.75
Hydrometer.....	.35
Sockets.....	.35
Bus bar length.....	.03
7x10.....	\$2.45
7x18.....	2.95
7x24.....	3.45
Snaggetti length.....	.07
Dials, 3".....	.30
Dials, 4".....	.40

We carry a complete line of all standard parts and sets. Let us know your wants. We can fill all your Radio requirements. We pay postage on orders of \$5.00 or over only.

### ROOT RADIO CO., Inc.


DEPT. D. 2525 BROADWAY, NEW YORK CITY

# FREE

## Your Choice

of one bound volume with each annual subscription

### Limited Supply



Greatest Collection of Radio Information Ever Published

- Reinartz Long Distance Circuit
- Ultra-Reinartz Circuit
- Flewelling "Flywheel" Circuit
- Grimes "Inverse Duplex" Circuit
- Single Tube Reflex Circuit
- Armstrong "Super-Heterodyne" Circuit
- Two, Three and Four Tube Reflex Circuits
- A. B. C. Lessons for Radio Beginners

In addition to these features these volumes contain many instructive articles, receiving set diagrams, how to make articles, new apparatus, pictures and illustrations, hook-up diagrams, broadcasting stations, technical articles and book reviews.

# 65 Numbers

13 Numbers in the Bound Volume; 52 Numbers in Year's Subscription. Volumes 2, 3, 4, and 5 Now Ready.

Your choice of one Bound Volume is free and postpaid with your one year's subscription or renewal.

This offer good only in the U. S. and possessions. One dollar additional for Canadian or foreign countries.

Additional volumes are \$2.00 each, but are only available to annual subscribers. This on account of our limited supply.

Orders for these Bound Volumes must be mailed us direct with full remittance, as they can not be supplied on orders through subscription agencies or news dealers.

Remittance must be by check, money order or draft. (Stamps not accepted.)

COUPON 11-10

Radio Digest, 123 W. Madison, Chicago

CHECK OFFER DESIRED


- One year's subscription and choice of one volume. Send Vol. .... Check or M. O. enclosed.....\$5.00
- One year's subscription and choice of two volumes. Send Vols. .... Check or M. O. enclosed.....\$7.00
- One year's subscription and additional Volumes Nos. ....

Be sure to write plainly your name and address, giving city and state.

IF YOU CAN'T BUY THEM AT YOUR DEALER'S SEND DIRECT TO US

"Red-Heads" are guaranteed radio phones. You run no risk when you buy them. Money back if, after 7 days' trial, you're not satisfied that they're the best receivers on the market at the price. Why not act right now and get a pair? It'll mean getting the maximum from broadcasting from the day you put them into use.

## RED-HEAD RADIO RECEIVERS



These remarkable head-sets are made by The Newman-Stern Co., one of the pioneer radio manufacturing houses in America.

### JUST OUT

The new 1924 Model F      The new 1924 "Red-Head" Jr.


\$6.50 PER PAIR Complete      \$5.00 PER PAIR Complete

This is the standard 3,000 ohm "Red-Head." The 1924 Model F has eleven improved features. Sensitive and fine-tuned; aluminum case; famous brown-red ear caps; military headband; high-grade cord.

The Junior Model has most of the quality features of the standard Model F here described. The resistance is 2,000 ohms per set instead of 3,000 ohms. A remarkable value.

"Red-Heads" sent prepaid on receipt of price if you are unable to get them at your dealer's.

THE NEWMAN-STERN COMPANY  
Dept. RD Newman-Stern Bldg. Cleveland



### Now A Practical Indoor Aerial

Ideal for sharp tuning. Reduces static to a minimum. Contains 600 feet of wire. Instantly collapsible and portable. Can be hung on door or placed under carpet. Noticeable directional effect. Particularly effective in large cities where several stations are broadcasting at the same time. One INDORARIAL used as antenna and another as ground gives interesting results.

At your dealer's, otherwise send purchase price and you will be supplied, postpaid.

ELECTRAD, Inc., 428 Broadway, NEW YORK

## ELECTRAD INDORARIAL

# Audio Amplification for the Flewelling Set

## Part III—Use of Filter in the Circuit

By E. T. Flewelling

IN LAST week's issue we discussed amplification and the Flewelling super-circuit up to the point of using a suitable filter circuit in connection with the amplifier. It has often been said of the Flewelling circuit that it consists of nothing more nor less than a straight regenerative circuit, having incorporated in it

its maximum and returning in the same manner to its zero point.

Speaking in general, such a voltage or current chain would be a more or less easy thing to filter, depending upon the apparatus used and our individual skill. Unfortunately, the writer believes we have a more difficult proposition on our

hands when we take up the matter of filtering out the variation frequency for the Flewelling circuit. This variation frequency is caused not by an Eaton oscillator, or other similar arrangement, but as has been said so many times, by the blocking and freeing of the tube action working in connection with the charge and discharging of the large .006-mfd. condenser, and this frequency is not believed to follow a sinusoidal form, but is more flat and subject to—perhaps an easy way of saying it—sharp corners and changes. Experience will teach that this is an extremely difficult type of output to filter.

### Use of High Resistances

In general, the writer would recommend the use of audio amplification with the Flewelling circuit without the use of a filter, the variation frequency whistle being subdued as much as possible by the use of separate B batteries and A batteries for the amplifier by setting the grid leak so that the variation frequency does not bother. The use of high resistances, such as variable grid leaks, across the transformer terminals, where experience shows that improved reception re-

sults, and an effort to keep the set and its amplifier as free from each other electrically as is possible, would be the writer's idea of how to build an amplifier for the Flewelling circuit. The use of separate A and B batteries may sound like a hardship, but with such tubes as the UV-199 or WD-11 or WD-12, is really

### Use Standard Types of Filters

It is an impossibility to give the constants for a filter and feel that they would be of any value to readers, because, aside from the difficulty of wave form spoken of above, their values would not be alike for various sets, and success with filters depends almost as much upon the experience and skill of the operator as it does upon more or less accurate descriptions. For those readers who wish to carry out the filter idea, I think it best to simply refer them to any of the standard or usual types of filters.

As the writer sees it, the secret—and there isn't any—of correct amplifier, or for that matter, correct set or detector construction, was shown in the photographs accompanying the first article in this series, and he believes that a close study of the constructional details of the set shown will well repay one's time. It has often been said that "simplicity is the keynote to efficiency." Our two pre-

vious articles on audio frequency amplification for the Flewelling circuit were purposely meant to emphasize the great and very apparent need for simplicity of construction, because it has so many times been demonstrated that the more clean-cut the construction of a set is, the better the results that the set will give us.

The writer has received scores of letters in which the statement is made, "I do not believe that I am getting the maximum results from my set; can you tell me what to expect in the way of long distance reception?" We haven't the space for a lengthy discussion of this point, but it might help a bit if I say that the set shown in the photographs in the first article is a plain regenerative set with three stages of audio frequency amplification. This amplification does not help the set out much so far as distance work is concerned, so that for this purpose it really amounted, aside from volume of sound delivered, to a single-tube set, yet it was found very possible to bring in 400, 500 and 600-mile stations on the ground alone, without the use of any other antenna than the set itself in various parts of the eastern United States during the month of August, when reception was not at its best anyway. This, then, is a convenient manner in which we can gauge our sets and is mentioned in the hope that some of our readers who try it may gain a little by such test, and if they care to go to the trouble, will write to the Digest, telling what they have been able to do.

Our articles have really emphasized the desirability of constructing our Radio sets along the line of what might really be called "wireless Radio sets." Sounds like a joke, doesn't it? But imagine the lack of confusion and the nice, clean-cut appearance of such a set, to say nothing of its vastly improved ability. Certainly it does seem worth our while to keep this idea in mind when we are "rolling our own."

(THE END.)

### AN ENTHUSIASTIC FLEWELLING USER


Gentlemen:

We finished building a one condenser super-set some time ago and must say that the results are wonderful. We can receive from Detroit, Schenectady, Chicago, Pittsburgh and a few other points on a piece of wire about 30 feet long which is hung around the room. We have never built a set that is as sensitive, or as critical, and yet so easily controlled. Using the ground wire only, long distance reception and amplification are fine. We have not as yet had any success in amplifying signals from the Flewelling detector but hope to in the near future.


It is the ideal set for places where erecting an outdoor aerial is not allowed.

We want to thank Mr. Flewelling and the Radio Digest for showing us how to get the most out of Radio at the least expense.

Very truly yours,  
The Battery Shop.



an Eaton oscillator to be used as a source of the so-called variation frequency employed with super-regenerative circuits. One of the several very easy ways to show that the Eaton oscillator is not incorporated in the circuit is to endeavor to operate a filter circuit satisfactorily before audio amplification. Were an Eaton oscillator incorporated in the circuit and used as a source for the variation frequency, the variation frequency would show upon examination a more or less sinusoidal curve, that is, the frequency would rise from zero, following more or less closely the form of a sine curve to



### MISSING WHAT YOU GET


YOUR set is probably bringing in DX stations you never hear because your rheostat cannot control your filament action. The Fil-Ko-Stat gives infinite adjustment and enables you to magnify the weak stations and bring them in strong and clear.

Full resistance 30 Ohms, adjusted to ALL TUBES. \$2 At All Dealers in High Grade RADIO SUPPLIES

## FIL-KO-STAT

Made and Guaranteed by  
Dx Instrument Co., Harrisburg, Pa.  
Sole International Distributors.  
Radio Stores Corp., 218 W. 34, N. Y. City

## Improved Ground Clamp




Equipped with Fahnestock Patent Wire Connectors

Easily Attached

No Soldering. For Radio Use Only

At Your Dealers

Fahnestock Electric Co.  
Long Island City, N. Y.



## WE REPAIR THE FOLLOWING RADIO TUBES

Dealers and Agents write for Special Discount Mail Orders Solicited and Promptly Attended to

WD-11 WD-12	OUR SPECIALTIES	5 WATT TRANSMITTERS	
UV-199	.....\$3.50	C-299	.....\$3.50
UV-200	.....2.75	C-300	.....2.75
UV-201	.....3.00	C-301	.....3.00
UV-201A	.....3.50	C-301A	.....3.50
WD-11	.....3.50	WD-12	.....3.50
DV-6	.....3.00	DV-6A	.....3.50
UV-202	.....4.00	C-302	.....4.00
UV-299	.....3.50		

H. & H. RADIO COMPANY  
P. O. Box 22-A  
Clinton Hill Station NEWARK, N. J.

### 80% of demonstrations result in sales for MU-RAD dealers

When a complete check on the radio sales of one Chicago store reveals that Mu-Rads are sold in eight out of ten competitive demonstrations, there must be a reason.

There is! Mu-Rad is easy to operate, uses an inside 2-ft. loop aerial, and is highly selective. Mu-Rad is guaranteed to receive at least 1000 miles.

Dealers: Write for Mu-Rad Proposition

Inquiries are solicited from responsible dealers only.

In order to help us weed out curiosity seekers, please use your business stationery in requesting this information.

We also carry a complete stock of WESTERN ELECTRIC CO. GENERAL RADIO CO.

parts. Write for details and discounts Chicago Radio Apparatus Co.

Jobbers of Good Radio Merchandise  
General Offices: 407 South Dearborn Street  
CHICAGO

### TWO SUPERSENSITIVE CIRCUITS

(Both Copyrighted)  
My Highly Improved Reinartz brings in all important stations on both coasts and Mexican border, loud, clear and without distortion. We dance to music from Atlanta received on one loud Baldwin unit. Build one of these wonderful sets from my blueprints and specifications, price 50c, or with a perfect and complete double wound spiderweb coil, \$3.00 by mail. No other windings used. Photo of my set on a glass panel with every order.

This copyrighted circuit is the most successful of any Reinartz modification yet produced, and is imitated the most. Thousands are in use.  
My W. D. II Circuit is especially designed for use with the "Pickle" tube and brings out the full value of that little tube as no other circuit can. Stations 1000 miles away come in clearly on one tube. This set is small, complete, portable. For the man who wishes the highest efficiency, this is the set to build. Price of blueprint and specifications, 50c, or with complete and perfect windings, \$3.00. Photo of set with every order.

Sets built from these plans will receive all broadcasting stations operating under the new laws. Their wave length range is from 170 to 800 meters.

### AUXILIARY TUNER

This new instrument connected to your present receiving set with one wire enables you to easily bring in both the long and short wave stations which you cannot get with your present equipment. It also enables you to eliminate that local interference so you may listen to distant stations.  
Copyrighted diagram and complete instructions for building and operating this instrument, 50c, or with all parts, including Condenser, Coils, Switches, and Panel, \$8.50. Complete instrument, \$15. All goods prepaid.

These instruments are easy to build, easy to operate. Everything clearly shown.  
S. A. TWITCHELL  
1925 Western Avenue, Minneapolis, Minn.

## Radio Bargains for THIS WEEK

### MILOPLEX SPECIALS

Guaranteed Genuine  
Split Variometer .....\$6.95  
1600 ohm Potentiometer..... 1.95

### REFLEX SPECIALS

Hilco Variocouplers.....\$6.25  
Erla Reflex Transformers..... 4.55  
Erla Audio Transformers..... 4.55  
Rathbon Variable Condensers:  
11 plate..... 2.69  
23 plate..... 3.15  
Reflex Crystal ..... .89  
Federal Phones, special at..... 5.25  
Hegehoz Transformers ..... 3.15  
"B" Metal Crystal..... .39  
Pigtail Connectors, per dozen..... .30

Clip this List - Check Items You Want Enclose With Money Order  
Your Order Will Be Filled By Return Mail Postage Free - Satisfaction or Money Back

FANS LIST OF BARGAINS FREE

RADIO BARGAINS  
17 N. LA SALLE ST-CHICAGO

## TRIGGER OF NEW YORK RADIO

EVERYTHING SOLD ON MONEY-BACK GUARANTEE. WE HANDLE NO BOOTLEG MERCHANDISE.

COCKADAY COMPLETE PARTS GUARANTEED \$12.50 ASSEMBLED \$17.50 Add \$2.50 to each for Cabinet

ERLA REFLEX 3 TUBE BEST OF PARTS \$45.00 ASSEMBLED \$67.50

COCKADAY 3 TUBE Unassembled \$32.50 INCLUDE CABINET ASSEMBLED \$42.50 DISTANCE VOLUME SELECTIVITY

LOUD SPEAKER  
Bristol .....20.00  
Atlas .....18.00  
Magnavox ..30.00  
Mercury .... 6.00  
Music Master .....26.00

Indoor Aerial	.....\$1.75	Baldwin's Original	.....\$8.50
Hydrometer	..... .50	Jefferson Transformer	..... 2.75
Voltmeter	..... 1.65	Amertran Transformer	..... 5.50
Freshman Variable Grid and Leak	..... .70	Acme Transformer	..... 3.75
Remler Mounted Variometer	..... 4.00	Wave Trap	..... 2.00
Freed-Eisemann 180° Coupler	..... 2.00	D. C. Charger	..... 5.75

We carry a complete line—from screws to sets.

You can purchase with an absolute guarantee. We carry no factory seconds or salvage merchandise. Goods shipped immediately. Please be sure to include postage on orders under \$10.00.

## TRIGGER OF NEW YORK

160 EAST 59TH STREET, NEAR THIRD AVENUE, NEW YORK CITY

# Questions and Answers

## DV-6A Tube

(4865) HCG, Kerlin, Ark.  
 In the August 11 issue you give a diagram of a simplex circuit using a variable condenser as the only tuner. I have a DV-6A DeForest tube. Will it give satisfaction and if so what voltage on filament and plate? Could a variometer be used in place of the honeycomb coil? What would be the range with this set with 180 foot aerial? Would this set be very selective using only a condenser for tuning?

What length of aerial would be efficient for a single tube reflex, how high from the ground? Is the lead-in from the single wire considered in the length given for an aerial?

In soldering connections should I solder the connections to the fixed Micadon condensers? Will this harm the condenser?

Should I use the .0005 fixed condenser with my DV-6A DeForest tube, and what grid leak? Will the Bradleystat control the current for a DV-16A.

What range of wave length would I get, using a 23-plate vernier condenser in the simplex as pictured in August 11 issue honeycomb coil to be used? What length of aerial will I need to send code 10 miles? Would I need a license to send 10 miles? This distance would not put me out of the state? What difference would a variometer make to be used to send code?

A.—A DV-6A DeForest tube with 45 volts plate potential can be effectively employed in the described circuit.

A variometer can be substituted for a honeycomb coil. The receiving range will approximate 1,200 miles.

A single circuit hook-up is not distinctive for selectivity although where there are no local broadcasting stations it should prove sufficiently so for satisfactory reception.

A 150-foot antenna with lead-in is efficient. Construct it at as great a height as possible.

If carefully done it is desirable to solder condenser connections. The fixed condenser should be .0005 mfd. with a 2-megohm leak.

A Bradleystat will be effective for tube control.

Range of wave lengths from 200 to 550 meters.


For transmission of code at a 10-mile range antenna can be 100 feet in length. A license is required for such transmission.

A variometer in the circuit under discussion would afford more selective tuning.

### Wave Trap

(5276) JFE, Humphrey, Neb.

Kindly advise, by diagram if possible, the making and hook-up of a wave trap that can be connected to a two-stage Armstrong regenerative set.



A.—We are herewith presenting sketch of a simple wave trap arrangement to be used in antenna circuit. Constructional details and method of operation appeared on page 14 of December 9, 1922, issue of Radio Digest.

Honeycomb coils of proper values can be used interchangeably for elimination of specific wave lengths.

### Amateur Transmission

(5106) DMcC, Philadelphia, Pa.

Would a single wire antenna of copper ribbon be suitable for transmission or would you advise an antenna of greater capacity than a single wire affords?

Would it be practical to supply the plate current for a three-tube transmitter, (1 oscillator, 1 modulator, and 1 amplifier), from a B battery of 135 volts or greater?

as I am unable to install a D. C. generator?

Would the radiation from this be as great as if a D. C. generator was used?

Would it be possible with any system of filters or rectifiers to supply the plate current from a spark coil (operated by a storage battery) suitable for phone transmission; could you publish hook-up for same? Can a Ford coil be used efficiently as a modulation transformer?

A.—Answering your inquiry in the matter of transmitting equipment we are advising that a two or three wire antenna is preferred to a single wire construction because of greater capacity.

It would be possible to supply plate current for described transmitter from a 135 volt B battery for a short time. However, transmitting tubes require quite a lot of current, so your B batteries will not last very long unless they are of the storage type. Radiation will be equal to that of D. C. generator as long as batteries last.

It would not be possible to supply plate current as suggested. However, rectified A. C., properly filtered, can be used for phone transmission.

The ratio of a Ford spark coil is too high to permit its use as a modulation transformer.

### Apparatus Construction

(4915) NWH, Toledo, Ohio.

I would like to have you give a sketch and amount of wire used in the Acme and D.X. Radio frequency transformers. Have been a reader of your newspaper ever since it has been on the market, and find it very good in every respect to a man who is in doubt about anything in Radio.

A.—In the matter of your request for constructional details of Acme and DX Radio frequency transformers we are advising that being a manufactured appa-

ratus, it does not come within the scope of our service.

In view of the extensive and heavy advertising campaign entailed in placing such apparatus on the market Radio Digest does not consider it ethical to extend its service to encroach upon the domain of manufacturers of commercial receiving sets and equipment.

Yet we hope for the privilege of serving you helpfully in any matter within the spirit of our gratuitous service.

### Radio Direction Finding

(5258) JAB, Detroit, Mich.

Being a Radiophan and a reader of the Radio Digest I am taking the liberty of enclosing a clipping which appeared in one of the Detroit papers today regarding the recent naval disaster along the California coast. I have questioned several fans for the solution of the Radio problem referred to in the clipping, but without success.

I will appreciate it very much if you will enlighten me as to why a Radio station on shore could determine the location of a vessel at sea when the commanders of that vessel could not determine their own location even with their advanced knowledge of navigation.

A.—Answering your inquiry with reference to the clipping, we are stating in explanation that practically all of the Pacific and Atlantic seaboard are lined with what are known as Radio Compass stations, which send out test signals. These signals are intercepted by loop antenna systems, or direction finders as they are termed, on board boats. Location of a boat's position is merely a matter of using the directional properties of the loop to determine its location with respect to the shore transmitting station.

**DEALERS**  
 PROMPT SHIPMENTS  
 LIBERAL DISCOUNTS

**ERLA REFLEX  
 CRYSTAL**



**ALL PARTS IN STOCK**

Note!!  
 We are the largest exclusive Radio Jobbers in the Middle West

**HUDSON-ROSS**  
 123 W. Madison St. Chicago

## WD-11 and WD-12 Tubes Repaired

- WD-11 or WD-12.....\$3.50
- C-300 or UV-200..... 2.75
- C-301 or UV-201..... 3.00
- C-302 or UV-202..... 3.50
- C-301A or UV-201A..... 3.50
- Moorehead Detectors..... 2.75
- Moorehead Amplifiers..... 3.00
- DV-6 or DV-6A..... 3.00
- Also the new UV-199..... 3.50
- NEW DX 1 1/2 VOLT TUBES. 4.00

All tubes guaranteed to work like new  
 Mail Orders Given Prompt Attention  
 "24 Hour Service"

### RADIO TUBE CORP.

55 HALSEY STREET NEWARK, N. J.


Tubes Sent Parcel Post, C. O. D.

## Latest Radio Sensation

Has Become Indispensable

**3 IN 1** PRIMARY SECONDARY AND CONDENSER

No Taps No Trouble



Only \$4 Only \$4

### VERNI-TUNER

(Trade Mark)

Saves Space - Labor - Money  
 HANDSOME APPEARANCE  
 FINEST WORKMANSHIP  
 MORE SELECTIVE—  
 THAN ANY OTHER COUPLER

For all regenerative circuits, for Home Combined Tuned Radio Frequency and Reflex, also Reinartz, Flewelling, Cockaday, etc.

FREE BOOKLET '14 Latest Circuits with each Verni-Tuner  
 At your dealer or postpaid on receipt of purchase price. Write for leaflet.

**HORNE ELECTRIC & MFG. CO.**  
 Mercer & Colgate Sts. Jersey City, N. J.




## KEYSTONE RADIO LIGHTNING ARRESTERS

\$2.00 \$2.00

Should be on every aerial the year 'round. Provides highly efficient lightning and static protection for the home. Fully approved by Fire Underwriters. Can be installed outdoors. Has no vacuum to lose. Install one in your aerial lead now—be safe. Install one in your aerial lead now—be safe. This pioneer radio arrester is backed by 31 years' experience in lightning arrester design. For sale by Dealers everywhere, or sent postpaid for \$2.00. Write for circular.

**Electric Service Supplies Co.**  
 178 Cambria Sts.  
 Philadelphia  
 Monadnock Bldg., Chicago  
 50 Church St., New York

## COLUMBIA ALL-CIRCUIT VARIOMETER



variometer can be used for MILOPLEX circuits.

Price \$5.50

Ask to see the nationally known Columbia line of licensed bakelite apparatus. Known satisfaction. A few more Columbia items:

- Moulded Bakelite Variocoupler.....\$6.00
- Gear Three Coil Mountings..... 5.00
- Gear Two Coil Mountings..... 3.50
- Inside Coil Mounting—"Vernier"..... 6.00
- All-Meter Variocoupler—150 to 2000 meters..... 7.00
- Mounted Coils, Coil Plugs, etc.

Write for our free literature

**COLUMBIA RADIO CORP.**  
 157 NORTH UNION STREET, CHICAGO



**ALWAYS** on the red hot spot and ready for use—without adjusting.

Approved by Jack Binns  
 Radio Editor N. Y. Tribune

Radio News says, "We found this detector very sensitive and also found that it holds its adjustments."


For Sale at All Reliable Dealers or Direct **\$2.00**

Ask Your Dealer for Booklet with New Reflex Hookups

**RANDEL WIRELESS CO.**  
 8 Central Avenue, Newark, N. J.

## SAVE MONEY Radeco Safety Fuses

"The biggest little thing in radio"



Price 50 cents each postpaid

**R**ADIO experts recognize that some means of protecting the delicate filament of vacuum tubes is necessary. Thousands of tubes are needlessly burnt out each year. Radeco Safety Fuses have been developed to prevent this waste. They are endorsed by the leading radio publications. You can now absolutely protect the tubes of your set by slipping a Radeco Fuse on one of the filament terminals of each of your tubes.

Guaranteed not to interfere with the efficiency of your set. Save money by ordering today one fuse for each of your tubes. Mention type of tube.

Dept. 6  
**RADIO EQUIPMENT COMPANY**  
 20 Stuart Street, Boston, Mass.

New England's Oldest Exclusive Radio House  
 Distributors of many other successful radio specialties  
**DEALERS:** We are going to appoint live distributors  
 Write for our proposition and full details

### READ WHAT ONE MAN SAYS

939 Dunlop Avenue  
 Forest Park, Illinois  
 Radio Equipment Company,  
 Gentlemen: About last January I purchased some of your Radeco Safety Fuses. I have never had cause to regret this purchase, because I believe it has saved me many dollars. So I am writing to thank you and will recommend them to my Radio friends. The fuses have not interfered in any way with the operation of my set, and you are entirely at liberty to use this letter as an "ad" for your product, if you should so desire. Wishing you success in your present enterprise, I am,  
 Yours truly,  
 Mr. Harvey F. Reese.

9/26/23

# Radiophone Broadcasting Stations

## Corrected Every Week—Part I

**AA3**, Denver, Colo. 440 meters. 1,500 mi. Fitzsimmons Gen. Hospital. (Educational Dept. U. S. Army). Fri, 8-9 pm, music, entertainment. Mountain.

**AQ6**, Canada, O. 425 meters. 500 mi. Hdqrs. 135th Field Artillery O. N. G. Wed, Fri, music. Sun, church services. Eastern.

**AS6**, San Antonio, Tex. 360 meters. 200 mi. U. S. Army. Ft. Sam Houston. Mon, Thurs, irregular.

**AV7**, St. Paul, Minn. 400 meters. 500 mi. 6th Inf. Minn. Nat'l Guard, St. Paul Armory. Irregular schedule. Central.

**AW5**, Dayton, O. McCook Field, U. S. Army. Experimental work only.

**BE1**, Tacoma, Wash. 400 meters. 100 mi. Camp Lewis, U. S. Army, Third Signal Co. Discontinued indefinitely.

**CFAC**, Calgary, Alta. Can. 430 meters. 1,000 mi. Calgary Herald. Club, "Night Hawks." Daily ex Sun, 12:30 pm, 3:30-4:30, 7:45-8:45, Thurs, 10:30, music, entertainment, news, market, weather. Mountain.

**CFCA**, Toronto, Ont. Can. 425 meters. 1,000 mi. Toronto Star. Daily ex Sun, 12 pm, weather, news, stock, 5:30-6 pm, news. Daily ex Sun, Wed, 8-9 pm, music. Sun, 7 pm, church services. Eastern.

**CFCF**, Montreal, P. Q. Can. 440 meters. 1,000 mi. Marconi Co. Daily ex Sun, 12:30 pm, music, entertainment, reports. Eastern.

**CFCH**, Ingoquois Falls, Ont. Can. 400 meters. 500 mi. Abitibi Power & Paper Co., Ltd. Daily, 9 pm, reports, music, entertainment. Experimental station. Eastern.

**CFCL**, Quebec, Que. Can. 410 meters. 50 mi. La Cie de L'Evenement.

**CFCK**, Edmonton, Alta. Can. 410 meters. 500 mi. Radio Supply Co. Daily ex Sun, 8:45 pm, music. Sun, 3:30-4:30 pm, Concert. Mountain.

**CFCL**, Victoria, B. C. Can. 400 meters. 500 mi. Centennial Methodist Church. Slogan, "Where Religion Cheers." Tues, Fri, 8:30-10:30 pm, concerts, lectures. Sun, 11 am, 7:30 pm, church services. Pacific.

**CFGN**, Calgary, Alta. Can. 275, 440 meters. 1,500 mi. W. W. Grant Radio Ltd. Slogan, "Voice of the Prairies." Mon, 11 pm, music. Wed, 10-11 am, dance music. Sat, 10-12 pm, dance music. Test program, Sat, after midnight. Mountain.

**CFGO**, Bellevue, P. Q. 275 meters. 300 mi. Semmelhaack-Dickson, Ltd. Daily ex Sat, Sun, 9:45-10:30 pm, news, markets, reports, sports, time, music. Sat, 9:30-11 pm, music. Sun, 9:15-10:45 pm, sacred music. Eastern.

**CFGW**, London, Ont. Can. 420 meters. 50 mi. The Radio Shop. Tues, Thurs, Sat, 8:30-9:30 pm, music, entertainment. Eastern.

**CFQC**, Sask., Sask. Can. 400 meters. 500 mi. The Electric Shop, Ltd. Slogan, "The Hub City of the West Where No. 1 Northern Hard Wheat Grows." Daily ex Sun, 1-1:30 pm, markets, reports, music. Mon, Tues, Thurs, Fri, 7:30-9 pm, news, reports, markets, entertainment. Sun, 9-9:45 pm, church services. Mountain.

**CFUC**, Montreal, P. Q. Can. 400 meters. 1,000 mi. Univ. of Montreal.

**CHBC**, Calgary, Alta. Can. 410 meters. 1,000 mi. W. W. Grant Radio Ltd. (Morning Alberta.) Daily ex Sat, 8:45-9:45 pm, news, stock quotations, music. Mountain.

**CHCD**, Quebec, Que. Can. 415 meters. 50 mi. Canadian Wireless and Electric Co. Mon, 7:30-9 pm; Wed, 8-9; Sat, 8-10, music. Eastern.

**CHCE**, Victoria, B. C. Can. 310 and 400 meters. 500 mi. Western Canada Radio Supply, Ltd. Daily ex Sun, 4:30-5:30 pm, 7:30-9:30. Sun, 9-10 pm, music, entertainment. Pacific.

**CHYC**, Montreal, Que. Can. 410 meters. 1,500 mi. Northern Elec. Co. No regular schedule.

**CJCA**, Edmonton, Alta. Can. 450 meters. 1,000 mi. Edmonton Journal, Ltd. Slogan, "The Sunniest Spot in Sunny Alberta." Club, "Igloo Hut." Daily ex Sun, 12:30 pm, weather, markets, 7:30-8 pm, Children's half hour. 8:30-9:30 pm, concert, reports. Mountain.

**CJCD**, Toronto, Canada. 410 meters. 200 mi. T. Eaton Co. Daily ex Sat, Sun, 4-4:30 pm, music. Eastern.

**CJCE**, Vancouver, B. C. Can. 420 meters. 150 mi. Sprout-Shaw Radio Co. Daily ex Sun, 12:30-1:30 pm, 3:30-5, 8-10, music, news. Pacific.

**CJCI**, St. John, N. B. Can. 400 meters. 500 mi. Maritime Radio Corp., Ltd. Mon, Wed, Fri, 7:30-9 pm, music. Sat, 9-11 pm, music. Eastern.

**CJCK**, Olds, Alta. Can. 400 meters. 500 mi. Percival W. Shackleton. Slogan, "The Best Town in the West." Tues, Thurs, 9:45-11 pm, music. Sat, 8:45-10 pm, music. Mountain.

**CJGC**, London, Ont. Can. 430 meters. 500 mi. London Free Press. Daily ex Sun, 9:30-10 am, 12-1 pm, 3:30-6, news, market and weather, 8-9, music, entertainment.

**CKAC**, Montreal, Que. Can. 430 meters. 1,000 mi. La Presse. Daily ex Sat, Sun, 4 pm, music; 4:30, weather, markets, stocks. Tues, Thurs, Sat, 7 pm, children's hour; 7:30, concert. Sun, 4:30 pm, sacred concert. Eastern.

**CKCD**, Vancouver, B. C. Can. 410 meters. 1,000 mi. Vancouver Daily Province. Daily ex Sun, 8:30-9:30 pm, music, news, entertainment. Pacific.

**CKCE**, Toronto, Ont. Can. 450 meters. 1,000 mi. Can. Ind. Telephone Co. Daily ex Sun, 11:55 am-12 pm, Arlington Time Signals. Eastern.

**CKKQ**, Regina, Sask. Can. 420 meters. 1,500 mi. Leader Pub. Co. "The Queen City of the West." Daily ex Sat, Sun, 9:54, time; 10:10-10:30 am, 1:15-2 pm, 7:30-8:15. Tues, 7:30-9 pm, music, entertainment, news, market, weather. Sat, silent night. Sun, 9, service. Mountain.

**CKOC**, Hamilton, Ont. Can. 410 meters. 100 mi. Wentworth Radio Supply Co., Ltd. Slogan, "In the Garden of Canada." Mon, Wed, Fri, 8-9 pm, music, entertainment. Sun, 7-8 pm, church services. Eastern.

**CKY**, Winnipeg, Man. Can. 450 meters. 1,000 mi. Manitoba Tel. Co. Daily ex Sun, 12:30-1:45 pm, Tues, Thurs, Fri, 8:15-10, music, entertainment, weather. Sun, 7 pm, church services; 9, sacred concert. Central.

**CVB**, Mexico City, Mex. 370 meters. 1,000 mi. El Espectador. Tues, Sat, 7:30-9 pm. Thurs, 8-10 pm, concert. Mexican time.

**KDKA**, E. Pittsburgh, Pa. 326 meters. 2,000 mi. Westinghouse Elec. & Mfg. Co. Daily ex Sun, 10:15 am, 12:30-1 pm, music; 6-10 pm, news, features, markets, concert; 9:55-10, time. Sun, 10:45 am, church service; 2:30 pm, Bible story; 3:45 pm, concert; 4:45 pm, 7:30, church service. Eastern.

**KDPM**, Cleveland, O. 270 meters. Westinghouse Elec. & Mfg. Co.

**KDPT**, San Diego, Calif. 244 meters. 500 mi. Southern Elec. Co. Daily ex Sun, 7-7:30 pm, news, weather, concerts, lecture. Tues, Sat, 8-10 pm. Sun, 11:30-12:30 pm, sermon. Pacific.

**KDYL**, Salt Lake City, Utah. 360 meters. 1,800 mi. Newhouse Hotel. Daily ex Sun, 8:30-8 pm, news, music, entertainment. Mountain.

**KDYM**, San Diego, Calif. 280 meters. Savoy Theater.

**KDYN**, Portland, Ore. 360 meters. 200 mi. Oregon Institute of Technology. Slogan, "The Radio School." Educational programs.

**KDYS**, Great Falls, Mont. 360 meters. 1,000 mi. Great Falls Tribune. Tues, Fri, 8-9 pm, concert. Mountain.

**KDYW**, Phoenix, Ariz. 360 meters. 100 mi. Smith Hughes & Co. Temporarily discontinued.

**KDZX**, Honolulu, T. H., Hawaii. 360 meters. 500 mi. Honolulu Star-Bulletin Co., Ltd. Daily ex Sun, 12:15-1:15 pm, reports; 6:30-7:30 pm, entertainment, music, talks. Sun, 11 am-12:15 pm, church services. 12th.

**KDZB**, Bakersfield, Calif. 240 meters. 500 mi. Frank Siefert. Daily ex Sun, 8-9 pm, reports, music. Sun, sacred program, irregular. Pacific.

**KDZE**, Seattle, Wash. 455 meters. 1,000 mi. The Rhodes Co. Mon, Wed, Fri, 8:30-10:30 pm, music; Fri, 12:30-1:30 pm, meeting; Sat, 2-3 pm, music. Pacific.

**KDZF**, Los Angeles, Calif. 278 meters. Automobile Club of Southern California. Not operating yet.

**KDZI**, Wenatchee, Wash. 360 meters. 700 mi. Elec. Supply Co. Temporarily discontinued.

**KDZK**, Reno, Nev. 360 meters. 50 mi. Nevada Machine Elec. Co. (Nevada State Journal). Sun, 7-8 pm. Pacific.

**KDZQ**, Denver, Colo. 360 meters. Nicholas Academy of Dancing.

**KDZR**, Bellingham, Wash. 261 meters. 200 mi. The Bellingham Pub. Co. Mon, Wed, Fri, 7-8:30 pm, music. Tues, Sat, Sun, 7-8 pm, Pacific.

**KDZT**, Seattle, Wash. 360 meters. 50 mi. Seattle Radio Assn.

**KFAD**, Phoenix, Ariz. 360 meters. 200 mi. McArthur Brothers. Daily ex Sun, 7:30-8:30 pm, news, weather, stock reports, music. Mountain.

**KFAE**, Pullman, Wash. 360 meters. 1,500 mi. State College of Washington. Mon, Wed, Fri, 7:30-9 pm, lectures, music, readings. Pacific.

**KFAF**, Denver, Colo. 360 meters. 1,500 mi. Western Radio Corp. Slogan, "Voice from the Rockies—Out Where the West Is." Mon, Tues, Fri, Sat, 8-9 pm; Thurs, 7:30-8, music, reports, news. Wed, silent. Mountain.

**KFAJ**, Boulder, Colo. 360 meters. 800 mi. Univ. of Colo. Tues, Thurs, Sat, 9 pm, time, music, addresses by faculty. Sat, 2:30-5 pm, football. Mountain.

**KFAN**, Moscow, Ida. 360 meters. 200 mi. The Electric Shop. Tues, Thurs, Sat, 7:30-8:30 pm, music, reports. Sun, church services. Pacific.

**KFAP**, Butte, Mont. 360 meters. Standard Pub. Co.

**KFAR**, Hollywood, Calif. 280 meters. Studio Lighting Service Co.

**KFAU**, Boise, Ida. 270 meters. 200 mi. Boise H. S. Daily ex Sun, 8:30-9 pm, markets, weather, news. Wed, Fri, 8-9 pm, concert. Mountain.

**KFAV**, Venice, Calif. 258 meters. 50 mi. Abbot Kinney Co. Mon, Tues, Wed, Fri, 8:30-9:30 pm, music. Pacific.

**KFAW**, Santa Ana, Calif. 280 meters. 100 mi. Radio Den. Daily ex Sun, 4:30-5 pm, news, reports, music. Mon, Thurs, 6:30-8:30 pm, concert. Pacific.

**KFAY**, Medford, Ore. 360 meters. 500 mi. Virgin Radio Service. Temporarily discontinued.

**KFBB**, Havre, Mont. 360 meters. 150 mi. F. A. Buttery Co. Daily ex Sun, 12:30 pm, a. g. programs, weather, news. Tues, Fri, 8-9:30 pm, music. Mountain.

**KFBG**, San Diego, Calif. 278 meters. 100 mi. W. K. Azbill. Thurs, Sun, 8-9 pm, Bible lesson, sermon. Pacific.

**KFDS**, San Francisco, Calif. 360 meters. John D. McKee.

**KFDU**, Lincoln, Neb. 240 meters. Neb. Radio Elec. Co.

**KFDV**, Fayetteville, Ark. 360 meters. 300 mi. Gilbrech & Stinson. Slogan, "Southern Gateway to the Ozarks." No regular schedule. Central.

**KFDX**, Shreveport, La. 360 meters. First Baptist Church.

**KFDY**, Brookings, S. D. 360 meters. S. D. State College of Agr. & Mech. Arts. Mon, Sat, 8:30 pm, music. Tues, Thurs, 11 am, music, lectures, news. Central.

**KFDZ**, Minneapolis, Minn. 360 meters. Harry O. Iverson.

**KFEA**, Portland, Ore. 360 meters. 75 mi. Meier & Frank Co. Inc. Daily ex Sun, 12 m, weather, reports; 4-5 pm, music; 6:30 pm, weather, crop, markets, reports. Thurs, 9-10 pm, concert. Sat, 11 am 12 m, children's hour. Pacific.

**KFEL**, Denver, Colo. 360 meters. Winner Radio Corp. Daily ex Sun, 9 am, 10, 11, 11:45, stock reports; 3-4 pm, music. Mon, Fri, 9-10 pm, 12-1 am, concerts. Sun, 9-10 am, church services. Mountain.

**KFEQ**, Oak, Neb. 360 meters. J. L. Scroggin. No regular schedule.

**KFER**, Fort Dodge, Ia. 231 meters. Auto Electric Service Co.

**KFEV**, Douglas, Wyo. 263 meters. 500 mi. Felix Thompson Radio Elec. Shop. Slogan, "You Tell 'Em." Weather reports and special warnings. Mountain.

**KFEW**, Minneapolis, Minn. 261 meters. 600 mi. Augsburg Seminary. Tues evening, music. Central.

**KFEY**, Kellogg, Ida. 360 meters. 50 mi. Bunker Hill & Sullivan Mining Co. Slogan, "Voice of the Coeur d'Aleneus." Pacific.

**KFEZ**, St. Louis, Mo. 360 meters. 800 mi. American Society of Mech. Engrs. Thurs, 8:30-9:30 pm, engineering program. Central.

**KFFB**, Boise, Ida. 273 meters. 70 mi. Jenkins Furn. Co. (Owyhee Hotel). Daily, 8-9 pm, concert. Mountain.

**KFFE**, Pendleton, Ore. 360 meters. 100 mi. Eastern Ore. Radio Co. Daily ex Sun, 8:30-9:30 pm, music. Pacific.

**KFFO**, Hillsboro, Ore. 229 meters. Dr. E. H. Smith. Daily, 6-7 pm, music, sports, news. Fri, 9-10 pm, Chamber of Commerce Community Program. Pacific.

**KFI**, Los Angeles, Calif. 469 meters. 2,000 mi. Earle C. Anthony, Inc. Daily ex Sun, 5-6 pm, 6:45-7:30 pm, 8-11 pm, Wed, Fri, Sat, 8-12 pm. Sun, 10:30-11:30 am, 4-5 pm, 6:45-7:30, 8-11. Pacific.

**KFIB**, St. Louis, Mo. 244 meters. Franklin W. Jenkins.

**KFID**, Iola, Kans. 246 meters. Ross Arbuclies Garage. Daily, 5:15-5:45 pm, Tues, 9-10 pm. Central.

**KFIF**, Portland, Ore. 360 meters. Benson Tech. Student Body.

**KFIK**, Gladbrook, Iowa. 234 meters. Gladbrook Elec. Co.

**KFIL**, Louisburg, Kans. 234 meters. 150 mi. Windisch Elec. Farm Equip. Co. Wed, Sat, 8-10:30 pm. Sun, 11-12 m, church services. Central.

**KFIO**, Spokane, Wash. 252 meters. North Central High School.

**KFIQ**, Yakima, Wash. 224 meters. 200 mi. Yakima Valley Broadcasting Assn. Slogan, "The Station That Will Make 224 Famous." Mon, Wed, Fri, 7:30-8:30 pm, concert. Sat, 7:30-8 pm, S. S. lesson. Sun, 4-5 pm, music. Pacific.

**KFIU**, Juneau, Alaska. 226 meters. Alaska Elec. Light & Power Co.

**KFIV**, Pittsburg, Kans. 240 meters. V. H. Broyles.

**KFIX**, Independence, Mo. 240 meters. Reorganized Church of Jesus Christ of Latter Day Saints.

**KFIY**, Seattle, Wash. 236 meters. Brott Laboratories.

**KFIZ**, Fond du Lac, Wis. 273 meters. Daily Commonwealth and Oscar H. Huelsman.

**KFJA**, Grand Island, Nebr. 244 meters. Central Power Co.

**KFJB**, Marshalltown, Iowa. 248 meters. 50 mi. Marshall Elec. Co. Tues, Fri, 8:30 pm. Central.

**KFJC**, Seattle, Wash. 270 meters. Post Intelligencer. Slogan, "Hello Folks." Daily ex Sun, 4-5 pm, music; 8:30-10, programs, dance music. Pacific.

**KFJD**, Grand Island, Nebr. 244 meters. 300 mi. Weld County Printing & Pub. Co.

**KFJE**, Oklahoma City, Okla. 252 meters. 120 mi. National Radio Mfg. Co. Slogan, "The Tired Hand." Daily ex Sun, 3 pm, concert; 6:30, baseball, football, police, announcements. Tues, 9 pm, concert. Sun, 3 pm, concert. Central.

**KFJH**, Selma, Calif. 273 meters. The Sugar Bowl.

**KFJI**, Astoria, Ore. 252 meters. 50 mi. E. E. Marsh and Liberty Theater. Daily ex Sun, 7-8 pm. Sun, 9:30-10:30 pm. Pacific.

**KFJJ**, Carrollton, Mo. 236 meters. Carrollton Radio Shop.

**KFJK**, Bristow, Okla. 233 meters. Delano Radio & Elec. Co. Daily ex Sun, 3-4 pm, music. Thurs, 8-9:30 pm, music. Sun, 7:30 pm, church services. Central.

**KFJL**, Ottumwa, Ia. 242 meters. 50 mi. Hardsoc Mfg. Co. Club, "Boiled Buds." Mon, Wed, Fri, 7:30-8:30 pm. Central.

**KFJM**, Grand Forks, N. D. 229 meters. 500 mi. University of North Dakota.

**KFJR**, Stevensville, Mont. 258 meters. 100 mi. Ashley C. Dixon & Son. Slogan, "The Bitter Root Valley Broadcasting Station." Fri, Sun, 8-9 pm, music; readings. Mountain.

**KFJU**, Kearney, Neb. 234 meters. 50 mi. Central Power Co.

**KFJV**, Dexter, Iowa. 224 meters. 50 mi. Thomas H. Warren. Daily ex Sun 9:15 am, 10:25, 1:45 pm, weather, markets. Tues, Fri, 8:30 entertainment. Central.

**KFJW**, Towanda, Kans. 266 meters. 50 mi. Le Gr Radio Co. Mon, Tues, Thurs, Sat, 7-8 pm; Fri, 7:30-8:30 pm. Central.

**KFJX**, Cedar Falls, Iowa. 229 meters. 250 mi. State Teachers College.

**KFJY**, Fort Dodge, Iowa. 246 meters. 250 mi. Where wall Radio Co. Slogan, "T. Dodge, 8:30, 9:30, Corn Is King." Daily ex Sun, 8:30 am. Sun, 11-10:30, 11:30, 12:20 pm, weather, baseball, football, 12-20 pm, church services. Spec. evening programs. Central.

**KFJZ**, Fort Worth, Texas. 229 meters. 100 mi. Texas National Guard, 112th Cavalry. Wed, 8:30-9:30 pm. Sunday, 8:30-10 pm. Program. Central.

**KFKA**, Greeley, Colo. 248 meters. Colorado State Teachers College.

**KFKB**, Milford, Kans. 286 meters. 100 mi. Brinkley-Jones-Hospital Assn. Slogan, "Watch Out, Here Comes Brinkley." Daily ex Sun, 10-12 midnight, music, lectures. Central.

**KFKH**, Lakeside, Colo. 226 meters. Denver Park Amusement Co. Closed for winter.

**KFKI**, Conway, Ark. 224 meters. 600 mi. Conway Radio Lab. Daily ex Sun, 12 m, weather, program. Tues, Fri, 8 pm, music. Sunday evening, church service. Central.

**KFKJ**, Butte, Mont. 283 meters. 250 mi. F. F. Gray.

**KFKK**, Hastings, Neb. 286 meters. 1,500 mi. Westinghouse Elec. & Mfg. Co.

**KFKL**, Colorado Springs, Colo. 234 meters. 50 mi. Nassour Bros. Radio Co.

**KFLA**, Butte, Mont. 283 meters. 25 mi. Abner R. Willson.

**KFLB**, Menominee, Mich. 248 meters. 100 mi. Signal Elec. Mfg. Co.

**KFLD**, Franklinton, La. 234 meters. 100 mi. Paul E. Greenlaw.

**KFLE**, Denver, Colo. 268 meters. National Educational Service. Daily, 7-7:30 pm, 11-12 midnight. Broadcasts for schools on request. Mountain.

**KFLH**, Salt Lake City, Utah. 261 meters. 500 mi. Erickson Radio Co., Inc.

**KFLP**, Cedar Rapids, Iowa. 240 Meters. 50 mi. Everett M. Foster.

**KFZ**, Spokane, Wash. 283 meters. 300 mi. Doerr-Mitchell Elec. Co. Slogan, "In the Heart of the Inland Empire." Tues, Fri, 7:30-9 pm, music. Sun, 6-7 pm, Pacific.

**KGB**, Tacoma, Wash. 252 meters. Tacoma Daily Ledger. "This is KGB in Tacoma, Washington, the Lumber Capital of America." Mon, Wed, Fri, 7-9 pm. Pacific.

**KGG**, Portland, Ore. 360 meters. 500 mi. Hallock & Watson Radio Service. Slogan, "The Rose City." Daily ex Sun, 5-6 pm, music, entertainment 7:30-8 pm, reports, Sat, 8-9 pm, answers to Radio questions. Sun, Wed, 9-10 pm, music. Pacific.

**KGN**, Portland, Ore. 360 meters. 100 mi. Northwest Radio Mfg. Co. Irregular schedule.

**KGU**, Honolulu, Hawaii. 360 meters. 150 mi. Marlon A. Mulrony, The Honolulu Advertiser. Daily, 7:30-9 pm. Tues, Thurs, Sat, special program. 15th meridien. (2 1/2 hours later than Pacific.)

**KGW**, Portland, Ore. 492 meters. 1,500 mi. Oregonian Pub. Co. Slogan, "Keep Growing Wiser." Daily ex Sun, 11:30 am, weather; 3:30-4 pm, woman's program; 7:30 pm, markets, weather. Daily ex Sat, Sun, 8-9 pm, music, entertainment. Mon, 9:30 pm, community program. Wed, Fri, 9 pm, lecture. Tues, Wed, Thurs, Sat, 10 pm, dance music. Fri, 10:30 pm, Hoot Owls. Sun, 6 pm, church services; 7 pm, concert. Pacific.

**KGV**, Lacey, Wash. 258 meters. 250 mi. St. Martins College. Slogan, "Out Where the Cedars Meet the Sea." Tues, Fri, Sun, 8:30-9:30 pm, news, concert, lecture, bedtime story. Pacific.

**KHJ**, Los Angeles, Calif. 395 meters. 2,000 mi. Los Angeles Times. Daily ex Sun, 12:30-1:15 pm, 2:30-3:30, 6:45-7:30, 8-12 midnight. Sun, 10-11 am, 8-10 pm. Pacific.

**KHQ**, Seattle, Wash. 360 meters. Louis Wasmer.

**KI**, Stockton, Calif. 360 meters. 100 mi. Gould. The Light Man. Daily ex Sun, 5-6 pm, concert. Mon, Wed, 9-10 pm, concert. Sun, 10-11 am, church services. Pacific.

**KJR**, Seattle, Wash. 283 meters. 1,500 mi. Northwest Radio Service Co. Daily ex Sun, 5:30-6:15 pm, reports. Mon, 7:30-8:30 pm, music. Fri, 8:30-9:30 pm, concerts, lecture, bedtime stories. Pacific.

**KIS**, Los Angeles, Calif. 360 meters. 500 mi. Bible Inst. of Los Angeles. Tues, 7-7:30 pm, Thurs, 8-9, sacred music, lectures, etc. Sun, 11:30-12:30 pm, 6-6:45, 8-9, church services. Pacific.

**KLN**, Del Monte, Calif. 261 meters. Monterey Elec. Shop. Discontinued temporarily.

**KLS**, Oakland, Calif. 360 meters. 1,500 mi. Warner Bros. Radio Supply Co. Daily, 11:30-1 pm. Fri, 8-9 pm. Sun, 12-1 pm. Pacific.

**KLX**, Oakland, Calif. 360 meters. 500 mi. Oakland Tribune. Daily ex Sun, 3:30-4:30 pm, music; 7-7:30, news, entertainment. Tues, 8-9 pm. Fri, 9-10 pm. Pacific.

## CHALLENGE!

ONE DOLLAR will be paid to the Radiophan submitting the most errors in any one station's listing. Letters must reach Radio Digest office not later than one week from date of issue corrected. Readers are not limited to correcting one station. Turn in corrections for as many stations as you can find — If you can find errors! Use separate sheet of paper for each station submitted and place name and address on each sheet. That's just how sure Radio Digest is that this Radiophone station directory is correct! To make the challenge fair for everyone, broadcasting stations and their employees are barred from this offer. Why? Because the broadcasters are the source of all the data given herein. They are (or should be) interested enough to answer the inquiry sent them every time data on their station appears. This inquiry contains a proof of their last listing and must either be corrected or oked as correct and returned to the Digest. Nevertheless, sometimes the stations

are careless and mistakes are made. But Radio Digest is so sure of the exactness of this directory that this challenge is made unconditionally. With reference to the directory: It appears in four parts, serially continuously; the first three parts are station data listings, arranged alphabetically; the fourth part is a state, city index of stations. The information contained in each station data listing is given in the following order: Call letters, city, state, wave length used, estimated sure range (by Radio Digest) in miles, owner's name, slogan used, if any, name of listener in "club," schedule of operating hours, and kind of time used. Four successive issues of Radio Digest will give one the most complete and accurate list of broadcasting stations obtainable. This service is original with this publication, and has been maintained from the start. Right of reproduction without permission of any or all of the data contained herein is denied.

**KFBE**, San Luis Obispo, Calif. 360 meters. 50 mi. R. H. Horn. Mon, Wed, Fri, 4:30-5:30 pm. Pacific.

**KFBG**, Tacoma, Wash. 261 meters. 200 mi. Church. Sun, 11 am-12:15 pm, 7:30-9. Pacific.

**KFBK**, Sacramento, Calif. 283 meters. 300 mi. Kimball-Upton Co. Slogan, "Heart of California." Daily ex Sun, 6-6:45 pm, concert, news, codes. Wed, 8-9:30 pm, concert. Pacific.

**KFBL**, Everett, Wash. 224 meters. 50 mi. Leese Bros. Daily ex Sun, 7:15-8:15 pm. Sun, 2-3 pm. Pacific.

**KFBS**, Trinidad, Colo. 360 meters. 75 mi. Chronicle News & Gas & Elec. Supply Co.

**KFBU**, Laramie, Wyo. 283 meters. Bishop N. S. Thomas.

**KFCB**, Phoenix, Ariz. 258 meters. Nielson Radio Supply Co. Daily, 7-7:30 pm, bedtime stories. Mountain.

**KFCD**, Salem, Ore. 360 meters. 100 mi. Salem Elec. Co. Tues, Wed, Fri, 7-8 pm. Pacific.

**KCFE**, Walla Walla, Wash. 360 meters. Frank A. Moore.

**KCFH**, Billings, Mont. 360 meters. 500 mi. Electric Service Station, Inc. Wed, Fri, Sun, 7:30-9 pm, music. Mountain.

**KCFK**, Colorado Springs, Colo. 258 meters. 50 mi. Colorado Springs Radio Co. Club, "Lion Tamers." Daily ex Sun, 12-1 pm, 5:15-6:15, music. Special concerts, 10-11 pm. Sun, 11-12:15 pm, 7:30-9:30, church. Mountain.

**KFCL**, Los Angeles, Calif. 360 meters. 1,500 mi. Los Angeles Union Stock Yards. Daily ex Sun, 10-10:30 am, 1:15-1:45 pm, 4-4:30, 8-8:20, live stock reports. Thurs, 9-9:20 pm. Pacific.

**KFCM**, Richmond, Calif. 244 meters. 500 mi. Richmond Radio Shop. Slogan, "Out Where the West Ends." Daily ex Sun, 1-2 pm, music. Tues, Fri, 8-9 pm, music. Pacific.

**KFCP**, Ogden, Utah. 360 meters. Ralph W. Flyers.

**KFCV**, Houston, Tex. 360 meters. 1000 mi. Fred Mahaffey, Jr. Daily ex Sun, 7:30-8 pm, markets, entertainment. Sun, 2-3 pm, entertainment. Central.

**KFCY**, Le Mars, Ia. 252 meters. 300 mi. Western Union College. Wed, Fri, 8-9 pm, music, educational. Central.

**KFZZ**, Omaha, Neb. 258 meters. Omaha Central H. S. Mon, Wed, Thurs, 3-4 pm; 7:30-8:30. Pacific.

**KFDA**, Baker, Ore. 360 meters. 25 mi. Adler's Music Store. Daily ex Sun, 5-6 pm, 7-8, music. Sun, 6-8 pm. Pacific.

**KFDD**, Boise, Idaho. 252 meters. St. Michael's Cathedral. Sun, 11:15-12:30 pm, 8-9:15 church services. Mountain.

**KFDH**, Tucson, Ariz. 360 meters. 200 mi. Univ. of Ariz. Temporarily discontinued. Mountain.

**KFDI**, Corvallis, Ore. 360 meters. Oregon Agri. College.

**KFDO**, Bozeman, Mont. 248 meters. 200 mi. H. Everett Cutting. Mon, Wed, Sat, 8-9 pm. Mountain.

**KFDP**, Des Moines, Iowa. 278 meters. 300 mi. Hawkeye Radio & Supply Co. Daily ex Sun, 3-3:45 pm, reports, music. Mon, 9-10 pm, music. Thurs, 9-10 pm, 11-12:30 am, music, entertainment. Central.

**KFDR**, York, Neb. 360 meters. 50 mi. Bullock's. Slogan, "The Little Station with the Big Kick." Club, "Radio Bats." Daily, 4-4:30 pm, children's hour; Wed, 8:30-10 pm, music; Sun, special afternoon program. Central.

**KFFP**, Moberly, Mo. 275 meters. 300 mi. First Baptist Church. Slogan, "The Gospel Messenger of the Air." Sun, 10:45 am, 8 pm, church services. Central.

**KFFQ**, Colorado Springs, Colo. 360 meters. 250 mi. The Markshel Motor Co. Daily, 8:15 am, weather; 4-5 pm, concert. Mon, Wed, Fri, 8-9:30 pm, special program. Mountain.

**KFFR**, Sparks, Nev. 226 meters. 50 mi. Jim Kirk. Fri, 7-8 pm, "Sagebrush Canaries." Pacific.

**KFFV**, Lamoni, Iowa. 360 meters. 600 mi. Grace-Land College. Wed, 9-9:20 am, music appreciation. Thurs, 8 pm, entertainment. Central.

**KFFX**, Omaha, Neb. 278 meters. 600 mi. The McGraw Co. Daily, 2:30-3:50 pm. Central.

**KFFY**, Alexandria, La. 360 meters. Pincus & Murphy, Inc.

**KFFZ**, Dallas, Tex. 360 meters. Al. G. Barnes Amusement Co.

**KFGA**, Baton Rouge, La. 254 meters. Louisiana State University. No regular schedule.

**KFGD**, Chickasha, Okla. 248 meters. 50 mi. Chickasha Radio & Elec. Co. Slogan, "Queen of the Washita." Daily ex Sun, 12-12:45 pm, 8-8:45, music. Central.

**KFGH**, Stanford Univ., Calif. 222 and 286 meters. 500 mi. Leland Stanford Junior University. No regular schedule.

**KFGI**, St. Louis, Mo. 286 meters. 800 mi. National Guards Missouri.

**KFGJ**, Arlington, Ore. 234 meters. Arlington Garage.

**KFGK**, Cheney, Kans. 229 meters. Cheney Radio Co.

**KFGQ**, Boone, Ia. 226 meters. Crary Hardware Co.

**KFGV**, Utica, Neb. 224 meters. 50 mi. Heidebreder Radio Supply Co. No regular schedule.

**KFGX**, Orange, Tex. 250 meters. First Presbyterian Church. Sun, 11 am, 7:30 pm, church services. Central.

**KFGZ**, Berrien Springs, Mich. 268 meters. Emanuel Missionary College.

**KFHA**, Gunnison, Colo. 252 meters. Colorado State Normal School. "Where the Sun Shines Every Day." Daily ex Sun, 8:30 am, weather, markets. Tues, 7:30 pm, entertainment. Mountain.

**KFHB**, Hooper, Ore. 280 meters. 50 mi. Rialto Theatre. Daily ex Mon, 6:20-6:35 pm, sports, news. Sun, 1-1:45 pm, music. Special programs 11 pm. Pacific.

**KFHD**, St. Joseph, Mo. 226 meters. 100 mi. Utz Electric Co. Daily ex Sun, 5:30-6 pm. Mon, Thurs, Sat, 8-9:30 pm, concert. Central.

**KFHF**, Shreveport, La. 266 meters. Central Christian Church.

**KFHH**, Neah Bay, Wash. 283 meters. Ambrose A. McCue.

**KFHI**, Wichita, Kans. 224 meters. Charles V. Dixon. Mon, Thurs, every third Sun, 8:15 pm. Central.

**KFHJ**, Santa Barbara, Calif. 360 meters. Fallon & Co. Wed, Thurs, Fri, Sat, 6-6:45 pm; Wed, Fri, 9-10 pm; Sun, 10 am, church services. Pacific.

**KFHQ**, Los Gatos, Calif. 242 meters. Curtis Bros. Hdwe. Store.

**KFHR**, Seattle, Wash. 270 meters. Star Elec. & Radio Co.

**KFHS**, Lihue, Hawaii. 275 meters. Clifford J. Dow.

**KFHU**, Mayhville, N. D. 261 meters. M. G. Sateren.




**KFHX**, Hutchinson, Kans. 229 meters. Robert Nelson.

(NOTE—The second part of the station data list will appear next week.)

# Radio

## Illustrated

A strange pair of Radiophans! At least they say the turtle enjoys ether music as much as its mistress, Miss Henriette Sloane of New York City. But, then, people say so much—and even call this fair lady a "DX hound," for she reports new long distance records almost daily to Radio editors. One of that crusty fraternity considered her a "pest" until he sent a photographer to investigate and found what you see below. We think it likely the editor revised his opinion as well as his vocabulary after this ocular evidence; don't you? K. & H. Photo



Two sets that aroused interest at the recent Radio show in New York. At the left is pretty Agnes Leonard with the largest receiver ever built, and above, a German set captured in the late war by our boys in the memorable battle of Château-Thierry  
 Left: Photo by United Above: Fotogram Photo