

JAEGER ELEKTRONIK

SEMICON 1997

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International
BUK 427-600A,B	Phi	MOS-N-FET-e	VFET, 600/30V, 45W, 80/275ns(2,8A) A: 4.3/17A, <1.1Ω(6.5A), B: 3.9/16A, <1.2Ω(6.5A)	16c	SOT-199		BUK 727-600, 2SK1463, 2SK1684, 2SK1859
BUK 428-500A,B	Phi	MOS-N-FET-e	VFET, 500/30V, 45W, 120/410ns(2.9A) A: 6.8/27A, <0.4Ω(8A), B: 6.1/24A, <0.5Ω(8A)	16c	SOT-199		2SK1206, 2SK1523, 2SK1696, 2SK1832
BUK 428-800A,B	Phi	MOS-N-FET-e	VFET, 800/30V, 45W, 160/450ns(2.6A) A: 3.4/14A, <1.5Ω(4A), B: 3/12A, <2Ω(4A)	16c	SOT-199		2SK809A, 2SK1463, 2SK1684, 2SK1859
BUK 428-1000A,B	Phi	MOS-N-FET-e	VFET, 1000/30V, 45W, 160/450ns(2.5A) A: 2.9/12A, <2Ω(3.5A), B: 2.6/10A, <2.6Ω(3.5A)	16c	SOT-199		BUK 426-1000, 2SK1770
BUK 436-50A,B	Phi	MOS-N-FET-e	=BUK 426-50A, B: A=50/200A, B=46/184A, 125W	18p	TO-3P		BUZ 346, 2SK1297, 2SK1379, 2SK1514
BUK 436-60A,B	Phi	MOS-N-FET-e	=BUK 426-60A, B: A=50/200A, B=46/184A, 125W	18p	TO-3P		2SK1297, 2SK1379, 2SK1514, 2SK2096
BUK 436-100A,B	Phi	MOS-N-FET-e	=BUK 426-100A, B: A=33/132A, B=31/124A, 125W	18p	TO-3P		BUZ 345, 2SK850, 2SK906, 2SK1429, ++

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International
KSV 3100 ACN-....	Sam	A/D-D/A-IC	8-Bit A/D- + 10-Bit D/A-Converter		40-DIP		
KSV 3110(CN-....)	Sam	A/D-D/A-IC	8 Bit A/D- + 10 Bit D/A-Conv., Video, TTL In/Out		40-DIP		
KSV 3208(CN)	Sam	A/D-IC	8 Bit, hi-speed, TV, Video, 20MSPs, TTL In/Out		28-DIP		
KSV 3310	Sam	D/A-IC	10 Bit, TV, Video, 20MHz		28-DIP		
KSV 3404	Sam						
KSV 13	Sie						

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International				
BUK 441-100	KT										
BUK 442-50A	KT										
BUK 442-60A	KT 208(A...V)	GUS	BU 806	Phi,Sgs,Tx	Si-N-Darl+Di	TV-HA, 400/200V, 8/15A, 60W, sat<1.5V(5A)	17j	TO-220	BU 806	17j	BU 10...
BUK 442-100	KT 209(A...V)	GUS	BU 806 AF		Si-N-Darl+Di	=BU 806: Iso	17c				
BUK 443-50A	KT 814 A,B,G,V	GUS	BU 806 FI	Tho	Si-N-Darl+Di	=BU 806: Iso, 30W	17c	TO-220Iso			
BUK 443-60A	KT 815 A,B,G,V	GUS	BU 807	Phi,Sgs,Tix	Si-N-Darl+Di	=BU 806: 330/150V	17j	TO-220	BU 806	17j	BU 18...
BUK 443-100	KT 816 A,B,G,V	GUS	BU 807 FI	Tho	Si-N-Darl+Di	=BU 807: Iso, 30W	17c	TO-220Iso			
BUK 444-200	KT 817 A,B,G,V	GUS	BU 808 DFI [SGS]	Sgs	Si-N-Darl+Di	=BU 808FI: integr. Damper-Diode	18c	TO-3P Iso			
BUK 444-400	KT 818 A,B,G,V	GUS	BU 808 FI [SGS]	Sgs	Si-N-Darl	CTV-HA, 1400/700V, 5/10A, 50W, hFE=25 sat<1.6V(5A)	18c	TO-3P Iso			
BUK 444-450	KT 819 A,B,G,V	GUS	BU 808 [Philips]	Phi	Si-N	3Ph-Motor Drv, 1500/700V, 12/20A, 160W, sat<1V(9V)	23a	TO-3			BUX 8...
BUK 444-500	KT 3030	Sam	BU 810	Sgs	Si-N-Darl+Di	S P, 600/400V, 7/10A, 75W, <0.62µs, sat<3V(7A)	17a	TO-220	2SD798	17j	2SD35...
BUK 444-600	KT 3031	Sam	BU 824	Phi	Si-N-Darl+Di	S P, 650/375V, 0.5/1A, 12.5W, hFE=325, <1/2.5µs	13h	TO-202			
BUK 444-800	KT 3032	Sam	BU 826	Phi	Si-N-Darl+Di	S P, 800/375V, 6/8A, 125W, <1.3/2.2µs, sat<2.5V(4A)	18j	TO-3P	BU 826	18j	BU ...
BUK 444-900	KT 3033	Sam	BU 826 A		Si-N-Darl+Di	=BU 826: 1000/400V	18j	TO-3P			
BUK 445-50A	KT 3040 J	Sam	BU 900	Tho	Si-N-Darl	Tripletion, 650/400V, 8A, 70W, hFE=7000, sat<4V(3A)	17j	TO-220			
BUK 445-60A	KT 3054 J	Sam	BU 902	Aeg	Si-N	El. Zündung/Ignition, Z-Diode					
BUK 445-800	KT 3064 J	Sam	BU 902 F		Si-N	S P, TV-SMPS	18j	TO-3P	BU 908	18j	BU 50...
BUK 445-900	KT 3107(A...V)	GUS	BU 903	Aeg,Phi	Si-N	=BU 902			BU 508 AF	16c	BU 50...
BUK 446-100	KT 3170 J,N	Sam	BU 903 F		Si-N				BU 903	18j	BU 50...
BUK 446-200	KT 5116 J	Sam	BU 908	Aeg	Si-N				BU 508 AF	16c	BU 50...
BUK 446-400	KT 8518	Sam	BU 908 AF		Si-N				BU 908	18j	BU 50...
BUK 446-500	KT 8520	Sam	BU 910	Sgs					BU 508 AF	16c	BU 50...
BUK 446-600	KT 8521	Sam	BU 911	Sgs					BU 806	17j	BU 80...
BUK 446-800	KT 8554(J)	Sam	BU 912						2SD798?	17j	2SD7...
BUK 446-900	KT 8555(J)	Sam	BU 920	Sgs					0798?	17j	2SD7...
BUK 447-100	KT 8557(J)	Sam	BU 920 P								BU 93...
BUK 448-100	KT 8592(N)	Sam	BU 920 PFI								BU 93...
BUK 449-100	KT 8593(N)	Sam	BU 920 T								2SD1...
BUK 450-100	KTA 200	Kec	BU 921								BU 93...
BUK 451-100	KTA 473	Kec	BU 921 P								2SD1...
BUK 452-100	KTA 490	Kec	BU 921 PFI								BU 93...
BUK 453-100	KTA 940	Kec	BU 921 T								2SD1...
BUK 454-100	KTA 950	Kec	BU 921 ZP								BU 93...
BUK 455-100	KTA 958(A)	Kec	BU 921 ZPFI								2SD1...
BUK 456-100	KTA 1001	Kec	BU 922								BU 93...
BUK 457-100	KTA 1015	Kec	BU 922 P								BU 93...
BUK 458-100	KTA 1021	Kec	BU 922 PFI								2SD1...
BUK 459-100	KTA 1023	Kec	BU 922 T								BU 93...
BUK 460-100	KTA 1024	Kec	BU 926	Tho							2SD1...
BUK 461-100	KTA 1023	Kec	BU 926								BU 93...
BUK 462-100	KTA 1024	Kec	BU 930	Sgs							2SD1...
BUK 463-100	KTA 1024	Kec	BU 930 P								BU 93...
BUK 464-100	KTA 1070	Kec	BU 930 Z								2SD1...
BUK 465-100	KTA 1070	Kec	BU 930 ZP								BU 93...
BUK 466-100	KTA 1270	Kec	BU 931	Sgs							2SD1...
BUK 467-100	KTA 1271	Kec	BU 931 Z								BU 93...
BUK 468-100	KTA 1272	Kec	BU 931 ZP								2SD1...
BUK 469-100	KTA 1273	Kec	BU 931 ZPFI								BU 93...
BUK 470-100	KTA 1274	Kec	BU 932								2SD1...
BUK 471-100	KTA 1275	Kec	BU 932 P								BU 93...
BUK 472-100	KTA 1275	Kec	BU 932 P								2SD1...
BUK 473-100	KTA 1275	Kec	BU 932 P								BU 93...

80.000 types

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International
2 SC 5085	Tos	Si-N	=2SC5084:	35a(2mm)	SOT-323		BFS 520, BFS 540
2 SC 5086	Tos	Si-N	=2SC5084:	35a(1,6mm)	SS Mini		2SC4839
2 SC 5087	Tos	Si-N	SMD, VHF/UHF, 20/12V, 80mA, 7GHz, F<2/Gp=13dB(1GHz)	44u	SOT-143		-
2 SC 5088	Tos	Si-N	=2SC5087:	44u(2mm)	SOT-343		-
2 SC 5089	Tos	Si-N	SMD, UHF, 20/10V, 40mA, 10GHz, F=1,7/Gp=7dB(2GHz)	35a	SOT-23		2SC3583, 2SC3585, 2SC3904, 2SC4591
2 SC 5090	Tos	Si-N	=2SC5089:	35a(2mm)	SOT-323		2SC4593, 2SC5190
2 SC 5091	Tos	Si-N	=2SC5089:	35a(1,6mm)	SS Mini		-
2 SC 5092	Tos	Si-N	SMD, UHF, 20/10V, 40mA, 10GHz, F=1,8/Gp=9,5dB(2GHz)	44u	SOT-143		2SC4094...95, 2SC4127
2 SC 5093	Tos	Si-N	=2SC5092:	44u(2mm)	SOT-343		2SC4843
2 SC 5094	Tos	Si-N	SMD, UHF, 20/10V, 15mA, 10GHz, F=1,8/Gp=7,5dB(2GHz)	35a	SOT-23		BFR 505, 2SC3585, 2SC5049, 2SC5089
2 SC 5095	Tos	Si-N	=2SC5094:	35a(2mm)	SOT-323		BFS 505, 2SC4899, 2SC5090, 2SC5190
2 SC 5096	Tos	Si-N	=2SC5094:	35a(1,6mm)	SS Mini		2SC4840...41, 2SC5091, 2SC5137
2 SC 5097	Tos	Si-N	SMD, UHF, 20/10V, 15mA, 10GHz, F=1,8/Gp=10dB(2GHz)	44u	SOT-143		2SC4095, 2SC4993, 2SC5092
2 SC 5098	Tos	Si-N	=2SC5097:	44u(2mm)	SOT-343		2SC4843, 2SC4994, 2SC5093
2 SC 5099	Sak	Si-N	P, 120/80V, 6A, 60W, 20MHz	{2SA1907 18c	TO-3P Iso	(BD 245 C) ³	2SC8385, 2SC4689, 2SD2064, (BD 245C...F) ³
2 SC 5100	Sak	Si-N	P, 160/120V, 8A, 75W, 20MHz	{2SA1908 18c	TO-3P Iso	(BD 250D) ³	2SC4386, (BD 245D...F) ³
2 SC 5101	Sak	Si-N	P, 200/140V, 10A, 80W, 20MHz	{2SA1909 18c	TO-3P Iso	(2SC3263) ³	2SC4387, (BD 245F) ³
2 SC 5103	Rhm	Si-N	S P, 100/60V, 5/10A, 10W, 120MHz, <0,3/1,8µs lo-sat<0,5V(4A)	30j	TO-251	2SC3303	2SC3303, 2SC4979
2 SC 5105	Hit	Si-N	Monitor-HA, 1500/800V, 12/20A, 50W, sat<5V(10A)	-18c	TO-3PFM		BU 2525AF, 2SC4692
2 SC 5106	Tos	Si-N	SMD, VHF/UHF, 20/10V, 30mA, 6GHz, Gp=11dB(1GHz)	35a	SOT-23		BFR 182, 2SC3011, 2SC4902, 2SC5064
2 SC 5107	Tos	Si-N	=2SC5106:	35a(2mm)	SOT-323		BFR 182W, 2SC4903, 2SC5065
2 SC 5108	Tos	Si-N	=2SC5106:	35a(1,6mm)	SS Mini		2SC5066, 2SC5138
2 SC 5109	Tos	Si-N	SMD, VHF/UHF, 20/10V, 60mA, 6GHz, Gp=10dB(1GHz)	35a	SOT-23		BFR770, BFR67, BFR183, 2SC3513, 2SC3704
2 SC 5110	Tos	Si-N	=2SC5109:	35a(2mm)	SOT-323		BFR 67W, BFR 183W, 2SC3937
2 SC 5111	Tos	Si-N	=2SC5109:	35a(1,6mm)	SS Mini		2SC5086
2 SC 5120	Hit	Si-N	Vid Out, 150/150V, 0,2/0,5A, 8W, 500MHz	14b	TO-126 Iso	(2SC3601) ³	2SC3787, 2SC3956, 2SC5024
2 SC 5124	Sak	Si-N	HA, 1500/800V, 10A, 100W, sat<5V(8A)	18c	(FM-100)	(2SC3688) ³	BU 2520AF, 2SC4589, 2SC4759, 2SD2373,++
2 SC 5132	Hit	Si-N+Di	=2SC5133: Iso	-18c	TO-3PFM	BU 508 DF	2SC4764, 2SD1556, 2SD2095, 2SD2370,++
2 SC 5133	Hit	Si-N+Di	Monitor-HA, 1500V, 6/16A, 50W, sat<5V(5A)	18j	TO-3P	BU 508 D	BU 2508D, 2SC3482, 2SC4293...94
2 SC 5136	Hit	Si-N	=2SC4197: 3800MHz, F=2,5/Gp=11dB(900MHz)	35a(1,6mm)	SS Mini		-
2 SC 5137	Hit	Si-N	=2SC4784:	35a(1,6mm)	SS Mini		2SC4841, 2SC5096, 2SC5140
2 SC 5138	Hit	Si-N	=2SC4902: F<3/Gp=13dB(900MHz)	35a(1,6mm)	SS Mini		2SC4841, 2SC5096, 2SC5140
2 SC 5139	Hit	Si-N	=2SC5050:	35a(1,6mm)	SS Mini		2SC5247
2 SC 5140	Hit	Si-N	=2SC4899:	35a(1,6mm)	SS Mini		2SC4841, 2SC5096, 2SC5137
2 SC 5141	Hit	Si-N	=2SC4906:	35a(1,6mm)	SS Mini		-
2 SC 5155	Say	Si-N	50/20V, 3A, 20W, 260MHz, hi-hFE=800...3200 140/1620ns, lo-sat<0,5V(2A)	30j	TO-251/252		2SD1584, 2SD1754(A)
2 SC 5187	Say	Si-N	SMD, S, 25/20V, 1,5A, 50/180ns	{2SA1935 39b	SOT-89		2SC2982, 2SC4377, 2SD1621, 2SD1766,++
2 SC 5188	Say	Si-N	SMD, S, 25/20V, 3A, 50/120ns	{2SA1898 39b	SOT-89		2SD1119, 2SD1620, 2SD2150
2 SC 5189	Say	Si-N	SMD, S, 25/20V, 5A, 50/180ns	{2SA1936 39b	SOT-89		2SD1963, 2SD2540
2 SC 5190	Mat	Si-N	SMD, SHFA, 9/6V, 30mA, 10GHz, F=1,7dB(900MHz)	35a(2mm)	SOT-323		2SC4593, 2SC4805, 2SC5090
2 SC 5218	Hit	Si-N	=2SC4900:	35a	SOT-23		2SC3583, 2SC3904, 2SC4591, 2SC5050
2 SC 5225	Hit	Si-N	Vid, 100/80V, 0,3A, 0,625W, 1,4GHz	7e	TO-92		-
2 SC 5226	Say	Si-N	SMD, VHF/UHF, 20/10V, 70mA, 7GHz, F=1dB(1GHz)	35a(2mm)	SOT-323		BFS 520, 2SC5085
2 SC 5227	Say	Si-N	=2SC5226:	35a	SOT-23		BFR 193, BFR 520, 2SC3445, 2SC5084
2 SC 5228	Say	Si-N	=2SC5226:	44u	SOT-143		2SC5087
2 SC 5229	Say	Si-N	=2SC5230: SMD	39b	SOT-89		BFR 193, 2SC3301, 2SC3607, 2SC5019
2 SC 5230	Say	Si-N	VHF/UHF, 20/10V, 70mA, 0,4W, 6,5GHz, F=1dB(1GHz)	7f	TO-92	2SC3355	2SC3355, 2SC3507, 2SC4968
2 SC 5231	Say	Si-N	SMD, VHF/UHF, 16/8V, 50mA, 9GHz, F=1,2dB(1GHz)	35a(1,6mm)	SS Mini		2SC5139, 2SC5247
2 SC 5238	Say	Si-N	CRT Display HA, 1500/800V, 50A, 160W, sat<5V(40A)	77j	=TOP-3L		-
2 SC 5245	Say	Si-N	SMD, VHF/UHF, 20/10V, 30mA, 11GHz, F=1,4dB(1,5GHz)	35a(2mm)	SOT-323		2SC5051
2 SC 5246	Hit	Si-N	=2SC5078:	35a(1,6mm)	SS Mini		2SC5139
2 SC 5247	Hit	Si-N	=2SC5080:	35a(1,6mm)	SS Mini		2SC5139
2 SC 5264	Say	Si-N	HA, S P, 1000/450V, 5A, 30W, sat<1V(2,5A) (Push-Pull Line Back)	17c	TO-220 Iso		-
2 SC 5265	Say	Si-N	HA, S P, 1200/600V, 4A, 30W, sat<1V(2A) (Push-Pull Line Back)	17c	TO-220 Iso		-
2 SC 5275	Say	Si-N	SMD, VHF/UHF, 20/10V, 30mA, 11GHz, F=1,4dB(1,5GHz)	35a(2mm)	SOT-323		2SC5051
2 SC 5276	Say	Si-N	=2SC5275:	35a(3mm)	SOT-23		2SC5050
2 SC 5277	Say	Si-N	=2SC5275:	35a(1,6mm)	SS Mini		2SC5139, 2SC5247
2 SC 5291	Say	Si-N	=2SC3902: 1,5W	=12b	(FLP)	(-2SC3902) ⁴	(-2SC3902) ⁴
2 SC 5296	Say	Si-N+Di	=2SC5297: int. Damper-Diode	18c	TO-3P Iso	BU 508 DF	BU 2508DF, 2SC4124, 2SC4763
2 SC 5297	Say	Si-N	CRT Display HA, 1500/800V, 8A, sat<5V(5A)	18c	TO-3P Iso	BU 2508 AF	BU 2508AF, 2SC3896, 2SC4758, 2SC5067
2 SC 5298	Say	Si-N+Di	=2SC5299: int. Damper-Diode	18c	TO-3P Iso		BU 2520DF, 2SC4125, 2SC4878
2 SC 5299	Say	Si-N	CRT Display HA, 1500/800V, 10A, 70W, sat<5V(8A)	18c	TO-3P Iso	(2SC3688) ³	BU 2520AF, BUH 715, 2SC4589, 2SC5068
2SD							
2 SD 11	Nec	Ge-N	S, 25V, 0,3A, 0,15W, 2,5MHz	2a	TO-5		ASY 73...75
2 SD 12	Mat	Si-N	LFS P, 75/40V, 2,5A, 60W	23a	TO-3	BD 245 C	BD 245B, BDV 93, 2N4915, 2SD895...896, ++
2 SD 13	Mat	Si-N	LFS P, 35/20V, 10A, 100W	38a	TO-36	(BD 245 C) ⁴	(BD 245, BDV 91, 2SC2681) ⁴
2 SD 14	Mat	Si-N	LFS P, 75/40V, 10A, 100W	38a	TO-36	(BD 245 C) ⁴	(BD 245B, BDV 93, 2SC2681) ⁴
2 SD 15	Sak	Si-N	LFS P, 60/40V, 6A, 80W, <1460/5100ns	23a	TO-3	BD 245 C	BD 245A, BDV 91, 2N4914...4915, ++
2 SD 16	Sak	Si-N	=2SD15: 100/55V	23a	TO-3	BD 245 C	BD 245C, BDV 95, 2N5758...5759, ++
2 SD 17	Sak	Si-N	=2SD15: 150/70V	23a	TO-3	2SC2837	BD 245D, BDX 11, 2N3442, 2SD731...732, ++
2 SD 18	Sak	Si-N	=2SD15: 200/85V	23a	TO-3	2SC3263	BD 245F, 2SC3263, 2SD555, 2SD751
2 SD 19	Nec	Ge-N	LF Drv,Out, 25V, 0,3A, 0,15W, hFE=31	{2SB219 2a	TO-5	AC 187 K	AC 127, AC 176, AC 187, 2SD72, 2SD352
2 SD 20	Nec	Ge-N	=2SD19: hFE=50	{2SB220 2a	TO-5	AC 187 K	AC 127, AC 176, AC 187, 2SD72, 2SD352
2 SD 21	Nec	Ge-N	=2SD19: hFE=72	{2SB221 2a	TO-5	AC 187 K	AC 127, AC 176, AC 187, 2SD72, 2SD352
2 SD 22	Nec	Ge-N	=2SD19: hFE=97	{2SB222 2a	TO-5	AC 187 K	AC 127, AC 176, AC 187, 2SD72, 2SD352
2 SD 23	Nec	Ge-N	=2SD19: hFE=150	{2SB223 2a	TO-5	AC 187 K	AC 127, AC 176, AC 187, 2SD72, 2SD352
2 SD 24	Say	Si-N	Vid P, 300V, 0,1A, 6W(Tc=70°), 25MHz	22a	TO-66	2SC1505	2SC1505...1507, 2SC1755...1757, 2SC1905,++
2 SD 24 Y		Si-N	=2SD24: 0,15A, 8MHz	22a	TO-66	2SC1505	2SC1505...1507, 2SC1755...1757, 2SC1905,++
2 SD 25	Nec	Ge-N	LF, 25V, 0,1A, 0,11W	2a	TO-1	AC 187 K	AC 127, AC 176, AC 187, 2SD30
2 SD 26	Mit	Si-N	LFS P, 40/30V, 7A, 50W	23a	TO-3	BD 245 C	BD 245, BDV 91, BDX 91, 2N5873...5874, ++
2 SD 26 A		Si-N	=2SD26: 60/40V	23a	TO-3	BD 245 C	BD 245A, BDV 91, BDX 91, 2N5873...5874, ++
2 SD 26 B		Si-N	=2SD26: 100/60V	23a	TO-3	BD 245 C	BD 245C, BDV 95, BDX 95, 2N5632...5633, ++
2 SD 26 C		Si-N	=2SD26: 150/80V	23a	TO-3	2SD2837	BD 245D, BDX 11, 2N3442, 2SD731...732, ++
2 SD 27	Mat	Ge-N	LF Drv,Out, 32V, 0,5A, 0,28W	2a	TO-1	AC 187 K	AC 127, AC 176, AC 187, 2SD72, 2SD352
2 SD 28	Son	Si-N	LFS P, 70/40V, 3A, 18W	22a	SOT-9	BD 243 C	BD 241A, BD 537, BD 937, 2SD712, ++
2 SD 29	Son	Si-N	=2SD28: 70/60V	22a	SOT-9	BD 243 C	BD 241B, BD 537, BD 937, 2SD712, ++
2 SD 30	Say	Ge-N	LF Drv,Out, 25V, 0,2A, 0,3W	{2SB22 2a°		AC 187 K	AC 127, AC 176(K), AC 187(K), 2SD72
2 SD 31	Mat	Ge-N	LF, 25V, 0,125A, 0,125W, hFE=50	{2SB172 2a	TO-1	AC 187 K	AC 127, AC 176, AC 187, 2SD30, 2SD72

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International
2 SD 32	Mat	Ge-N	=2SD31: hFE=90	12SB176 2a	TO-1	AC 187 K	3a AC 127, AC 176, AC 187, 2SD30, 2SD73
2 SD 33	Fui	Ge-N	LF, 20V, 0.05A, 0.15W	12SB33 2a	TO-1	AC 187 K	3a AC 127, 2SD30
2 SD 34	Fui	Ge-N	LF, 20V, 0.15A, 0.25W	12SB34 1a	-TO-7	AC 187 K	3a AC 127, AC 176, AC 187, 2SD30, 2SD72
2 SD 35	Mat	Ge-N	LF, 20V, 0.06A, 0.083W	37a	TO-2	-	AC 127, 2SD72
2 SD 36	Mat	Ge-N	LF, 20V, 0.06A, 0.083W	37a	TO-2	-	AC 127, 2SD72
2 SD 37	Fui	Ge-N	LF, 30V, 0.05A, 0.15W	12SB37 2a	TO-1	AC 187 K	3a AC 127, 2SD30
2 SD 38	Fui	Ge-N	LF, 30V, 0.15A, 0.25W	12SB38 1a	-TO-7	AC 187 K	3a AC 127, AC 176, AC 187, 2SD30, 2SD72
2 SD 41	Tos	Si-N	L.F.S.P. 80/80V, 10A, 200W	23a	TO-3	BD 317	23a BD 315, BD 317, 2N3772, 2N5629...31, ++
2 SD 43	Tos	Ge-N	LF, 25V, 0.05A, 0.11W	12SB43 2a	TO-1	AC 187 K	3a AC 127, 2SD30
2 SD 43 A		Ge-N	=2SD43: 45V, 0.15A	2a	TO-1	-	-
2 SD 44	Tos	Ge-N	LF, 30V, 0.05A, 0.08W	12SB44 2a	TO-1	AC 187 K	3a AC 127, 2SD30
2 SD 45	Son	Si-N	P, 150/100V, 5A, 50W, 20MHz	23a	TO-3	2SC3263	18j BD245D, BDX11, 2N3442, 2SD551, 2SD732, ++
2 SD 46	Son	Si-N	=2SD45: 150/75V	23a	TO-3	2SC3263	18j BD245D, BDX11, 2N3442, 2SD551, 2SD732, ++
2 SD 47	Son	Si-N	=2SD45: 100/50V	23a	TO-3	2SC3263	18j BD 245C, BDV 95, BDX 95, 2N5632...33, ++
2 SD 48	Fui	Si-N	P, 100/55V, 3A, 20W	2a	TO-8	(BD 243 C) ⁴	17j (BD 241C, BD 539C, BD 939, 2SD712, ++) ⁴
2 SD 49	Son	Si-N	P, 100/60V, 3A, 18W	22a	SOT-9	BD 243 C	17j BD 241C, BD 539C, BD 939, 2SD877, ++
2 SD 50	Hit, Fui	Si-N	P, 100/55V, 6A, 50W	23a	TO-3	BD 245 C	18j BD 245C, BDV 95, BDX 95, 2N5632...33, ++
2 SD 51	Son, Tos	Si-N	P, 100/50V, 6A, 50W	23a	TO-3	BD 245 C	18j BD 245C, BDV 95, BDX 95, 2N5632...33, ++
2 SD 51 A		Si-N	=2SD51: 150/110V	23a	TO-3	2SC3263	18j BD245D, BDX11, 2N3442, 2SD551, 2SD732, ++
2 SD 52	Fui, Sak, Tos	Si-N	P, 100/55V, 6A, 80W	23a	TO-3	BD 245 C	18j BD 245C, BDV 95, BDX 95, 2N5632...33, ++
2 SD 52 A		Si-N	=2SD52: 130/110V	23a	TO-3	2SC3263	18j BD245D, BDX11, 2N3442, 2SD551, 2SD732, ++
2 SD 53	Fui, Tos	Si-N	P, 90/50V, 10A, 100W	23a	TO-3	BD 245 C	18j BD 245C, BDV 95, BDX 95, 2N5632...33, ++
2 SD 53 A		Si-N	=2SD53: 130/110V	23a	TO-3	2SC3263	18j BD245D, BDX11, 2N3442, 2SD551, 2SD733, ++
2 SD 54	Fui, Tos	Si-N	P, 100/50V, 10A, 150W	38a	TO-36	(BD 249 C) ⁴	18j (BD 249C, BD 745C, 2SD1049) ⁴
2 SD 55	Tos	Si-N	P, 100/55V, 20A, 200W	23a	TO-3	(BD 317) ⁷	23a BDW 30, BDV 29, MJ 802, 2N3772, 2SD797, ++
2 SD 55 A		Si-N	=2SD55: 130/110V	23a	TO-3	-	BDW 30, BDV 32, BDY 58
2 SD 56	Son	Si-N	S P, 220/80V, 3A, 30W	22a	SOT-9	(BU 406)	17j D4403, TIP 75(A...C), 2SC867A, 2SC2767, ++
2 SD 57	Mit	Si-N	P, 30/20V, 3A, 20W	22a	SOT-9	BD 243 C	17j BD 241, BD 533, BD 933, 2SD877, ++
2 SD 58	Mit	Si-N	=2SD57: 60/40V	22a	SOT-9	BD 243 C	17j BD 241A, BD 535, BD 935, 2SD877, ++
2 SD 59	Mit	Si-N	P, 100/60V, 6A, 50W	23a	TO-3	BD 245 C	18j BD 245C, BDV 95, BDX 95, 2N5632...33, ++
2 SD 60	Mit	Si-N	=2SD59: 150/75V	23a	TO-3	2SC3263	18j BD245D, BDX11, 2N3442, 2SD551, 2SD732, ++
2 SD 61	Son	Ge-N	L.F.S, 30V, 0.1A, 0.12W	2a	TO-18L	AC 187 K	3a AC 127, 2SD30
2 SD 62	Son	Ge-N	L.F.S, 30V, 0.1A, 0.12W	2a	TO-18L	AC 187 K	3a AC 127, 2SD30
2 SD 63	Son	Ge-N	L.F.S, 25V, 0.1A, 0.12W	2a	TO-18L	AC 187 K	3a AC 127, 2SD30
2 SD 64	Son	Ge-N	L.F.S, 25V, 0.1A, 0.12W	2a	TO-18L	AC 187 K	3a AC 127, 2SD30
2 SD 65	Son	Ge-N	L.F.S, 25V, 0.1A, 0.12W	2a	TO-18L	AC 187 K	3a AC 127, 2SD30
2 SD 66	Son	Ge-N	L.F.S, 25V, 0.1A, 0.12W	2a	TO-18L	AC 187 K	3a AC 127, 2SD30
2 SD 67	Say	Si-N	S P, 120V, 5A, 50W, 100MHz	23a	TO-3	2SC3263	18j 2SC2706, 2SC2837, 2SC2987(A), 2SD1047
2 SD 68	Say	Si-N	=2SD67: 75V	23a	TO-3	(BD 245 C) ⁸	18j 2SC2681, 2SC2706, 2SC2837, (BD 245B, ++) ⁸
2 SD 69	Son	Si-N	P, 140/140V, 3A, 50W, 13MHz	23a	TO-3	BU608, 2SC3263	23a, 18j BD 12, 2N5760, 2SC2706, 2SC2837, ++
2 SD 70	Nec	Si-N	P, 40/25V, 2/3A, 15W	22a	-TO-66	BD 243 C	17j BD 239, BD 241, BD 933, 2SC2528, ++
2 SD 71	Nec	Si-N	P, 100/60V, 2/3A, 15W	22a	-TO-66	BD 243 C	17j BD 239C, BD 241C, BD 937, 2SC2528, ++
2 SD 72	Say	Ge-N	LF, 25V, 0.6A, 0.21W	12SB405 2a	TO-1	AC 187 K	3a AC 176, AC 187, 2SD352
2 SD 72 K		Ge-N	=2SD72: 0.72W	3a	TO-1°	AC 187 K	3a AC 176K, AC 187K, 2SD352
2 SD 73	Nec	Si-N	P, 100/60V, 5/7.5A, 60W, 20MHz	12SB506 23a	TO-3	BD 245 C	18j BD 245C, BDV 95, BDX 95, 2N5632...33, ++
2 SD 74	Nec	Si-N	=2SD73: 150/90V	12SB506 23a	TO-3	2SC3263	18j BD 245D, BDX 11, 2N3442, 2SD551, 2SD732
2 SD 75	Hit	Ge-N	LF, 25V, 0.1A, 0.15W	12SB75 2a	TO-1	AC 187 K	3a AC 127, AC 176, AC 187, 2SD30
2 SD 75 A		Ge-N	=2SD75: 45V	2a	TO-1	-	-
2 SD 77	Hit	Ge-N	LF, 25V, 0.1A, 0.15W	12SB77 2a	TO-1	AC 187 K	3a AC 127, AC 176, AC 187, 2SD30
2 SD 77 A		Ge-N	=2SD77: 45V	2a	TO-1	-	-
2 SD 78(A)	Nec	Si-N	L.F.S, 100/60(A=100/80)V, 2A, 1W	12SB504 2a	TO-39	(2SC4135) ⁴	30j BCX 40, BSS 15, 2N5320, (BD 529, ++) ⁶
2 SD 79	Nec	Si-N	=2SD78:	12SB505 43a	-TO-37	(BD 237) ⁴	14h (BD 237, BD 239C, BD 529, BD 529, BD 817, ++) ⁴
2 SD 80	Sak	Si-N	P, 30/20V, 6A, 50W, 1320/4500ns	23a	TO-3	BD 245 C	18j BD 245, BDV 91, BDX 91, 2N5873...74, ++
2 SD 81	Sak	Si-N	=2SD80: 60/40V	23a	TO-3	BD 245 C	18j BD 245A, BDV 91, BDX 91, 2N5873...74, ++
2 SD 82	Sak	Si-N	=2SD80: 100/60V	23a	TO-3	BD 245 C	18j BD 245C, BDV 93, BDX 93, 2N5632...33, ++
2 SD 83	Sak	Si-N	=2SD80: 150/75V	23a	TO-3	2SC3263	18j BD245D, BDX11, 2N3442, 2SD551, 2SD732, ++
2 SD 84	Sak	Si-N	=2SD80: 200/85V	23a	TO-3	(BU 608)	23a BD 245F, BD 550A, B, 2SC2262, 2SD751
2 SD 88(-1...-3)	Son	Si-N	S P, 100...300V, 5A, 80W	23a	TO-3	BU 608	23a BU 104, BU 606...608, BUX 18(A...C), ++
2 SD 88 A		Si-N	=2SD88: 10A, 120W	23a	TO-3	(BU 608)	23a BU 109, BUX 17A...C, BUY 18, BUX 43, ++
2 SD 90	Sak	Si-N	P, 30/20V, 3A, 20W, -/3, 8µs	22a	SOT-9	BD 243 C	17j BD 241, BD 533, BD 933, 2SD877, ++
2 SD 91	Sak	Si-N	=2SD90: 60/40V	22a	SOT-9	BD 243 C	17j BD 241A, BD 535, BD 935, 2SD877, ++
2 SD 92	Sak	Si-N	=2SD90: 100/55V	22a	SOT-9	BD 243 C	17j BD 241C, BD 937, 2SD712, 2SD877, ++
2 SD 93	Sak	Si-N	=2SD90: 150/70V	22a	SOT-9	BU406, 2SD1138	17j BD 241D, 2SD772(A,B)
2 SD 94	Sak	Si-N	=2SD90: 200/80V	22a	SOT-9	BU406, 2SD1138	17j BD 241F, 2SD772A,B
2 SD 96	Hit	Ge-N	LF Drv, Out, 25V, 0.25A, 0.3W	2a	TO-1	AC 187 K	3a AC 127, AC 176, AC 187, 2SD30, 2SD72
2 SD 100	Tos	Ge-N	LF Drv, 32V, 0.4A, 0.25W	12SB200 2a	TO-1	AC 187 K	3a AC 127, AC 176, AC 187, 2SD72, 2SD352
2 SD 100 A		Ge-N	=2SD100: 45V	2a	-	-	-
2 SD 101	Tos	Ge-N	LF Drv, 80V, 0.6A, 0.25W	2a	-	-	-
2 SD 102	Tos	Si-N	P, 110/80V, 3A, 25W, 1MHz, 3/10µs	12SB502 22a	TO-66	BD 243 C	17j BD 241C, BD 243C, BD 539D, BD 939, ++
2 SD 103	Tos	Si-N	=2SD102: 80/50V	12SB503 22a	TO-66	BD 243 C	17j BD 241B, BD 243B, BD 539B, BD 937, ++
2 SD 104	Tos	Ge-N	LF, 20V, 0.4A, 0.15W, hFE>60	12SB364 2a	TO-1	AC 187 K	3a AC 127, AC 176, AC 187, 2SD72, 2SD352
2 SD 105	Tos	Ge-N	=2SD104: hFE>35	12SB365 2a	TO-1	AC 187 K	3a AC 127, AC 176, AC 187, 2SD72, 2SD352
2 SD 107	Tos	Si-N-Darl	P, 80/60V, 5A, 50W, 30MHz, hFE=1k...10k	23a	TO-3	BDW 83 C	18j BDX 63A, MJ 1001, 2N6056, 2SD1124, ++
2 SD 108	Tos	Si-N-Darl	=2SD107: 80/40V	23a	TO-3	BDW 83 C	18j BDX 63A, MJ 1001, 2N6056, 2SD1124, ++
2 SD 110	Tos	Si-N	P, 130/110V, 10A, 100W, 1MHz, 3/12µs	23a	TO-3	2SC3263	18j BDX 11, 2N3442, 2SD551, 2SD732...733, ++
2 SD 111	Tos	Si-N	=2SD110: 100/80V	23a	TO-3	2N3055	23a BD 317, BDW 21C, BDV 53, 2N5632...33, ++
2 SD 113	Tos	Si-N	P, 100/80V, 30A, 200W, 1.5MHz, 3/10µs	23a	TO-3	-	BDW 30, BDV 29, MJ 802, 2SD797
2 SD 114	Tos	Si-N	=2SD113: 70/50V	23a	TO-3	-	BDW 30, BDV 29, MJ 802, 2SD797
2 SD 116	Fui	Si-N	P, 100/40V, 7A, 75W	23a	TO-3	BD 245 C	18j BD 245C, BDV 95, BDX 95, 2N5632...33, ++
2 SD 117	Fui	Si-N	=2SD116: 150/80V	23a	TO-3	2SC3263	18j BD245D, BDX11, 2N3442, 2SD551, 2SD732, ++
2 SD 118	Tos	Si-N	P, 130/110V, 7A, 100W, 2MHz	23a	TO-3	BU608, 2SC3263	23a, 18j BD245D, BDX11, 2N3442, 2SD551, 2SD732, ++
2 SD 119	Tos	Si-N	=2SD118: 100/80V	23a	TO-3	2N3055	23a BDW 21C, BDX 95, 2N3055, 2N5632...33, ++
2 SD 120	Hit	Si-N	L.F.S, 60/40V, 1.5A, 1W, 750/470ns	2a	TO-39	(2SC4135) ⁴	30j BCX 40, BSX 45...47, 2N5320...21, ++
2 SD 121	Hit	Si-N	=2SD120: 100/55V	2a	TO-39	(2SC4135) ⁴	30j BCX 40, BSS 15, BSX 46...47, 2N5320, ++
2 SD 122	Hit	Si-N	P, 60/40V, 3A, 15W	2a	TO-8	(BD 243 C) ⁴	17j (BD 241A, BD 535, BD 935, 2SD712, ++) ⁴
2 SD 123	Hit	Si-N	=2SD122: 100/55V	2a	TO-8	(BD 243 C) ⁴	17j (BD 241C, BD 539C, BD 939, 2SD712, ++) ⁴
2 SD 124	Hit	Si-N	P, 60/40V, 6A, 60W, 1.6/7.2µs	23a	TO-3	BD 245 C	18j BD 245A, BDV 91, BDX 91, 2N5873...74, ++
2 SD 124 A		Si-N	=2SD124: 75/50V, 7A	23a	TO-3	BD 245 C	18j BD 245B, BDV 93, BDX 93, 2N5874, ++
2 SD 125	Hit	Si-N	P, 100/55V, 6A, 60W, 1.6/7.7µs	23a	TO-3	BD 245 C	18j BD 245C, BDV 95, BDX 95, 2N5632...33, ++
2 SD 125 A		Si-N	=2SD125: 7A	23a	TO-3	BD 245 C	18j BD 245C, BDV 95, BDX 95, 2N5632...33, ++
2 SD 126	Hit	Si-N	P, 150/100V 6A, 60W, 1.6/8.2µs	23a	TO-3	2SC3263	18j BD245D, BDX11, 2N3442, 2SD551, 2SD732, ++
2 SD 127	Son	Ge-N	LF Drv, Out, 23V, 0.5A, 0.25W	2a	TO-1	AC 187 K	3a AC 127, AC 176, AC 187, 2SD72, 2SD352
2 SD 128	Son	Ge-N	=2SD127: 32V	2a	TO-1	AC 187 K	3a AC 127, AC 176, AC 187, 2SD72, 2SD352

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International	
2 SD 129	Tos	Si-N	P, 90/80V, 3A, 25W, 1MHz	22a	TO-66	BD 243 C	17j	BD 241B, BD 939, 2N4233, 2SD712, ++
2 SD 130	Tos	Si-N	=2SD129: 60/50V	22a	TO-66	BD 243 C	17j	BD 241A, BD 535, BD 935, 2N4232...33, ++
2 SD 131	Tos	Si-N	P, 100/80V, 5A, 50W, 20MHz	23a	TO-3	BD 245 C	18j	BD 245C, BDV 95, BDX 95, 2N5758...60, ++
2 SD 132	Nec	Si-N	P, 100/65V, 20/30A, 150W	68a				2SD363, 2SD372
2 SD 134	Son	Ge-N	S, 60V, 5mA, 0.03W	-2a				-
2 SD 136	Fui	Si-N	Vid P, 200/200V, 0.1A, 4W, 20MHz	-22	=TO-66	(BF 459) ⁴	14h	(BF 415, BF 417, BF 458...459,++) ⁴
2 SD 137	Fui	Si-N	=2SD136: 300/300V	-22	=TO-66	(BF 459) ⁴	14h	(BF 417, BF 459, 2SC3417, 2SC3503,++) ⁴
2 SD 138	Fui	Si-N	LF.Vid P, 200/200V, 1A, 30W	22a	=TO-66	2SD1138	17j	BUW 40(A,B), TIP 47...50, 2SC2020, ++
2 SD 139	Fui	Si-N	=2SD138: 300/300V	22a	=TO-66	(BUX 85)	17j	BUW 40(A,B), TIP 47...50, 2SC2020, ++
2 SD 141	Nec	Si-N	P, 20/12V, 2/3A, 15W	22a	=TO-66	BD 243 C	17j	BD 239, BD 241, BD 533, BD 933, ++
2 SD 142	Nec	Si-N	=2SD141: 40/20V	22a	=TO-66	BD 243 C	17j	BD 239, BD 241, BD 533, BD 933, ++
2 SD 143	Nec	Si-N	P, 80/40V, 1A, 15W	22a	=TO-66	BD 243 C	17j	BD 239B, BD 241B, BD 537, BD 937, ++
2 SD 144	Nec	Si-N	=2SD143: 100/50V	22a	=TO-66	BD 243 C	17j	BD 239C, BD 241C, BD 937, 2SD712, ++
2 SD 146	Fui	Si-N	P, 40/35V, 1A, 20W	22a	=TO-66	BD 243 C	17j	BD 239, BD 241, BD 533, BD 933, ++
2 SD 147	Fui	Si-N	=2SD146: 60/50V	22a	=TO-66	BD 243 C	17j	BD 239A, BD 241A, BD 535, BD 935, ++
2 SD 148	Fui	Si-N	P, 70V, 2A, 20W, 1.2MHz, -/3.8µs	22a	=TO-66	BD 243 C	17j	BD 239A, BD 241A, BD 537, BD 937, ++
2 SD 149	Fui	Si-N	LFS, 70V, 1A, 0.8W, 1.2MHz	2a	TO-39	BC 141	2a	BC 441, BCX 40, 2N1990, 2N2102, ++
2 SD 150	Nec	Si-N	P, 50/40V, 1/2A, 15W, >10MHz	{2SB613 22a	=TO-66	2SC1398	17j	BD 239, 2SC1398, 2SC2591, 2592, ++
2 SD 151	Nec	Si-N	P, 100/60V, 10/15A, 120W	23a	TO-3	2N3055	23a	BDY 53, 2N3055, 2N5632...33, 2SD426, ++
2 SD 152	Nec	Si-N	P, 50/70V, 1A, 15W	22a	=TO-66	2SD1138	17j	BD 239D, 2SC2073, 2SD608(A), 2SD1138, ++
2 SD 153	Nec	Si-N	S P, 250/200V, 10A, 120W	49m	TO-63			2N5540
2 SD 154	Nec	Si-N	P, 80/60V, 3A, 25W	{2SB614 22a	=TO-66	BC 243 C	17j	BD 241B, BD 243B, BD 537, BD 937, ++
2 SD 155	Nec	Si-N	P, 80V, 3A, 25W	{2SB616 22a	TO-66	BC 243 C	17j	BD 241B, BD 243B, BD 537, BD 937, ++
2 SD 156	Fui	Si-N	Vid P, 200/200V, 0.1A, 4W(Tc=70°), 20MHz	22a	TO-66	2SC1505	17j	2SC1505...1507, 2SC1755...1757, 2SC1819, ++
2 SD 157	Fui	Si-N	=2SD156: 300/300V	22a	TO-66	2SC1505	17j	2SC1505...1507, 2SC1755...1757, 2SC1819, ++
2 SD 158	Fui	Si-N	LF Out, Vid P, 200/200V, 1A, 30W, 15MHz	22a	TO-66	2SD1138	17j	BUW 40, TIP 47...50, 2SC782, 2SC2354, ++
2 SD 159	Fui	Si-N	=2SD158: 300/300V	22a	TO-66	(BUX 85)	17j	BUW 40, TIP 47...50, 2SC782, 2SC2354, ++
2 SD 160	Fui	Si-N	P, 100/55V, 1.5A, 25W, -/3.5µs	2a	TO-8	(BD 243 C) ⁴	17j	(BD 237, BD 239C, BD 241C, BD 937,++) ⁴
2 SD 161	Fui	Si-N	P, 120/70V, 10A, 100W, -/5µs	23a	TO-3	2SC2663	18j	BDX 11, 2N3442, 2SD551, 2SD732...733, ++
2 SD 162	Fui	Ge-N	LF, 20V, 0.03A, 0.65W	{2SB262 37a	TO-2			-
2 SD 163	Sak	Si-N	P, 60/40V, 10A, 100W, 1.56/6µs	23a	TO-3	BD 317	23a	BD 311, 2N3055, 2N5632...33, 2SD426, ++
2 SD 164	Sak	Si-N	=2SD163: 100/55V	23a	TO-3	BD 317	23a	BD 311, 2N3055, 2N5632...33, 2SD426, ++
2 SD 165	Sak	Si-N	=2SD163: 150/70V	23a	TO-3	2SC3263	18j	BDX 11, 2N3442, 2SD551, 2SD732...733, ++
2 SD 166	Sak	Si-N	=2SD163: 200/85V	23a	TO-3	MJ 15015	23a	MJ 15015, BDW 16, 2SC1585...86, 2SD665, ++
2 SD 167	Fui	Ge-N	LF Drv,Out, 20V, 0.5A, 0.2W	2a	TO-1	AC 187 K	3a	AC 127, AC 176, AC 187, 2SD72, 2SD352
2 SD 168	Fui	Si-N-Darl	P, 80/70V, 10A, 50W, hFE=2500	23a	TO-3	BDW 83 C	18j	BDV 65A, BDX 83B, BDX 85B, MJ3000...01, ++
2 SD 170	Hit	Ge-N	LF Drv,Out, 25V, 0.5A, 0.2W	{2SB370 2a	TO-1	AC 187 K	3a	AC 127, AC 176, AC 187, 2SD72, 2SD352
2 SD 170 A		Ge-N	=2SD170: 32V	2a	TO-1	(AC 187 K) ⁷	3a	AC 127, AC 176, 2SD352
2 SD 171-....	Son	Ge-N	S P, 450...600V, 3.5A, 125W	23a	TO-3	(BU 426 A)	18j	BUS 11(A), BUX 47(A), 2SC3156, 2SD640, ++
2 SD 172	Fui	Si-N	P, 60/40V, 10A, 100W	23a	TO-3	2N3055	23a	BD 245A, BD 315, 2N3055, 2N5877...78, ++
2 SD 173	Fui	Si-N	=2SD172: 100/60V	23a	TO-3	2N3055	23a	BD 245C, BD 317, 2N3055, 2N5632...33, ++
2 SD 174	Fui	Si-N	P, 60/40V, 5A, 50W	23a	TO-3	BD 245 C	18j	BD 245A, BDV 91, BDX 91, 2N5873...74, ++
2 SD 175	Fui	Si-N	=2SD174: 100/60V	23a	TO-3	BD 245 C	18j	BD 245C, BDV 95, BDX 95, 2N5758...59, ++
2 SD 176	Fui	Si-N	P, 90/50V, 10A, 100W	23a	TO-3	2N3055	23a	BD 245C, BD 317, 2N3055, 2N5632...33, ++
2 SD 177	Fui	Si-N	=2SD176: 120/70V	23a	TO-3	2SC3263	18j	BDX 11, 2N3442, 2SD551, 2SD732...733, ++
2 SD 178	Mat	Ge-N	LF, 20V, 0.3A, 0.225W	2a	TO-1	AC 187 K	3a	AC 127, AC 176, AC 187, 2SD72, 2SD352
2 SD 178 A		Ge-N	=2SD178: 40V	2a	TO-1	(AC 187 K) ⁷	3a	(AC 127, AC 176, 2SD352) ⁷
2 SD 178 B		Ge-N	=2SD178: 60V	2a	TO-1			-
2 SD 179	Nec	Si-N	S P, 300/300V, 40A, 580W	53b				-
2 SD 180	Nec	Si-N	P, 80/60V, 5/7A, 50W, 10MHz	{2SB626 23a	TO-3	BD 245 C	18j	BD 245B, BD 313, 2N5758, 2SD895...896, ++
2 SD 181	Nec	Si-N	P, 150/100V, 15A, 100W, 10MHz	23a	TO-3	MJ 15015	23a	MJ 15015, BD 745E, BDW 12, 2SC2607...08, ++
2 SD 181 A		Si-N	=2SD181: 250/200V, 10A	23a	TO-3			BUX 17(A...C), BUX 42, 2SC1586, 2SD583, ++
2 SD 182	Fui	Si-N	P, 40/30V, 1A, 10W	2a	TO-8	(2SC4135) ⁴	30j	(BD 135, BD 226, BD 507, BD 825,++) ⁴
2 SD 183	Fui	Si-N	=2SD182: 100/55V	2a	TO-8	(2SC4135) ⁴	30j	(BD 139, BD 230, BD 529, BD 829,++) ⁴
2 SD 184	Fui	Si-N	P, 60/40V, 1.5A, 25W, -/3.5µs	2a	TO-8	(BD 243 C) ⁴	17j	(BD 165, BD 233, BD 239A, BD 241A,++) ⁴
2 SD 185	Fui	Si-N	=2SD184: 100/55V	2a	TO-8	(BD 243 C) ⁴	17j	(BD 169, BD 237, BD 239C, BD 241C,++) ⁴
2 SD 186	Say	Ge-N	LF, 25V, 0.15A, 0.2W	{2SB186 2a	TO-1	AC 187 K	3a	AC 127, AC 176, AC 187, 2SD30, 2SD72
2 SD 187	Say	Ge-N	LF, 25V, 0.15A, 0.2W	{2SB187 2a	TO-1	AC 187 K	3a	AC 127, AC 176, AC 187, 2SD30, 2SD72
2 SD 188	Nip	Si-N	P, 100/80V, 7/12A, 60W, 10MHz	{2SB627 23a	TO-3	BD 245 C	18j	BD 245C, BD 317, 2N5758, 2SD895...896, ++
2 SD 189	Mat	Si-N	P, 80/80V, 5A, 50W, 12MHz	23a	TO-3	BD 245 C	18j	BD 245B, BDV 93, BDX 93, 2N5632...33, ++
2 SD 189 A		Si-N	=2SD189: 100/100V	23a	TO-3	BD 245 C	18j	BD 245C, BDV 95, BDX 95, 2N5632...33, ++
2 SD 190	Hit	Si-N	S,Vid P, 300V, 0.1A, 4W, 25MHz	-22	=TO-66	2SC1505	17j	2SC1505...1507, 2SC1755...1757, 2SC1819, ++
2 SD 191	Tos	Ge-N	LF, 30V, 0.15A, 0.15W	{2SB291 2a	TO-5	(AC 187 K)	3a	AC 127, AC 176, 2SD352
2 SD 192	Tos	Ge-N	LF, 30V, 0.15A, 0.15W	{2SB292 2a	TO-5	(AC 187 K)	3a	AC 127, AC 176, 2SD352
2 SD 193	Tos	Ge-N	LF, 35V, 0.4A, 0.25W, -/4.7µs	2a	TO-5	(AC 187 K)	3a	AC 127, AC 176, 2SD352
2 SD 194	Tos	Ge-N	LF, 32V, 0.4A, 0.25W	2a	TO-5	(AC 187 K)	3a	AC 127, AC 176, 2SD352
2 SD 195	Fui	Ge-N	LFS, 20V, 0.05A, 0.15W	2a	TO-1	(AC 187 K)	3a	AC 127, 2SD30
2 SD 196(A)	Fui	Si-N	P, 100/50V, 10A, 125...150W	38a	TO-36	(BD 249 C) ⁴	18j	(BD 249C, BD 745C, 2SD1049) ⁴
2 SD 197(A)	Fui	Si-N	=2SD196: 130/70V	38a	TO-36			(2SD1049) ⁴
2 SD 198	Mat	Si-N	S P, 300V, 1A, 25W(Tc=75°), 45MHz	23a	TO-3	BUW 11 A	18j	BU 126, 2SC2809, 2SD632
2 SD 199	Mat	Si-N	S P, 800V, 0.25/0.5A, 25W(Tc=75°), 7MHz	23a	TO-3			2SC3151
2 SD 200(A)	Mat	Si-N	TV-HA, 1500V, 2.5A, 10W(Tc=90°), sat<5V(2A)	23a	TO-3	BU 208 A	23a	BU 205...206, 2SC1922, 2SD575, 2SD818, ++
2 SD 201	Sak	Si-N	P, 90/60V, 6A, 50W, -/4µs	23a	TO-3	BD 245 C	18j	BD 245C, BDV 95, BDX 95, 2N5632...33, ++
2 SD 202	Sak	Si-N	=2SD201: 110/80V	23a	TO-3	BD 245 C	18j	BD 245C, 2N5633, 2SC2681, 2SD718, ++
2 SD 203	Sak	Si-N	=2SD201: 130/100V	23a	TO-3	2SC3263	18j	BD245D, BDX11, 2N4348, 2N5634, 2SD551, ++
2 SD 204	Nec	Si-N	P, 60/45V, 0.7A, 9W(Tc=25°)	2a	TO-5	(BD 139) ⁴	14h	(BD 137, BD 228, BD 517, BD 525,++) ⁴
2 SD 205	Nec	Si-N	=2SD204: 1W, 9W(Tc=25°)	2a	=TO-37	(BD 139) ⁴	14h	(BD 137, BD 228, BD 517, BD 525,++) ⁴
2 SD 206(A)	Shi	Si-N	P, 50/30V, 10A, 150W	23a	TO-3	BD 317	23a	BD 315, 2N5629...31, 2SC2608, 2SD1105, ++
2 SD 207(A)	Shi	Si-N	=2SD206: 100/60V	23a	TO-3	BD 317	23a	BD 317, 2N5629...31, 2SC2608, 2SD1105, ++
2 SD 208(A)	Shi	Si-N	=2SD206: 150/90V	23a	TO-3	MJ 15015	23a	BDW 12, MJ 15015, 2N3773, 2SC2607...08, ++
2 SD 211	Sak	Si-N	P, 60/40V, 10A, 100W, -/4.4µs	23a	TO-3	2N3055	23a	BD 311, BDW 21A, 2N3055, 2N5877...78, ++
2 SD 212	Sak	Si-N	=2SD211: 90/60V	23a	TO-3	2N3055	23a	BD 313, BDW 21C, 2N3055, 2N5632...33, ++
2 SD 213	Sak	Si-N	=2SD211: 110/80V	23a	TO-3	2SC3263	18j	BDW 21C, 2N3055, 2N5632...33, 2SD551, ++
2 SD 214	Sak	Si-N	=2SD211: 130/100V	23a	TO-3	2SC3263	18j	BDX 11, 2N3442, 2SD551, 2SD732...733, ++
2 SD 215	Fui	Si-N	LFS, 40/35V, 1A, 0.8W	2a	TO-39	BC 141	2a	BC 140...141, 2N1990, 2N2102, 2N2405, ++
2 SD 216	Fui	Si-N	=2SD215: 60/50V	2a	TO-39	BC 141	2a	BC 140...141, 2N1990, 2N2102, 2N2405, ++
2 SD 217	Nec	Si-N	P, 120/80V, 7/10A, 60W, 10MHz	{2SB648 23a	TO-3	2SC3263	18j	BD 245D, 2N3442, 2SD551, 2SD731...732, ++
2 SD 218	Nec	Si-N	=2SD217: 150/100V	{2SB649 23a	TO-3	2SC3263	18j	BD 245D, 2N3442, 2SD551, 2SD731...732, ++
2 SD 219	Sak	Si-N	LFS, 40/30V, 1A, 0.5W, 340/5000ns	2a	TO-5	BC 141	2a	BC 140...141, 2N1990, 2N2102, 2N2405, ++
2 SD 219 F		Si-N	=2SD222:	43a	=TO-37	BD 139 ⁴	14h	--2SD222
2 SD 220	Sak	Si-N	=2SD219: 80/50V	2a	TO-5	BC 141	2a	BC 140...141, 2N1990, 2N2102, 2N2405, ++
2 SD 220 F		Si-N	=2SD223:	43a	=TO-37	BD 139 ⁴	14h	--2SD223
2 SD 221	Sak	Si-N	=2SD219: 110/80V	2a	TO-5	BC 141	2a	BC 141, 2N1990, 2N2102, 2N2405, ++

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International		
2 SD 221 F		Si-N	=2SD224:	43a	=TO-37	BD 139 ^a	14h	=2SD224	
2 SD 222	Sak	Si-N	=2SD219: 1,5A, 10W	43a	=TO-37	BD 139 ^a	14h	(BD 135, BD 226, BD 233, BD 507,++) ^a	
2 SD 223	Sak	Si-N	=2SD219: 80/50V, 1,5A, 10W	43a	=TO-37	BD 139 ^a	14h	(BD 139, BD 230, BD 237, BD 527,++) ^a	
2 SD 224	Sak	Si-N	=2SD219: 110/80V, 1,5A, 10W	43a	=TO-37	BD 139 ^a	14h	(BD 139, BD 230, BD 237, BD 529,++) ^a	
2 SD 226	Mat	Si-N	P, 40/40V, 3A, 25W	22a	TO-66	BD 243 C	17j	BD 241, BD 243, BD 533, BD 933, ++	
2 SD 226 A		Si-N	=2SD226: 60/60V	22a	TO-66	BD 243 C	17j	BD 241A, BD 243A, BD 535, BD 935	
2 SD 226 B		Si-N	=2SD226: 80/80V	22a	TO-66	BD 243 C	17j	BD 241B, BD 243B, BD 537, BD 937	
2 SD 227	Nec, Mic	Si-N	Uni, 30/15V, 0,3/0,5A, 0,25W, 120MHz	(2SB642	7c°	TO-92	BC 639	7c	BC 337...338, BC 635, 2SC3377, 2SD1578,++
2 SD 228	Nec	Si-N	=2SD227: 0,4W	7c°	TO-92°	BC 639	7c	BC 337...338, BC 635, BC 637, BC 639, ++	
2 SD 231	Fui	Si-N	P, 50/40V, 30A, 125W, -/11µs	23a	TO-3			BDX 41, 2N3771, 2SD630	
2 SD 232	Fui	Si-N	=2SD231: 120/100V, -/13,5µs	23a	TO-3			BDW 30, 2N6032, 2N6274...6275	
2 SD 232 A		Si-N	=2SD231: 160/140V	23a	TO-3			BDW 32, BDY 58, 2N6276...6277	
2 SD 234	Mic, Tos	Si-N	P, 60/50V, 3A, 25W, 3MHz	(2SB434	17j	TO-220	BD 243 C	17j	BD 241A, BD 539A, BD 535, BD 935, ++
2 SD 235	Mic, Tos	Si-N	=2SD234: 50/40V	(2SB435	17j	TO-220	BD 243 C	17j	BD 241, BD 539A, BD 535, BD 935, ++
2 SD 236	Sak	Si-N	P, 40/30V, 1,5A, 10W, 340/5000ns	22a	TO-66	BD 243 C	17j	BD 239, BD 241, BD 933, 2N4231...33, ++	
2 SD 237	Sak	Si-N	=2SD236: 80/50V	22a	TO-66	BD 243 C	17j	BD 239B, BD 241B, BD 937, 2N4233, ++	
2 SD 238	Sak	Si-N	=2SD236: 110/80V	22a	TO-66	BD 243 C	17j	BD 239C, BD 241C, BD 939, 2SD381...382, ++	
2 SD 241	Sak	Si-N	LFS P, 60/40V, 4A, 25W	22a	SOT-9	BD 243 C	17j	BD 243A, BD 535, BDW 25, BDX 25, ++	
2 SD 242	Sak	Si-N	=2SD241: 90/60V	22a	SOT-9	BD 243 C	17j	BD 243C, BD 539B, BDW 25, BDX 25, ++	
2 SD 243	Sak	Si-N	=2SD241: 110/80V	22a	SOT-9	BD 243 C	17j	BD 243C, BD 539C, BDW 25, BDX 25, ++	
2 SD 244	Sak	Si-N	=2SD241: 130/100V	22a	SOT-9	(BU 406)	17j	BD 243D, BDW 25, BDX 25, 2SD960...961, ++	
2 SD 246	Mat	Si-N	TV-HA, 1500V, 4,5A, 16W(Tc=90°), sat<10V(4,5A)	23a	TO-3	BU 208 A	23a	BU 208...209(A), BU 508(A), 2SC2928, ++	
2 SD 247	old	Si-N	P, 80/60V, 5A, 50W	23a	TO-3	BD 245 C	18j	BD 245B, BDV 93, BDX 93, 2N5632...33, ++	
2 SD 249	Fui	Si-N	P, 50/40V, 30A, 125W, 0,8MHz	23a	TO-3			BDX 41, 2N3771, 2SD630	
2 SD 250	Fui	Si-N	=2SD249: 100/100V, 0,6MHz	23a	TO-3			BDY 29, MJ 802, 2SD797	
2 SD 251	Fui	Si-N	P, 200/200V, 2A, 30W, -/7,5µs	22a	TO-66	2SD1138	17j	BD 239F, BUX 67, 2SD610, 2SD1138, ++	
2 SD 254	Nec	Si-N	LF P, 70/50V, 2/3A, 20W	(2SB614	22a	=TO-66	BD 243 C	17j	BD 241A, BD 537, BD 937, BDY 78, ++
2 SD 255	Nec	Si-N	=2SD254:	(2SB615	22a	TO-66	BD 243 C	17j	BD 241A, BD 537, BD 937, BDY 78, ++
2 SD 256	Sak	Si-N	P, 60/40V, 4A, 25W, 1270/3300ns	22a	TO-66	BD 243 C	17j	BD 243A, BD 535, BD 539A, BDY 79, ++	
2 SD 257	Sak	Si-N	=2SD256: 90/60V	22a	TO-66	BD 243 C	17j	BD 243B, BD 539C, 2SD712, BDY 79, ++	
2 SD 258	Sak	Si-N	=2SD256: 110/80V	22a	TO-66	BD 243 C	17j	BD 243C, BD 539D, BD 955, BDY 79, ++	
2 SD 259	Sak	Si-N	=2SD256: 130/100V	22a	TO-66	(BU 406)	17j	BD 243D, BD 941, 2SC2516, 2SD960...961, ++	
2 SD 260	old	Si-N	P, 100/80V, 5A, 50W	23a	TO-3	BD 245 C	18j	BD 245C, BDV 95, BDX 95, 2N5632...33, ++	
2 SD 261	Nec, Mic	Si-N	Uni, 40/20V, 0,5/0,7A, 0,5W, 160MHz	(2SA643	7c°	TO-92°	BC 639	7c	BC 337, BC 535, 2SC3377, 2SD1225, ++
2 SD 262	Son	Si-N	S P, 300/140V, 12A, 125W	23a	TO-3			BUW 74...75, BUX 42, MJ 15022, 2SC3043, ++	
2 SD 265	Org	Si-N	S P, 800/400V, 6A, 100W, hFE=15...30	23a	TO-3	BU 426 A	18j	BU 326(A), BU 426(A), BU 526, BUX 47, ++	
2 SD 266	Org	Si-N	=2SD265: hFE=30...60	23a	TO-3	BU 426 A	18j	BU 326(A), BU 426(A), BU 526, BUX 47, ++	
2 SD 271	Org	Si-N	S P, 800/400V, 2A, 30W, hFE=15...30	22a	SOT-9	BUX 85	17j	BUV 36(A), BUX 84...85, 2SC3531	
2 SD 272	Org	Si-N	=2SD271: hFE=30...250	22a	SOT-9	BUX 85	17j	BUV 36(A), BUX 84...85, 2SC3531	
2 SD 273	Org	Si-N	S P, 800/400V, 5A, 80W, hFE=15...30	23a	TO-3	BU 426 A	18j	BU 426(A), BUS 11(A), BUW 11(A), ++	
2 SD 274	Org	Si-N	=2SD273: hFE=30...60	23a	TO-3	BU 426 A	18j	BU 426(A), BUS 11(A), BUW 11(A), ++	
2 SD 280	Org	Si-N-Darl	S P, 600/300V, 6A, 100W, hFE=350...3000	23a	TO-3			BUW 81, MJ 10013...14, 2SD605, 2SD705, ++	
2 SD 283	Nec	Si-N	P, 120/40V, 5/7A, 25W, hFE=42...80	22a	TO-66	BD 243 C	17j	BD 243C, BD 539D, BD 955, 2SD961, ++	
2 SD 284	Nec	Si-N	=2SD283: 20MHz, hFE=80-25	(2SB550	22a	TO-66	BD 243 C	17j	BD 243C, BD 539D, BD 955, 2SD961, ++
2 SD 285	Nec	Si-N	=2SD283: 100/40V	22a	TO-66	BD 243 C	17j	BD 243C, BD 539C, BD 953, 2SD613, ++	
2 SD 286	Nec	Si-N	P, 180/100V, 10A, 100W	23a	TO-3	2SC3263	18j	BD 245E, 2SC2607...08, 2SC3263, 2SD665, ++	
2 SD 287(A...C)	Nec	Si-N	P, 200V, 10/15A, 100W, 8MHz A=200/120V, B=200/140V, C=200/160V	(2SA651, 2SB539	23a	TO-3	2SC3263	18j	BD 245F, 2SC2607...08, 2SC3263, 2SD665, ++
2 SD 288	Nec, Mic	Si-N	P, 80/60V, 3/6A, 20W, 35MHz	17j	TO-220AB	BD 243 C ⁸	17j	2SC3252, 2SC3258, (BD 241B, BD 537,++) ⁸	
2 SD 289	Nec, Mic	Si-N	=2SD288:	17j	TO-220AA	BD 243 C ⁸	17j	2SC3252, 2SC3258, (BD 241B, BD 537,++) ⁸	
2 SD 290	Son	Si-N	P, 80/80V, 5A, 23W, 10MHz	22a	TO-66	BD 243 C	17j	BD 243B, BD 539B, BD 951, 2N4233A, ++	
2 SD 291	Son	Si-N	P, 70/40V, 3A, 18W, 4MHz	22a	TO-66	BD 243 C	17j	BD 241A, BD 537, BD 937, 2N4232...33, ++	
2 SD 292	Son	Si-N	=2SD291: 70/55V	22a	TO-66	BD 243 C	17j	BD 241A, BD 537, BD 937, 2N4232...33, ++	
2 SD 293	Org	Si-N	S P, 800/400V, 10A, 125W, hFE=14...27	23a	TO-3	S 2530 A	23a	BUS 12(A), BUW 26, BUW 35...36, BUX 81, ++	
2 SD 294	Org	Si-N	=2SD293: hFE=28...70	23a	TO-3	S 2530 A	23a	BUS 12(A), BUW 26, BUW 35...36, BUX 81, ++	
2 SD 295	Org	Si-N	S P, 800/400V, 30A, 200W, hFE=15...30	68a				2SC2204, 2SC2977	
2 SD 296	Org	Si-N	=2SD295: hFE=30...70	68a				2SC2204, 2SC2977	
2 SD 297	Nec	Si-N	S P, 150/80V, 3/5A, 25W, 40MHz	22a	TO-66	(BU 406)	17j	BD241D, 2N3441, 2SC2516, 2SD772(A,B), ++	
2 SD 299	Mat	Si-N	TV-HA, 1500V, 5A, 16W(Tc=90°), hFE>2, sat<10V(4,5A)	23a	TO-3	BU 208 A	23a	BU 208(A), BU 508(A), 2SC2928, 2SD820, ++	
2 SD 300	Mat	Si-N	=2SD299: hFE=3...8	23a	TO-3	BU 208 A	23a	BU 208(A), BU 508(A), 2SC2928, 2SD820, ++	
2 SD 301	Fui	Si-N-Darl	P, 80/70V, 10A, 50W, hFE=2500, -/30µs	23a	TO-3	BDW 83 C	18j	BDV 65A, BDX 83B, BDX 85B, MJ 3001, ++	
2 SD 310	Org	Si-N	S P, 800/400V, 15A, 150W, hFE=15...30	23a	TO-3			BUS 13(A), BUW 45...46, BUX 48(A...C)	
2 SD 311	Org	Si-N	=2SD310: hFE=30...60	23a	TO-3			BUS 13(A), BUW 45...46, BUX 48(A...C)	
2 SD 312	Mat	Si-N	S P, 800/600V, 0,5/1A, 25W(Tc=100°), 5MHz	23a	TO-3			2SC3151	
2 SD 313	Say, Mic	Si-N	P, 60/60V, 3/8A, 30W, 8MHz	(2SB507	17j	TO-220AB	BD 243 C	17j	BD241A, BD535, BD539A, BD935, 2SC3179, ++
2 SD 314	Say, Mic	Si-N	=2SD313:	(2SB508	17j	TO-220AA	BD 243 C	17j	=2SD313
2 SD 315	Say	Si-N	=2SD313: 4/10A, 35W	(2SB509	22a	TO-66	BD 243 C	17j	BD 243A, BD 535, BD 539A, 2N4232...33A, ++
2 SD 316(-1,-2)	Son	Si-N	P, 80...100V, 7A, 80W, 12MHz	23a	TO-3	BD 245 C	18j	BD 245C, BDV 95, BDX 95, 2N5632...33, ++	
2 SD 317	Mat	Si-N	P, 60/60V, 3A, 25W	17j	TO-220AB	BD 243 C	17j	BD 241A, BD 535, BD 539A, BD 935, ++	
2 SD 317 A		Si-N	=2SD317: 80/80V	17j	TO-220AB	BD 243 C	17j	BD 241B, BD 537, BD 539B, BD 937, ++	
2 SD 318	Mat	Si-N	=2SD317:	17j	TO-220AA	BD 243 C	17j	BD 241A, BD 535, BD 539A, BD 935, ++	
2 SD 318 A		Si-N	=2SD318: 80/80V	17j	TO-220AA	BD 243 C	17j	BD 241B, BD 537, BD 539B, BD 937, ++	
2 SD 319	Mat	Si-N	P, CTV, 110/80V, 10/30A, 100W, 1MHz	23a	TO-3	2N3055	23a	BD 317, 2N3055, 2N5632...33, 2SD426, ++	
2 SD 320	Say	Si-N	S P, 300/230V, 2/5A, 50W	23a	TO-3	(BU 608)	23a	2SC1463, 2SC2809, 2SD632	
2 SD 321	Mat	Si-N	S P, 250V, 6/15A, 60W, 8MHz	23a	TO-3	BU 608	23a	BU 606...608, BUX 18(A...C), 2SD1154, ++	
2 SD 322	Nec	Si-N	P, 120/80V, 7A, 80W	23a	TO-3	2SC2837	18j	BD 245D, 2N3442, 2SD551, 2SD731...733, ++	
2 SD 323	Nec	Si-N	=2SD322: 150/100V	23a	TO-3	2SC2837	18j	BD 245D, 2N3442, 2SD551, 2SD731...733, ++	
2 SD 324	Mat	Si-N	Vid P, 300V, 0,1/0,15A, 10W(Tc=70°), 30MHz	22a	TO-66	2SC1505	17j	2SC1505...1507, 2SC1755...1757, 2SC1819, ++	
2 SD 325	Say	Si-N	P, 35/35V, 1,5/3A, 10W, 8MHz	(2SB511	17j	TO-220	BD 243 C	17j	BD 239, BD 241, BD 533, BD 933, ++
2 SD 326	Son	Si-N	S P, 330/220V, 1A, 23W, 6,5MHz	22a	SOT-9	(BUX 85)	17j	TIP 47...50, 2SC782, 2SC867, 2SD859, ++	
2 SD 327	Nec, Mic	Si-N	Uni, 40/20V, 0,5/0,7A, 0,25W, 120MHz	(2SB723	7c	TO-92	BC 639	7c	BC 337, BC 635, 2SC3377, 2SD1225, ++
2 SD 328	Nec	Si-N	LFS, 100/60V, 1/1,5A, 0,8W, 50MHz	(2SB510	2a	TO-39	BC 141	2a	BC 141, 2N1990, 2N2102, 2N2405, ++
2 SD 329	Fui	Si-N	LFS, 70V, 1A, 0,8W, 30MHz, -/6,5µs	2a	TO-39	BC 141	2a	BC 140...141, 2N1990, 2N2102, 2N2405, ++	
2 SD 330	Say, Mic	Si-N	P, 50/50V, 2/5A, 20W, 8MHz	(2SB514	17j	TO-220AB	BD 243 C	17j	BD 239, BD 241, BD 535, BD 935, 2SC1398, ++
2 SD 331	Say, Mic	Si-N	=2SD330:	(2SB815	17j	TO-220AA	BD 243 C	17j	=2SD330
2 SD 332	Say	Si-N	P, 130/100V, 7A, 65W, 30MHz	23a	TO-3	2SC3263	18j	BD 245D, 2N3442, 2SD551, 2SD731...733, ++	
2 SD 334	Mat	Si-N	P, 110/80V, 6A, 75W	23a	TO-3	2SC3263	18j	BD 245C, 2N3442, 2SD551, 2SD731...733, ++	
2 SD 334 A		Si-N	=2SD334: 130/100V	23a	TO-3	2SC3263	18j	BD 245D, 2N3442, 2SD551, 2SD731...733, ++	
2 SD 335	Nec	Si-N	P, 80/60V, 3A, 30W	23a	TO-3	BD 245 C	18j	BD 245B, BDV 93, 2N4915, 2SD895...896, ++	
2 SD 336	Nec	Si-N	Uni, LF Drv, Out, 40/20V, 0,5A, 0,75W	(2SA707	7c°	TO-92°	BC 337	7a	BC 337, BC 635, BC 637, BC 639, ++
2 SD 338(-1,-2)	Son	Si-N	P, 70...90V, 7A, 60W, >3MHz	(2SB518	23a	TO-3	BD 245 C	18j	BD 245C, BDV 95, BDX 95, 2N5632...34, ++
2 SD 339(-1,-2)	Son	Si-N	=2SD338: 90...110V, 10A, 80W	(2SB519	23a	TO-3	BD 245 C	18j	BD 245C, BDV 95, BDX 95, 2N5632...34, ++
2 SD 340(-1,-2)	Son	Si-N	=2SD338: 110...140V, 12A, 100W	(2SB520	23a	TO-3	2SC3263	18j	BD 745E, 2N3442, 2SD551, 2SD733, ++

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International	
2 SD 341	Hit	Si-N	P, 100/60V, 15A, 115W, >0.8MHz	23a	TO-3	2N3055	23a	BD 317, BDW 10, 2N3055, 2SD1105, ++
2 SD 342	Son	Si-N	P, 70/40V, 3A, 35W	17j	TO-220AB	BD 243 C	17j	BD 241A, BD 537, BD 539A, BD 937, ++
2 SD 343	Son	Si-N	=2SD342:	17j	TO-220AA	BD 243 C	17j	BD 241A, BD 537, BD 539A, BD 937, ++
2 SD 344	Son	Si-N	=2SD342: 70/55V	17j	TO-220AB	BD 243 C	17j	BD 241A, BD 537, BD 539A, BD 937, ++
2 SD 345	Son	Si-N	=2SD342: 70/55V	17j	TO-220AA	BD 243 C	17j	BD 241A, BD 537, BD 539A, BD 937, ++
2 SD 346	Son	Si-N	P, 60/60V, 5A, 25W	17j	TO-220AB	BD 243 C	17j	BD 243A, BD 539A, BD 543A, BD 949, ++
2 SD 347	Son	Si-N	=2SD346:	17j	TO-220AA	BD 243 C	17j	BD 243A, BD 539A, BD 543A, BD 949, ++
2 SD 348	Say	Si-N	TV-HA, 1500/400V, 7/14A, 50W, sat<3.7V(5A)	23a	TO-3	BU 508 A	18j	BU 508(A), BU 908, 2SC3027...3028
2 SD 349	Nec	Si-N	SMD, LF, 30/25V, 0,05A	35a	SOT-23	BC 846	35a	BC 846...848, BCW 31...33, 2SC1622, ++
2 SD 350(A)	Mat	Si-N	TV-HA, 1500/700V, 5/11A, 22W(Tc=90°), sat<7V(4,5A) A: sat<1V(4,5A)	23a	TO-3	2SD350 A*	23a	BU 208(A), BU 508(A), 2SC2928, 2SD954,++
2 SD 351	Mat	Si-N	S P, 650/270V, 5/7A, 80W, 40MHz	23a	TO-3	BU 426 A	18j	BU 326(A), BU 426(A), 2SC2962, 2SC3092++
2 SD 352	Mat	Ge-N	LF, 32V, 1A, 0,22W	(2SB324 2a	TO-1	(AC 187 K) ⁷	3a	AC 176
2 SD 353	Say	Si-N	P, TV-VA, 150/150V, 2/6A, 60W, 8MHz	23a	TO-3	(BU 608)	23a	2SC1195, 2SC2809, 2SD1136, 2SD1159, ++
2 SD 355	Mit	Si-N	Uni, 30725V, 1/1,5A, 0,8W, 100MHz	(2SB525 7b	TO-92	BC 639	7c	BC 337...338, BC 635, BC 637, BC 639, ++
2 SD 356	Mit, Mic	Si-N	P, 90/80V, 0,8A, 10W, 70MHz	(2SB526 17j	=TO-220	2SC2592	17j	2SC1913(A), 2SC2275(A), 2SC2591...92, ++
2 SD 357	Mit	Si-N	=2SD356: 110/100V	(2SB527 17j	=TO-220	(2SD1138)	17j	2SC1913(A), 2SC2275(A), 2SC2591...92, ++
2 SD 358	Mit	Si-N	=2SD356: 130/120V	(2SB528 17j	=TO-220	(2SD1138)	17j	2SC1913(A), 2SC2275(A), 2SC2591...92, ++
2 SD 359	Mit, Mic	Si-N	P, 40/20V, 2/3A, 10W, 70MHz	(2SB529 17j	=TO-220	2SC1398	17j	2SC1398, 2SC3252, 2SD1505, 2SD1912
2 SD 360	Mit, Mic	Si-N	P, 40/20V, 2/3A, 10W, 70MHz	(2SB523 17j	=TO-220	2SC1398	17j	2SC1398, 2SC3252, 2SD1505, 2SD1912
2 SD 361	Mit	Si-N	P, 60/40V, 1,5/3A, 10W, 70MHz	(2SB524 17j	=TO-220	2SC1398	17j	2SC1398, 2SC3252
2 SD 362	Nec	Si-N	S P, 150/100V, 5/8A, 40W, 15MHz	22a	TO-66	BU 406	17j	BU 406...409, MJE 15030, 2SD772(A,B), ++
2 SD 363	Nec	Si-N	S P, 250/200V, 30A, 200W, <2/10,5µs	68a				2SD374
2 SD 363 A		Si-N	=2SD363: 350/300V	68a				2SD374
2 SD 364	Nec	Si-N	=2SD363: 450/400V	68a				2SD374
2 SD 365	Mat, Mic	Si-N	P, 60/60V, 3/6A, 25W, >3MHz	(2SB512 17j	TO-220AB	BD 243 C	17j	BD 241A, BD 535, BD 539A, BD 935, ++
2 SD 365 A		Si-N	=2SD365: 80/80V	17j	TO-220AB	BD 243 C	17j	BD 241B, BD 537, BD 539B, BD 937, ++
2 SD 366(A)	Mat, Mic	Si-N	=2SD365(A):	(2SB513 17j	TO-220AA	BD 243 C	17j	+2SD365(A)
2 SD 367	Mat	Ge-N	LF, 25V, 0,3W, 0,15W	(2SB475 2a	TO-1	AC 187 K	3a	AC 127, AC 176, AC 187, 2SD72, 2SD352
2 SD 368	Say	Si-N	TV-HA, 1300/400V, 5/10A, 50W	23a	TO-3	BU 208 A	23a	BU 207...208(A), BU 508(A), 2SC2928, ++
2 SD 369	Tos	Si-N	P, 80/60V, 10A, 100W, 2MHz	23a	TO-3	BD 317	23a	BD 315, BDW 21C, 2N3055, 2N5632...34, ++
2 SD 370	Tos	Si-N	P, 110/100V, 8A, 80W	23a	TO-3	BD 245 C	18j	BD 245C, BD 550, 2N3055, 2N5633...34, ++
2 SD 371	Tos	Si-N	P, 100/100V, 6A, 50W, 5MHz	(2SB531 23a	TO-3	BD 245 C	18j	BD 245C, BDV 95, BDX 95, 2N5632...34, ++
2 SD 372	Nec	Si-N	S P, 150/100V, 30/60A, 200W, 0,3/2µs	68a				2SD363
2 SD 373	Nec	Si-N	=2SD372: 250/200V	68a				2SD363
2 SD 373 A		Si-N	=2SD372: 350/300V	68a				-
2 SD 374	Nec	Si-N	=2SD372: 450/400V	68a				-
2 SD 375	Nec	Si-N	S P, 150/100V, 10/15A, 100W, 15MHz, 0,3/3,2µs	23a	TO-3			BUW 70, BUX 17(A...C), BUX 43, BUY 18, ++
2 SD 376	Nec	Si-N	=2SD375: 250/200V	23a	TO-3			BUW 72, BUX 17(A...C), BUX 43, BUY 18, ++
2 SD 376 A		Si-N	=2SD375: 350/300V	23a	TO-3			BUW 72, BUX 14, BUX 17A...C, BUX 43, ++
2 SD 377	Nec	Si-N	=2SD375: 450/400V	23a	TO-3			BUW 72, BUX 14, BUX 17C, 2SC3046, ++
2 SD 378	Nec	Si-N	LF.S, 100/60V, 2A, 1W	2a	TO-39	(2SC4135) ⁴	30j	BCX 40, BSS 15, BSV 84, 2N5320, ++
2 SD 379	Mat	Si-N	P, 80/80V, 5/7A, 60W, 10MHz	(2SB532 23a	TO-3	BD 245 C	18j	BD 245B, BD 313, BDV 93, BDX 93, ++
2 SD 380(A)	Mat	Si-N	TV-HA, 1500/700V, 5/13A, 50W(Tc=75°), sat<10V(5A) A: 1500/650V, 5/16A, sat<4.5V(4,5A)	23a	TO-3	BU 208 A	23a	BU 208(A), BU 508(A), 2SC2928, 2SD954,++
2 SD 381	Nec	Si-N	P, 130/120V, 1,5/3A, 20W, 45MHz	(2SB536 17j	TO-220AB	2SD1138	17j	2SC2238(A), 2SC2275(A), 2SD608(A), ++
2 SD 382	Nec	Si-N	=2SD381:	(2SB537 17j	TO-220AA	2SD1138	17j	+2SD381
2 SD 383	Hit	Si-N	S P, 300/300V, 5A, 100W	23a	TO-3	BU 608	23a	BU 606...608, BUX 16A...C, BUY 35, ++
2 SD 384	Shi	Si-N-Darl	P, 80/80V, 7A, 30W, hFE=1,5k...1,5k, <3/9µs	22a	TO-66	BD 901	22a	BD 647, BD 899, BDW 73B, BDX 53B, ++
2 SD 385	Shi	Si-N-Darl	=2SD384: 100/100V	22a	TO-66	BD 901	22a	BD 649, BD 901, BDW 73C, BDX 53C, ++
2 SD 386(A)	Say	Si-N	TV-VA, 200/120(A=200/150)V, 3/10A, 25W, 8MHz	17j	TO-220AB	(2SD1138) ⁷	17j	BD 241F, 2SD772A,B
2 SD 387(A)	Say	Si-N	=2SD386(A): 2A	(2SD1138 17j	TO-220AA	2SD1138	17j	BD239F, 2SC2660, 2SD610, 2SD760, 2SD1138
2 SD 388	Nec	Si-N	P, 150/100V, 8/12A, 80W, 9MHz	(2SB541 23a	TO-3	2SC3263	18j	BD 245D, 2N3442, 2SD551, 2SD732...733, ++
2 SD 389	Mat	Si-N	P, 60/60V, 3A, 25W	17j	TO-220AB	BD 243 C	17j	BD 241A, BD 539A, BD 535, BD 935, ++
2 SD 389 A		Si-N	=2SD389: 80/80V	17j	TO-220AB	BD 243 C	17j	BD 241B, BD 539B, BD 537, BD 937, ++
2 SD 390(A)	Mat	Si-N	=2SD389(A):	17j	TO-220AA	BD 243 C	17j	+2SD389(A)
2 SD 392	Mit	Si-N	Uni, 20/15V, 0,3/0,5A, 0,3W, 150MHz	(2SB542 7b	TO-92	BC 639	7c	BC 337...338, BC 635, BC 637, BC 639, ++
2 SD 393	Mit	Si-N	S P, 500/350V, 6A, 100W	23a	TO-3	BU 426 A	18j	BU 326(A), BU 426(A), BUX 15, 2SC3041, ++
2 SD 394	Mit	Si-N	S P, 700/400V, 6A, 100W	23a	TO-3	BU 426 A	18j	BU 326(A), BU 426(A), BUX 47, 2SC3092, ++
2 SD 395	Mit	Si-N	S P, 700/400V, 8A, 100W	23a	TO-3	BU 426 A	18j	BU 526(A), BUW 26, BUW 35...36, 2SC3049, ++
2 SD 396	Hit	Si-N	S P, 700/300V, 15A, 125W, <15/40µs	23a	TO-3			BUS 13(A), BUW 45...46, BUX 48(A...C), ++
2 SD 400(MP)	Say	Si-N	25/25V, 1/2A, 0,9W, 180MHz, sat<0,3V(0,5A)	(2SB544 7c(9mm)	TO-92L	2SD1207	7c(9mm)	2SC4483...85, 2SD1207
2 SD 400 P1, P2		Si-N	=2SD400(MP): 1W	7c ⁶	TO-92 ⁶	(2SC4135) ⁴	30j	(BD 505, BD 515, BD 525, 2SC2194, ++) ⁶
2 SD 401(A)	Nec	Si-N	TV-VA, 200/150V, 2/3A, 20(A=25)W, 5MHz	(2SB546 17j	TO-220AB	2SD1138	17j	BD 239F, 2SC2660, 2SD610, 2SD1138, ++
2 SD 402(A)	Nec	Si-N	=2SD401(A):	(2SB547 17j	TO-220AA	2SD1138	17j	+2SD401(A)
2 SD 404	Tos	Si-N	P, 50/40V, 6A, 40W	17j	TO-220	BD 243 C	17j	BD 243A, BD 543A, BD 797, BD 805, ++
2 SD 405	Nec	Si-N-Darl	LF.S, 70/70V, 2/3A, 1W, hFE=2k...12k, 0,4/3µs	2a	TO-39	(BD 679) ⁶	14h	2SC1879, 2SC1888, 2SD614...615, 2SD688
2 SD 406	Nec	Si-N-Darl	=2SD405: 100/100V	2a	TO-39	(BD 679) ⁶	14h	2SC1879, 2SD614...615, 2SD688
2 SD 407	Nec	Si-N-Darl	P, 100/100V, 5/8A, 25W, hFE=4000, 1,7/6µs	2a	TO-8	(BD 901) ⁴	17j	(BD 649, BD 901, BDW 23C, BDW 63C, ++) ⁴
2 SD 408	Nec	Si-N-Darl	=2SD407: 150/150V, hFE=3000	2a	TO-8			(2SD830, 2SD1128, 2SD1169, 2SD1590, ++) ⁴
2 SD 409	Nec	Si-N-Darl	=2SD407: 30W	22a	TO-66	BD 901	17j	BD 649, BD 901, BDW 23C, BDW 63C, ++
2 SD 410	Nec	Si-N-Darl	=2SD407: 150/150V, 30W, hFE=3000	22a	TO-66			2SD830, 2SD1128, 2SD1169, 2SD1590, ++
2 SD 411	Nec	Si-N-Darl	P, 100/80V, 10/15A, 80W, hFE=4000>1000, 1/7µs	23a	TO-3	BDW 83 C	18j	BDV 65B, BDW 83C, BDX 83C, BDX 85C, ++
2 SD 412	Nec	Si-N-Darl+Di	P, 150/100V, 15/20A, 100W, hFE=4000>1000	23a	TO-3			2SD1296, 2SD1299
2 SD 413	Fui	Si-N	S, Vid, 200/200V, 0,5A, 0,8W, 25MHz, -/7µs	2a	TO-39	MPS-U10 ⁶	13m	2SD576, 2SD624, (BF 757...759, MPS-U10+) ⁶
2 SD 414	Nec	Si-N	LF P, 120/80V, 0,8/1,5A, 10W, 45MHz	(2SB548 14h	TO-126	2SC3117	14h	-- 2SC2690(A), 2SD1382, 2SD1563(A)
2 SD 415	Nec	Si-N	=2SD414: 120/100V	(2SB549 14h	TO-126	2SC3117	14h	2SC2690(A), 2SD1382, 2SD1563(A)
2 SD 416	Say	Si-N	TV-HA, 1500/400V, 7/13A, 50W	23a	TO-3	BU 508 A	18j	BU 508(A), BU 908, 2SC3027...3028
2 SD 417	Fui	Si-N	S P, 250/200V, 7A, 75W, 30MHz, <2.5/4,5µs	23a	TO-3	BU 608	23a	BU 606...608, BUX 18(A...C), 2SD1154, ++
2 SD 418	Mat	Si-N	TV-HA, 1000/500V, 5/10A, 80W	23a	TO-3	BU 208 A	23a	BU 207...208(A), BU 508(A), 2SC1413, ++
2 SD 419	Sak	Si-N-Darl	P, 100/80V, 7/10A, 40W, 6MHz, hFE=2500, -/16µs	22a	TO-66	BD 901	17j	BD 649, BD 901, BDW 73C, BDX 53C, ++
2 SD 420	Sak	Si-N-Darl	=2SD419: 120/100V	22a	TO-66			BD 651, BDT 21, BDW 73D, BDX 53E, ++
2 SD 421	Sak	Si-N-Darl	=2SD419: 140/120V	22a	TO-66			BDX 53E,F, 2SD1386, 2SD1590...1591
2 SD 422	Fui	Si-N	S P, 250/200V, 4A, 30W, 30MHz, <2,5/4,5µs	22a	TO-66	BU 406	17j	BU 406...409, 2N6233...35, 2SC2767, ++
2 SD 423	Fui	Si-N	=2SD422: -/2,5µs	22a	TO-66	BU 406	17j	BU 406...409, 2N6233...35, 2SC2767, ++
2 SD 424	Tos	Si-N	HiFi Audio Out, 180/180V, 15A, 150W, 5MHz	(2SB554 23a	TO-3	MJ 15015	23a	BDW 12, MJ15015, 2N3773, 2SC2607...2608, ++
2 SD 425	Tos	Si-N	=2SD424: 140/140V, 12A, 100W	(2SB555 23a	TO-3	2SC3263	18j	BDW 12, BDV 54, 2SC1584, 2SD551, ++
2 SD 426	Tos	Si-N	=2SD424: 120/120V, 12A, 100W	(2SB556 23a	TO-3	2SC3263	18j	BDW 10, 2SD551, 2SD732, 2SD1105, ++
2 SD 427(S)	Tos	Si-N	=2SD424: 120/120V, 8A, 80(S=100)W	(2SB557 23a	TO-3	2SC3263	18j	BD 550, 2N5633...34, 2SD551, 2SD733, ++
2 SD 428	Tos	Si-N	=2SD424: 100/100V, 7A, 60W, 7MHz	(2SB558 23a	TO-3	BD 245 C	18j	BD 245C, BDV 95, BDX 95, 2N5632...33, ++
2 SD 429	Hit	Si-N	S P, 800/400V, 15A, 100W, <20/15µs	23a	TO-3			BUS13(A), BUW 45...46, BUX 48(A...C), ++
2 SD 430	old	Si-N	S P, 120/80V, 5A, 50W, 15MHz	23a	TO-3	2SC3263	18j	BD 245D, 2N4347, 2N5759, 2SD896, ++
2 SD 431	old	Si-N	S P, 120/80V, 7A, 60W, 20MHz	23a	TO-3	2SC3263	18j	BD 245D, 2N43

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International
2 SD 432	old	Si-N	S P, 130/100V, 10A, 100W, 15MHz	23a		18j	BD 245D, 2N3442, 2SD551, 2SD733, ++
2 SD 433	old	Si-N	S P, 250/150V, 10A, 100W, 15MHz	23a			BUX 17(A...C), 2SC1586, 2SD555, 2SD583, ++
2 SD 434	old	Si-N	S P, 200/200V, 20A, 200W	23a			BUV 11...12, BUW 58, BUW 73, BUX 11...12
2 SD 435	old	Si-N	=2SD434: 300/300V	23a			BUV 12, BUW 24, BUW 73, BUX 12, BUX 24
2 SD 436	old	Si-N	=2SD434: 400/400V	23a			BUV 24, BUX 24, 2SC3085
2 SD 437(W)	Say	Si-N	S P, 600/350(W-500/350)V, 10A, 80W, 2.5MHz	23a	S 2530 A	23a	BUW 12(A), BUW 25...26, BUX 80, 2SC3046++
2 SD 438(MP)	Say	Si-N	Uni, 100/80V, 0.7/1A, 0.9W, 100MHz, sat<0.6V(0.5A)	7c(9mm)	2SD1812	7c(9mm)	2SC4488, 2SC4489, 2SD667, 2SD1812
			MP=0.75W	(2SB560)			
2 SD 439	Say	Si-N	P, 20/18V, 1.2/2A, 8W, 150MHz, sat<0.5V(1A)	14h		14h	BD 135, BD 226, BD 375, 2SD1380, ++
2 SD 445	Org	Si-N-Darl	S P, 350/300V, 4A, 60W, hFE=350...3000	23a			BUW 28...29, 2SD650, 2SD706, 2SD1043, ++
2 SD 457	Nec	Si-N	S P, 250/200V, 55A, 200W	68a			
2 SD 458	Mat	Si-N	S P, 600/400V, 5/10A, 80W	23a			
2 SD 459	Shi	Si-N-Darl	P, 80/80V, 7A, 50W, hFE=1.5k...15k, 3/9µs	17j			
2 SD 460	Shi	Si-N-Darl	=2SD459: 100/100V	17j			
2 SD 461	Hit	Si-N	S P, 250/250V, 3A, 80W, 1MHz	23a			
2 SD 463	Shi	Si-N-Darl	P, 80/60V, 7A, 80W, hFE=3000, <10/16µs	23a			
2 SD 464	Shi	Si-N-Darl	=2SD463: 100/80V	23a			
2 SD 465	Shi	Si-N-Darl	S P, 500/400V, 50A, 400W, 5MHz, hFE>150, 1.5/11µs	-74			
2 SD 466	Shi	Si-N-Darl	=2SD465: 600/450V	-74			
2 SD 467	Hit	Si-N	Uni, 25/20V, 0.7/1A, 0.5W, 280MHz	(2SB561) 7c			
2 SD 468	Hit	Si-N	=2SD467: 1/1.5A, 0.9W, 190MHz	(2SB562) 7c(9mm)			
2 SD 469	Nec	Si-N	S P, 150/110V, 10/15A, 100W, 18MHz, 0.5/3.5µs	23a			
2 SD 470(-B)	Mat	Si-N	TV-HA, 1600/700V, 1A, 15W, sat<2V(0.8V)	22a			
2 SD 471	Nec	Si-N	Uni, 30/25V, 1/1.5A, 1W, 130MHz	(2SB564) 9b			
2 SD 472	Hit	Si-N-Darl+Di	P, 150/100V, 10/15A, 80W, hFE=1000, 2/9µs	23a			
2 SD 473	Hit	Si-N-Darl+Di	=2SD472: 100/100V, 15/20A, 100W	23a			
2 SD 474	Hit	Si-N	Uni, 30/30V, 0.1A, 0.05W, >100MHz	9b			
2 SD 475(A)	Hit	Si-N	P, 70/50(A=70/60)V, 4/8A, 40W, 7MHz	(2SB565) 17j			
2 SD 476(A)	Hit	Si-N	=2SD475(A):	(2SB566) 17j			
2 SD 477	Hit	Si-N	S P, 200/150V, 2/5A, 30W	(2SB567) 17j			
2 SD 478	Hit	Si-N	=2SD477:	(2SB568) 17j			
2 SD 479	Mot	Si-N-Darl	P, 40/40V, 4A, 40W, hFE=6000, (=2N6037)	(2SB569) 14h			
2 SD 480	Mot	Si-N-Darl	=2SD479: 60/60V, (=2N6038)	(2SB570) 14h			
2 SD 481	Mot	Si-N-Darl	=2SD479: 80/80V, (=2N6039)	(2SB571) 14h			
2 SD 482	Mot	Si-N	Vid P, 275/250V, 0.5A, 20W, (=2N5650)	14h			
2 SD 483	Mot	Si-N	=2SD482: 325/300V, (=2N5656)	14h			
2 SD 484	Mot	Si-N	=2SD482: 375/350V, (=2N5657)	14h			
2 SD 485	Mot	Si-N	P, 40/40V, 4A, 40W, (=2N5190)	(2SB575) 14h			
2 SD 486	Mot	Si-N	=2SD485: 60/60V, (=2N5191)	(2SB576) 14h			
2 SD 487	Mot	Si-N	=2SD485: 80/80V, (=2N5192)	(2SB577) 14h			
2 SD 488	Mot	Si-N	P, 40/40V, 3A, 30W, (=2N4921)	(2SB572) 14h			
2 SD 489	Mot	Si-N	=2SD488: 60/60V, (=2N4922)	(2SB573) 14h			
2 SD 490	Mot	Si-N	=2SD488: 80/80V, (=2N4923)	(2SB574) 14h			
2 SD 491	Mot	Si-N	P, 70/60V, 10A, 90W, (=MJE 3055)	(2SB57) 16h			
2 SD 492	Mot	Si-N	=2N3055	23a			
2 SD 493	Mot	Si-N	P, 60/40V, 5A, 75W, (=2N5977)	(2SB579) 16h			
2 SD 494	Mot	Si-N	=2SD493: 80/60V, (=2N5978)	(2SB580) 16h			
2 SD 495	Mot	Si-N	=2SD493: 100/80V, (=2N5979)	(2SB581) 16h			
2 SD 496	Mot	Si-N-Darl	P, 60/60V, 8A, 75W, hFE=3000, (=MJE 3043)	(2SB582) 16h			
2 SD 497	Mot	Si-N-Darl	=2SD496: 80/80V, (=MJE 3044)	(2SB583) 16h			
2 SD 498	Mot	Si-N-Darl	=2SD496: 100/100V, (=MJE 3045)	(2SB584) 16h			
2 SD 499	Mot	Si-N	P, 60/40V, 8A, 90W, (=2N5983)	16h			
2 SD 500	Mot	Si-N	=2SD499: 80/60V, (=2N5984)	16h			
2 SD 501	Mot	Si-N	=2SD499: 100/80V, (=2N5985)	16h			
2 SD 502	Mat	Si-N-Darl	P, 60/60V, 8A, 100W, hFE=3000, (=2N6055)	(2SB585) 23a			
2 SD 503	Mot	Si-N-Darl	=2SD502: 80/80V, (=2N6056)	(2SB586) 23a			
2 SD 504	Mot	Si-N-Darl	P, 60/60V, 12A, 150W, hFE=3000, (=2N6057)	(2SB587) 23a			
2 SD 505	Mot	Si-N-Darl	=2SD504: 80/80V, (=2N6058)	(2SB588) 23a			
2 SD 506	Mot	Si-N-Darl	=2SD504: 100/100V, (=2N6059)	(2SB589) 23a			
2 SD 507	Mit	Si-N	S P, 90/80V, 250A, 625W, >0.5MHz, <5/10µs	53b			
2 SD 508	Mit	Si-N	=2SD507: 110/100V	53b			
2 SD 509	Mit	Si-N	=2SD507: 130/120V	53b			
2 SD 510	Mit	Si-N	=2SD507: 150/140V	53b			
2 SD 511	Mit	Si-N	S P, 90/80V, 250A, 625W, >0.5MHz, <5/10µs	53b			
2 SD 512	Mit	Si-N	=2SD511: 110/100V	53b			
2 SD 513	Mit	Si-N	=2SD511: 130/120V	53b			
2 SD 514	Mit	Si-N	S P, 90/80V, 250A, 625W, >0.5MHz, <5/10µs	53b			
2 SD 515	Mit	Si-N	=2SD514: 110/100V	53b			
2 SD 516	Nec	Si-N	P, 20/16V, 1.5/3A, 5W, hFE=100...500, sat<0.5V(1A)	14h			
2 SD 517	Mat	Si-N	TV-HA, 1500/700V, 3/5A, 16W(Tc=90°), sat<5V(2A)	23a			
2 SD 518	Fui	Si-N	S P, 220/200V, 4A, 30W, 30MHz, <2.5/4.5µs	22a			
2 SD 519	Fui	Si-N	S P, 600/400V, 10A, 100W, <3.5/6.5µs	23a			
2 SD 520	Mit	Si-N-Darl	S P, 600/400V, 7A, 100W, hFE=350...1500	23a			
2 SD 521	Mit	Si-N-Darl	S P, 700/450V, 8/12A, 100W, hFE=200...1200	23a			
2 SD 522	Tos	Si-N	P, 100/60V, 10A, 100W	23a			
2 SD 523	Tos	Si-N-Darl+Di	P, 80/80V, 7A, 50W, hFE=2k...15k, 0.8/5.5µs	23a			
2 SD 524	Tos	Si-N-Darl+Di	P, 80/80V, 15A, 100W, hFE>2k, 0.8/7µs	23a			
2 SD 525	Tos	Si-N	HiFi Audio Out, 100/100V, 5A, 40W, 12MHz	(2SB595) 17j			
2 SD 526	Mic, Tos	Si-N	HiFi Audio Out, 80/80V, 4/8A, 30W, >3MHz	(2SB596) 17j			
2 SD 528	Hit	Si-N-Darl	S P, 600/500V, 8/12A, 100W, hFE=350	23a			
2 SD 529	Son	Si-N	S P, 850/320V, 5A, 85W, 4MHz, -/<5.5µs	23a			
2 SD 530	Fui	Si-N-Darl	P, 100/80V, 10A, 50W, hFE>750	23(3pins)			
2 SD 531(-1,-2)	Son	Si-N	P, -1: 100/60V, -2: 100/85V, 5A, 43W, 9MHz	17j			
2 SD 532	Son	Si-N	S P, 200/70V, 7A, 70W, 9MHz	23a			
2 SD 533	Son	Si-N	S P, 270/90V, 10A, 100W, 8MHz	23a			
2 SD 534	Son	Si-N	P, 110/110V, 12A, 100W, 5MHz	23a			
2 SD 535	Nec	Si-N	S P, 250/120V, 12/16A, 150W, 18MHz, 1.5/8µs	23a			
2 SD 536	Fui	Si-N	S P, 200/200V, 10A, 100W, 27MHz, -/1.8µs	23a			
2 SD 537	Fui	Si-N	=2SD536: 200/150V	23a			
2 SD 538(A)	Fui	Si-N	S P, 500/400V, 10A, 100(A=150)W, 15MHz, <2.2/4.5µs	23a			
2 SD 539(A)	Fui	Si-N	=2SD538(A): 400/350V	23a			
2 SD 540	Fui	Si-N	S P, 200/200V, 30A, 200W, 25MHz, -/2.2µs	68a			
2 SD 541	Fui	Si-N	=2SD540: 200/150V	68a			

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International
2 SD 542	Fui	Si-N	S P, 400/400V, 30A, 200W, 20MHz, -/3μs	68a			2SC1302, 2SC1401, 2SC1470, 2SC2250, ++
2 SD 543	Fui	Si-N	=2SD542: 400/350V	68a			2SC1302, 2SC1401, 2SC1470, 2SC2250, ++
2 SD 544(-1,-2)	Son	Si-N	=2SD531: ...	17j	TO-220AA	BD 243 C	-2SD531
2 SD 545(NP)	Say, Mic	Si-N	25/20V, 1/1.5A, 0.5W, 180MHz, sat<0.3V(0.5A) NP: TO-92	7c(9mm)	TO-92L	2SD1207	7c(9mm) 2SC4483...85, 2SD1207, 2SD1247, 2SD1331++
2 SD 546	Mat	Si-N	S P, TV-VA, 800/500V, 1/2A, 30W, 7MHz	22a	TO-66	BUX 85	17j BUV 36(A), BUX 84...85, 2SC1828, 2SC3352
2 SD 547	Tos	Si-N-Darl	S P, 600/450V, 50/100A, 400W, hFE>150, 1/10.5μs	-74			-
2 SD 548	Tos	Si-N-Darl	S P, 600/450V, 120A, 770W, hFE>150, 3/20μs				-
2 SD 549	Tos	Si-N-Darl	P, 30/30V, 1.5A, 15W, hFE>4000, 180/900ns	14h	TO-126	BD 679	14h BD 675, BD 775, 2SD985...986, 2SD1379, ++
2 SD 550	Tos	Si-N	P, 120/100V, 7A, 40W, 10MHz, 0.4/4.9μs	22a	TO-66	BD 243 C	17j BD 243C, BD 543D, MJ 15028, 2SD866
2 SD 551	Tos	Si-N	P, 150/150V, 12A, 100W, 15MHz	(2SB681) 23a	TO-3	2SC3263	18j BD 745E, 2SC1584, 2SD733, 2SD1047, ++
2 SD 552	Tos	Si-N	S P, 220/180V, 15A, 150W, 4MHz, 1/4μs	(2SB552) 23a	TO-3	2SC3263	18j BUX41, 2SC1586, 2SC2608, 2SC3263, 2SD583
2 SD 553	Tos	Si-N	70/50V, 7A, 40W, 10MHz, 0.3/3μs, sat<0.4V(4A)	17j	TO-220	2SD1062	17j 2SC3254, 2SD1237L
2 SD 554	Nec	Si-N	S P, 250/200V, 2A, 30W	(2SB599) 22a	TO-66	(BU 406)	17j BUX 67(A...C), 2N3583...85, 2SD610, ++
2 SD 555	Nec	Si-N	S P, LF P, 250/200V, 10/15A, 200W, 15MHz	(2SB600) 23a	TO-3		BUX 17A...C, BUY 18, 2SC1576, 2SD583, ++
2 SD 556	Sak	Si-N	S P, 110/80V, 15A, 120W, 8MHz, -/8.3μs	23a	TO-3	MJ 15015	23a BD 745C, BDW 10, 2N6530...31, 2SD1105, ++
2 SD 557	Sak	Si-N	=2SD556: 140/100V	23a	TO-3	MJ 15015	23a BD 745E, BDW 10, 2N6531, 2SC2607...08, ++
2 SD 558	Nec	Si-N-Darl	P, 90/70V, 2/3A, hFE=2k...12k, 0.4/3μs	30j	(10x8x5mm)	(BD 901) ⁴	17j 2SD1223, 2SD1520, 2SD1980, 2SD2410, ++
2 SD 560	Nec	Si-N-Darl+Di	150/100V, ±5/8A, 30W, hFE=2k...15k, 1/4, 7μs	(2SB601) 17j	TO-220	2SD1756	17j 2SD830, 2SD1128, 2SD1169, 2SD1590, ++
2 SD 565	Nec	Si-N-Darl+Di	S P, 400/400V, ±10/15A, 100W, hFE>800, 2.5/13μs	23a	TO-3		BU 920...922, MJ 10002...03, 2SD685, ++
2 SD 568	Nec	Si-N	P, 100/60V, 7/15A, 40W, sat<0.5V(5A)	(2SB707) 17j	TO-220	BD 243 C	17j BD 243C, BD 543B, BD 799, BD 809, ++
2 SD 569	Nec	Si-N	P, 100/80V, 7A, 40W	(2SB708) 17j	TO-220	BD 243 C	17j BD 243C, BD 543B, BD 799, BD 809, ++
2 SD 570	Mat, Mic	Si-N	P, 70/70V, 4/8A, 30W, >3MHz	(2SB604) 17j	TO-220	BD 243 C	17j BD 243A, BD 537, BD 539B, BD 951, ++
2 SD 571	Nec	Si-N	Uni, 60/50V, 0.7/1A, 1W, 110MHz	(2SB605) 9b		BC 639	7c BC 637, BC 639, BCX 24, 2SD667, ++
2 SD 572	Shi	Si-N-Darl	S P, 500/400V, 15A, 150W, 7MHz, hFE=150-80, <2/25μs	23a	TO-3		BU 932, 2SD683, 2SD711(A)
2 SD 573	Shi	Si-N-Darl	=2SD572: 600/450V	23a	TO-3		2SD683, 2SD711A
2 SD 574(A)	Shi	Si-N-Darl	S P, 120/120V, 30/100A, 400W, hFE>200, <2/9.5μs	68a			-
2 SD 575	Say	Si-N	TV-HA, 1400/600V, 2.5/6A, 50W	23a	TO-3	BU 208 A	23a BU 205...206, 2SC1922, 2SD818...819, ++
2 SD 575 L		Si-N	=2SD575: 1200/600V	23a	TO-3	BU 208 A	23a BU 204...206, 2SC1922, 2SD818...819, ++
2 SD 576	Fui	Si-N	S, Vid, 250/250V, 0.5A, 0.8W, 200MHz, <2/3μs	2a	TO-39	MPS-U10 ⁶	13m BFO 38...40, 2N5010, (BF 75)...759, ++ ⁶
2 SD 577	Mat	Si-N	TV-HA, 1500V, 3/12A, 16W(Tc=90°), sat<2.5V(3A)	23a	TO-3	BU 208 A	23a BU 208...209(A), BU 508(A), 2SC3023...24++
2 SD 578	Hit	Si-N-Darl	S P, 500/140V, 8A, 100W, B>350	23a	TO-3		BU 922, 2SD528, 2SD605, 2SD796, ++
2 SD 578(A)	Hit	Si-N	P, 180/140(A=180/160)V, 2A, 30W	(2SB608) 17j	TO-220	2SD1138	17j BD 239E, 2SC2660, 2SD760, 2SD1138, ++
2 SD 579(A)	Hit	Si-N	P, 100/80V, 4/8A, 40W	(2SB609) 22a	TO-66	BD 243 C	17j BD 243C, BD 539C, BD 953, 2N3767, ++
2 SD 580	Fui	Si-N	P, 60/50V, 1A, 20W, 1.2MHz	2a	TO-8	(BD 139) ⁴	14h (BD 137, BD 167, BD 228, BD 235...+) ⁴
2 SD 581(A)	Hit	Si-N	P, 150/100(A=150/120)V, 7/12A, 60W	(2SB611) 23a	TO-3	2SC3263	18j BDX 11, 2SD732, 2SD751, 2SD1046, ++
2 SD 582(A)	Hit	Si-N	P, 180/140(A=180/160)V, 12/15A, 100W	(2SB612) 23a	TO-3	MJ 15015	23a BDW 14, MJ 15015, 2SC2607...08, 2SD424, ++
2 SD 583	Hit	Si-N	P, 250/200V, 15/20A, 150W	(2SB613) 23a	TO-3		BUX 41, MJ 15022, MJ 15024, 2SC1586
2 SD 585	Mit	Si-N-Darl	110/110V, 7/12A, 80W, 20MHz, hFE=1.1...2.4k	(2SB615) 23a	TO-3	BDW 83 C	18j BDV 65C, BDX 63C, BDX 65C, 2SD1210
2 SD 586(A)	Nec	Si-N	P, 100/80(A=100/100)V, 5/8A, 60W, 15MHz	(2SB616) 19j			2SC2276, 2SD848(A), 2SD883(A)
2 SD 587(A)	Nec	Si-N	P, 120/100(A=120/120)V, 6/10A, 70W, 17MHz	(2SB617) 19j			2SC2276, 2SB848(A), 2SB883A
2 SD 588(A)	Nec	Si-N	P, 150/120(A=150/130)V, 7/12A, 80W	(2SB618) 19j			-
2 SD 589	Mat	Si-N	TV-HA, 1500V, 5A, 50W	23a	TO-3	BU 208 A	23a BU 208(A), BU 508(A), 2SC2928, 2SD954, ++
2 SD 590	Fui	Si-N	LFS, 100/90V, 2A, 1W, <150/2100ns, <150/2100	2a	TO-39	(2SC4135) ⁴	30j 2SD854, (BD 379, BD 529, 2SD1177...78...+) ⁶
2 SD 591	Mat	Si-N	Uni, In, 30V, 0.05A, 0.15W, 150MHz, F=2dB(1kHz)	7c	TO-92	BC 184, BC 239, BC 549, ++	7c BC 169, BC 184, BC 239, BC 549, ++
2 SD 592(NC)	Mat	Si-N	Uni, 30/25V, 1/1.5A, 0.75W, 200MHz	(2SB621) 7c	TO-92	BC 639	7c BC 337...338, BC 635, 2SD1225, 2SD1616, ++
2 SD 592A(ANC)		Si-N	=2SD592: 60/50V	7c	TO-92	BC 639	7c BC 637, BC 639, BCX 24, 2SD667, ++
2 SD 593	Sak	Si-N	S, 500/400V, 0.3A, 0.8W, 15MHz, -/10.8μs	2a	TO-39		2N5010...5015, 2SC1762
2 SD 594	Sak	Si-N	=2SD593: 800/700V	2a			2N5013...5015
2 SD 596	Nec	Si-N	SMD, LF, 30/25V, 0.7A, 170MHz	(2SB624) 35a	SOT-23	BC 817	35a BCW 65...66
2 SD 597	Mat	Si-N	P, 100/100V, 5/7A, 60W, 7MHz	(2SB625) 23a	TO-3	BD 245 C	18j BD 245C, BDV 95, BDX 95, 2SD731...732, ++
2 SD 598	Mat	Si-N	=2SD597: 120/120V, 6/8A, 80W, 6MHz	(2SB626) 23a	TO-3	BD 245 C	18j BD 245C, 2SC2681, 2SD731...732, ++
2 SD 599	Say	Si-N	Uni, 25/20V, 1A, 0.35W, 180MHz, sat<0.3V(0.5A)	7c	TO-92	BC 639	7c BC 337...338, BC 635, BC 637, BC 639, ++
2 SD 600	Say	Si-N	100/100V, 1/2A, 8W, 130MHz, sat<0.4V(0.5A)	(2SB631) 14h	TO-126	BD 139	14h BD 139, BD 230, BD 379, 2SD1684, ++
2 SD 600 K		Si-N	=2SD600: 120/120V	14h	TO-126	(BD 139) ⁷	14h 2SC2690(A), 2SD1382, 2SD1563, 2SD1684
2 SD 601	Mat	Si-N	SMD, Uni, 30/25V, 0.1/0.2A, 150MHz, Ur=110mV	(2SB709) 35a	SOT-23	BC 846	35a BC 846...848, BCW 31...33, BCW 71...72, ++
2 SD 601 A		Si-N	=2SD601: 60/50V	35a	SOT-23	BC 846	35a BC 846, BCW 71...72, 2SC3323...3324
2 SD 602	Mat	Si-N	SMD, Uni, 30/25V, 0.5/1A, 200MHz	(2SB710) 35a	SOT-23	BC 817	35a BC 817...818, BCW 65...66, BCX 19...20, ++
2 SD 602 A		Si-N	=2SD602: 60/50V	35a	SOT-23		35a BCW 65...66
2 SD 603	Mat	Si-N	Uni, 30/30V, 0.1/0.2A, 0.25W, 150MHz	9c		BC 546	7a BC 168, BC 183, BC 238, BC 548, ++
2 SD 604	Hit	Si-N-Darl	P, 180/180V, 5A, 100W, 8MHz, hFE=400...3200	23a	TO-3		2SD920...921, 2SD1090, 2SD1122...1123, ++
2 SD 605(D)	Sak	Si-N-Darl	S P, 600/500V, 7A, 80W, hFE=400-200	23a	TO-3		BUW 81(A), 2SD520...521, 2SD528, 2SD705++
2 SD 606	Sak	Si-N-Darl	S P, 600/500V, 15A, 100W, hFE=400-200	23a	TO-3		BUT 51P, 2SD573, 2SD683, 2SD711A
2 SD 608	Nec	Si-N	P, 160/160V, 1.5/3A, 20W, 45MHz	(2SB628) 17j	TO-220	2SC2592	17j BD 239D, 2SC2592, 2SD578, 2SD1138, ++
2 SD 608 A		Si-N	=2SD608: 180/180V	17j	TO-220	2SC2592	17j BD 239E, 2SC2592, 2SD578, 2SD1138, ++
2 SD 610	Nec	Si-N	P, 250/200V, 2/3A, 25W, 5MHz	(2SB630) 17j	TO-220	(BU 406)	17j 2SC2023, 2SD7728
2 SD 611	Fui	Si-N	P, 100/60V, 7A, 30W	22a	TO-66	BD 243 C	17j BD 243C, BD 543C, BD 801, 2N5429...30, ++
2 SD 611 A		Si-N	=2SD611: 120/80V	22a	TO-66	BD 243 C	17j BD 243C, BD 543D, 2SD550, 2SD866
2 SD 612	Say	Si-N	P, 25/25V, 2/3A, 10W, 100MHz, 50/500ns	(2SB632) 14h	TO-126	(BD 237) ⁸	14h BD 329, BD 375, 2SD1380
2 SD 612 K		Si-N	=2SD612: 35/35V	14h	TO-126	(BD 237) ⁸	14h BD 375, 2SD794(A), 2SD1380
2 SD 613	Say	Si-N	P, 100/85V, 6/10A, 40W, 15MHz, 280/4100ns	(2SB633) 17j	TO-220	BD 243 C	17j BD 243C, BD 543C, BD 801
2 SD 613 P		Si-N	=2SD613: 50W	19j			2SD587...588, 2SD883(A), 2SD848(A)
2 SD 614	Sak	Si-N-Darl	LFS, 100/80V, 3A, 0.8W, hFE=3000, -/4050ns	2a	TO-39	(BD 679) ⁶	14h 2SC2208, (BD 681, BDW 53C, D, 2SD1091...+) ⁶
2 SD 615	Sak	Si-N-Darl	=2SD614: 140/120V	2a	TO-39		(2SD830, 2SD1091, 2SD1128, 2SD1169) ⁶
2 SD 616	Say	Si-N	P, 120/100V, 7A, 60W, 15MHz	(2SB634) 23a	TO-3	2SC3263	18j BD 245C, 2SC2681, 2SD731...733, ++
2 SD 617	Sak	Si-N-Darl	P, 120/100V, 8A, 100W, hFE=2500	23a	TO-3	(BDW 83C) ⁷	18j BDV 65C, BDX 63C, 2SD922
2 SD 619	Fui	Si-N	Uni, 80/60V, 1.5A, 0.5W, 100MHz	7c	TO-92	(2SC4135) ⁴	30j MPS 651, 2SC3328, (BD 519, BD 527...+) ⁶
2 SD 620	Fui	Si-N	=2SD619: ...	14h	TO-126	BD 139	14h BD 139, BD 230, BD 379, 2SD1177...78, ++
2 SD 621	Say	Si-N	TV-HA, 2500/900V, 3/7A, 50W	23a	TO-3		2SD838
2 SD 622	Fui	Si-N	S P, 450/400V, 3A, 30W, 25MHz, -/5.5μs	22a	TO-66	(BU 406)	17j BUV63...65, TIP75B, 2SC1466, 2SC2929, ++
2 SD 624	Fui	Si-N	Vid, 200/150V, 0.5A, 0.8W, 50MHz, -/6.5μs	2a	TO-39	(MPS-U10) ⁶	13m 2SD413, 2SD576, (BF 757...759, MPS-U10+) ⁶
2 SD 625	Son	Si-N	LFS, 250/70V, 4A, 6.2W(Tc=25°), 60MHz	2a	TO-39	(BU 406) ⁶	17j BUY 49, (BU 406...409, 2SC2767...+) ⁶
2 SD 626	Say	Si-N-Darl	S P, 600/350V, 6A, 80W, hFE=300, <1/45μs	23a	TO-3		BUW 81, 2SD520, 2SD528, 2SD605, 2SD705++
2 SD 627	Say	Si-N	TV-HA, 1500/600V, 3/6A, 50W, sat<10V(2.5A)	23a	TO-3	BU 208 A	23a BU 208...209(A), BU 508(A), 2SC3023...24++
2 SD 628	Hit	Si-N-Darl+Di	100/100V, 10/15A, 80W, hFE=1k...20k, 2/8μs	(2SB638) 23a	TO-3	BDW 83 C	18j BDV 65B, BDX 83C, BDX 85C, 2N6059, ++
2 SD 629	Hit	Si-N-Darl+Di	=2SD628: 100W	(2SB639) 23a	TO-3	BDW 83 C	18j BDV 65B, BDX 83C, BDX 85C, 2N6059, ++
2 SD 630	Fui	Si-N	S P, 50/40V, 30A, 200W, 0.8MHz	23a	TO-3		BDX 41, BDY 29, MJ 802, 2N3771
2 SD 631	Fui	Si-N	S P, 60/50V, 40A, 200W	23a	TO-3		2N6032, 2N6274...6275
2 SD 632	Mat	Si-N	S P, 350/300V, 2.5/4A, 80W	23a	TO-3	(BU 608)	23a BUX 168, C, TIP 51...54, 2SC1463, 2SC2624
2 SD 633	Tos	Si-N-Darl+Di	100/100V, 7A, 40W, hFE=2k...15k, 0.8/5.5μs	(2SB673) 17j	TO-220	BD 901	17j BD 649, BD 901, BDW 73C, BDX 53C, ++
2 SD 634	Tos	Si-N-Darl+Di	=2SD633: 80/80V	(2SB674) 17j	TO-220	BD 901	17j BD 647, BD 899, BDW 73B, BDX 53B, ++
2 SD 635	Tos	Si-N-Darl+Di	=2SD633: 60/60V	(2SB675) 17j	TO-220	BD 901	17j BD 645, BD 897, BDW 73A, BDX 53A, ++

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International	
2 SD 636	Mat	Si-N	Uni, 30/25V, 0,1/0,2A, 0,4W, 150MHz	{2SB641 9c	BC 546	7a	BC 168, BC 183, BC 238, BC 548, ++	
2 SD 637	Mat	Si-N	=2SD636: 60/50V	{2SB642 9c	BC 546	7a	BC 174, BC 182, BC 190, BC 546, ++	
2 SD 638	Mat	Si-N	Uni, 30/25V, 0,5/1A, 0,6W, 200MHz	{2SB643 9c	(M Type) BC 639	7c	BC 337...338, BC 635, 2SC3377, 2SD1616, ++	
2 SD 639	Mat	Si-N	=2SD638: 60/50V	{2SB644 9c	BC 639	7c	BC 637, BC 639, 2N3700...01, 2SC2235, ++	
2 SD 640	Tos	Si-N	S P, 600/400V, 7A, 100W, 3MHz, 1/3,6µs	23a	TO-3	S 2530 A	23a	BU 526, BU 536, BU 626A, 2SD1094, ++
2 SD 641	Tos	Si-N	S P, 600/400V, 15A, 150W, 4MHz, 0,8/4,1µs	23a	TO-3			BUS 13(A), BUW 45...46, BUX 48A...C
2 SD 642	Tos	Si-N	S P, 600/400V, 40A, 300W, 1,2/4,8µs	68a				2SC1435
2 SD 643	Tos	Si-N-Darl	S P, 300/200V, 30/60A, 300W, hFE>150, 1/10,5µs	68a				-
2 SD 644	Tos	Si-N-Darl	S P, 600/450V, 30/60A, 300W, hFE>150, 1,5/14µs	68a				-
2 SD 645	Tos	Si-N-Darl	=2SD644: 350W	-74				-
2 SD 646(A)	Tos	Si-N-Darl	S P, 600/450V, 50/100A, 400W, hFE>150, 1,5/13µs	-74				-
2 SD 647(A)	Tos	Si-N-Darl	S P, 800/600V, 100A, 770W, hFE>100, 3/35µs					-
2 SD 648(A)	Tos	Si-N-Darl	S P, 300/300V, 400A, 2500W, hFE>100, 1/8µs					-
2 SD 649	Mat,Tos	Si-N	TV-HA, 1500/600V, 6A, 80W, sat<7V(3A)	23a	TO-3	BU 508 A	18j	BU 508(A), 2SC3025...3026, 2SD821, ++
2 SD 650	Hit	Si-N-Darl+Di	S P, 400/400V, 6/12A, 80W, hFE>500	23a	TO-3	BU 826	18j	BU 180A, BU 284, BU 826
2 SD 651	Hit	Si-N-Darl	S P, 400/400V, 4/8A, 30W, hFE>500	22a	TO-66			BU 910...912, 2SD977, 2SD1072, 2SD1245, ++
2 SD 652	Hit	Si-N-Darl	S P, 500/500V, 6A, 80W, hFE=3000	23a	TO-3			BU 322(A), BUW 81, 2SD796, 2SD980, ++
2 SD 654	Mit	Si-N	Uni, 50/30V, 0,5A, 0,57W, 190MHz	2a	TO-39	BC 141	2a	BC 140...141, BC 300...302, 2N3053, ++
2 SD 655	Hit	Si-N	Uni, 30/15V, 0,7/1A, 0,5W, 250MHz	7c	TO-92	BC 639	7c	BC 337...338, BC 635, BC 637, BC 639, ++
2 SD 656	Tos	Si-N	S P, 200/180V, 1,5A, 30W, >2MHz	22a	TO-66	2SD1138	17j	BD239F, BUX 67(A...C), 2SC783, 2SD1138, ++
2 SD 657	Tos	Si-N	S P, 200/200V, 1,5A, 50W	23a	TO-3			BD 239F, 2SC1195, 2SC2809, 2SD632
2 SD 658	Hit	Si-N	TV-HA, 1500/600V, 5/12A, 50W, sat<6V(5A)	23a	TO-3	BU 208 A	23a	BU 208(A), BU 508(A), 2SC2928, 2SD820, ++
2 SD 660	Fui	Si-N	Uni, S, 90/70V, 2A, 1W, 150/2100ns	2a	TO-39	(2SC1435) [†]	30j	BCX 40, BSS 15, BSV 84, 2N5320, ++
2 SD 661	Mat	Si-N	Uni, In, 35/35V, 0,1/0,2A, 0,4W, 200MHz	{2SB745 9c	BC 550	7a	BC 169, BC 184, BC 239, BC 549, ++	
2 SD 661 A	Mat	Si-N	=2SD661: 55/55V	9c	BC 550	7a	BC 414, BC 550, 2SC2675, 2SC2390, ++	
2 SD 662	Mat	Si-N	Vid, 250/200V, 70/100mA, 0,6W, 80MHz	{2SB1264 9c	BF 420 A	7c	BF 298...299, BF 422A, 2SC3468, ++	
2 SD 662 B	Mat	Si-N	=2SD662: 400/400V	9c	BF 487	7c	2SC2267, 2SC3469, 2SC4166, 2SD1385	
2 SD 663	Fjd	Si-N-Darl	S P, 500/500V, 6A, 80W, hFE=400, <3/25µs	23a	TO-3			BUW 81, 2SD520, 2SD528, 2SD605, 2SD705, ++
2 SD 664	Tos	Si-N-Darl+Di	P, 80/80V, 7A, 40W, hFE=2k...15k, 0,8/5,5µs	22a	TO-66	BD 901	17j	BD 647, BD 899, BDW 738, BDX 53B, ++
2 SD 665	Tos	Si-N	S P, 200/200V, 15A, 150W, 15MHz	{2SB645 23a	TO-3	2SC3263	18j	BDW 16, 2SC2607...2608, 2SD552, 2SD583, ++
2 SD 666(A)	Hit	Si-N	120/80(A=120/100)V, 50/100mA, 0,9A, 140MHz	{2SB646 7c(9mm)	TO-92L	2SC2632	7c(9mm)	2SC2632, 2SC3245(A), 2SC3248, 2SC3800
2 SD 667(A)	Hit	Si-N	=2SD666(A): 1/2A	{2SB647 7c(9mm)	TO-92L	2SD1812	7c(9mm)	2SC2383, 2SC3228, 2SD1292, 2SD1812
2 SD 668(A)	Hit	Si-N	L.F.S. Vid P, 180/120(A=180/160)V, 50/100mA, 20W 140MHz	{2SB648 14h	TO-126	BF 471	14h	BF 469, BF 471, BF 415, BF 417, 2SC3416
2 SD 669(A)	Hit	Si-N	=2SD668: 1,5/3A	{2SB649 14h	TO-126	2SC3117	14h	2SC3117
2 SD 670	Hit	Si-N-Darl+Di	P, 100/100V, 15/20A, 100W, hFE=1k...20k, 2/8µs	23a	TO-3	BDW 83 C	18j	BDV 67A, BDW 83C, BDX 67B, MJ 4035, ++
				{2SB650				
2 SD 671	Mat	Si-N	Uni, 30/18V, 0,5/1,5A, 0,6W, 150MHz	7c	TO-92	BC 639	7c	BC 337...338, BC 635, BC 637, BC 639, ++
2 SD 672	Mat	Si-N	S P, 300V, 1A, 40W(Tc=45°), 20MHz	23a	TO-3			2SC1463, 2SC2809, 2SD632
2 SD 673(A)	Hit	Si-N	P, 120/100V, 7A, 60W, 8(A=25)MHz	{2SB653 23a	TO-3	2SC3263	18j	BD 245C, 2SC2681, 2SD731...733, ++
2 SD 674(A)	Hit	Si-N	=2SD673: 120/120V, 80W	{2SB854 23a	TO-3	2SC3263	18j	BD 245C, 2SC2681, 2SD731...733, ++
2 SD 675(A)	Hit	Si-N	P, 160/140V, 12A, 100W, 8(A=25)MHz	{2SB655 23a	TO-3	2SC3263	18j	BD 745F, 2SD424, 2SD733, 2SD1047, ++
2 SD 676(A)	Hit	Si-N	=2SD675: 160/160V, 125W	{2SB656 23a	TO-3	2SC3263	18j	BD 745F, 2SC2607...2608, 2SD753, ++
2 SD 677	Fjd	Si-N	S P-S-Reg, 450/400V, 5A, 100W, <1,5/8µs	23a	TO-3	BU 426 A	18j	BU 426(A), BUW 11(A), BUW 71, BUX 45, ++
2 SD 678	Mat	Si-N-Darl	P, 60/60V, 3/4A, 25W, hFE=1k...10k	{2SB668 17j	TO-220	BD 901	17j	BD 715, BDW 23A, BDW 53A, 2SD837, ++
2 SD 678 A	Mat	Si-N-Darl	=2SD678: 80/80V	17j	TO-220	BD 901	17j	BD 717, BDW 23B, BDW 53B, 2SD837A, ++
2 SD 679	Mat	Si-N-Darl	P, 70/70V, 4/5A, 40W, hFE=1k...10k	{2SB669 17j	TO-220	BD 901	17j	BD 717, BDW 23B, BDW 53B, BDW 63B, ++
2 SD 679 A	Mat	Si-N-Darl	=2SD679: 90/90V	17j	TO-220	BD 901	17j	BD 901, BDW 23C, BDW 53C, BDW 63C, ++
2 SD 680	Mat	Si-N-Darl	P, 90/90V, 6A, 60W, hFE=1k...10k	{2SB670 23a	TO-3	BDW 83 C	18j	BDV 65B, BDX 63B, TIP 142, 2SD1170, ++
2 SD 680 A	Mat	Si-N-Darl	=2SD680: 110/110V	23a	TO-3	BDW 83 C	18j	BDV 65C, BDX 63C, TIP 142, 2SD1170, ++
2 SD 681	Mat	Si-N-Darl	P, 100/100V, 8A, 80W, hFE=1k...10k	{2SB671 23a	TO-3	BDW 83 C	18j	BDV 65B, BDX 63B, BDX 83C, TIP 142, ++
2 SD 681 A	Mat	Si-N-Darl	=2SD681: 120/120V	23a	TO-3	(BDW 83 C) ⁷	18j	BDV 65C, BDW 84D, BDX 63C, BDX 65C, ++
2 SD 682	Mat	Si-N-Darl	P, 120/120V, 8/10A, 110W, hFE=1k...10k	{2SB672 23a	TO-3			BDV 65C, BDV 67B, BDW 83D, BDX 65C, ++
2 SD 682 A	Mat	Si-N-Darl	=2SD682: 140/140V	23a	TO-3			BDV 67C
2 SD 683	Tos	Si-N-Darl+Di	S P, 600/400V, 15A, 150W, hFE>500, 0,4/18µs	23a	TO-3			BUT 51, 2SD573, 2SD606, 2SD711A
2 SD 683 A	Tos	Si-N-Darl+Di	=2SD683: 600/450V	23a	TO-3			BUT 51, 2SD573, 2SD606, 2SD711A
2 SD 684	Tos	Si-N-Darl	S P, 600/300V, 6A, 30W, hFE>1500, 1/13µs	22a	TO-66	2SD798	17j	BU 810, 2SC3579, 2SD798...799
2 SD 684 A	Tos	Si-N-Darl+Di	=2SD684: 600/400V, hFE>600	22a	TO-66	2SD798	17j	BU 810, 2SC3579, 2SD799
2 SD 685	Tos	Si-N-Darl+Di	S P, 600/400V, 10A, 100W, hFE=400, 1/17µs	23a	TO-3			BUW 81(A), MJ 10013...14, 2SC3262
2 SD 686	Tos	Si-N-Darl+Di	P, 100/80V, 4A, 30W, hFE>2000, 0,2/2,1µs	{2SB676 17j	TO-220	BD 901	17j	BD 901, BDW 23C, BDW 53C, BDW 63C, ++
2 SD 687	Tos	Si-N-Darl+Di	P, 60/40V, 3A, 25W, hFE>2000, 0,1/1,2µs	{2SB677 17j	TO-220	BD 901	17j	BD 899, BDW 23A, BDW 53A, BDW 63A, ++
2 SD 688	Tos	Si-N-Darl	L.F.S. 100/100V, 1,5A, 8W(Tc=25°), hFE>2000 0,3/2,7µs	{2SB678 17j	TO-39	(BD 679) ⁶	14h	2SC1879, 2SD406, (BD 681) ⁶
2 SD 688	Tos	Si-N-Darl	=2SD688: 10W	{2SB679 17j	TO-220	(BD 901)	17j	BDW 53C, 2SD837B
2 SD 690	Tos	Si-N	P, 70/50V, 7A, 40W, 10MHz, 0,2/3µs	22a	TO-66	BD 809	17j	BD 543B, BD 799, BD 809, 2N6372...73, ++
2 SD 691	Mat	Si-N-Darl+Di	P, 100V, 6A, 40W, hFE=500...3000	22a	TO-66	BD 901	17j	BD 649, BD 901, BDW 73C, BDX 53C, ++
2 SD 692	Mat	Si-N-Darl+Di	=2SD691: 50W	23a	TO-3	BDW 83 C	18j	BDV 65B, BDX 63B, BDX 83C, BDX 85C, ++
2 SD 693	Mat	Si-N-Darl+Di	S P, 450/450V, 10A, 80W, hFE>150	23a	TO-3			BU 922, BUW 81(A), MJ10003, 2SD685, ++
2 SD 694	Tos	Si-N-Darl	S P, 400/350V, 30/60A, 300W, hFE>150, 1,5/14µs	68a				-
2 SD 695	Tos	Si-N-Darl	S P, 400/350V, 30/60A, 350W, hFE>150, 1/11µs	-74				-
2 SD 696(A)	Tos	Si-N-Darl	S P, 400/350V, 50/100A, 400W, hFE>150, 1/13µs	-74				-
2 SD 697(A)	Tos	Si-N-Darl	S P, 500/450V, 100A, 770W, hFE>100, 3/35µs					-
2 SD 698	Tos	Si-N-Darl	S P, 200/200V, 600A, 2500W, hFE>150, 2/11µs					-
2 SD 699	Tos	Si-N-Darl	S P, 300/200V, 30/60A, 250W, hFE>150, 1,2/11,5µs	68a				-
2 SD 700	Tos	Si-N-Darl	S P, 300/200V, 200A, 770W, hFE>150, 1/12,5µs					-
2 SD 702	Tos	Si-N	S P, 400/300V, 40A, 300W, 1,2/4,8µs	68a				2SC1435, 2SC2366, 2SD642
2 SD 703	Tos	Si-N-Darl	S P, 200/150V, 30/60A, 300W, hFE>150, 1/10,5µs	68a				-
2 SD 704	Mit	Si-N	P, 50/50V, 5A, 40W, 10MHz, 1/2,5µs	18j	TO-3P	BD 245 C	18j	BD 245(A...C), BDV 91, BDV 93, BDV 95, ++
2 SD 705	Fjd	Si-N-Darl	S P, 600/400V, 8A, 80W, hFE=300, <3/32µs	23a	TO-3			BUW 81(A), 2SD520, 2SD528, 2SD605, ++
2 SD 706	Fjd	Si-N-Darl	S P, 345/345V, 6A, 80W, hFE=400...2000, <1/18µs	23a	TO-3			BU 322(A), BUX 28...29, 2SD720, ++
2 SD 707	Fjd	Si-N-Darl	S P, 500/350V, 8A, 100W, hFE=200...800, <1,4/21µs	23a	TO-3			BU 922, BUW 81(A), MJ 10013...13, ++
2 SD 708	Fjd	Si-N-Darl	S P, 345/345V, 6A, 30W, hFE=1000, <1/18µs	22a	SOT-9			BU 910...912, 2SD835, 2SD1114, 2SD1245, ++
2 SD 709	Fjd	Si-N-Darl	S P, 250/200V, 4A, 25W, hFE>1500, <1,7/33µs	22a	SOT-9			2SD816, 2SD834, 2SD1073
2 SD 710	Fjd	Si-N-Darl	S P, 300/250V, 15A, 150W, hFE=500-200, <5/15µs	23a	TO-3			BU 930...932, 2SD572...573, 2SD683, ++
2 SD 711	Fjd	Si-N-Darl	S P, 500/450V, 15A, 100W, hFE>100, <3/25µs	23a	TO-3			BU 932, 2SD572...573, 2SD606, 2SD683, ++
2 SD 711 A	Fjd	Si-N-Darl	=2SD711: 600/600V, hFE>200	23a	TO-3			BUT 51P, 2SD573, 2SD606, 2SD683, ++
2 SD 712	Mit	Si-N	P, 100/100V, 4A, 30W, 8MHz	{2SB682 17j	TO-220	BD 243 C	17j	BD 243C, BD 539C, BD 953, 2SD613, ++
2 SD 712 A	Mit	Si-N	=2SD712: 280/280V	17j	TO-220	(BU 406)	17j	TIP 75(A...C), 2SC2826, 2SC2929, ++
2 SD 713	Mit	Si-N	P, 100/100V, 5A, 40W, 8MHz	{2SB683 17j	TO-220	BD 243 C	17j	BD 243C, BD 539C, BD 953, 2SD613, ++
2 SD 715	Mit	Si-N-Darl	P, 110/110V, 7A, 80W, hFE=2k...24k	{2SB685 18j	TO-3P	BDW 83 C	18j	BDV 65C, BDW 83D, 2SD1210
2 SD 716	Tos	Si-N	Hifi Audio Out, 100/100V, 6A, 60W, 12MHz	{2SB686 18j	TO-3P	BD 245 C	18j	BD 245C, BDV 95, 2SC2681, 2SD895...96, ++
2 SD 717	Tos	Si-N	70/50V, 10A, 80W, 10MHz, 0,3/2,9µs, sat<0,4V(6A)	18j	TO-3P			2SD1187, 2SD1238L
2 SD 718	Tos	Si-N	P, 120/120V, 8A, 80W, 12MHz	{2SB688 18j	TO-3P	BD 245 C	18j	BD 245C, 2SC2681, 2SC2706, 2SC2837, ++

Original	Fabric.	Constr.	Info	(Compl.	Fig.	JAEGER	Fig.	International	
2 SD 720	Mit	Si-N-Darl	S P, 400/400V, 7A, 100W, hFE=400...1500		23a		TO-3	BU 322(A), BUX 29, 2SD707, 2SD796, ++	
2 SD 721	Sak	Si-N-Darl	P, 100/80V, 6/10A, 50W, hFE=1000, -/16,5µs	(2SB711	17j	BD 901	17j	BD 649, BD 901, BDW 73C, BDX 53C, ++	
2 SD 722	Sak	Si-N-Darl	=2SD721: 120/100V	(2SB712	17j	(BD 901) ⁷	17j	BD 651, BDT 21, BDW 73D, BDX 53E, ++	
2 SD 723	Hit	Si-N	P, 100/100V, 4A, 40W		17j	BD 243 C	17j	BD 243C, BD 539C, BD 953, 2SD712, ++	
2 SD 724	Hit	Si-N	P, 200/80V, 4A, 30W		17j		TO-220	BD 243F, 2SC2767, 2SD772A,B	
2 SD 725	Hit	Si-N	TV-HA, 1500/600V, 6A, 50W, sat<5V(5A)		23a	2SD725	23a	2SC2027	
2 SD 726	Hit	Si-N	P, 100/80V, 4/8A, 40W, 10MHz	(2SB690	17j	BD 243 C	17j	BD 243C, BD 539C, BD 953, 2SD712, ++	
2 SD 727	Mat	Si-N	P, 130/80V, 5/8A, 60W, 7MHz	(2SB891	18j	2SC2837	18j	BD 245D, 2SD731, 2SD751, 2SD1046, ++	
2 SD 728	Mat	Si-N	=2SD727: 150/100V, 6/10A, 70W	(2SB692	18j	2SC2837	18j	BD 245D, 2SC3263, 2SD731, 2SD751, ++	
2 SD 729	Hit	Si-N-Darl+Di	100/100V, 20/30A, 125W, hFE=1k...20k, 2/8µs	(2SB693	23a		TO-3	BDX 69B, MJ 11014, 2N6284	
2 SD 730	Hit	Si-N-Darl+Di	=2SD729: 25/40A		23a		TO-3	BDX 69B, MJ 11014, MJ 11016	
2 SD 731	Mat	Si-N	P, 170/120V, 7/12A, 80W, 7MHz	(2SB695	18j	2SC2837	18j	BD 245E, 2SC3263, 2SD751	
2 SD 732(K)	Say	Si-N	P, 150/120K=150/140V, 8/12A, 80W, 15MHz	(2SB696	23a	2SC3263	18j	BD 245D, 2SC2837, 2SD551, 2SD752, ++	
2 SD 733	Say	Si-N	P, 160/140V, 12/20A, 100W, 15MHz	(2SB697	23a	MJ 15015	23a	BD 745E, MJ 15015, 2SC2607...08, ++	
2 SD 733 K		Si-N	=2SD733: 180/160V		23a	MJ 15015	23a	BD 757F, MJ 15015, 2SC2607...08, ++	
2 SD 734	Say	Si-N	Uni.25/20V, 0,7/1,5A, 0,6W, 250MHz, sat<0,3V(0,5A)		7c	2SD1207	7c	2SC4483, 2SD1207, 2SD1302, 2SD1616, ++	
				(2SB698)					
2 SD 735	Hit	Si-N	P, 160/120V, 12/15A, 100W	(2SB699	20j	2SC3264	20j	2SC2526, 2SC2565, 2SC2766(A), 2SC2921, ++	
2 SD 736(A)	Hit	Si-N	=2SD735: 160/140V	(2SB700	20j	2SC3264	20j	2SC2526, 2SC2565, 2SC2766(A), 2SC2921, ++	
2 SD 737	Hit	Si-N	P, 160/160V, 12A, 120W		20j	2SC3264	20j	2SC2526, 2SC2565, 2SC2766(A), 2SC2921, ++	
2 SD 738(A)	Hit	Si-N	P, 160/160V, 12/15A, 125W, 10(A=25)MHz	(2SB702	20j	2SC3264	20j	2SC2526, 2SC2565, 2SC2766(A), 2SC2921, ++	
2 SD 741	Nec	Si-N	HF, LFS, P, 40/20V, 5/8A, 15W, 200MHz, 1,5/0,4µs		14h	(2SC3420)	14b	MJE 200, 2SC2270, 2SC2594, 2SD2147	
2 SD 743(A)	Nec	Si-N	LF P, TV, 100/80V, 4/6A, 40W, 17MHz	(2SB703	17j	BD 243 C	17j	BD 243C, BD 539C, BD 953, 2SD726, ++	
2 SD 745	Nec	Si-N	P, 140/140V, 10/15A, 120W, 15MHz	(2SB705	20j	2SC3264	20j	2SC2564...2565, 2SC2838, 2SD845, ++	
2 SD 745 A		Si-N	=2SD745: 150/150V		20j	2SC3264	20j	2SC2526, 2SC2565, 2SC2838, 2SD845, ++	
2 SD 745 B		Si-N	=2SD745: 160/160V		20j	2SC3264	20j	2SC2526, 2SC2565, 2SC2766(A), 2SC2921, ++	
2 SD 746	Nec	Si-N	P, 180/180V, 10/15A, 200W, 15MHz	(2SB706	4-SILP	(CBEC)			
2 SD 746 A		Si-N	=2SD746: 220/220V		4-SILP	(CBEC)			
2 SD 747	Mit	Si-N	S, 50/30V, 0,5A, 1W(Tc=25°), <1µs		2a	TO-18	(BC 337)	7a	BSW 61...64, BSX 33, 2N2221... 2222(A), ++
2 SD 748	Hit	Si-N	S P, 250/200V, 3A, 80W		23a	TO-3	(BU 608)	23a	TIP 51...54, 2SC1463, 2SD632
2 SD 748 A		Si-N	=2SD748: 250/250V		23a	TO-3	(BU 608)	23a	TIP 51...54, 2SC1463, 2SD632
2 SD 749	Mat	Si-N	S P, 750/300V, 3A, 50W		23a	TO-3	BUW 11 A	18j	BUW 11(A), BUX 46(A), 2SC3088, 2SC3448, ++
2 SD 750	Mat	Si-N	P, 110/80V, 15A, 100W, 1MHz		23a	TO-3	2N3055	23a	BD 317, BD 745C, 2N3055, 2N5629...31, ++
2 SD 751	Mat	Si-N	P, 200/140V, 9/15A, 100W, 7MHz	(2SB713	18j	TO-3P	2SC3263	18j	BD 245F, 2SC3263
2 SD 752	Hit	Si-N	P, 160/160V, 15/20A, 150W	(2SB722	23a	TO-3	MJ 15015	23a	BDW 12, MJ 15015, 2N3773, 2SC2607...08, ++
2 SD 753	Hit	Si-N	=2SD752: 200/200V	(2SB723	23a	TO-3	MJ 15015	23a	BDW 16, MJ 15015, 2SC1585, 2SC2607...08, ++
2 SD 754	Hit	Si-N	Uni, 25/20V, 0,7/1A, 0,625W, 280MHz	(2SB721	7e	TO-92	BC 337 ⁸	7a	(BC 337...338, BC 635, BC 637, BC 639, ++) ⁸
2 SD 755	Hit	Si-N	Uni, 100/100V, 0,05A, 0,75W, 350MHz	(2SB715	7c(9mm)	TO-92L	2SC2632	7c(9mm)	2SC2632, 2SC3245(A), 2SC3248, 2SD3800
2 SD 756	Hit	Si-N	=2SD755: 120/120V	(2SB716	7c(9mm)	TO-92L	2SC2632	7c(9mm)	2SC2632, 2SC3245(A), 2SC3248, 2SD3800
2 SD 756 A		Si-N	=2SD755: 140/140V		7c(9mm)	TO-92L	2SC2632	7c(9mm)	2SC2375, 2SC2631...32, 2SC3248, 2SC3245A, ++
2 SD 757	Hit	Si-N	LFS/Vid P, 160/160V, 0,05A, 140MHz	(2SB717	17j	TO-220	(BF 471) ⁴	14h	2SC3514, (BF415, BF417, BF469, BF471, ++) ⁴
2 SD 758	Hit	Si-N	=2SD757: 200/200V	(2SB718	17j	TO-220	(BF 471) ⁴	14h	2SC1819, (BF415, BF417, BF469, BF471, ++) ⁴
2 SD 759	Hit	Si-N	P, 160/160V, 2/4A, 25W, 100MHz	(2SB719	17j	TO-220	(2SD1138) ⁸	17j	2SC2529, 2SC2660
2 SD 760	Hit	Si-N	=2SD759: 200/200V	(2SB720	17j	TO-220	(2SD1138) ⁸	17j	2SC2660
2 SD 761	Say	Si-N	P, 180/180V, 1,5/3A, 20W, 6MHz		17j	TO-220	2SD1138	17j	BD 239E, 2SD608A, 2SD610, 2SD1138, ++
2 SD 762	Mat	Si-N	P, 60/60V, 3/4A, 25W	(2SB724	17j	TO-220	BD 243 C	17j	BD 241A, BD 535, BD 539A, BD 935, ++
2 SD 762 A		Si-N	=2SD762: 80/80V, 4A, 30W		17j	TO-220	BD 243 C	17j	BD 243B, BD 537, BD 539B, BD 951, ++
2 SD 763	Hit	Si-N	Uni, TV-HA, 120/60V, 1/1,5A, 0,9W, sat<0,5V(1A)		7c(9mm)	TO-92L	(2SD1812)	7c(9mm)	(2SC2383, 2SC3228, 2SD667(A), 2SD1812)
2 SD 764	Hit	Si-N	TV-HA, 1500/600V, 1,5A, 50W, sat<1,5V(1A)		23a	TO-3	(BU 208 A)	23a	BU 205...206, 2SC1922, 2SD818... 819, ++
2 SD 765	Hit	Si-N	TV-HA, 1500/800V, 3A, 50W, sat<5V(2,5A)		23a	TO-3	BU 208 A	23a	BU 207...209(A), BU 508(A), 2SC3023...24, ++
2 SD 766	Mat	Si-N	S P, LF Out, 300V, 0,7/2,5A, 30W, 45MHz		22a	TO-66	(BUX 85)	17j	BUW 40(A), TIP 47...50, 2SC782, ++
2 SD 767	Mat	Si-N	Uni, 60/60V, 0,1A, 0,25W, 150MHz, Ur=0,3V	(2SB725	7c	TO-92	BC 546	7a	BC 174, BC 182, BC 190, BC 546, ++
2 SD 768(K)	Hit	Si-N-Darl+Di	P, 120/120V, 6/10A, 40W, hFE=1k...20k, 1/3µs	(2SB727	17j	TO-220	2SD1756 ⁷	17j	BD 651, BDW 63D, BDW73D, BDT 21
2 SD 769	Mat	Si-N	Uni, 20/15V, 0,5A, 0,4W		7c	TO-92	BC 639	7c	BC 337... 338, BC 635, BC 637, BC 639, ++
2 SD 770	Mat	Si-N	=2SD769: 50/40V		7c	TO-92	BC 639	7c	BC 337, BC 635, BC 637, BC 639, ++
2 SD 771	Mat	Si-N	Uni, 25/25V, 0,05A, 0,15W, F=6dB(1kHz)		7c	TO-92	BC 546	7a	BC 168, BC 183, BC 238, BC 548, ++
2 SD 772	Mat	Si-N	P, 150/80V, 5A, 40W, 40MHz		17j	TO-220	(BU 406)	17j	MJE 15030
2 SD 772 A		Si-N	=2SD772: 200V		17j	TO-220	(BU 406)	17j	-
2 SD 772 B		Si-N	=2SD772: 250V		17j	TO-220	(BU 406)	17j	-
2 SD 773	Nec	Si-N	LF, 20/16V, 2A, 1W, 110MHz	(2SB733	9b		2SC3225	7c(9mm)	2SC3225, 2SC4484, 2SD1246...47
2 SD 774	Nec	Si-N	Uni, 100/50V, 1A, 1W, 95MHz	(2SB734	9b		2SD774	9b	2SD1616A, 2SD1768, 2SD1857, (BC 639) ¹³
2 SD 776	Tos	Si-N	S P, 200/180V, 5A, 100W, hi-hFE=500...2000		23a	TO-3			2SD1090
2 SD 777	Tos	Si-N	TV Reg, int. Z-Diode(C ·B, 55V), 55/55V, 4/20A 100W, hi-hFE=500...2500		23a	TO-3			-
2 SD 778	Mat	Si-N	Uni, 30/25V, 0,1A, 0,4W		9c	BC 546	7a	BC 168, BC 183, BC 238, BC 548, ++	
2 SD 779	Mat	Si-N	=2SD778: 60/50V		9c	BC 546	7a	BC 174, BC 182, BC 190, BC 546, ++	
2 SD 780	Nec	Si-N	SMD, Uni, 60/50V, 0,3A, 140MHz	(2SB736	35a	BC 817	35a	BCW 65...66	
2 SD 780 A		Si-N	=2SD780: 80/80V		35a	SOT-23			BCW 66
2 SD 781	Hit	Si-N	S P, TV-HA, 150/60V, 2/2,5A, sat<0,6V(1,5A)		14h	TO-126			2SD975
2 SD 782	Hit	Si-N	TV-HA, 300/80V, 5A, 30W		17j	TO-220	BU 406	17j	BU 406...408, 2SD884...885, 2SD1150, ++
2 SD 783	Hit	Si-N	TV-HA, 1500/600V, 4A, 50W, sat<5V(3,5A)		23a	TO-3	BU 208 A	23a	BU 208...209(A), BU 508(A), 2SC2928, ++
2 SD 784	Hit	Si-N	=2SD783: 1700/700V, 5A, sat<5V(4,5A)		23a	TO-3	2SC3026	23a	BU 209(A), 2SC3026
2 SD 785	Hit	Si-N	=2SD783: 1900/700V, 5A		23a	TO-3	(BU 209) ⁷	23a	2SC2125
2 SD 786(S)	Rhm	Si-N	LF, In, 50/40V, 0,3A, 0,25W, 100MHz	(2SB737	7c, 41c	TO-92, -	BC 550	7a	BC 184, BC 413...414, BC 550, 2SC2390, ++
2 SD 787	Hit	Si-N	LF Out, 20/16V, 2A, 0,9W, 100MHz	(2SB738	7c(9mm)	TO-92L	2SD1207	7c(9mm)	2SD1100, 2SD1014, 2SD1146, 2SD1207, ++
2 SD 788	Hit	Si-N	=2SD787: 20/20V	(2SB739	7c(9mm)	TO-92L	2SD1207	7c(9mm)	2SD1100, 2SD1014, 2SD1146, 2SD1207, ++
2 SD 789	Hit	Si-N	LF Out, 100/50V, 1A, 0,9W, 100MHz	(2SB740	7c(9mm)	TO-92L	2SD1812	7c(9mm)	2SC2383, 2SC3228, 2SD667(A), 2SD1812, ++
2 SD 790	Hit	Si-N	=2SD789: 100/70V	(2SB741	7c(9mm)	TO-92L	2SD1812	7c(9mm)	2SC2383, 2SC3228, 2SD667(A), 2SD1812, ++
2 SD 792	Mat	Si-N	TV-HA, 1500/700V, 5A, 35W(Tc=90°), sat<1,5V(4,5A)		23a	TO-3	BU 208 A	23a	BU 208(A), BU 508(A), 2SC2928, 2SD954, ++
2 SD 793	Nec	Si-N	P, 40/30V, 3A, 10W, 65MHz	(2SB743	14h	TO-126	2SD1348	14h	BD 785, MJE 240...244, 2SD1348
2 SD 794(A)	Nec	Si-N	P, 70/45(A=70/60V), 3/5A, 10W, 60MHz	(2SB744	14h	TO-126	(BD 189) ⁸	14h	BD 787, BD 789, MJE 240...244
2 SD 795(A)	Nec	Si-N	P, 50/40(A=50/50V), 3/6A, 20W, 95MHz, sat<0,7V(2A)		17j	TO-220	(BD 243 C) ⁸	17j	2SC3252, 2SC3258
2 SD 796	Fjd	Si-N-Darl	S P, 500/450V, 8A, 100W, hFE>200, <1,4/21µs		23a	TO-3			BU 922, BUW 81(A), 2SD707, 2SD685, ++
2 SD 797	Tos	Si-N	S P, 100/80V, 30A, 200W, 3MHz, 1,5/7µs		23a	TO-3			BDW 30, BDY 29, MJ 802
2 SD 798	Tos	Si-N-Darl	S P, 600/300V, 6A, 30W, hFE>1500, 1/13µs		17j	TO-220	2SC798	17j	BU 810, 2SC3579
2 SD 799	Tos	Si-N-Darl+Di	S P, 600/400V, 6A, 30W, hFE>600, 1/13µs		17j	TO-220	2SD798	17j	BU 810, 2SC3579
2 SD 800	Hit	Si-N	S P, 750/300V, 4A, 30W, 8MHz, <1/350ns		23a	TO-3	BUW 11 A	18j	BUS 11(A), BUW 11(A), BUX 82...83, ++
2 SD 801	Hit	Si-N	S P, TV-SN, 800/375V, 6A, 50W		23a	TO-3	BU 426 A	18j	BU 326(A), BU 426(A), BU 526, 2SD1093
2 SD 802	Hit	Si-N	=2SD801: 900/400V		23a	TO-3	BU 426 A	18j	BU 326A, BU 426A, BU 526, 2SD1093
2 SD 803	Mat	Si-N-Darl+Di	P, 120/100V, 8A, 100W, hFE>						

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International	
2 SD 807	Sak	Si-N	TV-HA, 1500/800V, 5A, 50W, sat<1V(2A)	23a	TO-3	BU 208 A	23a	BU 208(A), BU 508(A), 2SC2928, 2SD954,++
2 SD 808	Hit	Si-N	Uni, 25/20V, 0.5A, 0.4W, 250MHz	7c	TO-92	BC 337	7a	BC 337...338, BC 635, BC 637, BC 639, ++
2 SD 809(1)	Nec	Si-N	P, 100/50V, 1/2A, 10W, 85MHz, sat<0.6V(1A)	{2SB731 14h	TO-126	BD 139	14h	BD 139, BD 230, BD 379, 2SD1177...78, ++
2 SD 810	Sak	Si-N	20/20/20V, 4A, 30W, hi-hFE=400>200, sat<0.3V(3A)	17j	TO-220	-	-	-
2 SD 811	Tos	Si-N	S P, 900/400V, 6/10A, 50W, 5MHz	23a	TO-3	BU 426 A	18j	BU 526, BU 536, BUW 12A, BUW 47A, ++
2 SD 812	Mat	Si-N	P, 80/80V, 5/8A, 40W, 15MHz	{2SB747 17j	TO-220	BD 243 C	17j	BD 243B, BD 539B, BD 543B, BD 951, ++
2 SD 813	Mat	Si-N	SMD, 25/20V, 0.5A, 150MHz, sat<0.4V(0.5A)	{2SB779 35a	SOT-23	(BC 817) ¹⁷	35a	2SC3265, (BC 817...818, BCX 19...20) ¹⁷
2 SD 814	Mat	Si-N	SMD, in, 150/150V, 50/100mA, 150MHz	{2SB792 35a	SOT-23	-	-	-
2 SD 814 A		Si-N	=2SD814: 185/185V	35a	SOT-23	-	-	-
2 SD 815	Fjd	Si-N-Darl	S P, 120/120V, 30A, 300W, hFE=300, <3/11µs	68a				
2 SD 816	Fjd	Si-N-Darl	S P, 300/300V, 4A, 30W, hFE=1500, <2/20µs	17j	TO-220	-	-	2SD1073
2 SD 817	Tos	Si-N	TV-HA, 1500/600V, 1.5A, 50W	23a	TO-3	(BU 208 A)	23a	BU 205...206, 2SC1922, 2SC3023...24, ++
2 SD 818	Tos, Tho	Si-N	TV-HA, 1500/600V, 2.5A, 50W, 3MHz, sat<8V(2A)	23a	TO-3	BU 208 A	23a	BU 205...206, 2SC1922, 2SD849...850, ++
2 SD 819	Tos, Tho	Si-N	=2SD818: 3.5A, sat<8V(3A)	23a	TO-3	BU 208	23a	BU 208...209(A), BU 508(A), 2SC3023...24, ++
2 SD 820	Tos	Si-N	=2SD818: 5A, sat<5V(4A)	23a	TO-3	BU 208	23a	BU 208(A), BU 508(A), 2SC2928, 2SD954, ++
2 SD 821	Tos	Si-N	=2SD818: 6A, sat<5V(5A)	23a	TO-3	BU 508 A	18j	BU 508(A), 2SC3025...3026, 2SD649, ++
2 SD 822	Tos	Si-N	=2SD818: 7A, sat<5V(6A)	23a	TO-3	BU 508 A	18j	BU 508(A), 2SC3027...3028, 2SD1011, ++
2 SD 823	Say	Si-N	P, TV-HA, 200/90V, 6/10A, 40W, 15MHz, sat<1.5V(5A)	17j	TO-220	BU 406	17j	BU 406...409, 2SD884...885, 2SD1150, ++
2 SD 824(A)	Hit	Si-N	120/100V, 6A, 60W, 10(A=25)MHz, sat<0.3V(5A)	{2SB748 20j		2SC3264	20j	2SC2525...26, 2SC2564...65, 2SD745(A,B), ++
2 SD 825(A)	Hit	Si-N	120/120V, 7A, 80W, 10(A=25)MHz, sat<0.3V(5A)	{2SB749 20j		2SC3264	20j	2SC2525...26, 2SC2564...65, 2SD745(A,B), ++
2 SD 826	Say	Si-N	Strobo Flash, 60/20V, 5/8A, 10W, 120MHz, 30/340ns	14h	TO-126	-	-	BDX 35...37
			lo-sat<0.5V(3A)					
2 SD 827	Hit	Si-N-Darl+Di	S P, 500/500V, 4A, 50W, hFE>500	20j				(2SD932)
2 SD 828	Hit	Si-N-Darl+Di	=2SD827: hFE=2000	20j				(2SD932)
2 SD 829(K)	Hit	Si-N-Darl+Di	P, 150/120V, 15A, 100W, hFE=4000	20j				(2SD852)
2 SD 830	Fuj	Si-N-Darl	P, 150/100V, 5A, 30W, hFE=2k...20k, -9µs	17j	TO-220	2SD1756	17j	BDX 53F, 2SD1128, 2SD1169, 2SD1590
2 SD 831	Fuj	Si-N-Darl	S P, 500/400V, 20A, 150W, hFE=500	23a	TO-3	-	-	BUT 13, MJ 10001, MJ 10005, MJ 10008...09
2 SD 832	Fuj	Si-N-Darl	S P, 600/400V, 50A, 400W, hFE=200, <1/10.5µs	=74				-
2 SD 833	Fjd	Si-N-Darl	P Motor Drv, 60/60V, 7A, 40W, hFE>4000	17j	TO-220	2SD1756	17j	(BD 645, BD 897, BDW 73A, BDX 53A, ++)
2 SD 834	Fjd	Si-N-Darl	S-Reg, 250/200V, 4A, 25W, B>1500, <1.7/33µs	17j	TO-220	-	-	2SD816, 2SD1073
2 SD 835	Fjd	Si-N-Darl	S-Reg, 400/400V, 6A, 40W, hFE=400, <1/18µs	17j	TO-220	-	-	BU 910...912, 2SD1114, 2SD1245
2 SD 836	Mat	Si-N-Darl+Di	P, 60/60V, 2A, 35W, hFE=1k...10k, 0.4/4µs	{2SB750 17j	TO-220	BD 901	17j	BD 715, BDW 23A, BDW 53A, BDW 63A, ++
2 SD 836 A		Si-N-Darl+Di	=2SD836: 80/80V	17j	TO-220	BD 901	17j	BD 717, BDW 23B, BDW 53B, BDW 63B, ++
2 SD 836 B		Si-N-Darl+Di	=2SD836: 100/100V	17j	TO-220	BD 901	17j	BDW 23C, BDW 53C, BDW 63C, ++
2 SD 837	Mat	Si-N-Darl+Di	P, 60/60V, 4A, 40W, hFE=1k...10k, 0.3/4µs	{2SB751 17j	TO-220	BD 901	17j	BD 645, BD 897, BDW 23A, BDW 63A, ++
2 SD 837 A		Si-N-Darl+Di	=2SD837: 80/80V	17j	TO-220	BD 901	17j	BD 647, BD 899, BDW 23B, BDW 63B, ++
2 SD 837 B		Si-N-Darl+Di	=2SD837: 100/100V	17j	TO-220	BD 901	17j	BD 649, BD 901, BDW 23C, BDW 63C, ++
2 SD 838	Say	Si-N	TV-HA, 2500/900V, 3/6A, 50W, sat<10V(1.5A)	23a	TO-3	-	-	2SD621
2 SD 839	Mit	Si-N-Darl	P, 35/30V, 4A, 30W, hFE=1000...3000, -3.7µs	17j	TO-220	BD 901	17j	BD 713, BDW 23, BDW 53, BDW 63, ++
2 SD 840	Mit	Si-N-Darl	P, 70/60V, 5A, 40W, hFE=1000...3000, -5.5µs	17j	TO-220	BD 901	17j	BD 647, BD 899, BDW 23B, BDW 63B, ++
2 SD 841	Tos	Si-N	S P, TV-SN, 800/400V, 3A, 40W, 4MHz, <1/8µs	17j	TO-220	BUT 11 A	17j	BUT 11(A), BUW 46(A), 2SC3047, 2SC3086, ++
2 SD 842	Tos	Si-N-Darl+Di	P, 80/80V, 30A, 150W, hFE=4000>1000, 0.7/10.5µs	23a	TO-3	-	-	BDX 69A...C, MJ 11014, 2SD1460, ++
2 SD 843	Tos	Si-N	DC-DC Conv., 100/80V, 7A, 40W, 10MHz, sat<0.5V(4A)	17j	TO-220	-	-	(2SD1237L) ⁷
			0.4/3µs	{2SB753				
2 SD 844	Tos	Si-N	P, 50/50V, 7A, 60W, 15MHz, sat<0.4V(4A)	{2SB754 18j	TO-3P	2SD844	18j	2SD1063
2 SD 845	Tos	Si-N	P, 150/150V, 12A, 120W, 20MHz	{2SB755 20j		2SC3264	20j	2SC2526, 2SC2766(A), 2SC2838, 2SC2921, ++
2 SD 846	Tos	Si-N	P, 200/200V, 15A, 150W, 20MHz	{2SB756 20j		2SC3264	20j	2SC2773...2774, 2SC3264, 2SC3370
2 SD 847	Fjd	Si-N	P, S-Reg, 40/40V, 15A, 80W, <1/3µs	{2SB757 18j	TO-3P	BD 249 C	18j	BD 249, BD 545, BD 745, 2SC3256
2 SD 848	Nec	Si-N	P, 120/120V, 7A, 80W	19j				2SC2276, 2SD588
2 SD 848 A		Si-N	=2SD848: 130/130V	19j				2SC2276, 2SD588
2 SD 849	Mat	Si-N	TV-HA, 1500/600V, 3/5A, 70W, sat<5V(3A)	23a	TO-3	BU 208 A	23a	BU 208...209(A), BU 508(A), 2SD850, ++
2 SD 850	Mat	Si-N	TV-HA, 1500/700V, 3/5A, 65W, sat<4V(2.5A)	23a	TO-3	BU 208 A	23a	BU 208...209(A), BU 508(A), 2SD849, ++
2 SD 851	Nec	Si-N-Darl+Di	S P, 150/100V, ±10/20A, 80W, hFE=3k>1k, 1/7µs	20j				2SD829
2 SD 852	Nec	Si-N-Darl+Di	S P, 150/100V, ±15/30A, 100W, hFE=3k>1k, 1/7µs	20j				2SD829
2 SD 854	Mit	Si-N	S, 100/80V, 2.2A, 10W(Tc=25°), 100MHz, <100/500ns	2a	TO-39	-	-	-
2 SD 855	Mat	Si-N	P, 60/60V, 1/2A, 30W, -1µs	{2SB760 17j	TO-220	BD 243 C	17j	BD 239A, BD 241A, 2SC1398, 2SC3252, ++
2 SD 855 A		Si-N	=2SD855: 80/80V	17j	TO-220	BD 243 C	17j	BD 239B, BD 241B, 2SC2275(A), 2SC3252, ++
2 SD 855 B		Si-N	=2SD855: 100/100V	17j	TO-220	BD 243 C	17j	BD 239C, BD 241C, 2SC2275(A), 2SC2528, ++
2 SD 856	Mat	Si-N	P, 60/60V, 3/5A, 35W, -3µs	{2SB761 17j	TO-220	BD 243 C	17j	BD 241A, BD 535, BD 539A, BD 935, ++
2 SD 856 A		Si-N	=2SD856: 80/80V	17j	TO-220	BD 243 C	17j	BD 241B, BD 537, BD 539B, BD 937, ++
2 SD 856 B		Si-N	=2SD856: 100/100V	17j	TO-220	BD 243 C	17j	BD 241C, BD 539C, BD 937, 2SD613, ++
2 SD 857	Mat	Si-N	P, 60/60V, 4/8A, 40W, -1.4µs	{2SB762 17j	TO-220	BD 243 C	17j	BD 243A, BD 535, BD 539A, BD 949, ++
2 SD 857 A		Si-N	=2SD857: 80/80V	17j	TO-220	BD 243 C	17j	BD 243B, BD 537, BD 539B, BD 951, ++
2 SD 857 B		Si-N	=2SD857: 100/100V	17j	TO-220	BD 243 C	17j	BD 243C, BD 539C, BD 953, 2SD613, ++
2 SD 858	Mat	Si-N	P, 60/60V, 5/10A, 60W, -1.4µs	{2SB763 18j	TO-3P	BD 245 C	18j	BD 245A, BDV 91, 2SD895, 2SD718, ++
2 SD 858 A		Si-N	=2SD858: 80/80V	18j	TO-3P	BD 245 C	18j	BD 245B, BDV 93, 2SD895, 2SD718, ++
2 SD 858 B		Si-N	=2SD858: 100/100V	18j	TO-3P	BD 245 C	18j	BD 245C, BDV 95, 2SD895, 2SD718, ++
2 SD 859	Mat	Si-N	P, 350/250V, 0.75A, 35W, -2µs, sat<1V(1A)	17j	TO-220	BUX 85	17j	BUW 40(A,B), BUX 85, TIP 47...50
2 SD 859 A		Si-N	=2SD859: 400/300V	17j	TO-220	BUX 85	17j	BUW 40(A,B), BUX 85, TIP 48...50
2 SD 859 B		Si-N	=2SD859: 450/350V	17j	TO-220	BUX 85	17j	BUW 40(A,B), BUX 85, TIP 49...50
2 SD 860	Mat	Si-N	P, 350/250V, 1A, 40W, -2µs, sat<1V(2A)	17j	TO-220	BUX 85	17j	BUW 40(A,B), BUX 85, TIP 47...50
2 SD 860 A		Si-N	=2SD860: 400/300V	17j	TO-220	BUX 85	17j	BUW 40(A,B), BUX 85, TIP 48...50
2 SD 860 B		Si-N	=2SD860: 450/350V	17j	TO-220	BUX 85	17j	BUW 40(A,B), BUX 85, TIP 49...50
2 SD 861	Mat	Si-N	P, 350/250V, 1.5A, 45W	17j	TO-220	BUX 85	17j	BUW 40(A,B), BUX 85, TIP 47...50
2 SD 861 A		Si-N	=2SD861: 400/300V	17j	TO-220	BUX 85	17j	BUW 40(A,B), BUX 85, TIP 48...50
2 SD 861 B		Si-N	=2SD861: 450/350V	17j	TO-220	BUX 85	17j	BUW 40(A,B), BUX 85, TIP 49...50
2 SD 862	Mat	Si-N	P, 20/16V, 2A, 10W	14h	TO-126	BD 237	14h	BD 175, BD 233, BD 329, BD 375, ++
2 SD 863	Say	Si-N	Uni, 60/50V, 1/2A, 0.9W, 150MHz	{2SB764 7c(9mm)	TO-92L	2SD1207	7c(9mm)	2SD1014, 2SD1146, 2SD1207, 2SD1292, ++
2 SD 864(K)	Hit	Si-N-Darl+Di	P, 120/120V, 3/6A, 30W, hFE=1k...20k	{2SB765 17j	TO-220	2SD1756	17j	BDW 53D, BDW 63D, 2SD1147
2 SD 865	Fjd	Si-N-Darl	S P, 300/300V, 4A, 40W, hFE=1500, <2/20µs	22a	SOT-9	-	-	2SD816, 2SD977, 2SD1073
2 SD 866	Mat	Si-N	130/80V, 7/15A, 40W, 30MHz, sat<0.5V(5A)	{2SB870 17j	TO-220	-	-	-
2 SD 866 A		Si-N	=2SD866: 150/100V	17j	TO-220	-	-	-
2 SD 867	Tos	Si-N	S P, 130/110V, 10A, 100W, 3MHz, 1.5/5.7µs	23a	TO-3	2SC3263	18j	BD 245D, 2N3442, 2N4348, 2SD551, ++
2 SD 868	Tos	Si-N+Di	=2SD818: int. Damper-Diode	23a	TO-3	BU 208 D	23a	BU 208D, 2SD1301, 2SD1171...1175, ++
2 SD 869	Tos	Si-N+Di	=2SD819: int. Damper-Diode	23a	TO-3	BU 208 D	23a	BU 208D, 2SD1171...1175, ++
2 SD 870	Tos	Si-N+Di	=2SD820: int. Damper-Diode	23a	TO-3	BU 208 D	23a	BU 208D, 2SD1171...1175, ++
2 SD 871	Tos	Si-N+Di	=2SD821: int. Damper-Diode	23a	TO-3	BU 508 D	18j	BU 508D
2 SD 872	Mit	Si-N	S P, 500/400V, 5A, 40W, -3µs	17j	TO-220	BUT 56 A	17j	BUT 54A, BUT 56(A), 2SC2827, 2SC3497, ++
2 SD 873	Tos	Si-N	=2N3773	23a	TO-3	(2SC3281) ⁴	=16j	=2N3773
2 SD 874	Mat	Si-N	SMD, Uni, 30/25V, 1/1.5A, 200MHz	{2SB766 39b	SOT-89	-	-	BC 868, BCX 68, 2SC2883, 2SC2982
2 SD 874 A		Si-N	=2SD874: 60/50V	39b	SOT-89	-	-	BCX 55...56, 2SC3444, 2SD1005, 2SD1418
2 SD 875	Mat	Si-N	SMD, Uni, 80/80V, 0.5/1A, 120MHz	{2SB767 39b	SOT-89	-	-	2SC3438, 2SD968(A), 2SD1006...07, 2SD1767
2 SD 876	Mat	Si-N	200/150V, 1/2.5A, 40W, 25MHz, hi-hFE=500...2000	17j	TO-220	-	-	2SC2317

Original	Fabric.	Constr.	Info	{ Compl. Fig.	JAEGER	Fig.	International		
2 SD 877	Tos	Si-N	P, 110/80V, 3A, 25W, 3MHz, 1,5/7µs	{2SB502A	22a	TO-66	BD 243 C	17j	BD 241C, BD 939, BDW 25, BDX 25, ++
2 SD 878	Tos	Si-N	=2N3055		23a	TO-3	2N3055	23a	*2N3055
2 SD 879	Say	Si-N	30/10V, 3/5A, 0,75W, 200MHz, sat<0,4V(3A)	{2SB893	7c	TO-92	2SD1347	7c(9mm)	2SD1347
2 SD 880	Tos	Si-N	P, 60/60V, 3A, 30W, 3MHz, 0,8/2,3µs	{2SB834	17j	TO-220	BD 243 C	17j	BD 241A, BD 537, BD 937, 2SD712, ++
2 SD 882	Nec	Si-N	P, 40/30V, 3/7A, 10W, 90MHz, sat<0,5V(2A)	{2SB772	14h	TO-126	2SD882	14h	BD 785, MJE 240...244, 2SD794(A)
2 SD 883	Nec	Si-N	P, 100/100V, 6A, 70W	{2SB773	19j				2SC2276, 2SD587...588, 2SD848(A)
2 SD 883 A		Si-N	=2SD883: 120/120V		19j				2SC2276, 2SD587...588, 2SD848(A)
2 SD 884	Mat	Si-N	TV-HA, 330/200V, 7/10A, 40W, sat<1V(5A), -/~3µs		17j	TO-220	BU 406	17j	BU 406...408, 2SC3173, 2SC3590...91, ++
2 SD 885	Mat	Si-N	=2SD884: 330/330V		17j	TO-220	BU 406	17j	BU 406...408, 2SC3173, 2SC3590...91, ++
2 SD 886	Mat	Si-N	P, 80/60V, 3/6A, 40W, 50MHz, hi-hFE=500...1500		17j	TO-220			2SD887...888, 2SD1157, 2SD1943, 2SC1983
2 SD 886 A		Si-N	=2SD886: 100/80V		17j	TO-220			2SC2316, 2SC2491
2 SD 887	Mat	Si-N	P, 80/60V, 4/8A, 40W, 50MHz, hi-hFE=500...2000		17j	TO-220			2SC2315...16, 2SC2491, 2SD1157
2 SD 888	Mat	Si-N	P, 80/60V, 6/10A, 50W, 50MHz, hi-hFE=500...2000		17j	TO-220			2SC2315...16, 2SC2491, 2SD1158
2 SD 889	Mat	Si-N	30/25V, hi-Ueb=15V, 0,1/0,2A, 0,4W, 150MHz	{2SB774	7c	TO-92	2SC3071	7c(9mm)	2SC3114, 2SC3135, 2SD1206, 2SD1807
2 SD 890	Mat	Si-N	100/100V, hi-Ueb=15V, 0,02A, 0,25W, 150MHz		7c	TO-92	2SC3071	7c(9mm)	2SC3071, 2SC3492, 2SD1011
2 SD 891	Mat	Si-N-Darl	Uni, 30/25V, 0,2A, 0,25W, hFE=2k...20k		7c	TO-92	BC 879	7c	BC 517, BC 617, BC 875, MPS-A13...14, ++
2 SD 891 A		Si-N-Darl	=2SD891: 60/50V		7c	TO-92	BC 879	7c	BC 875, BSR 50...52, MPS-A27...29, ++
2 SD 892	Mat	Si-N-Darl	Uni, 30/25V, 0,5/0,75A, 0,4W, 150MHz, hFE=2k...20k		7c	TO-92	BC 879	7c	BC617, BC875, BSR50...52, MPS-A27...29, ++
2 SD 892 A		Si-N-Darl	=2SD892: 60/50V		7c	TO-92	BC 879	7c	BC 875, BSR 50...52, MPS-A27...29, ++
2 SD 893	Mat	Si-N-Darl	Uni, 30/25V, 1/1,5A, 0,75W, 150MHz, hFE=2k...20k		7c	TO-92	BC 879	7c	BC617, BC875, BSR50...52, MPS-A27...29, ++
2 SD 893 A		Si-N-Darl	=2SD893: 60/50V		7c	TO-92	BC 879	7c	BC 875, BSR 50...52, MPS-A27...29, ++
2 SD 894	Say	Si-N-Darl	P, 30/25V, 1,5/2,5A, 10W, 120MHz		14h	TO-126	(BD 679) ⁸	14h	2SD985...986, 2SD1379
2 SD 895	Say	Si-N	P, 100/85V, 6/10A, 60W, 15MHz, 0,2/4,7µs	{2SB775	18j	TO-3P	BD 245 C	18j	BD 245C, BDV 95, 2SC2681, 2SD718, ++
2 SD 896	Say	Si-N	P, 120/100V, 7/11A, 70W, 15MHz, 0,2/6,6µs	{2SB776	18j	TO-3P	BD 245 C	18j	BD 245C, 2SC2681, 2SC2837, 2SD718, ++
2 SD 897(A)	Hit	Si-N+Di	TV-HA, 1500V, 1,5A, 50W, sat<5V(1A)		23a	TO-3	BU 208 D	23a	BU 208D, 2SD1171...1175, 2SD1301
2 SD 898(A,B)	Hit	Si-N+Di	=2SD897: 3A(B=3,5A), sat<5V(2,5A)		23a	TO-3	BU 208 D	23a	BU 208D, BU 508D, 2SD1171...1175
2 SD 899(A)	Hit	Si-N+Di	=2SD897: 4A(A=5A), sat<5V(3,5A)		23a	TO-3	BU 208 D	23a	BU 208D, BU 508D, 2SD1171...1175
2 SD 900(A,B)	Hit	Si-N+Di	=2SD897: 5A(B=6A), sat<5V(4,5A)		23a	TO-3	BU 208 D	23a	BU 208D, BU 508D, 2SD1171...1175
2 SD 901	Nec	Si-N	P, 200/150V, 2A, 25W		17j	TO-220	2SD1138	17j	BD 239F, 2SC2660, 2SD760, 2SD1138, ++
2 SD 902	Say	Si-N	S P, 350/300V, 4A, 80W		23a	TO-3	BUW 11 A	18j	BU 326(A), BU 426(A), BUW 11(A), ++
2 SD 903	Fui.Say	Si-N+Di	CTV-HA, 1500/600V, 7/10A, 50W, sat<5V(4A)		23a	TO-3	BU 508 D	18j	BU 508D, 2SD994, 2SC3682, 2SD1732, ++
2 SD 904	Fui.Say	Si-N+Di	CTV-HA, 1500/600V, 7/10A, 50W, sat<5V(3A)		23a	TO-3	BU 508 D	18j	BU 508D, 2SD994, 2SC3682, 2SD1732, ++
2 SD 905	Hit	Si-N	TV-HA, 1400/650V, 8A, 50W, sat<10V(8A)		23a	TO-3	BU 508 A	18j	BU 508(A), 2SC3027...3028, 2SD1279
2 SD 906	Hit	Si-N	TV-HA, 1400/650V, 8A, 50W		23a	TO-3	BU 508 A	18j	BU 508(A), 2SC3027...3028, 2SD1279
2 SD 907	Fjd	Si-N	P, 80/80V, 10A, 80W, <1/3µs	{2SB777	18j	TO-3P	BD 245 C	18j	BD 245B, BD 545B, BDV 93, 2SC256, ++
2 SD 908	Fjd	Si-N	=2SD907: 120/120V		18j	TO-3P	BD 245 C	18j	BD 245C, BD 545D, 2SC2681, 2SD1047, ++
2 SD 909	Fjd	Si-N	P, 80/80V, 15A, 80W		18j	TO-3P	BD 249 C	18j	BD 249B, BD 545B, BD 745B
2 SD 910	Fjd	Si-N	=2SD909: 120/120V		18j	TO-3P	BD 249 C	18j	BD 249C, BD 545D, BD 745D
2 SD 911	Fjd	Si-N	P, 80/80V, 15A, 100W		23a	TO-3	BD 249 C	18j	BD 249B, BD 317, BD 545B, BD 745B, ++
2 SD 912	Fjd	Si-N	=2SD911: 120/120V		23a	TO-3	BD 249 C	18j	BD 249C, BD 545D, BD 745D, 2N5630...31, ++
2 SD 913	Fjd	Si-N	P, S-Reg, 200/80V, 25A, 150W, <1/2,9µs		23a	TO-3			BDW 36, BUW 11...12, BUW 11...12, ++
2 SD 914	Fjd	Si-N	=2SD913: 200/120V		23a	TO-3			BDW 36, BUW 11...12, BUW 11...12, ++
2 SD 915	Fjd	Si-N-Darl	P,S-Reg, 600/600V, 30A, 200W, hFE=300>100, <3/16µs		≈74				-
2 SD 916	Fjd	Si-N-Darl	P, S-Reg, 60/60V, 7A, 30W, hFE>800		17j	TO-220	BD 901	17j	BD 645, BD 897, BDW 73A, BDX 53A, ++
2 SD 917	Mat	Si-N	TV-HA, 330/200V, 7/10A, 70W, sat<1V(5A)		18j	TO-3P	(2SD1680)	18c	(BU 426(A), BU 926)
2 SD 918	Nec	Si-N	P, 250/250V, 2A, 80W		19j				-
2 SD 919	Mat	Si-N	Uni, 30/25V, 0,5A, 0,4W, 200MHz	{2SB780	40c		BC 337	7a	BC 337...338, BC 635, BC 637, BC 639, ++
2 SD 920	Fjd	Si-N-Darl	P, 200/180V, 5A, 100W, 25MHz, hFE>700		23a	TO-3			2SD929, 2SD931, 2SD1090, 2SD1122...23
2 SD 921	Fjd	Si-N-Darl	=2SD920: 80W		18j	TO-3P			2SD1090, 2SD1122...23
2 SD 922	Fjd	Si-N-Darl	P, 150/100V, 10A, 100W, 25MHz, hFE>700		23a	TO-3			2SD1123, 2SD1210
2 SD 923	Fjd	Si-N-Darl	=2SD922: 80W		18j	TO-3P			2SD1123, 2SD1210
2 SD 926	Hit	Si-N	P, 50/50V, 4A, 30W		17j	TO-220	BD 243 C	17j	BD 243, BD 535, BD 539A, BD 949, ++
2 SD 927	Hit	Si-N	=2SD926: 60/60V		17j	TO-220	BD 243 C	17j	BD 243A, BD 535, BD 539A, BD 949, ++
2 SD 928	Hit	Si-N	=2SD926: 80/80V		17j	TO-220	BD 243 C	17j	BD 243B, BD 537, BD 539B, BD 951, ++
2 SD 929	Fjd	Si-N-Darl	P Reg, 200/180V, 5A, 80W, hFE>700		23a	TO-3			2SD776, 2SD920...921, 2SD931, 2SD1123
2 SD 930	Fjd	Si-N-Darl	P, 200/180V, 5A, 30W, hFE=5000		17j	TO-220			2SD1023, 2SD1025
2 SD 931	Fjd	Si-N-Darl	P, 200/180V, 5A, 50W, hFE>700		23a	TO-3			2SD776, 2SD920...921, 2SD929, 2SD1123
2 SD 932	Hit	Si-N-Darl	S P, 500/300V, 6A, 80W, hFE=1500		20j				-
2 SD 933(H)	Hit	Si-N-Darl+Di	int.Z-Diode(C+B), 300/300V, 6/12A, 80W, hFE>500		23a	TO-3			(2SD650, 2SD706, 2SD1043, 2SD1461)
2 SD 934(K)	Hit	Si-N-Darl+Di	S P, 300/300V, 6/12A, 80W, hFE=1500>500		20j				2SD932
2 SD 935	Mat	Si-N	S P, 250/100V, 5A, 60W		18j	TO-3P	(BU 426 A)	18j	TIP 55A...58A, 2SC2305, 2SC2624, 2SD1150
2 SD 936	Tos	Si-N-Darl	S P, 300/250V, 30/60A, 400W, hFE>150, 1/12,5µs		≈74				-
2 SD 937	Tos	Si-N-Darl	=2SD936: 400/350V		≈74				-
2 SD 938	Tos+	Si-N-Darl	=2SD936: 600/450V		≈74				-
2 SD 939	Tos	Si-N-Darl	S P, 300/250V, 40/80A, 400W, hFE>150, 1/12,5µs		≈74				-
2 SD 940	Tos	Si-N-Darl	=2SD939: 400/350V		≈74				-
2 SD 941	Tos	Si-N-Darl	=2SD939: 600/450V		≈74				-
2 SD 942	Tos	Si-N-Darl	S P, 300/250V, 50A, 400W, hFE>150, 1/10,5µs		≈74				-
2 SD 943	Tos	Si-N-Darl	=2SD942: 400/350V		≈74				-
2 SD 944	Rhm	Si-N-Darl	P, 40V, 2A, 5W, 150MHz, hFE=4000	{2SB786	14h	TO-126	(BD 679) ⁸	14h	2SD1379
2 SD 946	Mat	Si-N-Darl	P, 30/25V, 1/1,5A, 150MHz, hFE=4k...40k	{2SB895	14h	TO-126	(BD 679) ¹³	14h	BD 477A.8, BD 875, BDX 42, 2SD1379, ++
2 SD 946 A		Si-N-Darl	=2SD946: 60/50V		14h	TO-126	(BD 679) ¹³	14h	BD 875, BDX 42...44, 2SD1376, ++
2 SD 946 B		Si-N-Darl	=2SD946: 100/80V		14h	TO-126	(BD 879) ¹³	14h	BD 879, BDX 44, 2SD1376, 2SD1953
2 SD 947(F)	Rhm	Si-N-Darl	P, 40V, 2A, 5W, 150MHz, hFE>4000		14b	TO-126 Iso	2SD947	14b	2SD1509, (2SD1379) ³
2 SD 948	Mat	Si-N	TV-HA, 1600V, 1A, 25W		22a	TO-66			BU 505, 2SD470, 2SD1575
2 SD 949	Mat	Si-N	TV-HA, 1500V, 2A, 40W		23a	TO-3	BU 208 A	23a	BU 205...206, 2SC1922, 2SD627, 2SD818, ++
2 SD 950	Mat	Si-N+Di	TV-HA, 1500V, 3/4,5A, 42W, sat<5V(2A)		23a	TO-3	BU 208 D	23a	BU 208D, 2SC3480, 2SD993, 2SD1171...75, ++
2 SD 951	Mat	Si-N+Di	TV-HA, 1500V, 3/5A, 65W, sat<5V(2,5A)		23a	TO-3	BU 208 D	23a	BU 208D, 2SC3480, 2SD993, 2SD1171...75, ++
2 SD 952	Mat	Si-N+Di	TV-HA, 1500V, 3/5A, 70W, sat<5V(3A)		23a	TO-3	BU 508 D	18j	BU 508D, 2SC3480, 2SD1173...75
2 SD 953	Mat	Si-N+Di	TV-HA, 1500V, 5/7A, 95W, sat<5V(4,5V)		23a	TO-3	BU 508 D	18j	BU 508D, 2SD1174...75
2 SD 954	Mat	Si-N	TV-HA, 1500V, 5/7A, 95W, sat<1,5V(4,5A)		23a	TO-3	BU 508 A	18j	BU 508(A)
2 SD 955	Hit	Si-N	LF, 120/80V, 0,05A, 0,625W		7e	TO-92	2SC2632	7c(9mm)	2SC1890A, 2SC2240, 2SC2363, 2SC3245(A)++
2 SD 956	Hit	Si-N+Di	TV-HA, 1500V, 2,5A, 50W, sat<5V(2A)		23a	TO-3	BU 208 D	23a	BU 208D, 2SC3479, 2SD993, 2SD1171...75, ++
2 SD 957	Hit	Si-N+Di	TV-HA, 1500V, 6A, 50W		23a	TO-3			(2SD903...904, 2SD994)
2 SD 957 A		Si-N+Di	=2SD957: 7A, sat<5V(5A)		23a	TO-3			(2SD903...904, 2SD994)
2 SD 958	Mat	Si-N	LF, In, 120/120V, 20/50mA, 0,4W, 200MHz	{2SB788	9c		2SC2632	7c(9mm)	2SC1775A, 2SC2240, 2SC2389, 2SC2459, ++
2 SD 959	Mat	Si-N	P, 130/80V, 3/6A, 30W, 30MHz, sat<0,5V(2A)	{2SB867	17j	TO-220			-
2 SD 960	Mat	Si-N	=2SD959: 4A, 35W, sat<0,5V(3A)	{2SB868	17j	TO-220			-
2 SD 961	Mat	Si-N	=2SD959: 5A, 40W, sat<0,5V(4A)	{2SB869	17j	TO-220			-
2 SD 962	Sak	Si-N-Darl	P, 200/200V, 5A, 80W, hFE=3000		23a	TO-3			2SD776, 2SD920...921, 2SD929, 2SD931, ++
2 SD 963		Si-N-Darl	=2SD962: 100W		23a	TO-3			2SD776, 2SD920...921, 2SD929, 2SD931, ++
2 SD 965	Mat	Si-N	LF, Strobo Flash, 40/20V, 5/8A, 0,75W, 150MHz		7c	TO-92	2SD2179	9c	2SC3671, 2SD1145, 2SD1244, 2SD2249, ++
2 SD 966	Mat	Si-N	=2SD965: 1W	{2SB873	7c(9mm)	TO-92L			2SD1934, 2SD1961

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International	
2 SD 967	Mat	Si-N-Darl	Uni, 30/25V, 0.2A, 0.4W, hFE=7000	9c		BC 879	7c	BC 517, BC 617, BC 875, MPS-A13...13, ++
2 SD 968	Mat	Si-N	SMD, LF, 100/100V, 0.5/1A, 120MHz	(2SB789) 39b	SOT-89			BCX 56, 2SC2881, 2SC3438, 2SD1005...07, ++
2 SD 968 A		Si-N	=2SD968: 120/120V	39b	SOT-89			2SC2881, 2SD1007, 2SD1418...1419
2 SD 969	Mat	Si-N	25/20V, 0.5A, 0.6W, 150MHz, sat<0.4V(0.5A)	(2SB790) 9c		2SD1207	7c	12SD1207, 2SD1246...47, (BC 337...338) ¹⁷
2 SD 970	Hit	Si-N-Darl+Di	P, 120/120V, 8/12A, 40W, hFE=1k...20k	(2SB791) 17j	TO-220	(BD 901) ¹⁷	17j	BD 651, BDT 21, BDW 73D, BDX 53D
2 SD 971	Sak	Si-N-Darl	S P, 300/300V, 6A, 50W, hFE=2000	17j	TO-220			BU 910...912, 2SD1088...1089, 2SD1307, ++
2 SD 972	Sak	Si-N-Darl	S P, 50/50V, 4A, 30W, hFE=3000, -1.7µs	(2SB1005) 17j	TO-220	BD 901	17j	BD 715, BDW 23A, BDW 53A, BDW 63A, ++
2 SD 973	Mat	Si-N	LF Drv, Out, 30/25V, 1/1.5A, 1W, 200MHz	(2SB793) 9c	(M Type)	BC 639	7c	BC 337...338, BC 635, 2SD1225, 2SD1616, ++
2 SD 973 A		Si-N	=2SD973: 60/50V	9c		BC 639	7c	BC 337A, BC 635, BC 637, BC 639, ++
2 SD 974	Hit	Si-N	S, TV, 120/60V, 1/1.5A, 0.9W, sat<0.3V(1A)	7c(9mm)	TO-92L	2SD1812	7c(9mm)	2SC2383, 2SC2228, 2SD667(A), 2SD1812, ++
2 SD 975	Hit	Si-N	S P, TV-HA, 150/60V, 2/2.5A, sat<0.5V(1.5A)	14h	TO-126			2SD781
2 SD 976	Hit	Si-N	TV-HA, 300/120V, 7A, 50W	17j	TO-220	BU 406	17j	BU 406...408, 2SD884...885, 2SD1163, ++
2 SD 976 A		Si-N	=2SD976: 350/150V	17j	TO-220	BU 406	17j	BU 406, BU 408, 2SC3175, 2SC3591
2 SD 977	Say	Si-N-Darl	450/350V, 4A, 40W, hFE=300, sat<2.5V(4A), <1/25µs	17j	TO-220AA			BU 911...912, 2SD987, 2SD1072, 2SD1245, ++
2 SD 978		Si-N-Darl	=2SD977: 5/10A, hFE>400	17j	TO-220AB			BU 911...912, 2SD987, 2SD1072, 2SD1245, ++
2 SD 979	Say	Si-N-Darl	S P, 450/350V, 10/15A, 100W, hFE=900>250, <1/25µs	18j	TO-3P			BU 921...922, BUW 81(A), 2SD685, ++
2 SD 980	Say	Si-N-Darl	=2SD979: 7A	18j	TO-3P			BU 921...922, BUW 81(A), 2SD707, ++
2 SD 981	Fjd	Si-N-Darl	P Reg, 200/180V, 5A, 100W, 25MHz, hFE=3000>700	23a	TO-3			2SD776, 2SD920...921, 2SD929, 2SD931, ++
2 SD 982	Fjd	Si-N-Darl	=2SD981: 40W	17j	TO-220	2SD1756	17j	2SD930, 2SD1023, 2SD1025, 2SD1756
2 SD 983	Fjd	Si-N-Darl	=2SD981: 150/100V, 40W	17j	TO-220	2SD1756	17j	BDX 53F, 2SD830, 2SD1128, 2SD1169, ++
2 SD 985	Nec	Si-N-Darl+Di	P, 150/60V, ±1.5/3A, 10W, hFE=2k...30k	(2SB794) 14h	TO-126	2SD986	14h	2SD2019
2 SD 986	Nec	Si-N-Darl+Di	=2SD985: 150/80V	(2SB795) 14h	TO-126	2SD986	14h	2SD2019
2 SD 987	Nec	Si-N-Darl+Di	S P, 500/400V, ±5/10A, 40W, hFE>200, 1/13µs	17j	TO-220	2SD798	17j	BU 912, 2SD798...799, 2SD1245
2 SD 990	Hit	Si-N-Darl	P, 100/80V, 3A, 30W, 80MHz, hFE=500	17j	TO-220	BD 901		BDW 23C, BDW 53C, BDW 63C, 2SD837B, ++
2 SD 991	Hit	Si-N-Darl+Di	int. Z-Diode(C - B), 300/300V, 6/10A, 50W, hFE>500	17j	TO-220			(2SD971, 2SD1071, 2SD1088...89, 2SD1113+)
2 SD 992(Z)	Nec	Si-N	P, 30/30V, 2/3A, 10W, lo-sat<0.5V(2A)	30j	TO-251	2SC4135 ¹⁸	30j	2SC3076, 2SD1801...02 ¹⁸
			Rbe=1kΩ	Z: TO-252				
2 SD 993	Say	Si-N+Di	CTV-HA, 1500/600V, 3/6A, 50W, sat<10V(2.5A)	23a	TO-3	BU 208 D	23a	BU 208D, 2SC3480, 2SD1171...75, 2SD1654++
2 SD 994	Say	Si-N+Di	CTV-HA, 1500/600V, 8/14A, 50W, sat<5V(5A)	23a	TO-3	BU 508 D	18j	BU 508D, BU 2508D, 2SC3683
2 SD 995	Say	Si-N+Di	CTV-HA, 2500/900V, 3/7A, 50W	23a	TO-3			-
2 SD 997	Nec	Si-N	P, 250/200V, 10A, 200W, 15MHz	(2SB796) 23a	TO-3			BUX 17(A...C), 2SC1586, 2SD555, 2SD583
2 SD 998	Nec	Si-N-Darl	P, 100/60V, 1.5A, 10W, hFE=7000	14h	TO-126	(BD 679)	14h	BD 681, 2SD1376
2 SD 999	Nec	Si-N	SMD, Uni, 30/25V, 1/1.5A, 130MHz	(2SB798) 39b	SOT-89			BC 868, BCX 54, BCX 68, 2SC2883, ++
2 SD 1000	Nec	Si-N	SMD, Uni, 60/50V, 0.7/1A, 110MHz	(2SB799) 39b	SOT-89			BCX 56, 2SC2881, 2SD1005...07, 2SD1418, ++
2 SD 1001	Nec	Si-N	SMD, Uni, 80/80V, 0.3/0.5A, 140MHz	(2SB800) 39b	SOT-89			2SC2882, 2SC3438, 2SD875, 2SD968(A)
2 SD 1002	Nec	Si-N	SMD, Uni, 45/45V, 1A, 160MHz	39b	SOT-89			BCX 54...56, 2SC3444, 2SD874A, 2SD1368, ++
2 SD 1003	Nec	Si-N	=2SD1002: 60/60V	39b	SOT-89			BCX 55...56, 2SC3444, 2SD874A, 2SD1368, ++
2 SD 1004	Nec	Si-N	=2SD1002: 100/80V	39b	SOT-89			BCX 56, 2SD1005, 2SD1368, 2SD1418...19
2 SD 1005	Nec	Si-N	SMD, 100/80V, 1/1.5A, 100MHz	(2SB804) 39b	SOT-89			BCX 56, 2SC2881, 2SD1368, 2SD1418...19
2 SD 1006	Nec	Si-N	SMD, 100/100V, 0.7/1.2A, 90MHz	(2SB805) 39b	SOT-89			BCX 56, 2SC2881, 2SD1368, 2SD1418...19
2 SD 1007	Nec	Si-N	=2SD1006: 120/120V	(2SB806) 39b	SOT-89			2SC2881, 2SC4373, 2SD1418...19
2 SD 1008	Tos	Si-N						-
2 SD 1009	Mat	Si-N	SMD, Uni, In, 150/150V, 0.05A, 160MHz	(2SB807) 39b	SOT-89			-
2 SD 1010	Mat	Si-N	In, 50/40, hi-Ueb=15V, 50/100mA, 0.3W, 200MHz	7c	TO-92	2SC3071	7c(9mm)	2SC3495, 2SC3071, (2SC3112...13)
			hi-hFE=400...2000, Ur=80mV					
2 SD 1011		Si-N	In, 100/100V, hi-Ueb=15V, 20/50mA, 0.3W, 200MHz	7c	TO-92	2SC3071	7c(9mm)	2SC3495, 2SC3071
			hi-hFE=400...2000, Ur=80mV					
2 SD 1012	Say	Si-N	20/15V, 0.7/1.5A, 0.25W, 250MHz	(2SB808) 41c		2SD1207	7c	2SC3225, 2SD1207, 2SD1835
2 SD 1014	Son	Si-N	S, 50/50/50V, 2A, 0.9W, hFE=150...1500	7c(9mm)	TO-92L			-
2 SD 1015	Son	Si-N	S, 140/50/50V, 2A, 0.9W, hFE=150...1500	7c(9mm)	TO-92L			-7
2 SD 1016	Say	Si-N	TV-HA, 1500/600V, 7A, 50W	23a	TO-3	BU 508 A	18j	BU 508A, 2SC3027...28, 2SC3686, 2SD822, ++
2 SD 1017	Nec	Si-N	TV-Reg, 250/250V, 2A, 50W	16j	(MP-80)	(BUW 11 A)	18j	TIP 51...55, 2SC2809
2 SD 1018	Nec	Si-N	=2SD1017: 4A, 80W	16j	(MP-80)	(BUW 11 A)	18j	TIP 51...54, 2SC2624, 2SC3083
2 SD 1020	Nec	Si-N	Uni, 30/25V, 0.7/1A, 0.35W, 170MHz	(2SB810) 40c	(SST)	2SD1207	7c	2SC4483, 2SC4485...2SD1207, 2SD1616
2 SD 1021	Nec	Si-N	Uni, 30/25V, 1/1.5A, 0.35W, 100MHz	(2SB811) 40c	(SST)	BC 639	7c	BC 337...338, BC 635, BC 637, BC 639, ++
2 SD 1022	Shi	Si-N-Darl	100/100V, 5/8A, 30W, 20MHz, hFE=1.5k...1.5k, <2/8µs	17j	TO-220	BD 901	17j	BD 649, BD 901, BDW 23C, BDW 63C, ++
2 SD 1023	Shi	Si-N-Darl+Di	200/200V, 5/8A, 30W, 20MHz, hFE=3k>1.5k, <2/13µs	17j	TO-220	BU 806	17j	BU 806, 2SD1025
2 SD 1024	Shi	Si-N-Darl	100/100V, 8/12A, 50W, 20MHz, hFE=15k>1.5k, <2/8µs	17j	TO-220	BD 901	17j	BD 649, BD 901, BDW 23C, BDW 63C, ++
2 SD 1025	Shi	Si-N-Darl+Di	200/200V, 8/12A, 50W, 20MHz, hFE=3k>1.5k, <2/13µs	17j	TO-220	2SD1756	17j	2SD1141, 2SD1756
2 SD 1026	Shi	Si-N-Darl+Di	100/100V, 15/22A, 100W, 20MHz, hFE=4k>1.5k, <2/8µs	16j		BDW 83 C	18j	BDV 67A, BDW 83C, 2SD1296, 2SD1299, ++
2 SD 1027	Shi	Si-N-Darl+Di	200/200V, 15/22A, 100W, 20MHz, hFE=3k>1.5k, <2/13µs	16j				2SD1515
2 SD 1029	Say	Si-N	P, 60/60V, 4/8A, 40W, 8MHz	(2SB813) 17j	TO-220	BD 243 C	17j	BD 243A, BD 539A, BD 535, BD 949, ++
2 SD 1029 K		Si-N	=2SD1029: 100/90V	17j	TO-220	BD 243 C		BD 243B, BD 539B, BD 537, BD 951, ++
2 SD 1030	Mat	Si-N	=2SD1010: SMD	35a	SOT-23			2SC3689
2 SD 1031	Sak	Si-N-Darl	P, 120/120V, 6/8A, 50W, hFE=4000>700, -/4.5µs	17j	TO-220	2SD1756	17j	BD 651, BDT 21, BDW 73D, BDX 53D, ++
2 SD 1032	Mat	Si-N	P, 60/60V, 4/8A, 60W, 0.2/1.4µs	(2SB812) 18j	TO-3P	BD 245 C	18j	BD 245A, BDV 91, 2SC2681, 2SD895...896, ++
2 SD 1032 A		Si-N	=2SD1032: 80/80V	18j	TO-3P	BD 245 C	18j	BD 245B, BDV 93, 2SC2681, 2SD895...896, ++
2 SD 1032 B		Si-N	=2SD1032: 100/100V	18j	TO-3P	BD 245 C	18j	BD 245C, BDV 95, 2SC2681, 2SD895...896, ++
2 SD 1033	Nec	Si-N	Vid Out, 200/150V, 2/3A, 20W, 10MHz	(2SB768) 30j	TO-252	(2SD1138) ⁶	17j	2SD1250(A), 2SD1557, (2SD610, 2SD1138) ⁶
2 SD 1033(A)	Tos	Si-N-Darl	S P, 600/450V, 300A, 1250W, hFE=300>150, 2/12µs					-
2 SD 1035	Fui	Si-N	S P, 150/120/100V, 3A, 40W, 1.5MHz, -/5µs	17j	TO-220			-
2 SD 1036	Fui	Si-N	S P, 150/120/100V, 15A, 150W, 1.5MHz, -/5µs	20j				-
2 SD 1037	Fui	Si-N	S P, 150/120/100V, 30A, 180W, 1.5MHz, -/4.5µs	20j				-
2 SD 1038	Fui	Si-N	S P, 150/120/100V, 40A, 180W, 1.5MHz, -/5µs	20j				-
2 SD 1039	Fui	Si-N	=2SD1035:	22a	TO-66			-
2 SD 1040(A)	Fui	Si-N	=2SD1036: 120W	23a	TO-3			-
2 SD 1041	Fui	Si-N	=2SD1037: 200W	23a	TO-3			-
2 SD 1042	Fui	Si-N	=2SD1038:	23a	TO-3			-
2 SD 1043	Mat	Si-N-Darl+Di	S P, 430V, 5A, 80W, hFE=1000	23a	TO-3			BU 322(A), BU 921...922, 2SD1461, ++
2 SD 1044	Mat	Si-N-Darl+Di	S P, 100/80V, 6A, 60W, hFE=700...10k	18j	TO-3P			TIP 142, 2SD1170, 2SD1230
2 SD 1044 A		Si-N-Darl+Di	=2SD1044: 170/170V	18j	TO-3P			2SD921, 2SD1090, 2SD1122...1123
2 SD 1045	Hit	Si-N	Uni, 30/10V, 3A, 0.9W, 200MHz	7c(9mm)	TO-92L	2SD1347	7c(9mm)	2SD1347, 2SD1507, 2SD1617, 2SD1864
2 SD 1046	Say	Si-N	P, 150/120V, 8/12A, 80W, 15MHz, 220/7680ns	(2SB816) 18j	TO-3P	2SC2837	18j	BD 245D, 2SC2837, 2SC3263, 2SD751, ++
2 SD 1047	Say	Si-N	P, 160/140V, 12/15A, 100W, 15MHz, 200/7560ns	(2SB817) 18j	TO-3P	2SD1047	18j	BD 745F, 2SC3263
2 SD 1048	Say	Si-N	=2SD1012: SMD	(2SB815) 35a	SOT-23			BCW 65...66
2 SD 1049	Fjd	Si-N	P, 120/80V, 2.5A, 80W, <1/2.9µs	18j	TO-3P	BD 249 C	18j	BD 249C
2 SD 1050	Hit	Si-N-Darl+Di	P, 100/100V, 10A, 80W, hFE=1k...20k	20j				2SD851...852, 2SD1087, 2SD1129
2 SD 1051	Mat	Si-N	Uni, 50/40V, 1.5/3A, 1W, 150MHz	(2SB819) 9c	(M Type)	2SD1207	7c	MPS 650...651, 2SC3328, 2SD619, 2SD1207++
2 SD 1052	Tos	Si-N	50/50V, 3A, 30W, 5MHz, hi-hFE=250...750, 1.5/4.8µs	17j	TO-220			2SC1983, 2SD1943
2 SD 1052 A		Si-N	=2SD1052: hFE=400...1200	17j	TO-220			2SC1983, 2SD1943
2 SD 1053	Nec	Si-N	S P, 400/350V, 1A, 15W	30j	TO-251/252	(BUX 85) ⁴	17j	2SC3362...3363, 2SC3632, (BD 410) ⁴
2 SD 1054	Hit	Si-N	S P, 300/250V, 3A, 80W	23a	TO-3	BUW 11 A	18j	BU 126, TIP51...54, 2SC1463, 2SD632
2 SD 1055	Rhm	Si-N	Uni, 40/32V, 2/2.5A, 0.75W, 100MHz	(2SB822) 9c		2SD1207	7c	MPS 650, 2SC3328, 2SD1207, 2SD1227, ++

Original	Fabric.	Constr.	Info	{Compl.	Fig.	JAEGER	Fig.	International	
2 SD 1056	Fjd	Si-N-Darl	S P. 600/600V, 50A, 400W, hFE>100, <3/16μs		-74				
2 SD 1059	Say	Si-N	P. 100/85V, 6A, 40W		17j	TO-220	BD 243 C	17j	BD 243C, BD 543C, BD 801, 2SD550, ++
2 SD 1060	Say	Si-N	S P. 60/50V, 5/9A, 30W, 30MHz, lo-sat<0.4V(3A)		17j	TO-220	2SD1062	17j	2SC3253, 2SC3258, 2SD1236L
2 SD 1061	Say	Si-N	S P. 60/50V, 7/12A, 40W, 10MHz, lo-sat<0.4V(4A)	(2SB824)	17j	TO-220	2SD1062	17j	2SC3254, 2SD1237L
2 SD 1062	Say	Si-N	S P. 60/50V, 12/15A, 40W, 10MHz, lo-sat<0.4V(6A)	(2SB825)	17j	TO-220	2SD1062	17j	2SC3345, 2SD1212
2 SD 1063	Say	Si-N	S P. 60/50V, 7/14A, 60W, 10MHz, lo-sat<0.4V(4A)	(2SB826)	18j	TO-3P	2SD1065	18j	2SD1187
2 SD 1064	Say	Si-N	S P. 60/50V, 12/17A, 80W, 10MHz, lo-sat<0.4V(6A)	(2SB827)	18j	TO-3P	2SD1065	18j	2SD1238L
2 SD 1065	Say	Si-N	S P. 60/50V, 15/20A, 90W, 10MHz, lo-sat<0.4V(8A)	(2SB828)	18j	TO-3P	2SD1065	18j	2SD1840
2 SD 1066	Fjd	Si-N-Darl	S P. 600/600V, 100A, 770W, hFE>100, <4/16μs		-74				
2 SD 1067	Fjd	Si-N-Darl	S P. 600/600V, 30A, 200W, hFE=200, <3/16μs						
2 SD 1068	Son	Si-N	S P. TV-HA, 1000/900V, 10mA, 25W, 8.5MHz	(2SB832)	17j	TO-220			2SC4256, 2SC4451
2 SD 1069	Tos	Si-N-Di	TV-HA, 300/150V, 7/15A, 40W, 18MHz, sat<1.5V(5A)		17j	TO-220	BU 406 D	17j	BU 406...408, 2SC3589...91, 2SD1163(A)++
2 SD 1070	Nec	Si-N	P. 100/60V, 10/20A, 60W		16j	(MP-80)	BD 245 C	18j	BD 245C, BD 545C, BDV 95, 2SC2681, ++
2 SD 1071	Fjd	Si-N-Darl	S-Reg, 450/450V, 6A, 40W, hFE=1500>500		17j	TO-220	2SD798	17j	BU 910...912, 2SD798...99, 2SD1245
2 SD 1072	Fjd	Si-N-Darl	S-Reg, 450/450V, 5A, 60W, hFE=2500>500, <1.5/18μs		17j	TO-220	(BU 806)	17j	BU 911...912, 2SD978, 2SD987, 2SD1245, ++
2 SD 1073	Fjd	Si-N-Darl	S P. 300/250V, 4A, 40W, hFE=3000>1000		17j	TO-220	(BU 806)	17j	BU 910...912, 2SD816, 2SD978, 2SD987, ++
2 SD 1074	Hit	Si-N	P, 120/80V, 1A, 10W, hFE=160	(2SB844)	30j	TO-251/252	2SC4135	30j	2SC2983, 2SC4134, 2SD1283...84, 2SD1220++
2 SD 1075	Hit	Si-N	=2SD1074: hFE=100	(2SB845)	30j	TO-251/252	2SC4135	30j	2SC2983, 2SC4134, 2SD1283...84, 2SD1220++
2 SD 1076	Hit	Si-N	P, 25/25V, 2.5A, 20W	(2SB836)	30j	TO-251/252	(2SC1398)*	17j	2SC3073, 2SC3386, 2SD1221, 2SD1802, ++
2 SD 1077 L,S	Hit	Si-N	=2SD1076: 35/35V	(2SB837)	30j	TO-251/252	(2SC1398)*	17j	2SC3073, 2SC3386, 2SD1221, 2SD1802, ++
2 SD 1078	Hit	Si-N	P, 50/50V, 2A, 20W	(2SB838)	30j	TO-251/252	2SC4135	30j	2SC3076, 2SD1281...1282, 2SD1801, ++
2 SD 1079	Hit	Si-N	=2SD1078: 80/80V	(2SB839)	30j	TO-251/252	2SC4135	30j	2SC3386, 2SD1281...82, 2SD1815...16*
2 SD 1080 L,S	Hit	Si-N	P, 180/120V, 1.5A, 20W	(2SB840)	30j	TO-251/252	(2SD1138)*	17j	2SC4027, 2SD1033, 2SD1250(A), 2SD1557
2 SD 1081 L,S	Hit	Si-N	=2SD1080: 180/160V	(2SB841)	30j	TO-251/252	(2SD1138)*	17j	2SC4027, 2SD1033, 2SD1250(A), 2SD1557
2 SD 1082	Hit	Si-N	=2SD1080: 200/160V	(2SB842)	30j	TO-251/252	(2SD1138)*	17j	2SD1032, 2SD1250(A), 2SD1557
2 SD 1083 L,S	Hit	Si-N	P, TV, 150/60V, 2A, 10W, hFE>150, sat<0.5V(1.5A)		30j	TO-251/252	(2SD1138)*	17j	2SD1033, 2SD1250(A), 2SD1557
2 SD 1084	Hit	Si-N-Darl	S P. 500/400V, 50A, 400W, hFE=300		-74				
2 SD 1085	Hit	Si-N-Darl+Di	Z-Di(C · B), 300/300V, 3/6A, 40W, hFE=3000>500		17j	TO-220	(BU 806)	17j	2SD816, 2SD1073, (BU 806...807)
2 SD 1087	Tos	Si-N-Darl+Di	100/100V, 15A, 100W, 14MHz, hFE=3k>1k, 0.7/10.5μs		20j				2SD829, 2SD852, 2SD1129...1130
2 SD 1088	Tos	Si-N-Darl	S P. 300/250V, 6A, 30W, hFE=5k>2k, 1/13μs		17j	TO-220	(BU 806)	17j	BU 910...912, 2SD835, 2SD1114, 2SD1307, ++
2 SD 1089	Tos	Si-N-Darl	S P. 350/350V, 6A, 30W, hFE=1000, <2/30μs		17j	TO-220	(BU 806)	17j	BU 910...912, 2SD835, 2SD1114, 2SD1307, ++
2 SD 1090	Tos	Si-N	TV Reg, 200/180V, 5A, 80W, hi-hFE=500...2000		18j	TO-3P			
2 SD 1091	Mat	Si-N-Darl+Di	P, 170V, 4A, 40W, hFE=2k...12k		17j	TO-220	2SD1756	17j	2SC3186, 2SD930, 2SD1023, 2SD1121
2 SD 1092	Tos	Si-N	TV Reg, Z-Diode(C · B, 55V), 55/55V, 4/20A, 80W hi-hFE=500...2500		18j	TO-3P			2SC2825
2 SD 1093	Hit	Si-N	TV SMPS, 1000/400V, 7A, 50W, <5/11μs, sat<5V(4A)		23a	TO-3	BU 903	18j	BU 536, BU 546, BU 902...903
2 SD 1094	Hit	Si-N	TV SMPS, 1000/400V, 10A, 50W, <5/21μs, sat<1V(4A)		23a	TO-3	S 2530 A	23a	BU 626A
2 SD 1095	Hit	Si-N	TV-HA, 1200V, 1.5A, 50W		23a	TO-3	(2SC1413)*	23a	BU 204...206, 2SD1097, 2SC1132, 2SC1167++
2 SD 1096	Hit	Si-N	P, 25/20V, 1A, 10W		30j	TO-251/252	2SC4135	30j	2SD1078...79, 2SD1295, 2SD1801
2 SD 1097	Hit	Si-N	TV-HA, 1200V, 2.5A, 50W		23a	TO-3	BU 208 A	23a	BU 204...206, 2SC1132, 2SC1922, 2SD818, ++
2 SD 1098	Hit	Si-N	TV-HA, 1200V, 3A, 50W		23a	TO-3	BU 208 A	23a	BU 207...209(A), 2SC1875, 2SD850, ++
2 SD 1099	Hit	Si-N	TV-HA, 1200V, 5A, 50W		23a	TO-3	BU 208 A	23a	BU 207...209(A), 2SC2928, 2SD954, ++
2 SD 1100	Hit	Si-N	LF Drv.Out, 20/16V, 2A, 0.9W, hFE=400		7c(9mm)	TO-92L	2SC3225	7c(9mm)	2SC3225, 2SC4389, 2SD1014, 2SD1146
2 SD 1101	Hit	Si-N	SMD, Uni, 25/20V, 0.7/1A	(2SB831)	35a	SOT-23			BCW 65...66
2 SD 1102	Hit	Si-N	TV-HA, 1200V, 4A, 50W		23a	TO-3	BU 208 A	23a	BU 207...209(A), 2SC1358, 2SD1495, ++
2 SD 1103	Hit	Si-N	TV-HA, 1200V, 5A, 50W		23a	TO-3	BU 208 A	23a	BU 207...209(A), 2SC2928, 2SD954, ++
2 SD 1104	Hit	Si-N	TV-HA, 1200V, 6A, 50W		23a	TO-3	BU 508 A	18j	BU 508(A), 2SC3025...3026, 2SD821, ++
2 SD 1105	Mat	Si-N	P, 120/80V, 15/30A, 200W, 1MHz		23a	TO-3	(2SC3264)*	20j	BDW 10, 2N5630...31, 2SC1584, 2SD752, ++
2 SD 1106	Nec	Si-N-Darl	S P. 450/450V, 50A, 400W, hFE=300		-74				
2 SD 1107	Nec	Si-N-Darl	=2SD1106: 500/500V		-74				
2 SD 1109	Nec	Si-N	P, 100/100V, 6A, 70W		16j	(MP-80)	BD 245 C	18j	BD 245C, BDV 95, 2SC2681, 2SC2837, ++
2 SD 1109 A		Si-N	=2SD1109: 120/120V		16j	(MP-80)	BD 245 C	18j	BD 245C, 2SC2681, 2SC2706, 2SC2837, ++
2 SD 1110	Nec	Si-N	P, 120/120V, 7/12A, 80W, 15MHz	(2SB849)	16j	(MP-80)	BD 245 C	18j	BD 245C, 2SC2681, 2SC2706, 2SC2837, ++
2 SD 1110 A		Si-N	=2SD1110: 130/130V		16j	(MP-80)	2SC2837	18j	BD 245D, 2SC2706, 2SD731, 2SD1046, ++
2 SD 1111	Say	Si-N-Darl	Uni, 80/50V, 0.7/2A, 0.6, hFE=25k>5k		7c	TO-92	BC 879	7c	BC 879, BSR51...52
2 SD 1112	Mat	Si-N	S P. 300/300V, 0.2/0.4A, 10W, 70MHz		30j	TO-251/252	BF 759*	13h	2SC3129, 2SC3588, 2SC3805, 2SC4003, ++*
2 SD 1113	Hit	Si-N-Darl+Di	int Z-Diode(C · B), 300/300V, 6/10A, 40W, hFE>500		17j	TO-220	(BU 806)	17j	(2SD971, 2SD991, 2SD1071, 2SD1088...89++)
2 SD 1114	Hit	Si-N-Darl+Di	S P. 400/300V, 6/10A, 50W, hFE=500		17j	TO-220	(BU 806)	17j	BU 910...912, 2SD835, 2SD1245
2 SD 1115	Hit	Si-N-Darl+Di	S P. 400/300V, 3/6A, 40W, hFE=500, 1/22μs		17j	TO-220	(BU 806)	17j	2SD977...978, 2SD987, 2SD1072
2 SD 1116	Hit	Si-N-Darl	S P. 400/300V, 3A, 40W, hFE=500		17j	TO-220	(BU 806)	17j	2SD977...978, 2SD987, 2SD1072
2 SD 1117	Fjd	Si-N	P, 40/40V, 10A, 50W	(2SB850)	17j	TO-220	BD 809	17j	BD 705, BD 743, BD 805, BD 905, ++
2 SD 1117 A		Si-N	=2SD1117: 80/80V		17j	TO-220	BD 809	17j	BD 709, BD 743B, BD 809, BD 909, ++
2 SD 1118	Fjd	Si-N-Darl	P, 80/50V, 10A, 50W, hFE>300, <1/5μs		17j	TO-220	BDW 93 C	17j	BDT 63A, BDT 65A, BDW 93B, BDX 33B, ++
2 SD 1119	Mat	Si-N	SMD, Uni, 40/25V, 3/5A, 150MHz		39b	SOT-89			2SC4521, 2SD1624
2 SD 1120	Mat	Si-N-Darl	P, 200/150V, 2A, 40W, hFE=1000		17j	TO-220			2SC3186, 2SD930, 2SD1023, 2SD1121
2 SD 1121	Mat	Si-N-Darl	P, 200/200V, 3A, 50W, hFE=1000		17j	TO-220	2SD1756	17j	2SC3186, 2SD930, 2SD1023, 2SD1025
2 SD 1122	Mat	Si-N-Darl	P, 200/150V, 5A, 80W, hFE=1000		18j	TO-3P			2SD921, 2SD1090, 2SD1123
2 SD 1123	Mat	Si-N-Darl	P, 200/150V, 8A, 100W, hFE=1000		18j	TO-3P			
2 SD 1124	Mat	Si-N-Darl	P, 80/60V, 8A, 80W, hFE=1000		18j	TO-3P	BDW 83 C	18j	BDV 65A...C, TIP 141...142
2 SD 1125	Mat	Si-N-Darl	P, 80/60V, 12A, 100W, hFE=1000		18j	TO-3P	BDW 83 C	18j	BDV 65A...C, BDV 67A...D, BDW 83B...D, ++
2 SD 1126	Hit	Si-N-Darl+Di	P, 120/120V, 10/15A, 50W, hFE=1k...20k	(2SB955)	17j	TO-220	2SD1756 ⁷	17j	BDT 63C, BDT 65C, BDX 33D, 2SD1607, ++
2 SD 1127	Hit	Si-N-Darl+Di	P, 120/120V, 10/15A, 50W, hFE=1000		17j	TO-220	2SD1756 ⁷	17j	BDT 63C, BDT 65C, BDX 33D, 2SD1607, ++
2 SD 1128	Fjd	Si-N-Darl	P, 150/100V, 5A, 30W, 22MHz, hFE=5000>700		17j	TO-220	2SD1756	17j	BDX 53F, 2SD830, 2SD1169, 2SD1590
2 SD 1129	Hit	Si-N-Darl	P, 100/100V, 15A, 100W, hFE=1k...20k, <2.5/10μs		20j				2SD829, 2SD852
2 SD 1130	Hit	Si-N-Darl	P, 100/100V, 20A, 100W, hFE=1k...20k, <2.5/10μs		20j				
2 SD 1131	Hit	Si-N	P, 50/50V, 4A, 40W, 8MHz		17j	TO-220	BD 243 C	17j	BD 243A, BD 535, BD 539A, BD 949, ++
2 SD 1132	Hit	Si-N	=2SD1131: 60/60V		17j	TO-220	BD 243 C	17j	BD 243A, BD 535, BD 539A, BD 949, ++
2 SD 1133	Hit	Si-N	P, 70/50V, 4/8A, 40W, 7MHz	(2SB857)	17j	TO-220	BD 243 C	17j	BD 243A, BD 537, BD 539B, BD 949, ++
2 SD 1134	Hit	Si-N	=2SD1133: 70/60V	(2SB858)	17j	TO-220	BD 243 C	17j	BD 243A, BD 537, BD 539B, BD 951, ++
2 SD 1135	Hit	Si-N	P, 100/80V, 4/8A, 40W, 10MHz	(2SB859)	17j	TO-220	BD 243 C	17j	BD 243C, BD 539C, BD 953, 2SD712, ++
2 SD 1136	Hit	Si-N	TV-HA, 200/80V, 4/5A, 30W, sat<1.5V(4A)		17j	TO-220	BU 406	17j	BU 406...408, 2SD823, 2SD1150, 2SD1159, ++
2 SD 1137	Hit	Si-N	TV-HA, 100/100V, 4/5A, 40W	(2SB860)	17j	TO-220	BD 243 C	17j	BD 243C, BD 539C, BD 953, 2SD712, ++
2 SD 1138	Hit	Si-N	LF P, TV-VA, 200/150V, 2/5A, 30W	(2SB861)	17j	TO-220	2SD1138	17j	BD 239F, 2SC2660, 2SD610, 2SD760
2 SD 1139	Hit	Si-N	P, 200/150V, 2A, 30W		17j	TO-220	2SD1138	17j	BD 239F, 2SC2660, 2SD610, 2SD760
2 SD 1140	Tos	Si-N-Darl	Uni, 30/30V, 1.5A, 0.9W, hFE=7k>4k, 200/900ns		7c(9mm)	TO-92L	(BD 679) ⁶	14h	2SD1536, 2SD1786, 2SD1861, 2SD2046, ++
2 SD 1141	Hit	Si-N-Darl+Di	S P. 400/300V, 6/10A, 40W, hFE=3000>500		17j	TO-220	(BU806)	17j	BU 910...912, 2SD835, 2SD1114, 2SD1245
2 SD 1142									

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International
2 SD 1143	Nec	Si-N	TV-HA, 1500V, 5A, 50W	23a	TO-3	BU 208 A	23a BU 208(A), BU 508(A), 2SC2928, 2SD954,++
2 SD 1145	Say	Si-N	Drv, 60/20V, 5/8A, 0.9W, 120MHz, sat<0.5V(3A)	7c(9mm)	TO-92L	(2SD2179) ⁷	9c 2SC4482
2 SD 1146	Son	Si-N	LF Drv,Out, 50/50V, 2A, 0.9W, hFE=300	7c(9mm)	TO-92L	2SD1207	7c(9mm) 2SC3328, 2SC4145, 2SD1207, 2SD2182
2 SD 1147	Fjd	Si-N-Darl	P, 120/80V, 5A, 30W, 22MHz, hFE=5k>1k	{2SB862	17j	TO-220	2SD1756 ⁷
2 SD 1148	Tos	Si-N	HiFi Audio Out, 140/140V, 10A, 100W, 20MHz	{2SB863	18j	TO-3P	2SD2837
2 SD 1149	Mat	Si-N	=2SD1011: SMD	35a	SOT-23		2SC3651
2 SD 1150	Say	Si-N	TV-HA, 350/90V, 6A, 40W	17j	TO-220	BU 406	17j BU 406, BU 408, 2SC3175, 2SC3591, ++
2 SD 1151	Mat	Si-N-Darl+Di	TV-HA, 1500V, 5A, 95W, hFE=40...150	23a	TO-3		
2 SD 1152	Hit	Si-N	Uni, 55/50V, 0.1A, 0.2W	7c	TO-92	BC 546	7a BC 167, BC 182, BC 237, BC 547, ++
2 SD 1153	Say	Si-N-Darl	80/50V, 1.5/3A, 0.9W, hFE=4000, 120MHz	{2SB865	7c(9mm)	TO-92L	2SD1153
2 SD 1154	Mat	Si-N	TV-HA, 350/200V, 7A, 50W	23a	TO-3	BU 608	23a 2SD1579, 2SD1978, 2SD1981, 2SD2067
2 SD 1155	Fjd	Si-N-Darl	S P, 400/400V, 50A, 300W, hFE=400, <2/12.5µs	=74			
2 SD 1156	Mit	Si-N	S P, 100/80V, 5A, 58W	49m	TO-59		N25002, N25004, N25284...5285
2 SD 1157	Fjd	Si-N	P, 80/50V, 4A, 25W, hi-hFE=400>250, <0.5/3.8µs	17j	TO-220		2SC2315...16, 2SC2491
2 SD 1158	Fjd	Si-N	P, 80/50V, 8A, 40W, hi-hFE=400>250, <0.5/3.8µs	17j	TO-220		2SC4024, 2SD1947
2 SD 1159	Say	Si-N	TV-HA, 200/60V, 4.5/10A, 40W, 10MHz	17j	TO-220	BU 406	17j BU 406...408, 2SC3189, 2SC3589, 2SD1163++
2 SD 1160	Tos	Si-N+Di	S P, TV, Rbe=800Ω, 50/20V, 2/4A, 10W, sat<0.6V(2A)	30j	TO-251/252		
2 SD 1161	Say	Si-N+R	SMD, Re=100...160Ω, Uni, 30/15V, 0.03A, 100MHz	35a	SOT-23		
2 SD 1162	Nec	Si-N-Darl	S P, 500V, 5/10A, 40W, hFE=400...3000, 1/18µs	17j	TO-220	BU 922T	
2 SD 1163	Hit	Si-N	TV-HA, 300/120V, 7/10A, 40W, sat<2V(5A)	17j	TO-220	BU 406	17j BU 406...408, 2SC3173, 2SC3590, 2SD1364++
2 SD 1163 A		Si-N	=2SD1163: 350/150V, sat<1V(5A)	17j	TO-220	BU 406	17j BU 406...408, 2SC3175, 2SC3591, ++
2 SD 1164	Nec	Si-N-Darl+Di	P, 150/60V, ±1.5/3A, 10W, hFE=2k...30k, 0.5/2µs	30j	TO-251/252		2SC4339, {2SD985...986}⁴
2 SD 1165(A)	Nec	Si-N-Darl	S P, 1000/900V, 100A, 1250W, hFE=150, <3/38µs				
2 SD 1166	Tos	Si-N-Darl	S P, 1000/900V, 200A, 2500W, hFE=150, <3/38µs				
2 SD 1168	Mat	Si-N	S P, TV-HA, 1500/800V, 5A, 50W, <1/2.5µs	23a	TO-3	BU 208 A	23a BU 208A, BU 508(A), 2SC2928, 2SD954,++
2 SD 1169	Mat	Si-N-Darl	P, 150/80V, 5A, 40W, hFE=5k...20k, 0.5/5µs	17j	TO-220	2SD1756	17j (2SD1128) ¹³
2 SD 1170	Sak	Si-N-Darl	P, 120/120V, 6A, 70W, hFE=4000	18j	TO-3P		2SD921, 2SD923, 2SD1090, 2SD1210, ++
2 SD 1171	Mat	Si-N+Di	TV-HA, 1500V, 5A, 50W	23a	TO-3	BU 508 D	18j BU 208D, BU 508D, 2SC3481...82, 2SC3681++
2 SD 1172	Mat	Si-N+Di	TV-HA, 1500V, 5A, 65W	23a	TO-3	BU 508 D	18j BU 208D, BU 508D, 2SC3481...82, 2SC3681++
2 SD 1173	Mat	Si-N+Di	TV-HA, 1500V, 5A, 70W	23a	TO-3	BU 508 D	18j BU 508D, 2SC3481...82, 2SC3681, 2SD953,++
2 SD 1174	Mat	Si-N+Di	TV-HA, 1500V, 5A, 95W	23a	TO-3	BU 508 D	18j BU 508D, 2SC3481...82, 2SC3681, 2SD953,++
2 SD 1175	Mat	Si-N+Di	TV-HA, 1500V, 5A, 100W	23a	TO-3	BU 508 D	18j BU 508D, 2SD953, 2SC3481...82, 2SC3681,++
2 SD 1176	Mat	Si-N-Darl+Di	P, 60/60V, 8A, 45W, hFE=1k...10k, <1/7µs	{2SB872	17j	TO-220	BD 901
2 SD 1176 A		Si-N-Darl+Di	=2SD1176: 80/80V	17j	TO-220	BD 901	17j BD 645, BD 897, BDW 73A, BDW 53A, ++
2 SD 1177	Hit	Si-N	LF P, TV-VA, 100/60V, 2/3A, 20W, 230MHz	{2SB874	14h	TO-126	(BD 237) ⁸
2 SD 1178	Hit	Si-N	=2SD1177: 100/80V	{2SB875	14h	TO-126	(BD 237) ⁸
2 SD 1179	Hit	Si-N	LF P, TV-VA, 120/100V, 1.5A, 20W,	{2SB876	14h	TO-126	2SC3117
2 SD 1180	Hit	Si-N	=2SD1179: 120/110V	{2SB877	14h	TO-126	2SC3117
2 SD 1181	Hit	Si-N	P, 180V, 1.5A, 10W	17n	=TO-220	(2SD1138) ⁵	17j (2SC2238A, B, 2SC2344, 2SD608A, 2SD1138+) ⁵
2 SD 1182	Hit	Si-N	=2SD1181: 50W	17n	=TO-220	(2SD1138) ⁵	17j (2SC2660, 2SD760, 2SD772A, B, ++) ⁵
2 SD 1183	Hit	Si-N	TV SMPS, 1200/800V, 3A, 50W, <2/11µs	23a	TO-3	BU 903	BU 546, BU 903, 2SC1875, 2SD1098, ++
2 SD 1184	Hit	Si-N	TV SMPS, 1500/800V, 3A, 50W, <2/11µs	23a	TO-3	BU 208 A	23a BU 208(A), BU 508(A), BU 908, 2SC3023,++
2 SD 1185	Hit	Si-N	TV SMPS, 1200/800V, 5A, 50W, <2/11µs	23a	TO-3	BU 903	BU 546, BU 903, 2SD1099, 2SD1103, ++
2 SD 1186	Hit	Si-N	TV SMPS, 1200/800V, 5A, 50W, <2/11µs	23a	TO-3	BU 208 A	23a BU 208(A), BU 508(A), BU 908, 2SC2928,++
2 SD 1187	Tos	Si-N	P, 100/80V, 10A, 80W, 10MHz, 0.5/3.3µs	18j	TO-3P		2SD1840
2 SD 1188		Si-N					
2 SD 1189	Rhm	Si-N	LF P, 40/32V, 2A, 5W, 100MHz, sat<0.8V(2A)	{2SB891	14b	TO-126 Iso	2SC3422
2 SD 1190	Say	Si-N-Darl+Di	P, 70/60V, 4/6A, 30W, 20MHz, hFE=5k>2k	{2SB880	17j	TO-220	BD 901
2 SD 1191	Say	Si-N-Darl+Di	=2SD1190: 7/10A	{2SB881	17j	TO-220	BD 901
2 SD 1192	Say	Si-N-Darl+Di	=2SD1190: 10/15A	{2SB882	17j	TO-220	BDW 93C
2 SD 1193	Say	Si-N-Darl+Di	=2SD1190: 15/20A	{2SB883	18j	TO-3P	BDW 83C
2 SD 1194	Say	Si-N-Darl+Di	P, 110/100V, 3/5A, 30W, 20MHz, hFE=4k>1.4k	{2SB884	17j	TO-220	BD 901
2 SD 1195	Say	Si-N-Darl+Di	=2SD1194: 5/8A	{2SB885	17j	TO-220	BD 901
2 SD 1196	Say	Si-N-Darl+Di	=2SD1194: 8/12A	{2SB886	17j	TO-220	BD 901
2 SD 1197	Say	Si-N-Darl+Di	=2SD1194: 10/15A	{2SB887	18j	TO-3P	BDW 83 C
2 SD 1198	Mat	Si-N-Darl	Uni, 30/25V, 1A, 1W, 150MHz, hFE>4k...40k	9c	BC 879	7c	BC 617...618, BC 875, BSR 50...52, ++
2 SD 1198 A		Si-N-Darl	=2SD1198: 60/50V	9c	BC 879	7c	BC 618, BC 875, BSR 50...52, 2SD893A, ++
2 SD 1199	Mat	Si-N	=2SD1010: 0.4W	9c			=2SD1010
2 SD 1200	Rhm	Si-N	P, 80/80V, 0.7A, 5W, 120MHz	{2SB889	14b	TO-126 Iso	(BD 139) ³
2 SD 1201	Hit	Si-N-Darl+Di	S P, 500/400V, 10A, 100W, hFE>200, <8/20µs	23a	TO-3		BU 323A, BU 922, BUW 81(A), 2SD685, ++
2 SD 1202	Hit	Si-N-Darl	S P, 500/400V, 10A, 100W, hFE=100, <5/10µs	23a	TO-3		BU 323A, BU 922, BUW 81(A), 2SD685, ++
2 SD 1203	Hit	Si-N-Darl+Di	S P, 500/400V, 15A, 100W, hFE>200, <8/20µs	23a	TO-3		BU 932, 2SD572...573, 2SD711(A), ++
2 SD 1204	Hit	Si-N-Darl	S P, 500/400V, 15A, 100W, hFE=100, <5/10µs	23a	TO-3		BU 932, 2SD572...573, 2SD711(A), ++
2 SD 1205	Mat	Si-N-Darl	=2SD892:	9c		=2SD892	=2SD892
2 SD 1205 A		Si-N-Darl	=2SD892A:	9c		=2SD892A	=2SD892A
2 SD 1206	Mat	Si-N	30/25V, hi-Ueb=15V, 0.1A, 0.4W, 150MHz	{2SB894	9c	2SC3071	7c(9mm) 2SD889, 2SD1206, 2SD1807, (BC 548, ++)
2 SD 1207	Say	Si-N	60/50V, 2/4A, 1W, 150MHz, sat<0.4V(1A)	{2SB892	7c(9mm)	TO-92L	2SD1207
2 SD 1208	Tos	Si-N-Darl	P, int. Z-Diode(C -B, 60V), 45/45V, 5/20A, 100W hFE=2k...20k	23a	TO-3	BDW 83C	18j BDX 638, TIP 142, 2SD628...629, ++
2 SD 1209	Hit	Si-N-Darl	Uni, 60/60V, 1/2A, 0.9W, hFE>4000	{2SA1193	7c(9mm)	TO-92L	2SD1153
2 SD 1210	Nec	Si-N-Darl+Di	P, 150/100V, ±10/20A, 80W, 200MHz, hFE=1k...30k	16j	(MP-80)		7c(9mm) 2SD1153, 2SD1660, 2SD1809, 2SD1981, ++
2 SD 1211	Mat	Si-N	Uni, 120/120V, 0.5/1A, 1W, 200MHz	{2SB987	7c(9mm)	TO-92L	2SD1812
2 SD 1212	Say	Si-N	S P, 60/30V, 12/20A, 35W, 120MHz, sat<0.4V(5A) 200/530ns	{2SB903	18j	TO-220	2SC3346
2 SD 1213	Say	Si-N	S P, 60/30V, 20/30A, 50W, 120MHz, sat<0.4V(8A) 300/620ns	{2SB904	18j	TO-3P	
2 SD 1214	Mat	Si-N-Darl+Di	P, 25/25V, 2A, 35W, hFE=1k...10k, <1/7µs	17j	TO-220	BD 901	17j BD 713, BDW 23, BDW 53, BDW 63, ++
2 SD 1215	Mat	Si-N-Darl+Di	P, 25/25V, 4A, 40W, hFE=1k...10k, <1/8µs	17j	TO-220	BD 901	17j BD 713, BDW 23, BDW 53, BDW 63, ++
2 SD 1216	Mat	Si-N-Darl+Di	P, 25/25V, 8A, 45W, hFE=1k...10k, <1/9µs	17j	TO-220	BD 901	17j BD 643, BD 895, BDW 73, BDX 53, ++
2 SD 1217	Mat	Si-N-Darl+Di	P, 50/50V, 2A, 35W, hFE=1k...10k, <1/7µs	17j	TO-220	BD 901	17j BD 715, BDW 23A, BDW 53A, BDW 63A, ++
2 SD 1218	Mat	Si-N-Darl+Di	P, 50/50V, 4A, 40W, hFE=1k...10k, <1/8µs	17j	TO-220	BD 901	17j BD 715, BDW 23A, BDW 53A, BDW 63A, ++
2 SD 1219	Mat	Si-N-Darl+Di	P, 50/50V, 8A, 45W, hFE=1k...10k, <1/9µs	17j	TO-220	BD 901	17j BD 645, BD 897, BDW 73A, BDX 53A, ++
2 SD 1220	Tos	Si-N	TV Audio Out, 150/150V, 1.5A, 10W, 100MHz	{2SB905	30j	TO-251/252	(2SD1138) ⁸
2 SD 1221	Tos	Si-N	P, 60/60V, 3A, 20W, 3MHz, 0.8/2.3µs	{2SB906	30j	TO-251/252	2SC3303
2 SD 1222	Tos	Si-N-Darl+Di	P, 60/40V, 3A, 15W, hFE=5k>2k, 100/1200ns	{2SB907	30j	TO-251/252	(BD 901) ⁶
2 SD 1223	Tos	Si-N-Darl+Di	P, 100/80V, 4A, 15W, hFE=5k>2k, 200/2.1µs	{2SB908	30j	TO-251/252	(BD 901) ⁴
2 SD 1224	Tos	Si-N-Darl	P, 30/30V, 1.5A, 10W, hFE=10k>4k, 180/900ns	30j	TO-251/252		2SC4339, 2SD1520, 2SD1955
2 SD 1225(M)	Rhm	Si-N	LF Drv,Out, 40/32V, 1A, 1W, 150MHz	{2SB909	9c	BC 639	7c 2SC312, 2SD1222, 2SD1759, 2SD1799, ++
2 SD 1226(M)	Rhm	Si-N	LF Drv,Out, 80/80V, 0.7/1A, 1W, 120MHz	{2SB910	9c	BC 639	7c BC 635, BC 637, BC 639, 2SD667, ++
2 SD 1227(M)	Rhm	Si-N	LF Drv,Out, 40/32V, 2/2.5A, 1W, 100MHz	{2SB911	9c	2SC3225	7c(9mm) BC 639, 2SC2235, 2SC2383, 2SD667, ++
2 SD 1228(M)	Rhm	Si-N	LF Drv,Out, 50/50V, 0.5A, 0.6W, 250MHz	9c	BC 337	7a	MPS 650...651, 2SC3328, 2SD1146, 2SD1207
2 SD 1229	Say	Si-N-Darl+Di	70/60V, 10/15A, 60W, hFE=5k>2k, 0.6/4.8µs	{2SB912	18j	TO-3P	BDW 83C
2 SD 1230	Say	Si-N-Darl+Di	110/100V, 8/12A, 60W, hFE=4k>1.5k, 0.6/6.4µs	{2SB913	18j	TO-3P	BDW 83C

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International	
2 SD 1231	Say	Si-N-Darl+Di	70/60V, 10A, 70W, hFE=5000, 20MHz, 0,6/4,8µs	23a	TO-3	BDW 83C	18j	BDV 65A, BDX 83B, BDX 85B, MJ 3001, ++
2 SD 1232	Say	Si-N-Darl+Di	70/60V, 15A, 80W, hFE=5000, 20MHz	23a	TO-3	BDW 83C	18j	BDV 67A, BDW 83B, BDX 67A, MJ 4034, ++
2 SD 1233	Say	Si-N-Darl+Di	110/100V, 8A, 70W, hFE=4000	23a	TO-3	BDW 83C	18j	BDV 65C, BDX 63C, BDX 65C, 2SD922, ++
2 SD 1234	Say	Si-N-Darl+Di	110/100V, 10A, 80W, hFE=4000, 20MHz	23a	TO-3	BDW 83C	18j	BDV 65C, BDW 83D, BDX 65C, 2SD922, ++
2 SD 1235	Say	Si-N	S P, 60/30V, 8/15A, 30W, 120MHz, lo-sat<0,4V(3A) 100/530ns	17j {2SB919	TO-220	2SC3346	17j	2SC3254...3255
2 SD 1236	Say	Si-N	=2SD1236L: 120/80V	17j	TO-220			-
2 SD 1236 L	Say	Si-N	S P, 90/80V, 5/9A, 30W, 20MHz, lo-sat<0,4V(3A) 100/1600ns	17j {2SB920L	TO-220			2SC3258
2 SD 1237	Say	Si-N	=2SD1237L: 120/80V	17j	TO-220			-
2 SD 1237 L	Say	Si-N	S P, 90/80V, 7/12A, 40W, 20MHz, lo-sat<0,4V(4A) 100/2000ns	17j {2SB921L	TO-220			-
2 SD 1238	Say	Si-N	=2SD1238L: 120/80V	17j	TO-220			-
2 SD 1238 L	Say	Si-N	S P, 90/80V, 12/20A, 80W, 20MHz, lo-sat<0,4V(6A) 200/1900ns	18j {2SB922L	TO-3P			2SD1840
2 SD 1239	Say	Si-N	P, 120/80V, 20A, 100W	23a	TO-3	BD 249 C	18j	BC 249C, BD 745D, 2SD1049
2 SD 1240	Say	Si-N	P, 120/80V, 25A, 120W	23a	TO-3	BD 249 C	18j	BC 249C
2 SD 1241	Mat	Si-N	P, 60/60V, 5A, 60W	18j	TO-3P	BD 245 C	18j	BD 245A, BDV 91, 2SC2681, 2SD895...896, ++
2 SD 1241 A		Si-N	=2SD1241: 80/80V	18j	TO-3P	BD 245 C	18j	BD 245B, BDV 93, 2SC2681, 2SD895...896, ++
2 SD 1242	Mat	Si-N	P, 60/60V, 6A, 70W	18j	TO-3P	BD 245 C	18j	BD 245A, BDV 91, 2SC2681, 2SD895...896, ++
2 SD 1242 A		Si-N	=2SD1242: 80/80V	18j	TO-3P	BD 245 C	18j	BD 245B, BDV 93, 2SC2681, 2SD895...896, ++
2 SD 1243	Mat	Si-N	P, 60/60V, 10A, 100W	18j	TO-3P	BD 245 C	18j	BD 245A, BD 545A, BDV 91, 2SC2681, ++
2 SD 1243 A		Si-N	=2SD1243: 80/80V	18j	TO-3P	BD 245 C	18j	BD 245B, BD 545B, BDV 93, 2SC2681, ++
2 SD 1244	Mat	Si-N	=2SD965: 1W	{2SB1050 9c		2SD2179	9c	-2SD965
2 SD 1245	Mat	Si-N-Darl+Di	S P, 500/400V, 6A, 40W, hFE=500...5000	17j	TO-220	2SD798	17j	BU 810, BU 912, 2SD798...799, ++
2 SD 1246	Say	Si-N	LF Drv, Out, 30/25V, 2/5A, 0,75W, 150MHz lo-sat<0,4V(1,5A)	{2SB926 7c	TO-92	2SD1207	7c(9mm)	2SC3225, 2SC4389, 2SC4484, 2SD1207, ++
2 SD 1247	Say	Si-N	=2SD1246: 2,5A, 1W	{2SB927 7c(9mm)	TO-92L	2SD1347	7c(9mm)	2SC4487, 2SD879, 2SD1347
2 SD 1248	Hit	Si-N-Darl+Di	P, 120/120V, 8/12A, 40W, hFE=1k...20k	17j	TO-220	2SD1756 ⁷	17j	BD 651, BDT 21, BDW 73D, BDX 53D, ++
2 SD 1249	Mat	Si-N	350/250V, 0,75/1,5A, 35W, 30MHz, 0,2/2,5µs	30j	(TO-220MF)	(BUX 85) ⁴	17j	(BUW 40(A,B), TIP 47...50, 2SD859(A,++) ⁴
2 SD 1249 A		Si-N	=2SD1249: 400/300V	30j	(TO-220MF)	(BUX 85) ⁴	17j	(BUW 40(A,B), TIP 48...50, 2SD859A,++) ⁴
2 SD 1250(A)	Mat	Si-N	P, 200/150(A=200/180)V, 2/3A, 30W, 20MHz	{2SB928 30j	(TO-220MF)	(2SD1138) ⁴	17j	(2SD1033, 2SC2660, 2SD760, 2SD1138,++) ⁴
2 SD 1251	Mat	Si-N	P, 60/60V, 4/6A, 30W, 1MHz	30j	(TO-220MF)	(BD 243 C) ⁴	17j	2SD1904, 2SD1906, (BD 241A, BD 535,++) ⁴
2 SD 1251 A		Si-N	=2SD1251: 80/80V	30j	(TO-220MF)	(BD 243 C) ⁴	17j	2SD1906, 2SD2200, (BD 241B, BD 537,++) ⁴
2 SD 1252	Mat	Si-N	P, 60/60V, 3/5A, 35W, 30MHz, 0,5/2,9µs	{2SB929 30j	(TO-220MF)	(BD 243 C) ⁴	17j	2SD1902...03, (BD 241A, BD 535, BD 935,++) ⁴
2 SD 1252 A		Si-N	=2SD1252: 80/80V	30j	(TO-220MF)	(BD 243 C) ⁴	17j	2SD1906, 2SD2200, (BD 241B, BD 537,++) ⁴
2 SD 1253	Mat	Si-N	P, 60/60V, 4/8A, 40W, 20MHz, 0,4/1,7µs	{2SB930 30j	(TO-220MF)	(BD 243 C) ⁴	17j	2SD1904, 2SD2198, (BD 243A, BD 535,++) ⁴
2 SD 1253 A		Si-N	=2SD1253: 80/80V	30j	(TO-220MF)	(BD 243 C) ⁴	17j	2SD1906, 2SD2200, (BD 243B, BD 537,++) ⁴
2 SD 1254	Mat	Si-N	P, 130/80V, 3/6A, 30W, 30MHz, lo-sat<0,5V(2A) 500/2650ns	{2SB931 30j	(TO-220MF)			2SD1529
2 SD 1255	Mat	Si-N	P, 130/80V, 4/8A, 35W, 30MHz, lo-sat<0,5V(3A) 500/2650ns	{2SB932 30j	(TO-220MF)			-
2 SD 1256	Mat	Si-N	P, 130/80V, 5/10A, 40W, 30MHz, lo-sat<0,5V(4A) 500/1650ns	{2SB933 30j	(TO-220MF)			-
2 SD 1257	Mat	Si-N	P, 130/80V, 7/15A, 40W, 30MHz, lo-sat<0,5V(5A) 500/1600ns	{2SB934 30j	(TO-220MF)			-
2 SD 1257 A		Si-N	=2SD1257: 150/100V	30j	(TO-220MF)			-
2 SD 1258	Mat	Si-N	200/150, 1/2,5A, 40W, 25MHz, hi-hFE=500...2000	30j	(TO-220MF)			-
2 SD 1259	Mat	Si-N	80/60V, 3/6A, 40W, 50MHz, hi-hFE=500...2500	30j	(TO-220MF)	(2SD1273) ⁶	17c	-
2 SD 1259 A		Si-N	=2SD1259: 100/80V	30j	(TO-220MF)			-
2 SD 1260	Mat	Si-N-Darl+Di	P, 60/60V, 2/4A, 35W, 20MHz, hFE=1k...10k	{2SB937 30j	(TO-220MF)	(BD 901) ⁴	17j	(BD 715, BDW 23A, BDW 53A, 2SD837,++) ⁴
2 SD 1260 A		Si-N-Darl+Di	=2SD1260: 80/80V	30j	(TO-220MF)	(BD 901) ⁴	17j	(BD 717, BDW 23B, BDW 53B, 2SD837A,++) ⁴
2 SD 1261	Mat	Si-N-Darl+Di	P, 60/60V, 4/8A, 40W, 20MHz, hFE=1k...10k	{2SB938 30j	(TO-220MF)	(BD 901) ⁴	17j	(BD 715, BDW 23A, BDW 53A, 2SD837,++) ⁴
2 SD 1261 A		Si-N-Darl+Di	=2SD1261: 80/80V	30j	(TO-220MF)	(BD 901) ⁴	17j	(BD 717, BDW 23B, BDW 53B, 2SD837A,++) ⁴
2 SD 1262	Mat	Si-N-Darl+Di	P, 60/60V, 8/12A, 45W, 20MHz, hFE>1k...10k	{2SB939 30j	(TO-220MF)	(BD 901) ⁴	17j	(BD 645, BD 897, BDW 73A, BDX 53A,++) ⁴
2 SD 1262 A		Si-N-Darl+Di	=2SD1262: 80/80V	30j	(TO-220MF)	(BD 901) ⁴	17j	(BD 647, BD 899, BDW 73B, BDX 53B,++) ⁴
2 SD 1263	Mat	Si-N	P, 350/250V, 0,75/1,5A, 35W, 30MHz, 0,5/2,5µs	17c	SOT-186	2SC3752	17c	2SC3309, 2SC3969, (BUW 40...TIP 47...50) ³
2 SD 1263 A		Si-N	=2SD1263: 400/300V	17c	SOT-186	2SC3752	17c	2SC3309, 2SC3969, (BUW 40...TIP 48...50) ³
2 SD 1264(A)	Mat	Si-N	=2SD1260(A):	{2SB940 17c	SOT-186	(2SC4159) ⁷	17c	2SC2988, 2SC4382, 2SD1587, 2SD2337
2 SD 1265(A)	Mat	Si-N	=2SD1251:	17c	SOT-186	2SD1411	17c	BD 951F, 2SC3851, 2SD1408, 2SD2000
2 SD 1266(A)	Mat	Si-N	=2SD1252(A):	{2SB941 17c	SOT-186	2SD1411	17c	BDT 31F, 2SC3851, 2SD1408, 2SD2000
2 SD 1267(A)	Mat	Si-N	=2SD1253(A):	{2SB942 17c	SOT-186	2SD1411	17c	BD 951F, 2SC3851, 2SD1408, 2SD2000
2 SD 1268	Mat	Si-N	=2SD1254:	{2SB943 17c	SOT-186			-
2 SD 1269	Mat	Si-N	=2SD1255:	{2SB944 17c	SOT-186			-
2 SD 1270	Mat	Si-N	=2SD1256:	{2SB945 17c	SOT-186			-
2 SD 1271(A)	Mat	Si-N	=2SD1257(A):	{2SB946 17c	SOT-186			-
2 SD 1272	Mat	Si-N	=2SD1258:	17c	SOT-186			(2SC2317) ³
2 SD 1273	Mat	Si-N	=2SD1259:	17c	SOT-186	2SD1273	17c	2SD1944, (2SD1943, 2SC1983) ³
2 SD 1273 A		Si-N	=2SD1259A:	17c	SOT-186			2SD2092
2 SD 1274	Mat	Si-N	P, 150/80V, 5A, 40W, 40MHz	17c	SOT-186			2SC3566, 2SC4334, 2SD772(A,B)
2 SD 1274 A		Si-N	=2SD1274: 200/80V	17c	SOT-186			2SC4153, (BD 243F, 2SD772A,B) ³
2 SD 1274 B		Si-N	=2SD1274: 250/80V	17c	SOT-186			(2SD772B) ³
2 SD 1275	Mat	Si-N-Darl+Di	=2SD1260:	{2SB949 17c	SOT-186	(BD 901) ³	17j	BDT 61F, 2SD1790, 2SD1825, 2SD1987
2 SD 1275 A		Si-N-Darl+Di	=2SD1260A:	17c	SOT-186	(BD 901) ³	17j	BDT 61AF, 2SD1414, 2SD1788, 2SD1933
2 SD 1276	Mat	Si-N-Darl+Di	=2SD1261:	{2SB950 17c	SOT-186	(BD 901) ³	17j	BDT 61F, 2SD1790, 2SD1825, 2SD1987
2 SD 1276 A		Si-N-Darl+Di	=2SD1261A:	17c	SOT-186	(BD 901) ³	17j	BDT 61AF, 2SD1414, 2SD1788, 2SD1933
2 SD 1277	Mat	Si-N-Darl+Di	=2SD1262:	{2SB951 17c	SOT-186	2SD1415	17c	BD 643F, BDT 63F, 2SD1416, 2SD1826...27
2 SD 1277 A		Si-N-Darl+Di	=2SD1262A:	17c	SOT-186	2SD1415	17c	BD 645F, BDT 63AF, 2SC4062, 2SD1415...16
2 SD 1278	Mat	Si-N	S P, 1200/650V, 8A, 100W, <1/5µs	23a	TO-3	BU 508 A	18j	BU 508(A), 2SC3412, 2SD905...906, 2SD1498
2 SD 1279	Tos	Si-N	TV-HA, 1400/600V, 10A, 50W, 3MHz, sat<5V(8A)	23a	TO-3	2SD1279	23a	2SC3688
2 SD 1280	Mat	Si-N	SMD, Uni, 20/20V, 1/2A, 150MHz	{2SB956 39b	SOT-89			BC 868, BCX 54...56, BCX 68, 2SC2884, ++
2 SD 1281	Hit	Si-N	P, 100/60V, 2A, 20W	{2SB957 30j	TO-251/252	2SC4135	30j	2SC4135, 2SD1250, 2SD1557, 2SD1815...16
2 SD 1282	Hit	Si-N	P, 100/80V, 2A, 20W	{2SB958 30j	TO-251/252	2SC4135	30j	2SC4135, 2SD1250, 2SD1557, 2SD1815...16
2 SD 1283	Hit	Si-N	P, 120/100V, 2A, 20W	{2SB959 30j	TO-251/252	2SC4135	30j	2SC4135, 2SD1250, 2SD1557, 2SD1815...16
2 SD 1284	Hit	Si-N	P, 120/110V, 2A, 20W	{2SB960 30j	TO-251/252	2SC4135	30j	2SC4135, 2SD1250, 2SD1557, 2SD1815...16
2 SD 1286(Z)	Nec	Si-N-Darl+Di	P, 60/60V, ±1/2A, 8W, hFE=2k...30k, 0,5/2µs	{2SB963 30j	TO-251/252 Z: TO-252	(BD 679) ⁴	14h	2SC2871, 2SC4500, 2SD1598, 2SD1800, ++
2 SD 1287	Hit	Si-N-Darl	S P, 300/250V, 30A, 150W, hFE=300	23a	TO-3			BUT 13, MJ 10022...10023
2 SD 1288	Nec	Si-N	P, 120/120V, 7/10A, 70W, 55MHz	{2SB965 16j	(MP-80)	BD 245 C	18j	BD 245C, BD 545D, 2SD718, 2SD1046, ++
2 SD 1289	Nec	Si-N	P, 120/120V, 8/12A, 80W, 60MHz	{2SB966 16j	(MP-80)	BD 245 C	18j	BD 245C, BD 545D, 2SD718, 2SD1046, ++
2 SD 1290	Mat	Si-N+Di	TV-HA, 1500V, 3A, 50W, sat<5V(2A)	18j	TO-3P	BU 508 D	18j	BU 508D, 2SC3479, 2SC3481...3482
2 SD 1291	Mat	Si-N+Di	TV-HA, 1500V, 3A, 50W, sat<5V(2,5A)	18j	TO-3P	BU 508 D	18j	BU 508D, 2SC3479, 2SC3481...3482
2 SD 1292	Rhm	Si-N	LF Drv, Out, 120/80V, 1/2A, 0,9W, 100MHz	{2SB1041 7c(9mm)	TO-92L	2SD1812	7c(9mm)	2SC2383, 2SC3228, 2SD667(A), 2SD1812, ++

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International	
2SD 1293(M)	Rhm	Si-N	=2SD1292: 1W	{2SB1042 9c	2SD1812	7c	2SC2383, 2SC3228, 2N3700...01, 2SD667	
2SD 1294	Tos	Si-N-Darl	P, int. Z-Diode(C -B, 60V), 60/60V, 5/20A, 80W	18]	TO-3P	BDW 83 C	18j	BDV 65, TIP 140...142, 2SD1124, 2SD1170
2SD 1295	Mat	Si-N	P. 50/40V, 1.5/3A, 20W, 150MHz	{2SB968 30j	TO-252	2SC4135	30j	2SC3076, 2SD1078, 2SD1281...1284, ++
2SD 1296	Nec	Si-N-Darl+Di	P, 150/100V, ±15/30A, 100W, hFE=1k...30k, -7jμs	16j	(MP-80)			BDV 67D, 2SD1027, 2SD1299, 2SD1515
2SD 1297	Nec	Si-N-Darl+Di	P, 150/100V, 25/50A, 100W, hFE=1k...30k, -7jμs	16j	(MP-80)			
2SD 1298	Nec	Si-N-Darl+Di	P, 500/400V, ±10/30A, 100W, hFE=200...2000, -11jμs	16j	(MP-80)			2SC3262, 2SD979
2SD 1299	Nec	Si-N-Darl+Di	P, 150/100V, 15A, 100W, hFE=5000	16j	(MP-80)			BDV 67D, 2SD1027, 2SD1297, 2SD1515
2SD 1300	Hit	Si-N	TV-HA, 1500V, 3A, 50W	23a	TO-3	BU 208 A	23a	BU 208(A), 2SC3023...24, 2SD849...850, ++
2SD 1301	Mat	Si-N+Di	TV-HA, 1500V, 2A, 45W, sat<3V(1A)	23a	TO-3	BU 208 D	23a	BU 208D, 2SD993
2SD 1302	Mat	Si-N	Muting, 25/20V, 0.5/1A, 0.6W, 200MHz lo-sat<0.4V(0.5A), Ron=1Ω	7c	TO-92			-
2SD 1303	Mat	Si-N	LF Drv.Out, 20/20V, 1A, 1W	{2SB971 7c(9mm)	TO-92L	2SD1207	7c(9mm)	2SC2236, 2SD863, 2SD1247, 2SD1331, ++
2SD 1304	Mat	Si-N	SMD, int. Z-Diode(C -B), 20/20V, 0.1/0.2A, 150MHz	35a	SOT-23	(BC 846)	35a	(BC 846...848, BCW 31...33, 2SC1622, ++)
2SD 1305	Mat	Si-N	SMD, 185/185V, 0.15A, 120MHz	35a	SOT-23			BFN 24, BFN 26, 2SC3360
2SD 1306	Hit	Si-N	SMD, Uni.Muting, 30/15V, 0.7A, 250MHz	35a	SOT-23			BCW 65...66
2SD 1307	Mat	Si-N-Darl	S P, 350/300V, 6A, 35W, hFE=2500	17j	TO-220	(BU 806)	17j	BU 910...912, 2SD835, 2SD1089, 2SD1114, ++
2SD 1308	Nec	Si-N-Darl+Di	P, 100/100V, ±5/10A, 30W, hFE=2k...20k	{2SB974 15j	(MP-40)	2SD1756	17j	BDX 53F, 2SD1025, 2SD1590...1591
2SD 1309	Nec	Si-N-Darl+Di	P, 150/100V, ±8/12A, 40W, hFE=2k...15k	{2SB975 15j	(MP-40)	2SD1756	17j	BDX 53F, 2SD1025, 2SD1500, 2SD1756
2SD 1310	Nec	Si-N	P, 60/60V, 3/5A, 30W, 16MHz	{2SB1038 15j	(MP-40)	BD 243 C	17j	BD 241A, BD 535, BD 539A, BD 935, ++
2SD 1311	Nec	Si-N	P, 100/100V, 4/6A, 40W, 20MHz	{2SB1039 15j	(MP-40)	BD 243 C	17j	BD 241C, BD 539C, BD 937, 2SD712, ++
2SD 1312	Nec	Si-N	LF Drv.Out, 120/80V, 1/2A, 1W, 120MHz	{2SB984 9b		2SD1812	7c	2N3700...01, 2SC2383, 2SC3228, 2SD667
2SD 1313	Tos	Si-N	S P, 800/350V, 25/35A, 200W, 6MHz, 0.8/3.5jμs	77j	TOP-3L			2SC3989
2SD 1314	Tos	Si-N-Darl	S P, +Diode(E -B), 600/450V, 15/30A, 150W, <1/15jμs	77j	TOP-3L			-
2SD 1315	Mat	Si-N-Darl	P, 150/80V, 5A, 40W, 20MHz, hFE=5k...20k, 0.5/5jμs	17c	SOT-186	(2SD1756) ³	17j	2SD1590, (2SD1169) ³
2SD 1316	Mat	Si-N-Darl+Di	int. Z-Diode(C -B), 30/30V, 2/4A, 35W, hFE=1k...10k	30j	(TO-220MF)	(BD 901) ⁶	17j	(BD 713, BDW 23, BDW 53, BDW 63, ++) ⁶
2SD 1317	Mat	Si-N-Darl+Di	int. Z-Diode(C -B), 30/30V, 4/8A, 40W, hFE=1k...10k	30j	(TO-220MF)	(BD 901) ⁶	17j	(BD 713, BDW 23, BDW 53, BDW 63, ++) ⁶
2SD 1318	Mat	Si-N-Darl+Di	int. Z-Diode(C -B), 30/30V, 8/12A, 45W, hFE=1k...10k	30j	(TO-220MF)	(BD 901) ⁶	17j	(BD 643, BD 895, BDW 73, BDX 53, ++) ⁶
2SD 1319	Mat	Si-N-Darl+Di	int. Z-Diode(C -B), 60/60V, 2/4A, 35W, hFE=1k...10k	30j	(TO-220MF)	(BD 901) ⁶	17j	(BD 715, BDW 23A, BDW 53A, BDW 63A, ++) ⁶
2SD 1320	Mat	Si-N-Darl+Di	int. Z-Diode(C -B), 60/60V, 4/8A, 40W, hFE=1k...10k	30j	(TO-220MF)	(BD 901) ⁶	17j	(BD 715, BDW 23A, BDW 53A, BDW 63A, ++) ⁶
2SD 1321	Mat	Si-N-Darl+Di	int. Z-Diode(C -B), 60/60V, 8/12A, 45W, hFE=1k...10k	30j	(TO-220MF)	(BD 901) ⁶	17j	(BD 645, BD 897, BDW 73A, BDX 53A, ++) ⁶
2SD 1322	Mat	Si-N-Darl+Di	=2SD1316:	17c	SOT-186			-
2SD 1323	Mat	Si-N-Darl+Di	=2SD1317:	17c	SOT-186			-
2SD 1324	Mat	Si-N-Darl+Di	=2SD1318:	17c	SOT-186			-
2SD 1325	Mat	Si-N-Darl+Di	=2SD1319:	17c	SOT-186			-
2SD 1326	Mat	Si-N-Darl+Di	=2SD1320:	17c	SOT-186			-
2SD 1327	Mat	Si-N-Darl+Di	=2SD1321:	17c	SOT-186			-
2SD 1328	Mat	Si-N	SMD, Uni, 25/20V, 0.5/1A, 200MHz, Ron=1Ω	{2SB970 35a	SOT-23	(BC 817)	35a	(BC 817...818, BCX 19...20, 2SC3325, ++)
2SD 1329	Hit	Si-N-Darl+Di	Z-Di(C -B), 50/50V, 6/10A, 40W, hFE>2000, 0.4/8jμs	17j	TO-220	(BD 901) ¹³	17j	2SD2024, (BD 645, BD 897, BDW 23A, ++) ¹³
2SD 1330	Mat	Si-N	=2SD1302:	9c	-2SD1302			-2SD1302
2SD 1331	Hit	Si-N	LF Drv.Out, 40/40V, 1.5A, 0.9W	7c(9mm)	TO-92L	2SD1207	7c(9mm)	2SC4486, 2SD1051, 2SD1146, 2SD1207, ++
2SD 1332	Mat	Si-N	P, 100/100V, 5A, 60W, 20MHz	{2SB979 18j	TO-3P	2SC2837	18j	BD 245C, 2SD718, 2SD895...896, 2SD731, ++
2SD 1333	Mat	Si-N	P, 120/120V, 6A, 70W	{2SB980 18j	TO-3P	2SC2837	18j	BD 245C, 2SD718, 2SD896, 2SD731, ++
2SD 1334	Mat	Si-N	P, 140/140V, 7A, 80W	{2SB981 18j	TO-3P	2SC2837	18j	BD 245D, 2SD1046...1047, 2SD731, ++
2SD 1335	Mat	Si-N	P, 150/150V, 9A, 100W	{2SB982 18j	TO-3P	2SC3281	~16j	BD 245D, 2SC2987(A), 2SC2838, 2SD1047
2SD 1336	Mat	Si-N-Darl+Di	P, 150/100V, 6/10A, 35W, 20MHz, hFE>1500, 0.7/5.5jμs	17c	SOT-186	(2SD1756) ³	17j	2SD1590, (2SD1023, 2SD1025, 2SD1113, ++) ³
2SD 1336 A	Mat	Si-N-Darl+Di	=2SD1336: 180/120V	17c	SOT-186	(2SD1756) ³	17j	2SD1792, (2SD991, 2SD1088, 2SD1113, ++) ³
2SD 1337	Say	Si-N	TV-HA, 1500/600V, 2.5A, 50W	23a	TO-3	BU 208 A	23a	BU 205...206, 2SC3023...3024, 2SD627, ++
2SD 1338	Say	Si-N+Di	TV-HA, 1500/600V, 2.5A, 50W	23a	TO-3	BU 208 D	23a	BU 208D, BU 800, 2SD993, 2SD1301
2SD 1339	Say	Si-N	TV-HA, 1500/600V, 3.5A, 50W	23a	TO-3	BU 208 A	23a	BU 208...209(A), 2SD849...850, 2SD783, ++
2SD 1340	Say	Si-N+Di	TV-HA, 1500/600V, 3.5A, 50W	23a	TO-3	BU 208 D	23a	BU 208D, BU 800, 2SD993, 2SD1171...75, ++
2SD 1341	Say	Si-N	TV-HA, 1500/600V, 5A, 50W	23a	TO-3	BU 208 A	23a	BU 208(A), BU 508(A), 2SC2928, 2SD954, ++
2SD 1342	Say	Si-N+Di	TV-HA, 1500/600V, 5A, 50W	23a	TO-3	BU 208 D	23a	BU 208D, BU 508D, BU 800, 2SD1171...75
2SD 1343	Say	Si-N	TV-HA, 1500/600V, 6A, 50W	23a	TO-3	BU 508 A	18j	BU 508(A), 2SC3025...3026, 2SD821...822
2SD 1344	Say	Si-N+Di	TV-HA, 1500/600V, 6A, 50W	23a	TO-3	BU 508 D	18j	BU 508D, 2SD903...904
2SD 1345	Shi	Si-N	P, 60/50V, 7/12A, 40W, 10MHz, 0.2/1.2jμs	{2SB983 17j	TO-220	BD 243 C	17j	BD 243A, BD 543A, BD 797, 2SC3254, ++
2SD 1346	Mat	Si-N	TV-HA, 1400V, 2.5A, 40W	17j	TO-220			BU 505
2SD 1347	Say	Si-N	60/50V, 3/6A, 1W, 150MHz, sat<0.5V(2A)	{2SB985 7c(9mm)	TO-92L	2SD1347	7c(9mm)	2SC4487, 2SC4482, 2SD1145
2SD 1348	Mat	Si-N	=2SD1347: 4/6A, 10W	{2SB986 14h	TO-126	2SD1348	14h	(BD 785, BD 787, BD 789, MJE 240...244, +)
2SD 1349	Shi	Si-N-Darl	S P, 500/400V, 7/14A, 50W, 11MHz, hFE=150...5000	17j	TO-220			BU 810, 2SD1533
2SD 1350	Mat	Si-N	S, 400/400V, 0.5/1A, 1W, 55MHz, 0.4/4.3jμs	9c	(M Type)			2SC4645
2SD 1350 A	Mat	Si-N	=2SD1350: 600/500V, 1/5jμs	9c				
2SD 1351	Mat	Si-N	P, 60/60V, 3A, 30W, 3MHz, <0.2/2.3jμs	{2SB988 17j	TO-220	BD 243 C	17j	BD 241A, BD 539A, BD 535, BD 935, ++
2SD 1352	Mat	Si-N	P, 80/80V, 4A, 30W, 8MHz	{2SB989 17j	TO-220	BD 243 C	17j	BD 243B, BD 539B, BD 537, BD 951, ++
2SD 1353	Tos	Si-N	P, 50/50V, 3A, 30W, 5MHz, hi-hFE=250...1200, 2/8jμs	=15j				2SD1052, 2SC1983, 2SD1943, 2SD1157
2SD 1354	Tos	Si-N	P, 60/60V, 3A, 30W, 3MHz, 0.8/2.3jμs	{2SB994 =15j		BD 243 C	17j	BD 241A, BD 539A, BD 535, BD 935, ++
2SD 1355	Tos	Si-N	P, 100/100V, 5A, 40W, 12MHz	{2SB995 =15j		BD 243 C	17j	BD 243C, BD 539C, BD 543C, BD 953, ++
2SD 1356	Tos	Si-N	P, 80/50V, 4A, 30W, 8MHz	=15j		BD 243 C	17j	BD 243B, BD 539B, BD 543B, BD 951, ++
2SD 1357	Tos	Si-N-Darl+Di	P, 100/100V, 7A, 40W, hFE=2k...15k, 0.8/5.5jμs	=15j		BD 901	17j	BD 649, BD 901, BDW 73C, BDX 53C, ++
2SD 1358	Tos	Si-N-Darl+Di	=2SD1347: 80/80V	=15j		BD 901	17j	BD 647, BD 899, BDW 73B, BDX 53B, ++
2SD 1359	Tos	Si-N-Darl+Di	=2SD1357: 60/60V	=15j		BD 901	17j	BD 645, BD 897, BDW 73A, BDX 53A, ++
2SD 1360	Tos	Si-N-Darl+Di	S P, 600/400V, 6A, 30W, hFE=1000-600, 1/13jμs	=15j		2SD798	17j	BU 810, 2SC3579, 2SD798...799
2SD 1361	Tos	Si-N-Darl	S P, 300/250V, 6A, 30W, hFE=5000-2000, 1/13jμs	=15j				BU 910...912, 2SD1088...89, 2SD1113...14, ++
2SD 1362	Tos	Si-N	100/80V, 7A, 40W, 10MHz, 0.4/3jμs	{2SB992 =15j				2SD1237L
2SD 1363	Tos	Si-N	70/50V, 7A, 40W, 10MHz, 0.2/3jμs	{2SB993 =15j		2SD1062	17j	2SC3254, 2SD1237L
2SD 1364	Tos	Si-N+Di	TV-HA, 300/150V, 7/15A, 40W, 18MHz, sat<1.5V(5A)	=15j		BU 406 D	17j	BU 406...408, 2SC3590...91, 2SD1163, ++
2SD 1365	Tos	Si-N	S P, 800/400V, 3A, 40W, 4MHz, <1/8jμs	=15j		BUT 11 A	17j	BUT 11(A), BUV 46(A), 2SC3086, 2SC3490, ++
2SD 1366	Hit	Si-N	SMD, LF, 25/20V, 1/1.5A, 240MHz	{2SB1000 39b	SOT-89			BC 868, BCX 54...56, BCX 68, 2SC3444, ++
2SD 1366 A	Hit	Si-N	=2SD1366: 30/25V	39b	SOT-89			BCX 54...56, 2SC2873, 2SC3444, 2SD874A, ++
2SD 1367	Hit	Si-N	SMD, LF, 20/16V, 2/3A, 100MHz	{2SB1001 39b	SOT-89			2SC2883, 2SC3443, 2SC3439, 2SC2982
2SD 1368	Hit	Si-N	SMD, LF, 100/50V, 1/1.5A, 100MHz	{2SB1002 39b	SOT-89			BCX 56, 2SD1005, 2SD1368, 2SD1418...19, ++
2SD 1369	Tos	Si-N-Darl+Di	P, 60/40V, 3A, 25W, hFE=5000, <0.2/1.9jμs	=15j		BD 901	17j	BD 715, BDW 23A, BDW 53A, BDW 63A, ++
2SD 1370	Tos	Si-N-Darl+Di	P, 100/80V, 4A, 30W, hFE=4000, <0.2/1.9jμs	=15j		BD 901	17j	BDW 23C, BDW 53C, BDW 63C, 2SD837B, ++
2SD 1371	Say	Si-N	P, 300/300V, 2A, 40W, 5MHz	17j	TO-220	(BU 406)	17j	TIP 75(A...C), BUT 93, 2SC2023, 2SC3055, ++
2SD 1372	Say	Si-N	P, 300/300V, 4A, 50W, 5MHz	17j	TO-220	(BU 406)	17j	TIP 75(A...C), BUT 93, 2SC2907, 2SC2440, ++
2SD 1373	Say	Si-N	P, 300/300V, 4A, 50W, 5MHz	18j	TO-3P	BUW 11 A	18j	BUW 11(A), TIP 51...54, 2SD2624, ++
2SD 1374	Say	Si-N	P, 300/300V, 3A, 50W	23a	TO-3	BUW 11 A	18j	BUW 11(A), TIP 51...54, 2SD632, ++
2SD 1375	Say	Si-N	P, 300/300V, 4A, 90W	23a	TO-3	BUW 11 A	18j	BUW 11(A), TIP 51...54, 2SD632, ++
2SD 1376	Hit	Si-N-Darl+Di	P, 120/120V, 1.5/3A, 20W, hFE=2k...30k	{2SB1012 14h	TO-126	2SD986	14h	2SD985...986, 2SD1953, 2SD2019
2SD 1377	Hit	Si-N-Darl	P, 120/120V, 8/12A, 40W, hFE=1k...20k, 0.5/6.5jμs	17j	TO-220	2SD1756	17j	BD 651, BDT 21, BDW 73D, BDX 53D, ++
2SD 1378	Rhm	Si-N	80/80V, 0.7A, 10W, 120MHz, sat<0.4V(0.5A)	{2SB1007 14h	TO-126	BD 13		

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International		
2 SD 1382	Rhm	Si-N	=2SD1381: 10W	14h	TO-126	25C3117	14h	25C2690(A), 25C2803, 25D781	
2 SD 1383	Rhm	Si-N-Darl	SMD, Uni, 40/32V, 0,3/1,5A, 250MHz, hFE>1000	=35d	(MMT)				
2 SD 1383 K		Si-N-Darl	=2SD1383:	35a	SOT-23			BCV 27, BCV 47, 2SD1478A	
2 SD 1384	Rhm	Si-N	LF Drv.Out, 40/32V, 2/2,5A, 0,75W, 100MHz	{2SB1010	7c(9mm)	TO-92L	25D1207	7c(9mm)	25C3328, 25C4145, 25D1146, 25D1207, ++
2 SD 1385	Mat	Si-N	LF, Vid, 400/400V, 0,1/0,2A, 1W, 40MHz	9c		BF 487	7c		MPS-A45, 25C2267, 25C3118, 25C3469
2 SD 1386	Hit	Si-N-Darl+Di	P, 140/140V, 8A, 50W, hFE=4000	17j	TO-220	25D1756	17j		BDX 53E, F, 25D1590...91, 25D1756
2 SD 1387	Say	Si-N	LF Drv.Out, 20/16V, 2A, 0,7W, hFE=250	{2SB1013	7c	TO-92	25D1207	7c	25C3225, 25C3673, 25D1207, 25D1835, ++
2 SD 1388	Say	Si-N	LF Drv.Out, 60/50V, 1A, 0,7W, hFE=250	{2SB1014	7c	TO-92	BC 639	7c	BC 337A, BC 637, 25C3939, 25D1616(A), ++
2 SD 1389	Sak	Si-N	S P, 1200/650V, 6A, 50W	23a	TO-3	BU 903			BU 546, BU 903, 25C3343...44, 25D1104, ++
2 SD 1390	Mat	Si-N	TV-HA, 1500/700V, 1A, 40W, sat<5V(2A)	17j	TO-220				BU 505
2 SD 1391	Mat	Si-N	TV-HA, 1500/700V, 5/17A, 100W, sat<2V(4,5A)	18j	TO-3P	BU 508 A	18j		BU508(A), BU908, 25C3485...86, 25D1496...97
2 SD 1392	Nec	Si-N-Darl+Di	Z-Di(C -B), 60±10V, 5/10A, 30W, hFE=2k...20k, 1/9µs	15j	(MP-40)	(BD 901) ¹³	17j		(BD 645, BD 897, BDW 23A, BDW 63A, ++) ¹³
2 SD 1393	Say	Si-N-Darl+Di	int. Z-Di(C -B, 60V), 50V, 2A, 30W, hFE=4k>1k	17j	TO-220	BD 901	17j		BD 715, BDW 23A, BDW 53A, BDW 63A, ++
2 SD 1394	Say	Si-N-Darl+Di	int. Z-Di(C -B, 60V), 50V, 3/5A, 30W, hFE=4k>1k	17j	TO-220	BD 901	17j		BD 715, BDW 23A, BDW 53A, BDW 63A, ++
2 SD 1395	Say	Si-N-Darl+Di	int. Z-Di(C -B, 60V), 50V, 5/8A, 40W, hFE=4k>1k	17j	TO-220	BD 901	17j		BD 645, BD 897, BDW 23A, BDW 63A, ++
2 SD 1396	Say	Si-N+Di	=2SD1400: int. Damper-Diode	18j	TO-3P	BU 508 D	18j		BU 705D, 25C3479, 25D1290...91, 25D1876
2 SD 1397	Say	Si-N+Di	=2SD1401: int. Damper-Diode	18j	TO-3P	BU 508 D	18j		BU 706D, 25C3480, 25D1729, 25D1877
2 SD 1398	Say	Si-N+Di	=2SD1402: int. Damper-Diode	18j	TO-3P	BU 508 D	18j		BU 508D, 25C3481, 25D1730, 25D1878
2 SD 1399	Say	Si-N+Di	=2SD1403: int. Damper-Diode	18j	TO-3P	BU 508 D	18j		BU 508D, 25C3482, 25D1732, 25D1879
2 SD 1400	Say	Si-N	TV-HA, 1500/800, 2,5/10A, 80W, 3MHz, sat<8V(2A)	18j	TO-3P	BU 705 *	18j		BU 705, 25C3483, 25D1493...94
2 SD 1401	Say	Si-N	TV-HA, 1500/800V, 3,5/10A, 80W, 3MHz, sat<8V(2,5A)	18j	TO-3P	BU 508 A	18j		BU 508A, BU 908, 25C3484...86, 25D1495
2 SD 1402	Say	Si-N	TV-HA, 1500/800V, 5/16A, 120W, 3MHz, sat<5V(4A)	18j	TO-3P	BU 508 A	18j		BU508A, BU908, 25C3485...86, 25D1496...97
2 SD 1403	Say	Si-N	TV-HA, 1500/800V, 6/16A, 120W, 3MHz, sat<5V(5A)	18j	TO-3P	BU 508 A	18j		BU 508A, BU 908, 25C3486, 25D1497
2 SD 1404	Tos	Si-N+Di	TV-HA, 300/150V, 7/15A, 25W, 18MHz, sat<1,5V(5A)	17c	SOT-186	(BU 406) ³	17j		(BU 406...408, 25C3590...91, 25D884...85, +) ³
2 SD 1405	Tos	Si-N	=2SD1353: Iso, 25W	17c	SOT-186				25C3677, 25C3852, 25D1948, 25D1972
2 SD 1406	Tos	Si-N	=2SD1354: Iso, 25W	{2SB1015	17c	SOT-186	25C3299	17c	25C3299, 25C3746, 25D1913, 25D2012, ++
2 SD 1407	Tos	Si-N	=2SD1355: Iso, 30W	{2SB1016	17c	SOT-186	25D1411	17c	25C3691, 25D1411, 25D1488, 25D1940
2 SD 1408	Tos	Si-N	=2SD1356: Iso, 25W	{2SB1017	17c	SOT-186	25D1411	17c	25C3691, 25C3746, 25C3851, 25D2000
2 SD 1409	Tos	Si-N-Darl+Di	=2SD1360: Iso, 25W	17c	SOT-186	25D1409	17c		(25C3579, 25D798...799) ³
2 SD 1410	Tos	Si-N-Darl	=2SD1361: Iso, 25W	17c	SOT-186	25D1409	17c		25D2017, (25D1088, 25D1113, 25D1976)
2 SD 1411	Tos	Si-N	=2SD1362: Iso, 30W	{2SB1018	17c	SOT-186	25D1411	17c	25C4550
2 SD 1412	Tos	Si-N	=2SD1363: Iso, 30W	{2SB1019	17c	SOT-186	25D1411	17c	25C3747
2 SD 1413	Tos	Si-N-Darl+Di	P, 60/40V, 3/6A, 20W, hFE>2000, 0,1/1,2µs	{2SB1023	17c	SOT-186	25D1415	17c	BDT 61F, 25D1790, 25D1796, 25D1987, ++
2 SD 1414	Tos	Si-N-Darl+Di	P, 100/80V, 4/6A, 20W, hFE>2000, 0,2/2,1µs	{2SB1024	17c	SOT-186	25D1415	17c	25D1589, 25D1788, 25D1928, 25D2015
2 SD 1415	Tos	Si-N-Darl+Di	=2SD1357: Iso, 30W	{2SB1020	17c	SOT-186	25D1415	17c	25C4062, 25D1791, 25D1830, 25D2025
2 SD 1416	Tos	Si-N-Darl+Di	=2SD1358: Iso, 30W	{2SB1021	17c	SOT-186	25D1415	17c	25C4062, 25D1791, 25D1830, 25D2025
2 SD 1417	Tos	Si-N-Darl+Di	=2SD1359: Iso, 30W	{2SB1022	17c	SOT-186	25D1415	17c	25C4062, 25D1791, 25D1826, 25D2025
2 SD 1418	Hit	Si-N	SMD, Uni, 120/80V, 1/2A, 140MHz	{2SB1025	39b	SOT-89			25C3646, 25D1420...1421
2 SD 1419	Hit	Si-N	=2SD1418: 120/100V	{2SB1026	39b	SOT-89			25C3646, 25D1420...1421
2 SD 1420	Hit	Si-N	SMD, LF Drv.Out, 180/120V, 1,5/3A	{2SB1027	39b	SOT-89			25C3649
2 SD 1421	Hit	Si-N	=2SD1420: 180/160V	{2SB1028	39b	SOT-89			25C3649
2 SD 1422	Hit	Si-N	SMD, LF Drv.Out, 100/60V, 2A	{2SB1029	39b	SOT-89			25C3647, 25C4132, 25D1420...1421
2 SD 1423	Mat	Si-N	=2SD638: 0,3W	{2SB1030	40c				*25D638
2 SD 1423 A		Si-N	=2SD639: 0,3W		40c				*25D639
2 SD 1424	Mat	Si-N	=2SD1010:		40c				*25D1010
2 SD 1425	Tos	Si-N+Di	TV-HA, 1500/600V, 2,5A, 80W, 3MHz, sat<8V(2A)	77j	-TOP-3L	BU 508 D	18j		BU 706D, 25C3479, 25D1290...91, 25D1728
2 SD 1426	Tos	Si-N+Di	TV-HA, 1500/600V, 3,5A, 80W, 3MHz, sat<8V(3A)	77j	-TOP-3L	BU 508 D	18j		BU 706D, 25C3480, 25D1729, 25D1877
2 SD 1427	Tos	Si-N+Di	TV-HA, 1500/600V, 5A, 80W, 3MHz, sat<5V(4A)	77j	-TOP-3L	BU 508 D	18j		BU 508D, 25C3481, 25D1730, 25D1878
2 SD 1428	Tos	Si-N+Di	TV-HA, 1500/600V, 6A, 80W, 3MHz, sat<5V(5A)	77j	-TOP-3L	BU 508 D	18j		BU 508D, 25C3482, 25D1732, 25D1879
2 SD 1429	Tos	Si-N	TV-HA, 1500/600V, 2,5A, 80W, 3MHz, sat<8V(2A)	77j	-TOP-3L	BU 705 *	18j		BU 705, 25C3483, 25D1493...94
2 SD 1430	Tos	Si-N	TV-HA, 1500/600V, 3,5A, 80W, 3MHz, sat<8V(3A)	77j	-TOP-3L	BU 508 A	18j		BU 706, 25C3484, 25D1495
2 SD 1431	Tos	Si-N	TV-HA, 1500/600V, 5A, 80W, 3MHz, sat<5V(4A)	77j	-TOP-3L	BU 2508 A	18j		BU2508A, BU 908, 25C3485...86, 25C4291, ++
2 SD 1432	Tos	Si-N	TV-HA, 1500/600V, 6A, 80W, 3MHz, sat<5V(5A)	77j	-TOP-3L	BU 2508 A	18j		BU2508A, BU 908, 25C3486, 25D1496...97, ++
2 SD 1433	Tos	Si-N	TV-HA, 1500/600V, 7A, 80W, 3MHz, sat<5V(6A)	77j	-TOP-3L	S 2000 A, A3	16j		BU 508A, BU 908, S 2000A, 25C3686...87
2 SD 1434	Tos	Si-N	TV-HA, 1700/800V, 5A, 80W	77j	-TOP-3L				
2 SD 1425...1432 Fl	Tho	Si-N	=2SD1425...1432: Iso	18c	TO-3P Iso				
2 SD 1435	Hit	Si-N-Darl+Di	100/100V, 15/20A, 100W, hFE=1k...20k, 2/8µs	{2SB1031	18j	TO-3P	BDW 83 C	18j	BDV 67A, BDW 83C, 25D1026
2 SD 1436	Hit	Si-N-Darl+Di	120/120V, 10/15A, 80W, hFE=1...20k, 0,8/4µs	{2SB1032	18j	TO-3P	(BDW 83 C) ⁷	18j	BDV 65C, BDV 67B, BDW 83D, 25D1210
2 SD 1437	Rhm	Si-N	P, 80/60V, 3/6A, 40W, 8MHz	{2SB1033	17j	TO-220	BD 243 C	17j	BD 241B, BD 537, BD 539B, BD 937, ++
2 SD 1438	Tos	Si-N-Darl+Di	P, 80/80V, 2A, 15W, hFE=5k>2k, 100MHz	{2SB1034	14h	TO-126	BD 679, BD 779, 25N6039, 25D1376	14h	BD 679, BD 779, 25N6039, 25D1376
2 SD 1439	Mat	Si-N+Di	TV-HA, 1500V, 3/10A, 50W, 2MHz, sat<5V(2A)	18j	TO-3P	BU 508 D	18j		BU 508D, BU 706D, 25C3480...3482
2 SD 1440	Mat	Si-N+Di	TV-HA, 1500V, 3A, 50W, sat<5V(2,5A)	18j	TO-3P	BU 508 D	18j		BU 508D, BU 706D, 25C3480...3482
2 SD 1441	Mat, Tho	Si-N+Di	TV-HA, 1500V, 4/15A, 70W, 2MHz, sat<1V(3A)	18j	TO-3P	BU 508 D	18j		BU 508D, BU 706D, 25C3480...3482
2 SD 1442	Mat	Si-N	P, 40/20V, 7/12A, 30W, 150MHz, 0,3/0,4µs lo-sat<0,6V(5A)	{2SB925	17j	TO-220	25C3346	17j	25C3254, 25D1235
2 SD 1442 A		Si-N	=2SD1442: 50/40V	17j	TO-220	25C3346	17j		25C3254, 25D1235
2 SD 1443	Mat	Si-N	P, 40/20V, 10/20A, 40W, 120MHz, 0,3/0,5µs lo-sat<0,6V(10A)	{2SB871	17j	TO-220	25C3346	17j	25C3255, 25C3345, 25D1212
2 SD 1443 A		Si-N	=2SD1443: 50/40V	17j	TO-220	25C3346	17j		25C3255, 25C3345, 25D1212
2 SD 1444(A)	Mat	Si-N	=2SD1442: Iso	{2SB953	17c	SOT-186	(25D1411) ⁸	17c	25C3747, 25C4327
2 SD 1445(A)	Mat	Si-N	=2SD1443(A): Iso	{2SB948	17c	SOT-186			25C3709, 25C4064...65
2 SD 1446	Mat	Si-N-Darl+Di	TV-HA, 500/400V, 6/10A, 40W, hFE>500, sat<1,5A(3A)	17c	SOT-186				
2 SD 1447	Mit	Si-N	LF Drv.Out, 30/25V, 1/1,5A, 0,9W, 100MHz	{2SB1035	7c(9mm)	TO-92L	25D1207	7c(9mm)	25C2236, 25D863, 25D1146, 25D1207, ++
2 SD 1448(Z)	Nec	Si-N	P, 70/45V, 3/5A, 10W, 60MHz, Z, TO-252	30j	TO-251	25C3303	30j		25C3303, 25C3386, 25C4978, 25D1815...16
2 SD 1449	Mat	Si-N	=2SD958: 0,3W	40c		-2SD958			*2SD958
2 SD 1450	Mat	Si-N	=2SD1302: 0,3W	40c		-2SD1302			*2SD1302
2 SD 1451	Hit	Si-N	TV-HA, 1500/600V, 1,5A, 50W	18j	TO-3P	BU 705 *	18j		BU 705, 25C3483, 25D1492...94
2 SD 1452	Hit	Si-N	TV-HA, 1500/600V, 2,5A, 50W	18j	TO-3P	BU 705 *	18j		BU 705, 25C3483, 25D1493...94
2 SD 1453	Hit	Si-N	TV-HA, 1500/600V, 3A, 50W, sat<5V(2,5A)	18j	TO-3P	BU 508 A	18j		BU 706, 25C3484, 25D1495
2 SD 1454	Hit	Si-N	TV-HA, 1500/600V, 4A, 50W	18j	TO-3P	BU 508 A	18j		BU 508A, BU 706, 25C3484, 25D1495
2 SD 1455	Hit, Tho	Si-N	TV-HA, 1500/600V, 5A, 50W, sat<5V(4,5A)	18j	TO-3P	BU 508 A	18j		BU 508A, BU 908, 25C3485...86, 25D1496...97
2 SD 1456	Hit	Si-N	TV-HA, 1500/600V, 6A, 50W, sat<5V(5A)	18j	TO-3P	BU 508 A	18j		BU 508A, BU 908, 25C3486, 25D1497
2 SD 1457(A)	Mat	Si-N-Darl+Di	200/150(A=200)V, 6/10A, 60W, 15MHz, hFE=700...10k	16c	(TOP-3F)				(25D921, 25D1090, 25D1122...23) ³
2 SD 1458	Mat	Si-N	20/20V, hi-Ueb=15V, 0,7/1,5A, 1W, 55MHz, hi-hFE>1k	9c					25C3070, 25C3616, 25C4204, 25D1582
2 SD 1459	Say	Si-N	CTV-VA, LF Out, 150/150V, 1,5/3A, 30W, 8MHz	{2SB1037	17j	TO-220	25D1138	17j	BD 239D, 25C2073, 25D608(A), 25D1138, ++
2 SD 1460	Tos	Si-N-Darl+Di	S P, 100/100V, 30A, 200W, hFE=4k>1k, 10MHz	23a	TO-3				25D730
2 SD 1461									

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International
2 SD 1469(M)	Rhm	Si-N	=2SD1468: 0.6W	9c	BC 337	7a	BC 337...338, BC 635, BC 637, BC 639, ++
2 SD 1470	Hit	Si-N-Darl	SMD, Uni, 60/60V, 1/2A, hFE=2k...100k	39b	SOT-89		BST 50, 52, 2SD1511, 2SD1834
2 SD 1471	Hit	Si-N-Darl	SMD, Uni, 40/30V, 0.3/0.5A, hFE=2k...100k	39b	SOT-89		BCV 29, BCV 49
2 SD 1472	Hit	Si-N-Darl+Di	SMD, Uni, 120/120V, 1.5/3A, hFE=2k...30k	39b	SOT-89		-
2 SD 1473	Hit	Si-N	SMD, L.F.S. 500/400V, 0.5A	39b	SOT-89		-
2 SD 1474	Mat	Si-N	100/60V, hi-Ueb=15V, 6/12A, 40W, hi-hFE=300...2000 0.3/2.1µs, lo-sat<0.5V(5A)	17c	SOT-186		(2SC4553, 2SD1947)
2 SD 1475	Mat	Si-N	=2SD1476: Iso	17c	SOT-186	2SD1411	2SC3691, 2SC3746, 2SC4549, 2SC4596, ++
2 SD 1476	Mat	Si-N	P, 80/80V, 4/8A, 35W, 50MHz, 350/1300ns	17j	TO-220	BD 243 C	BD 243B, BD 537, BD 539B, BD 951, ++
2 SD 1477	Mat	Si-N	Uni, 30/25V, 0.1A, 0.4W, hFE=300	9c	BC 546	7a	BC 168, BC 183, BC 238, BC 548, ++
2 SD 1478	Mat	Si-N-Darl	=2SD892: SMD, 200MHz	35a	SOT-23		BCV 27, 2SD1183
2 SD 1478 A	Mat	Si-N-Darl	=2SD892A: SMD, 200MHz	35a	SOT-23		BCV 47
2 SD 1479	Mat	Si-N	TV-HA, 1500/700V, 2.5/6A, 80W, 2MHz, sat<5V(2A)	18j	TO-3P	BU 705 *	BU 705, 2SC3483, 2SD1493...94
2 SD 1480	Mat	Si-N	P, 60/60V, 2/4A, 25W, 20MHz, 0.2/4.2µs {2SB1052	17c	SOT-186	(2SC1398) ³	BD 936F, 2SD1585, 2SD1985, 2SD2012
2 SD 1481	Nec	Si-N-Darl+Di	Z-Di(C -B), 60±10V, 2/4A, 15W, hFE=2k...20k, 0.5/3µs	17j	TO-220	(BD 901)	(BD 715, BDW 23A, BDW 53B, 2SD0837,++)
2 SD 1482	Mat	Si-N	SMD, Uni, 40/40V, 0.1A	35a	SOT-23	BC 846	BC 846...847, BCW 71...72, BCW 81, ++
2 SD 1483	Mat	Si-N	=2SD1458: SMD	39b	SOT-89		2SC4390, 2SD1870, 2SD1950
2 SD 1484	Rhm	Si-N	SMD, L.F. 50/50V, 0.5A, 250MHz	-35d	(MMT)		-
2 SD 1484 K	Mat	Si-N	=2SD1484:	35a	SOT-23	BC 817	BC 817, BCW 65...66, 2SC3325, 2SC3441, ++
2 SD 1485	Mat	Si-N	=2SD1332: {2SB1054	16c	(TOP-3F)	(BD 245C) ³	2SC4385, 2SD2064, (BD 245C, 2SC2837,++) ³
2 SD 1486	Mat	Si-N	=2SD1333: {2SB1055	16c	(TOP-3F)	(2SC2837) ³	2SC4385, 2SD2064, (BD 245D, 2SC3181,++) ³
2 SD 1487	Mat	Si-N	=2SD1334: {2SB1056	16c	(TOP-3F)	(2SC2837) ³	2SC4386, 2SD2052, (BD 245D, 2SD1046,++) ³
2 SD 1488	Mat	Si-N	=2SD1335: {2SB1057	16c	(TOP-3F)	(2SC2837) ³	2SC4386, 2SD2052, (BD 245D, 2SC2837,++) ³
2 SD 1489	Hit	Si-N	LF Drv.Out, 20/16V, 2A, 0.75W, 80MHz	{2SB1058	7c	TO-92	2SC3225, 2SD1100, 2SD1146, 2SD1207, ++
2 SD 1490	Hit	Si-N	LF Drv.Out, 70/50V, 1A, 0.75W, 80MHz	{2SB1059	7c	TO-92	BC 639, 2SD667, 2SD1616(A), 2SD1768, ++
2 SD 1491	Nec	Si-N-Darl+Di	Z-Di(C -B), 60±10V, ±2/3A, 10W, hFE=2k...20k, 0.5/4µs	14h	TO-126		-
2 SD 1492	Hit	Si-N	TV-HA, 1500/600V, 1.5A, 50W	18j	TO-3P	BU 705 *	BU 705, 2SC3483
2 SD 1493	Hit	Si-N	TV-HA, 1500/800V, 2.5A, 50W	18j	TO-3P	BU 705 *	BU 705, 2SC3483
2 SD 1494	Hit	Si-N	TV-HA, 1500/800V, 3A, 50W, sat<5V(2.5A)	18j	TO-3P	BU 508 A	BU 706, 2SC3484
2 SD 1495	Hit	Si-N	TV-HA, 1500/600V, 4A, 50W	18j	TO-3P	BU 508 A	BU 508(A), BU 706, 2SC3484
2 SD 1496	Hit	Si-N	TV-HA, 1500/600V, 5A, 50W, sat<5V(4.5A)	18j	TO-3P	BU 508 A	BU 508(A), BU 908, 2SC3485...86, 2SC3685
2 SD 1497	Hit	Si-N	TV-HA, 1500/650A, 50W, sat<5V(5A)	18j	TO-3P	BU 508 A	BU 508(A), BU 908, 2SC3482, 2SC3685
2 SD 1498	Hit	Si-N	TV-HA, 1400/650V, 8A, 50W	18j	TO-3P	BU 508 A	BU 508(A), BU 908, 2SC3687
2 SD 1499	Mat	Si-N	=2SD1485: 40W {2SB1063	17c	SOT-186	2SD1411	BD 953F, BDT41AF, 2SD1407, 2SD1940, ++
2 SD 1500	Tos	Si-N-Darl+Di	P, 150/100V, 10A, 40W, 20MHz, hFE=5k>1k, 0.6/4µs	17j	TO-220	2SD1756	2SD1756
2 SD 1501	Hit	Si-N	LF Drv.Out, 70/50V, 1A, 1W, hFE=250	9c	2SD1207	7c	2SD667, 2SD774, 2SD1616(A), 2SD1768, ++
2 SD 1502	Nec	Si-N-Darl	S P, 300/300V, 0.3/0.6A, 15W, 15MHz, hFE=1.5k...30k	17j	TO-220		2SD1798
2 SD 1503	Hit	Si-N	TV-HA, 900/400V, 6A, 50W	18j	TO-3P	BU 508 A	BU 508(A), BU 908, 2SC3636, 2SC3642
2 SD 1504	Hit	Si-N	LF Drv.Out, Muting, 30/15V, 0.5/1A, 0.3W, 300MHz Ron=0.5Ω(lb=2mA)	41c	(SPAK)	(BC 337)	(BC 337...338, 2SD774, 2SC3377, 2SD1302+)
2 SD 1504	Hit	Si-N	LF Drv.Out, Muting, 30/15V, 0.5/1A, 0.3W, 300MHz Ron=0.5Ω(lb=2mA)	41c	(SPAK)	(BC 337)	(BC 337...338, 2SD774, 2SC3377, 2SD1302+)
2 SD 1505	Rhm	Si-N	P, 60/50V, 3/4.5A, 30W, 90MHz	{2SB1064	17j	TO-220	BD 241A, BD 535, BD 935, 2SC3252, ++
2 SD 1506	Rhm	Si-N	=2SD1505: 10W {2SB1065	14h	TO-126	2SD1348	BD 177, BD 439, BD 785, 2SD1348, ++
2 SD 1507(M)	Rhm	Si-N	=2SD1505: 1W {2SB1066	9c	(ATR)	2SD1347	2SC4487, 2SD1145, 2SD1347, 2SD1864
2 SD 1508	Tos	Si-N-Darl	P, 30/30V, 1.5/3A, 10W, hFE=7k>4k, 180/900ns	14b	TO-126 Iso	2SD947	2SD947
2 SD 1509	Tos	Si-N-Darl+Di	P, 80/80V, 2A, 10W, 100MHz, hFE=5k>2k, 0.4/4.6µs	14b	TO-126 Iso		-
2 SD 1510	Mat	Si-N-Darl+Di	P, 60/60V, 4/8A, 35W, hFE=1k...10k	17c	SOT-186	2SD1415	BDT 61F, 2SD1790, 2SD1796, 2SD1987, ++
2 SD 1511	Mat	Si-N-Darl	Uni, 100/80V, 1/1.5A, 150MHz, hFE=4k...40k	39b	SOT-89		BST 52, 2SD1472
2 SD 1512	Mat	Si-N	=2SD1011:	40c			-2SD1011
2 SD 1513	Nec	Si-N	Uni, 20/16V, 2/3A, 0.75W, 200MHz {2SB1068	7c	TO-92	2SD1207	2SC3225, 2SD1100, 2SD1146, 2SD1207, ++
2 SD 1514	Shi	Si-N-Darl	P, 100/100V, 15A, 100W, hFE=4000, <2/22µs	16j	(MTO-3P)	BDW 83 C	BDV 67A, BDW 83C, 2SD1026
2 SD 1515	Shi	Si-N-Darl	=2SD1514: 200/200V	16j	(MTO-3P)		2SD1027
2 SD 1516	Mat	Si-N	130/80V, 2/5A, 25W, 25MHz, sat<0.5V(2A), 0.1/2.8µs	17j	TO-220	(2SD1138) ¹⁷	2SD1528
2 SD 1517	Mat	Si-N	=2SD1516: Iso	17c	SOT-186	(2SC4159) ¹⁷	2SD1268
2 SD 1518	Tos	Si-N	S P, 900/400V, 6/10A, 50W, 5MHz	18j	TO-3P	BU 426 A	BU 426A, BUW 11(A), 2SC3153, 2SD1503, ++
2 SD 1519	Tos	Si-N	TV-HA, 1500/600V, 10A, 80W, 3MHz, sat<5V(8A)	77j	=TOP-3L	2SC3688	BU 2520A, 2SC3688
2 SD 1520 L,S	Hit	Si-N-Darl+Di	100/80V, 4A, 20W, hFE=1k...20k, 0.5/5.5µs {2SB1072	30j	TO-251/252	(BD 679) ⁴	2SC4345, 2SD1223, (BDW 23C, BDW 53C,++)
2 SD 1521	Hit	Si-N-Darl+Di	int. Z-Di(C -B), 50/50V, 1.5/3A, 10W, hFE=2k...30k 0.5/2µs	14h	TO-126	(BD 679)	(2SC4341, 2SD1376, 2SD1438)
2 SD 1522	Hit	Si-N-Darl+Di	S P, 500/450V, 10A, 100W, hFE=500	18j	TO-3P		BUT 51P, 2SC3262, 2SD979, 2SD1298
2 SD 1523	Hit	Si-N-Darl	S P, 450/450V, 15A, 100W, hFE=500	18j	TO-3P		BUT 51P, 2SD1466
2 SD 1524	Hit	Si-N-Darl	S P, 450/450V, 10A, 100W, hFE=300	18j	TO-3P		BUT 51P, 2SC3262, 2SD979, 2SD1298
2 SD 1525	Tos	Si-N-Darl+Di	S P, 100/100V, 30A, 150W, hFE=4k>1k, 1.5/11.5µs	77j	TOP-3L		-
2 SD 1526	Mat	Si-N	LF Drv.Out, 130/40V, 1/1.5A, 1W, 200MHz	9c		2SD1812	2N3700...01, 2SC2383, 2SC3228, 2SD1812
2 SD 1527	Hit	Si-N	S P, 1000/1000V, 0.5A, 25W, 5MHz	17j	TO-220	(BUX 85)	(BUX 36A, BUX 85, 2SC3178, 2SC3531,++)
2 SD 1528	Mat	Si-N	130/80V, 3/6A, 30W, 25MHz, sat<0.5V(2A), <0.5/2µs	17j	TO-220		-
2 SD 1529	Mat	Si-N	=2SD1528:	30j	(TO-220MF)		2SD1254...55
2 SD 1530	Mat	Si-N	=2SD1528: Iso	17c	SOT-186		-
2 SD 1531	Mat	Si-N	P, 50/40V, 2A, 5W, 150MHz	14h	TO-126	BD 237	BD 177, BD 235, BD 377, 2SD1177...78, ++
2 SD 1532	Sak	Si-N-Darl	P, 120/100V, 4A, 30W, hFE=3000	17j	TO-220	2SD1756	BDT 21, BDW 53D, BDW 63D, 2SD1147, ++
2 SD 1533	Mat	Si-N-Darl	S P, 500/400V, 7/14A, 50W, 20MHz, hFE>500, 1.5/12µs	17j	TO-220		BU 810
2 SD 1534	Mat	Si-N-Darl	=2SD1533:	30j	(TO-220MF)		2SC4220, 2SC4598, (BU 810) ⁶
2 SD 1535	Mat	Si-N-Darl	=2SD1533: Iso	17c	SOT-186		(BU 810) ³
2 SD 1536(M)	Rhm	Si-N-Darl	Uni, 40/40V, 2A, 1W, 150MHz, hFE=20k>1k	9c	(ATR)		2SD1786, 2SD1861, 2SD1916, 2SD1931
2 SD 1537	Mat	Si-N	P, 40/20V, 4/8A, 25W, 120MHz, 0.2/0.6µs {2SB1069	17j	TO-220	(BD 243 C) ³	2SC2562, 2SC3253, 2SD1235
2 SD 1537 A	Mat	Si-N	=2SD1537: 50/40V	17j	TO-220	(BD 243 C) ³	2SC2562, 2SC3253, 2SD1235
2 SD 1538(A)	Mat	Si-N	=2SD1537(A):	30j	(TO-220MF)		2SD1903, (2SC2562, 2SC3253, 2SD1235) ⁶
2 SD 1539(A)	Mat	Si-N	=2SD1537(A): Iso	17c	SOT-186	2SC3299	2SC3299, 2SC4327, 2SD1444(A)
2 SD 1540	Tos	Si-N-Darl	P, 100/60V, 6A, 60W, hFE=800	23a	TO-3	BDW 83 C	BDV 65B, BDW 63B, TIP 142, 2SD1170, ++
2 SD 1541	Mat	Si-N+Di	TV-HA, 1500V, 3/10A, 50W, 2MHz, sat<5V(2A)	16c	(TOP-3F)	S 2055 AF	BU 508DF, 2SC3480, 2SD1554, 2SD1650
2 SD 1542	Tos	Si-N	TV-HA, 1500/600V, 1.5A, 40W	18c	TO-3P Iso	(BU 705) ³ *	2SD1653, (BU 705, 2SC3483, 2SD1492...94) ³
2 SD 1543	Tos	Si-N	TV-HA, 1500/600V, 2.5A, 40W, 3MHz, sat<8V(2A)	18c	TO-3P Iso	(BU 705) ³ *	2SD1563, (BU 705, 2SC3483, 2SD1493...94) ³
2 SD 1544	Tos	Si-N	TV-HA, 1500/600V, 3.5A, 40W, 3MHz, sat<8V(3A)	18c	TO-3P Iso	S 2000 AF	BU 508AF, 2SD1654, (BU 706, 2SC3484) ³
2 SD 1545	Tos	Si-N	TV-HA, 1500/600V, 5A, 50W, 3MHz, sat<5V(5A)	18c	TO-3P Iso	BU 508 AF	BU508AF, 2SD1655, (BU908, 2SC3485...86,++) ³
2 SD 1546	Tos	Si-N	TV-HA, 1500/600V, 6A, 50W, 3MHz, sat<5V(5A)	18c	TO-3P Iso	BU 508 AF	BU 508AF, 2SD1556, (BU 908, 2SC3486,++) ³
2 SD 1547	Tos	Si-N	TV-HA, 1500/600V, 7A, 50W, 3MHz, sat<5V(6A)	18c	TO-3P Iso	BU 508 AF	BU 508AF, 2SC3895, (BU 908, 2SC3686,++) ³
2 SD 1548	Tos	Si-N	TV-HA, 1400/600V, 10A, 50W, 3MHz, sat<5V(8A)	18c	TO-3P Iso	2SC4924	BU 2520AF, 2SC4199(A), 2SC4797, (2SD1519) ³
2 SD 1549	Tos	Si-N	TV-HA, 1000/800V, 5A, 50W	18c	TO-3P Iso	BU 508 AF	BU 508AF, 2SD1655, (BU 908, 2SC3642,++) ³
2 SD 1550	Tos	Si-N	TV-HA, 1000/400V, 10A, 50W	18c	TO-3P Iso	2SC4924	BU 2520AF, 2SC4125, (2SC3688, 2SD1519) ³
2 SD 1551	Tos	Si-N	TV-HA, 1500/600V, 5A, 50W	18c	TO-3P Iso	BU 508 AF	BU 508AF, 2SC4293...94, 2SD1655, ++
2 SD 1552	Tos	Si-N	TV-HA, 1500/600V, 5A, 50W	18c	TO-3P Iso	BU 508 AF	BU 508AF, 2SC4293...94, 2SD1655, ++
2 SD 1553	Tos	Si-N+Di	=2SD1543: int. Damper-Diode	18c	TO-3P Iso	2SD1555	BU 508DF, BU 706DF, 2SD1649, 2SD2089
2 SD 1554	Tos	Si-N+Di	=2SD1544: int. Damper-Diode	18c	TO-3P Iso	2SD1555	BU 508DF, BU 706DF, 2SD1650, 2SD2089
2 SD 1555	Tos	Si-N+Di	=2SD 1545: int. Damper-Diode	18c	TO-3P Iso	2SD1555	BU 508 DF, 2SD1651, 2SD2095, 2SD2125

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International	
2 SD 1556	Tos	Si-N+Di	=2SD 1546: int. Damper-Diode	18c	TO-3P Iso	(2SD1555) ⁷	18c	BU 508DF, 2SC3892A, 2SD1652, 2SD2125
2 SD 1557	Nec	Si-N	=2SD1033:	30j	TO-251	•SD1033)	-	-2SD1033
2 SD 1558	Hit	Si-N-Darl	P, 60/60V, 4/8A, 40W, hFE=1k...20k, 0.5/7μs	(2SB1077 17j)	TO-220	2SD1756	17j	BD 715, BDW 23A, BDW 53A, 2SD837, ++
2 SD 1559	Hit	Si-N-Darl+Di	100/100V, 20/30A, 100W, hFE=1k...20k, 1/9μs	(2SB1079 18j)	TO-3P	-	-	2SD1597, 2SD2083, 2SD2256
2 SD 1562	Rhm	Si-N	LF P, 120/120V, 1.5/3A, 20W, 80MHz	(2SB1085 17j)	TO-220	2SD1138	17j	BD 239D, BD 959, 2SC2275, 2SD1138, ++
2 SD 1562 A		Si-N	=2SD1562: 160/160V	17j	TO-220	2SD1138	17j	BD 239D, 2SC2238(A, B), 2SD608(A), 2SD1138++
2 SD 1563	Rhm	Si-N	=2SD1562: 10W	(2SB1086 14h)	TO-126	2SC3117	14h	2SC2690(A), 2SD781
2 SD 1563 A		Si-N	=2SD1563: 160/160V	14h	TO-126	2SC3117	14h	2SC3117, 2SD669
2 SD 1564	Nec	Si-N-Darl+Di	Z-Di(C •B), 50/50V, 5/10A, 30W, hFE=2k...20k, 1/9μs	17j	TO-220	2SD1756	17j	2SD1147, (BDW 23A, BDW 63A)
2 SD 1565	Nec	Si-N-Darl+Di	P, 100/100V, 5/10A, 30W, hFE=2k...20k, 1/4, 7μs	17j	TO-220	2SD1756	17j	2SD1147, (BDW 23C, BDW 63C)
2 SD 1566	Nec	Si-N-Darl+Di	P, 150/100V, ±10/20A, 60W, hFE=9k...1k, 1/7μs	15j	(MP-40)	-	-	-
2 SD 1567	Nec	Si-N	P, 60/60V, 3/5A, 30W, 16MHz	(2SB1089 17j)	TO-220	BD 243 C	17j	BD 241A, BD 535, BD 935, 2SC3252, ++
2 SD 1568	Nec	Si-N	P, 100/100V, 4/6A, 40W, 20MHz	(2SB10 17j)	TO-220	BD 243 C	17j	BD 243C, BD 537, BD 539C, 2SC3253, ++
2 SD 1569	Nec	Si-N	60/60V, 3/7A, 30W, 100MHz, hi-hFE=800...3200 lo-sat<0.5V(2A)	17j	TO-220	-	-	-
2 SD 1571	Tos	Si-N	S P, TV-SMPS, 800/400V, 3/6A, 30W, 4MHz, <1/8μs	17c	SOT-186	2SC3752	17c	BUT 11(A)F, 2SC3353, 2SC3749, 2SC4304, ++
2 SD 1572	Hit	Si-N-Darl	60/60V, 8/12A, 40W, hFE=1k...20k, 0.5/7,5μs	(2SB1091 17j)	TO-220	BD 901	17j	BD 645, BD 897, BDW 73A, BDX 53A, ++
2 SD 1573	Hit	Si-N	LF, S, 600/600V, 0,1A, 1W	9c	-	-	-	-
2 SD 1574	Mat	Si-N-Darl	P, 100/80V, 1A, 10W, hFE=4k...40k	30j	TO-251/252	-	-	2SD1465, 2SD1980, 2SD2410
2 SD 1575	Mat	Si-N	TV-HA, 1500/700V, 2/6A, 40W, 2MHz, sat<5V(2A)	17c	SOT-186	-	-	BU 505F, (BU 506) ³
2 SD 1576	Mat	Si-N	=2SD1575: 80W	16c	(TOP-3F)	S 2000 AF	18c	2SD1543, 2SD1653, (BU 705, 2SC3483,++) ³
2 SD 1577	Mat	Si-N	TV-HA, 1500/700V, 5/17A, 100W, 2MHz, sat<2V(4,5A)	16c	(TOP-3F)	2SD1577	16c	-
2 SD 1577 FI	Tho	Si-N	=2SD1577:	18c	TO-3P Iso	2SD1577	16c	-
2 SD 1578	Hit	Si-N	LF Drv, Out, 30/15V, 0,7A, 0,5W, 300MHz, hFE=550	9c	-	2SC3225	7c(9mm)	2SC3225, 2SC4204, 2SC4389, 2SD1984, ++
2 SD 1579	Nec	Si-N-Darl+Di	LF, S, 150/80V, ±1,5/3A, 1W, hFE=2k...30k, 0,5/2μs	9b	(SP-8)	-	-	2SD1659, 2SD2213
2 SD 1580	Rhm	Si-N	P, 100/80V, 7/10A, 40W, 5MHz	17j	TO-220	BD 243 C	17j	BD 243C, BD 543C, BD 801, 2SD550, ++
2 SD 1581	Nec	Si-N	30/25V, hi-Ueb=15V, 2/3A, 350MHz, hi-hFE=800...3200	9b	(2SC3225)	-	7c(9mm)	2SC4389, 2SD1581, 2SD1779
2 SD 1582	Nec	Si-N	60/50V, hi-Ueb=15V, 1/1,5A, 1W, 250MHz, hi-hFE=800...3200	9b	-	-	-	2SD1779
2 SD 1583(Z)	Nec	Si-N	30/20V, 2/3A, 10W, 270MHz, hFE=800...3200 0,6/1,8μs, lo-sat<0.5V(1A)	30j	TO-251	(2SC3908) ⁴	14h	2SC3474, 2SC5155
2 SD 1584	Nec	Si-N	60/60V, 3/5A, 10W, >50MHz, hFE=800...3200 0,9/3,6μs, lo-sat<0.5V(2A)	30j	TO-251	-	-	2SD1719, 2SD1755
2 SD 1585	Nec	Si-N	=2SD1567: Iso, 15W	(2SB1094 17c)	SOT-186	2SC3299	17c	BD935F, 2SC3690, 2SC3851...52, 2SD1913, ++
2 SD 1586	Nec	Si-N	=2SD1568: Iso, 20W	(2SB1095 17c)	SOT-186	2SD1411	17c	BD 953F, 2SC3475, 2SC3691, 2SD1407, ++
2 SD 1587	Nec	Si-N	TV, LF P, 200/150V, 2/3A, 25W, 5MHz	(2SB1096 17c)	SOT-186	(2SD1138) ³	17j	2SC4382, 2SD2337, (BD 239F, 2SC2660,++) ³
2 SD 1588	Nec	Si-N	P, 100/60V, 7/15A, 30W, sat<0.5V(5A)	(2SB1097 17c)	SOT-186	2SD1411	17c	2SC3692, 2SC4550, 2SD1271, 2SD1411
2 SD 1589	Nec	Si-N-Darl+Di	100/100V, ±5/10A, 20W, hFE=2k...20k, 1/4, 7μs	(2SB1098 17c)	SOT-186	2SD1415	17c	BD 647F, 2SD1785, 2SD1829, 2SD1928
2 SD 1590	Nec	Si-N-Darl+Di	150/100V, 8/12A, 25W, hFE=2k...15k, 1/4, 7μs	(2SB1099 17c)	SOT-186	-	-	2SD1591, 2SD1792, 2SD1974, 2SD2101
2 SD 1591	Nec	Si-N-Darl+Di	150/100V, ±10/25A, 30W, hFE=1k...30k, 1/7μs	(2SB1100 17c)	SOT-186	-	-	2SD1794, 2SD2101, (2SD1500) ³
2 SD 1592	Nec	Si-N-Darl	S P, 500/300V, 5/10A, 30W, hFE=400...3000, 1/18μs Rbe=500Ω	17c	SOT-186	(2SD1409) ¹⁸	17c	2SD1409 ¹⁸
2 SD 1593	Nec	Si-N	60/60V, 3/5A, 20W, 110MHz, hi-hFE=800...3200 lo-sat<0,5V(2A)	17c	SOT-186	2SD1273 ¹⁷	17c	2SD1948, 2SD1972, 2SD2127, 2SD2164
2 SD 1594	Nec	Si-N	100/100V, 6/10A, 30W, 110MHz, hFE=800...3200	17c	SOT-186	-	-	2SC4553, 2SD1947
2 SD 1595	Nec	Si-N-Darl+Di	Z-Di(C •B), 60/60V, 5/10A, 20W, hFE=2k...20k, -9μs	17c	SOT-186	2SD1415	17c	2SD1415...17, 2SD1589, 2SD1633, 2SD2079++
2 SD 1597	Hit	Si-N-Darl+Di	P, 120/120V, 30/45A, 80W, hFE>1000, -7μs	18j	TO-3P	-	-	-
2 SD 1598	Nec	Si-N-Darl	P, 60/60V, 1A, 10W, hFE=8000	30j	TO-251/252	(BD 679) ⁴	14h	2SC2871, 2SD1465, 2SD1164, 2SD1800
2 SD 1599	Hit	Si-N-Darl	80/80V, 4/8A, 40W, hFE=1k...20k, 0,5/7μs	(2SB1077 17j)	TO-220	BD 901	17j	BDW 23B, BDW 53B, BDW 63B, 2SD837A, ++
2 SD 1600	Hit	Si-N-Darl	80/80V, 8/12A, 40W, hFE=1k...20k, 0,5/7,5μs	(2SB1091 17j)	TO-220	BD 901	17j	BD 647, BD 899, BDW 73B, BDX 53B, ++
2 SD 1601	Hit	Si-N-Darl+Di	60/60V, 4/8A, 40W, hFE=1k...20k, 1/7μs	(2SB1101 17j)	TO-220	BD 901	17j	BD 715, BDW 23A, BDW 53A, 2SD837, ++
2 SD 1602	Hit	Si-N-Darl+Di	=2SD1601: 80/80V	(2SB1102 17j)	TO-220	BD 901	17j	BD 717, BDW 23B, BDW 53B, 2SD837A, ++
2 SD 1603	Hit	Si-N-Darl+Di	60/60V, 8/12A, 40W, hFE=1k...20k, 0,5/6μs	(2SB1103 17j)	TO-220	BD 901	17j	BD 645, BD 897, BDW 73A, BDX 53A, ++
2 SD 1604	Hit	Si-N-Darl+Di	=2SD1604: 80/80V	(2SB1104 17j)	TO-220	BD 901	17j	BD 647, BD 899, BDW 73B, BDX 53B, ++
2 SD 1605	Hit	Si-N-Darl+Di	120/120V, 3/6A, 30W, hFE=1k...20k, 0,7/8μs	(2SB1105 17j)	TO-220	2SD1756	17j	BDW 53D, BDW 63D, 2SD830, 2SD1147, ++
2 SD 1606	Hit	Si-N-Darl+Di	120/120V, 6/12A, 40W, hFE=1k...20k, 0,6/9μs	(2SB1106 17j)	TO-220	2SD1756	17j	BDT 21, BDW 63D, 2SD830, 2SD1147, ++
2 SD 1607	Hit	Si-N-Darl+Di	P, 120/120V, 10A, 40W, hFE=5000	(2SB1107 17j)	TO-220	2SD1756	17j	BDT 63C, BDT 65D, BDX 33D, 2SD1126
2 SD 1608	Mat	Si-N-Darl	120/120V, 8/12A, 50W, 20MHz, hFE=1k...20k	(2SB1108 17c)	SOT-186	(2SD1756) ³	17j	BD 649F, BDT 63CF, 2SD1773, 2SD1590, ++
2 SD 1609	Hit	Si-N	P, 160/160V, 0,1A, 140MHz	(2SB1109 14h)	TO-126	BF 459	14h	BF 415, BF 457...459, 2SC3416, 2SC3502, ++
2 SD 1610	Hit	Si-N	=2SD1609: 200/200V	(2SB1110 14h)	TO-126	BF 459	14h	BF 415, BF 458...459, 2SC3416, 2SC3502, ++
2 SD 1611	Mat	Si-N-Darl+Di	S P, 500/400V, 6/10A, 40W, 15MHz, hFE>500	30j	(TO-220MF)	-	-	-
2 SD 1612	Hit	Si-N-Darl+Di	P, 120/120V, 6A, 40W, hFE=5000	15j	-	2SD1756	17j	BDW 63D, BDW 73D, BDX 53D, 2SD1147, ++
2 SD 1613	Hit	Si-N-Darl+Di	P, 120/120V, 8A, 40W, hFE=5000	15j	-	2SD1756	17j	BDW 73D, BDX 33D, BDX 53D, 2SD651, ++
2 SD 1614	Nec	Si-N	SMD, Uni, 40/20V, 2/3A, 200MHz	(2SB1114 39b)	SOT-89	-	-	2SC2873, 2SD1119, 2SD1766, 2SD2532
2 SD 1615	Nec	Si-N	SMD, 60/60V, 1/2A, >80MHz, sat<0,3V(1A)	(2SB1115 39b)	SOT-89	-	-	2SC3444, 2SC5053, 2SD1622...23, 2SC4409++
2 SD 1615 A		Si-N	=2SD1615: 120/60V	39b	SOT-89	-	-	(2SC3646, 2SD1418...19) ¹⁷
2 SD 1616	Nec	Si-N	60/50V, 1/2A, 0,75W, 160MHz, sat<0,3V(1A)	(2SB1116 7c)	TO-92	2SD1207	7c	2SC4485...86, 2SD1207, 2SD1835
2 SD 1616 A		Si-N	=2SD1616: 120/60V	7c	TO-92	(2SD1812) ¹⁷	7c	2SC4488...89, 2SD1812, 2SD1857, ++) ¹⁷
2 SD 1617	Nec	Si-N	LF Out, 40/25V, 3/5A, 1W, 200MHz, sat<0,5V(3A)	9b	-	2SD1347	7c(9mm)	2SC4487, 2SD1347
2 SD 1618	Say	Si-N	SMD, LF, 20/15V, 0,7/1,5A, 250MHz, sat<0,08V(0,1A)	39b	SOT-89	-	-	2SC2982, 2SC4390
2 SD 1619	Say	Si-N	SMD, LF, 25/25V, 1/2A, 180MHz	(2SB1118 39b)	SOT-89	-	-	-
2 SD 1620	Say	Si-N	SMD, Strobo, 30/20V, 3/5A, 200MHz, sat<0,4V(3A)	39b	SOT-89	-	-	BC 868, BCX 68, BCX 54...56, 2SC3444, ++
2 SD 1621	Say	Si-N	SMD, LF, 30/25V, 2/5A, 150MHz, sat<0,4V(1,5A)	39b	SOT-89	-	-	2SD1624
2 SD 1622	Say	Si-N	SMD, LF, 60/50V, 1/2A, 150MHz, sat<0,3V(0,5A)	39b	SOT-89	-	-	2SC2982, 2SD1620
2 SD 1623	Say	Si-N	SMD, LF, 60/50V, 2/4A, 150MHz, sat<0,4(1A)	39b	SOT-89	-	-	-
2 SD 1624	Say	Si-N	SMD, LF, 60/50V, 3/6A, 150MHz, sat<0,5V(2A)	39b	SOT-89	-	-	2SC4409, 2SD2391, 2SD2533
2 SD 1625	Say	Si-N-Darl	SMD, LF, 80/50V, 0,7/2A, 200MHz, hFE>5000	(2SB1125 39b)	SOT-89	-	-	-
2 SD 1626	Say	Si-N-Darl	SMD, LF, 80/50V, 1,5/3A, 120MHz, hFE>4000	(2SB1126 39b)	SOT-89	-	-	BST 51...52
2 SD 1627	Say	Si-N-Darl	SMD, LF, 30/25V, 2/3A, 120MHz, hFE>4000	39b	SOT-89	-	-	2SD1472
2 SD 1628	Say	Si-N	SMD, 60/20V, 5/8A, 120MHz, 30/340ns, sat<0,5V(3A)	39b	SOT-89	-	-	2SD1784
2 SD 1629	Nec	Si-N-Darl+Di	Z-Di(C •B), 60/60±10V, ±1,2/3A, 10W, B=2k...30k 0,5/4μs	17j	TO-220	-	-	-
2 SD 1630	Nec	Si-N-Darl+Di	Z-Di(C •B), 60/60±10V, ±1/2A, 10W, B=2k...30k 0,5/2μs	14h	TO-126	-	-	-
2 SD 1631	Tos	Si-N-Darl	=2SD1140: 1W	9c	(BD 679) ⁶	-	14h	2SD1536, 2SD1786, 2SD1861, 2SD2046, ++
2 SD 1632	Mat	Si-N+Di	S P, TV-HA, 1500V, 4/15A, 70W, 2MHz, sat<1V(3A)	16c	(TOP-3F)	BU 508 DF	16c	BU 508DF, 2SD1554...55, 2SD1650, 2SD2089

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International	
2 SD 1633	Mat	Si-N-Darl	100/100V, 5/8A, 30W, 15MHz, hFE=1.5k...15k, <3/8μs	17c	SOT-186	2SD1415	17c	2SD1589, 2SD1785, 2SD1829, 2SD1928
2 SD 1634	Mat	Si-N-Darl	100/100V, 8/12A, 50W, 15MHz, hFE=1.5k...15k, <3/8μs	17c	SOT-186	2SD1415	17c	2SD4063, 2SD1415, 2SD1590...91, 2SD1791
2 SD 1635	Mat	Si-N-Darl+Di	S P, 1500V, 5A, 100W, B=40...150	23a	TO-3			
2 SD 1636	Mat	Si-N	LF.Vid, 300V, 0.07A, 1W, 80MHz	9c		BF 420 A	7c	BF 299, BF 487, BF 420A, 2SC3468, ++
2 SD 1637	Rhm	Si-N-Darl+Di	Z-Di(C +B), 60/60±10V, 2/3A, 15W, hFE=1k...10k	14h	TO-126			
2 SD 1638	Rhm	Si-N-Darl+Di	P, 100/100V, 2/3A, 15W, hFE=1k...10k	14h	TO-126			2SD1376, 2SD1953
2 SD 1639	Mit	Si-N	P, 100/80V, 2.2A, 10W(Tc=25°)	2a	TO-39			BUY 41, 2N4300, 2SC1680
2 SD 1640	Mat	Si-N-Darl+Di	P, 120/100V, 2/3A, 150MHz, hFE=4k...40k	14b	TO-126			
2 SD 1641	Mat	Si-N	TV-Reg, Z-Di(C +B), 55/55V, 4/20A, 80W, 45MHz hFE=500...2500, R _c =2k2	18j	TO-3P			
2 SD 1642	Hit	Si-N	LF, 100/60V, 2A, 0, 7W	7c	TO-92	(2SC4135) ⁴	30j	2SD1015, (BD 529, 2SD1281...1282,++) ⁶
2 SD 1643	Mat	Si-N	80/60V, 3/6A, 50W, 50MHz, hi-hFE=500...2500	16c	(TOP-3F)			
2 SD 1643 A	Mat	Si-N	=2SD1643: 100/80V	16c	(TOP-3F)			
2 SD 1644	Mat	Si-N-Darl	SMD, int. Z-Di(C +B, 95V), 95/95V, 1A, hFE=10000	39b	SOT-89			BST 52
2 SD 1645	Mat	Si-N-Darl	+Z-Di(C +E+C +B), 60V, 1A, 5W, 150MHz, hFE=4k...40k	14h	TO-126			
2 SD 1646	Rhm	Si-N-Darl+Di	=2SD1638: 25W	17j	TO-220			
2 SD 1647	Rhm	Si-N-Darl+Di	=2SD1637: 25W	17j	TO-220			
2 SD 1648	Say	Si-N	SMD, LF, 30/20V, 0,02A	35c	SOT-23			
2 SD 1649	Say	Si-N+Di	TV-HA, 1500/800V, 2.5/10A, 50W, 3MHz, sat<8V(2A)	18c	TO-3P Iso	BU 508 DF	16c	2SD706DF, 2SD1553, 2SD2089
2 SD 1650	Say	Si-N+Di	TV-HA, 1500/800V, 3.5/10A, 50W, 3MHz, sat<8V(2.5A)	18c	TO-3P Iso	BU 508 DF	16c	BU 706DF, 2SD1554, 2SD2089
2 SD 1650 FI	Tho	Si-N+Di	=2SD1650	18c	TO-3P Iso	BU 508 DF	16c	BU 706DF, 2SD1554, 2SD2089
2 SD 1651	Say	Si-N+Di	TV-HA, 1500/800V, 5/16A, 60W, 3MHz, sat<5V(4A)	18c	TO-3P Iso	(BU 508 DF)	16c	BU 508DF, 2SD4293, 2SD1556, 2SD2125
2 SD 1652	Say	Si-N+Di	TV-HA, 1500/800V, 6/16A, 60W, 3MHz, sat<5V(5A)	18c	TO-3P Iso	(BU 508 DF)	16c	BU 508DF, 2SD4293, 2SD1556, 2SD2125
2 SD 1653	Say	Si-N	=2SD1649: ohne/without Damper-Diode	18c	TO-3P Iso	S 2000 AF	18c	BU 705F, 2SD1543, (2SC3483, 2SD1493...94) ³
2 SD 1654	Say	Si-N	=2SD1650: ohne/without Damper-Diode	18c	TO-3P Iso	S 2000 AF	18c	BU 706F, 2SD1544, (2SC3484, 2SD1495,++) ³
2 SD 1655	Say	Si-N	=2SD1651: ohne/without Damper-Diode	18c	TO-3P Iso	BU 508 AF	16c	BU 508AF, 2SC4142...43, 2SD1545...46, ++
2 SD 1656	Say	Si-N	=2SD1652: ohne/without Damper-Diode	18c	TO-3P Iso	BU 508 AF	16c	BU 508AF, 2SC4294, 2SD1546...47, ++
2 SD 1657	Mat	Si-N	LF, 25/15V, 0,7A, 0,6W, 150MHz	7c	TO-92	BC 337	7a	BC 337...338, BC 635, BC 637, BC 639, ++
2 SD 1658	Tos	Si-N-Darl+Di	int. Z-Di(C +B, 60V), 50/50V, 2A, 10W, B=5k>2k	~14b				
2 SD 1659	Nec	Si-N-Darl+Di	L.F.S. 150/60V, ±1,5A, 1W, hFE=10000	9b				2SD1579, 2SC2213
2 SD 1660(M)	Rhm	Si-N-Darl+Di	=2SD1638: 1W	9c				2SD1978, 2SD1981, 2SD2067
2 SD 1661(M)	Rhm	Si-N-Darl+Di	=2SD1637: 1W	9c				
2 SD 1662	Tos	Si-N-Darl+Di	P, 100/100V, 15A, 100W, 14MHz, hFE=5k>1k, 1/3,5μs	18j	TO-3P	BDW 83 C	18j	BDV 67A, BDW 83C, 2SD1026
2 SD 1663	Mat	Si-N	TV-HA, 1500V, 5/10A, 80W, 2MHz, sat<2V(4,5A)	16c	(TOP-3F)	BU 508 AF	16c	BU 508AF, BU 706, 2SC3894, 2SD1655...56, ++
2 SD 1664	Rhm	Si-N	SMD, LF, 40/32V, 1/2A, 150MHz	(2SB1132)	SOT-89			BCX 54...56, 2SC3444, 2SC4539, 2SD1622, ++
2 SD 1665	Rhm	Si-N	Uni, 120/120V, 1,5/3A, 1W, 80MHz	(2SB1130)		2SD1812	7c	2SD1015, 2SD1812, 2SD1857
2 SD 1665 A(M)	Say	Si-N	=2SD1665: 160/160V	9c		2SD1812	7c	2SD1812, 2SD1857A
2 SD 1666	Say	Si-N	P, 60/60V, 3/8A, 25W, 8MHz	17c	TO-220 Iso	2SC3299	17c	2SC3299, 2SC3852, 2SD1585, 2SD2012, ++
2 SD 1667	Say	Si-N	S P, 60/50V, 5/9A, 25W, 30MHz, 100/1600ns	(2SB1134)	TO-220 Iso	2SC3299	17c	2SC3299, 2SC3746, 2SD1411
			lo-sat<0,4V(3A)					
2 SD 1668	Say	Si-N	S P, 60/50V, 7/12A, 30W, 10MHz, 200/1200ns	(2SB1135)	TO-220 Iso	2SD1411	17c	2SC3747, 2SD1412
			lo-sat<0,4V(4A)					
2 SD 1669	Say	Si-N	S P, 60/50V, 12/15A, 30W, 10MHz, 200/1250ns	(2SB1136)	TO-220 Iso	(2SD1062) ³	17j	2SC4065
			lo-sat<0,4V(6A)					
2 SD 1670	Nec	Si-N-Darl+Di	S P, 150/100V, ±10/20A, 65W, hFE=1k...30k, 1/7μs	18c	=TO-3P Iso			2SD1895, 2SD2439
2 SD 1671	Nec	Si-N-Darl+Di	S P, 150/100V, ±15/30A, 70W, hFE=1k...30k, 1/7μs	18c	=TO-3P Iso			BDV 67DF
2 SD 1672	Nec	Si-N-Darl+Di	S P, 150/100V, 25/50A, 70W, hFE=1k...30k, 1/7μs	18c	=TO-3P Iso			
2 SD 1673	Nec	Si-N-Darl+Di	S P, 500/400V, 10A, 70W, hFE=600	18c	=TO-3P Iso			(BU 922, BUW 81, MJ 10003, 2SD685,++) ³
2 SD 1676	Hit	Si-N+R	S, 20/20V, 0,6A, 0,3W, R _b =R _e =6.8kΩ, 0,3/2,2μs	41c	(SPAK)	(BC 337) ¹⁸	7a	(+BC 338...) ¹⁸
2 SD 1677	Say	Si-N	TV-HA, 1500/800V, 5A, 100W, sat<5V(4,5A)	18j	TO-3P	BU 508 A	18j	BU 508A, BU 908, 2SC3481...3482, ++
2 SD 1678	Tos	Si-N-Darl+Di	P, 100/100V, 15A, 100W, hFE=5000, <2,5/21μs	20j				2SD1087
2 SD 1679	Mat	Si-N	SMD, int. Z-Di(C +B, 18V), 18/18V, 0,5/1A, 170MHz	35a	SOT-23			
2 SD 1680	Mat	Si-N	TV-HA, S P, 330/200V, 7/10A, 70W, 30MHz, sat<1V(5A)	16c	(TOP-3F)	2SD1680	16c	(BU 124(A), 2SC2305, 2SC2656, 2SD917) ³
2 SD 1681	Say	Si-N	P, 20/18V, 1,2/2A, 10W, 150MHz, lo-sat<0,3V(0,3A)	14b	TO-126 Iso	2SD1682	14b	(BD 135, BD 165, BD 226, BD 235,++)
			50/270ns	(2SB1141)				
2 SD 1682		Si-N	S P, 60/50V, 2,5/5A, 10W, 140MHz, lo-sat<0,3V(1A)	14b	TO-126 Iso	2SD1682	14b	(BD 177, BD 439, BD 785, 2SD1348,++)
			35/580ns	(2SB1142)				
2 SD 1683	Say	Si-N	S P, 60/50V, 4/6A, 10W, 150MHz, lo-sat<0,5V(2A)	14b	TO-126 Iso	(2SD1348) ³	14h	(BD 189, BD 439, BD 785, 2SD1348,++)
			70/685ns	(2SB1143)				
2 SD 1684	Say	Si-N	P, 120/100V, 1,5/2A, 10W, 120MHz, lo-sat<0,3V(0,5A)	14b	TO-126 Iso	(2SC3117) ³	14h	(BD 233, 2SC2481, 2SC2690(A), 2SC3621) ³
			80/1050ns	(2SB1144)				
2 SD 1685	Say	Si-N	P, 60/20V, 5/8A, 10W, 120MHz, lo-sat<0,5V(3A)	14b	TO-126 Iso			(BDX 35...37, 2SD826)
			30/340ns					
2 SD 1686	Hit	Si-N-Darl+Di	P, 120/120V, 3A, 20W, hFE=5000, 0,5/6,6μs	15c				2SD1785, 2SD2015, (BDW 53D, BDW 63D,++) ³
2 SD 1687	Hit	Si-N-Darl+Di	P, 60/60V, 3A, 20W, hFE=5000	15c		(BD 901) ³	17j	2SD1413, 2SD1790, 2SD1796, 2SD1987, ++
2 SD 1688	Hit	Si-N-Darl+Di	P, 120/120V, 8A, 25W, hFE=7000	15c				2SD1590...91, (BD 651, BDW 73D++) ³
2 SD 1689	Hit	Si-N-Darl+Di	P, 120/120V, 6A, 25W, hFE=5000, 1/2,7μs	15c				2SD1785, 2SD1336, (BD 651, BDW 63D,++) ³
2 SD 1690	Hit	Si-N-Darl+Di	P, 120/120V, 8A, 25W, hFE=5000, 0,4/6,5μs	15c				2SD1590...91, 2SD1792, (BD 651, BDW 73D++) ³
2 SD 1691	Nec	Si-N	60/60V, 5/8A, 20W, <1/3,5μs, sat<0,3V(2A)	(2SB1151)	TO-126			2SD826
2 SD 1692	Nec	Si-N-Darl+Di	150/100V, ±3/5A, 15W, hFE=2k...20k, 0,5/3μs	(2SB1149)	TO-126			2SC4342
2 SD 1693	Nec	Si-N-Darl+Di	Z-Diode(C +B), 60/60±10V, ±3/5A, 15W, hFE=2k...20k	14h	TO-126			
			0,5/3μs	(2SB1150)				
2 SD 1694	Nec	Si-N	P, 60/60V, 3/5A, 250MHz, hi-hFE=800...3200, <2/6μs	14h	TO-126			
			lo-sat<0,4V(2A)					
2 SD 1695	Nec	Si-N-Darl+Di	Z-Di(C +B), 31/31±4V, ±2/3A, hFE=2k...30k, 0,5/4μs	14h	TO-126			
2 SD 1696	Nec	Si-N-Darl+Di	Z-Di(C +B), 31/31±4V, ±4A, hFE=10k, 0,5/4μs	14h	TO-126			
2 SD 1697	Nec	Si-N-Darl+Di	100/80V, ±0,8/1,2A, 1W, hFE=4k...50k, 0,5/3,5μs	9b				
2 SD 1698	Nec	Si-N-Darl+Di	=2SD1697: 0,75W	7c	TO-92			
2 SD 1699	Nec	Si-N-Darl+Di	=2SD1697: SMD	39b	SOT-89			BST 52, 2SD1472, 2SD1511
2 SD 1700	Nec	Si-N-Darl+Di	=2SD1697: int. Z-Diode(C +B), 60/60±10V	9b	(SP-8)			
2 SD 1701	Nec	Si-N-Darl+Di	=2SD1698: int. Z-Diode(C +B), 60/60±10V	7c	TO-92			
2 SD 1702	Nec	Si-N-Darl+Di	=2SD1699: int. Z-Diode(C +B), 60/60±10V	39b	SOT-89			
2 SD 1703	Mat	Si-N	P, 160/160V, 12A, 120W	18j	TO-3P	2SD1047	18j	BD 745F, 2SC3907, 2SD1047
2 SD 1704	Mat	Si-N	L.F.S. P, 170/170V, 15A, 150W	77j	TOP-3L	2SC3281	~16j	2SC3281, 2SD1718
2 SD 1705	Mat	Si-N	P, 130/80V, 10/20A, 70W, 20MHz, 0,5/2,2μs	(2SB1154)	(TOP-3F)	(2SC2837) ³	18j	(BD 245D, 2SC2706, 2SC2837) ³
2 SD 1706	Mat	Si-N	P, 130/80V, 15/25A, 80W, 20MHz, 0,5/2,2μs	(2SB1155)	(TOP-3F)	(2SD1047) ³	18j	(BD 745E, 2SC2987A, 2SD1047) ³
2 SD 1707	Mat	Si-N	P, 130/80V, 20/30A, 100W, 20MHz, 0,5/2,2μs	(2SB1156)	(TOP-3F)			(BD 745E, BD 249D) ³
2 SD 1708	Tos	Si-N-Darl+Di	P, 120/120V, 2A, hFE=6000, <1,2/13,8μs	14b	TO-126 Iso			(2SD1376) ³
2 SD 1709	Say	Si-N+Di	TV-HA, 1500/800V, 5A, 100W, sat<5V(4,5A)	18j	TO-3P	BU 508 D	18j	BU 508D, 2SC3481...82, 2SC3681...82, ++
2 SD 1710	Say	Si-N	TV-HA, 1500/800V, 5A, 50W, sat<5V(4,5A)	18c	TO-3P Iso	2SD1577	16c	BU 508AF, 2SC4142...43, 2SD1655...56, ++
2 SD 1711	Say	Si-N+Di	=2SD1710: int. Damper-Diode	18c	TO-3P Iso	BU 508 DF	16c	BU 508DF, 2SC4293...94, 2SD1555...56, ++
2 SD 1712	Mat	Si-N	P, 100/100V, 5A, 60W, 20MHz	(2SB1157)	(TOP-3F)	(BD 245 C) ³	18j	(BD 245C, 2SD895...896, 2SD1187,++) ³
2 SD 1713	Mat	Si-N	P, 120/120V, 6A, 70W, 20MHz	(2SB1158)	(TOP-3F)			(BD 245D, 2SC3181, 2SD896, 2SD1046,++) ³

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International
2 SD 1714	Mat	Si-N	P, 140/140V, 7A, 80W, 20MHz	{2SB1159 16c	(TOP-3F)		(BD 245D, 2SC2706, 2SC2837, 2SD1046, ++) ³
2 SD 1715	Mat	Si-N	P, 150/150V, 9A, 100W, 20MHz	{2SB1160 16c	(TOP-3F)		(BD 245D, 2SC2837, 2SD1046...47, ++) ³
2 SD 1716	Mat	Si-N	P, 160/160V, 12A, 120W, 20MHz	{2SB1161 16c	(TOP-3F)		(BD 745F, 2SC2987A, 2SD1047, 2SD1703, ++) ³
2 SD 1717	Mat	Si-N	P, 160/160V, 12A, 120W, 20MHz	{2SB1162 77j	(TOP-3L)	2SC3281	2SC3280...3281, 2SD1704, 2SD2029
2 SD 1718	Mat	Si-N	P, 180/180V, 15A, 150W, 20MHz	{2SB1163 77j	(TOP-3L)	2SC3281	2SC3281, 2SD1704
2 SD 1719	Mat	Si-N	100/60V, hi-Ueb=15V, 6/12A, 40W, 30MHz, 0,3/2,1µs hi-hFE=300...2000, lo-sat<0,5V(5A)	30j	(TO-220MF)		-
2 SD 1720	Rhm	Si-N	LF P, 80/60V, 5/10A, 40W, 8MHz	17j	TO-220	BD 243 C	BD 243B, BD 543B, BD 951, 2SD613, ++
2 SD 1721	Nec	Si-N	LF Drv, Out, 60/50V, 2A, 1W	9b		2SD1207	MPS 650...651, 2SC3328, 2SD1207, ++
2 SD 1722	Say	Si-N	S P, 60/50V, 5/8A, 20W, 180MHz, lo-sat<0,4V(3A) 50/520ns	-14h {2SB1165	-SOT-82		2SD826, 2SD1685
2 SD 1723	Say	Si-N	S P, 60/50V, 8/12A, 20W, 180MHz, lo-sat<0,4V(4A) 50/520ns	-14h {2SB1166	-SOT-82		-
2 SD 1724	Say	Si-N	S P, 120/100V, 3/6A, 20W, 180MHz, lo-sat<0,4V(1,5A) 100/950ns	-14h {2SB1167	-SOT-82		-
2 SD 1725	Say	Si-N	S P, 120/100V, 4/8A, 20W, 180MHz, lo-sat<0,4V(2A) 100/950ns	-14h {2SB1168	-SOT-82		-
2 SD 1726	Fjd	Si-N-Darl	S-Reg, 150/100V, 7A, 25W, hFE=1,5k...10k, <2/17µs	17c	SOT-186		2SD1590...91
2 SD 1727	Mat	Si-N+Di	TV-HA, 1500/700V, 1,5/5A, 60W, sat<8V(1A)	18j	TO-3P	(BU 508 D)	BU 706D, 2SC3479, 2SD1290...1291, ++
2 SD 1728	Mat	Si-N+Di	TV-HA, 1500/700V, 2,5/7A, 60W, sat<8V(2A)	18j	TO-3P	(BU 508 D)	BU 706D, 2SC3479, 2SD1290...1291, ++
2 SD 1729	Mat	Si-N+Di	TV-HA, 1500/700V, 3,5/10A, 60W, sat<8V(3A)	18j	TO-3P	BU 508 D	BU 508D, BU 706D, 2SC3480...3482, ++
2 SD 1730	Mat	Si-N+Di	TV-HA, 1500/700V, 5A, 100W, sat<8V(4A)	18j	TO-3P	BU 508 D	BU 508D, 2SC3481...82, 2SC3681, 2SC4291++
2 SD 1731	Mat	Si-N+Di	TV-HA, 1500/700V, 6/18A, 100W, sat<8V(5A)	18j	TO-3P	BU 508 D	BU 508D, 2SC3482, 2SC3681, 2SC4292, ++
2 SD 1732	Mat	Si-N+Di	TV-HA, 1500/700V, 7/20A, 120W, sat<8V(6A)	18j	TO-3P	BU 508 D	BU 508D, 2SC3682...3683
2 SD 1733(F5)	Rhm	Si-N	LF Out P, 120/80V, 1A, 10W, 100MHz sat<0,4V(0,5A)	{2SB1181 30j	TO-251 F5: TO-252	2SC4135	2SC4134, 2SD1074...75, 2SD1283...1284, ++
2 SD 1734	Mat	Si-N	TV-HA, 1500/700V, 1,5/5A, 40W, 2MHz, sat<8V(1A)	17c	SOT-186		2SD1575, (BU 505, BU 506, 2SD1390) ³
2 SD 1735	Mat	Si-N	TV-HA, 1500/700V, 1,5/5A, 60W, 2MHz, sat<8V(1A)	16c	(TOP-3F)	(BU 705) ³ *	2SD1542, (BU 705, BU 706, 2SSC3483) ³
2 SD 1736	Mat	Si-N	TV-HA, 1500/700V, 2,5/7A, 60W, 2MHz, sat<8V(2A)	16c	(TOP-3F)	(BU 705) ³ *	2SD1543, (BU 705, BU 706, 2SSC3483) ³
2 SD 1737	Mat	Si-N	TV-HA, 1500/700V, 3,5/10A, 60W, 2MHz, sat<8V(3A)	16c	(TOP-3F)	S 2000 AF	BU 508AF, 2SD1544, (BU 706, 2SC3484) ³
2 SD 1738	Mat	Si-N	TV-HA, 1500/700V, 5/15A, 100W, 2MHz, sat<8V(4A)	16c	(TOP-3F)	2SD1577	BU 508AF, 2SD1545, (2SSC3485...86) ³
2 SD 1739	Mat	Si-N	TV-HA, 1500/700V, 6/18A, 100W, 2MHz, sat<8V(5A)	16c	(TOP-3F)	2SD1577	BU 508AF, 2SD1546, (2SC3486, 2SD1497) ³
2 SD 1740	Fjd	Si-N-Darl	S-Reg P, 150/100V, 5A, 30W, 22MHz, hFE=700	17c	SOT-186		2SD1590, (BDX 53F, 2SD1128, 2SD1169, ++)
2 SD 1741(A)	Mat	Si-N	=2SD1250(A): 15W	{2SB1171 -30j	(I Type)	(2SD1138) ⁶	2SD1033, 2SD1250(A), 2SD1557
2 SD 1742	Mat	Si-N	=2SD1252(A): 15W	{2SB1172 -30j	(I Type)	(BD 243 C) ⁶	2SC3386, 2SD1221, 2SD1802
2 SD 1743	Mat	Si-N	=2SD1253(A): 15W	{2SB1173 -30j	(I Type)	(BD 243 C) ⁶	2SC3074, 2SC3518, 2SC3592, 2SD1803
2 SD 1744	Mat	Si-N	=2SD1254: 15W	{2SB1174 -30j	(I Type)		-
2 SD 1745	Mat	Si-N	=2SD1255: 15W	{2SB1175 -30j	(I Type)		-
2 SD 1746	Mat	Si-N	=2SD1256: 15W	{2SB1176 -30j	(I Type)		-
2 SD 1747(A)	Mat	Si-N	=2SD1257(A): 15W	{2SB1177 -30j	(I Type)		-
2 SD 1748(A)	Mat	Si-N-Darl+Di	=2SD1260(A): 15W	{2SB1178 -30j	(I Type)		2SD1222
2 SD 1749(A)	Mat	Si-N-Darl+Di	=2SD1261(A): 15W	{2SB1179 -30j	(I Type)		-
2 SD 1750(A)	Mat	Si-N-Darl+Di	=2SD1262(A): 15W	{2SB1180 -30j	(I Type)		-
2 SD 1751	Mat	Si-N	=2SD1480: 15W	{2SB1170 -30j	(I Type)	2SC4135	2SC3474, 2SD1079, 2SD1281...1282
2 SD 1752(A)	Mat	Si-N	=2SD1445(A): 15W	{2SB1148 -30j	(I Type)		(2SD1803...1804) ⁷
2 SD 1753	Mat	Si-N	=2SD1258: 15W	-30j	(I Type)		-
2 SD 1754(A)	Mat	Si-N	=2SD1259(A): 15W	-30j	(I Type)		-
2 SD 1755	Mat	Si-N	=2SD1719: 15W	-30j	(I Type)		-
2 SD 1756	Hit	Si-N-Darl	P, 200/200V, 10/15A, 40W, hFE=1500, 0,9/11,5µs	17j	TO-220	2SD1756	17j
2 SD 1757K	Rhm	Si-N	SMD, 30/15V, 0,5A, 150MHz, lo-sat<0,4V(0,5A)	35a	SOT-23	(BC 817) ¹⁷	2SC3265, 2SC4519
2 SD 1758(F5)	Rhm	Si-N	LF Out, 40/32V, 2/2,5A, 10W, 100MHz sat<0,8V(2A)	{2SB1182 30j	TO-251 F5: TO-252	2SC4135	2SC3076, 2SD1078...79, 2SD1801, ++
2 SD 1759(F5)	Rhm	Si-N-Darl	LF Out, 40/40V, 2/3A, 10W, hFE=1k...200k	{2SB1183 30j	TO-251 F5: TO-252		2SC4338, 2SD1222, 2SD1817, 2SD2410
2 SD 1760(F5)	Rhm	Si-N	LF Out, 60/50V, 3/4,5A, 15W, 90MHz	{2SB1184 30j	TO-251/252 F5: TO-252	2SC3303	2SC3592, 2SC3386, 2SD1221, 2SD1802, ++
2 SD 1761	Rhm	Si-N	LF Out, 80/60V, 3/6A, 30W, 8MHz	{2SB1187 17c	SOT-186	2SD1411	2SC3690, 2SC3746, 2SC3851, 2SD1586, ++
2 SD 1762	Rhm	Si-N	=2SD1760: 25W	{2SB1185 17c	SOT-186	2SC3299	2SC3299, 2SC3690...91, 2SC3746, 2SD1913
2 SD 1763	Rhm	Si-N	LF Out, 120/120V, 1,5/3A, 20W, 80MHz	{2SB1186 17c	SOT-186	2SC4159	2SC3298(A,B), 2SC3364, 2SC3564, 2SC4370
2 SD 1763 A	Si-N		=2SD1763: 160/160V	17c	SOT-186	2SC4159	2SC3298(A,B), 2SC4159, 2SC4370
2 SD 1764	Rhm	Si-N-Darl+Di	int. Z-Di(C-B), 60/60(±10)V, 2/3A, 20W, hFE=1...10k	17c	SOT-186		(BDT 61F, 2SD1413, 2SD1796, 2SD1825, ++)
2 SD 1765	Rhm	Si-N-Darl+Di	P, 100/100V, 2/3A, 20W, hFE=1k...10k	17c	SOT-186	(BD 901) ³	2SD1414, 2SD1788, 2SD1828, 2SD2015, ++
2 SD 1766	Rhm	Si-N	SMD, LF, 40/32V, 2/2,5A, 100MHz	{2SB1188 39b	SOT-89		2SC2873, 2SD1623, 2SD1766, 2SD2532, ++
2 SD 1767	Rhm	Si-N	SMD, LF, 80/80V, 0,7/1A, 120MHz	{2SB1189 39b	SOT-89		BCX56, 2SD1005...07, 2SD1368, 2SD1418...19
2 SD 1768(S)	Rhm	Si-N	LF Drv, Out, 100/80V, 1/2A, 0,3W, 100MHz	41c	(SPT)	BC 639	BC 639, 2SD667, 2SD774, 2SD1616A, ++
2 SD 1769	Sak	Si-N-Darl+Di	P, 120/120V, 6/10A, 50W, 100MHz, hFE=2000, 0,5/7µs	17j	TO-220	2SD1756	(BD 651, BDT 21, BDW 73D, BDX 53D, ++)
2 SD 1770	Mat	Si-N	LF P, 200/150V, 1/2A, 25W, 20MHz	{2SB1190 17j	TO-220	2SD1138	BD 239F, 2SC2238B, 2SD387(A), 2SD1138
2 SD 1770 A	Mat	Si-N	=2SD1770: 200/180V	17j	TO-220	2SD1138	BD 239F, 2SC2238B, 2SD387(A), 2SD1138
2 SD 1771(A)	Mat	Si-N	=2SD1770(A):	{2SB1191 30j	(TO-220MF)	(2SD1138) ⁶	2SD1250, (BD 239F, 2SC2238B), 2SD1138) ⁶
2 SD 1772(A)	Mat	Si-N	=2SD1770(A): Iso	17c	SOT-186	(2SC4159) ⁷	2SC3298B, 2SC4382, 2SD1587, 2SD2337 ³
2 SD 1773	Mat	Si-N-Darl	120/120V, 8/12A, 50W, 20MHz, hFE=1k...20k	{2SB1193 17c	SOT-186		BD 649F, BDT 63CF, 2SD1590...91
2 SD 1774	Mat	Si-N	80/60V, 2/4A, 25W, 40MHz, hi-hFE=500...2500	17j	TO-220	2SD1273	2SC3852, 2SD1157, 2SD1943, 2SC1983
2 SD 1774 A	Mat	Si-N	=2SD1774: 100/80V	17j	TO-220		-
2 SD 1775(A)	Mat	Si-N	=2SD1774(A):	30j	(TO-220MF)		2SC3474, 2SD1754
2 SD 1776(A)	Mat	Si-N	=2SD1774(A): Iso	17c	SOT-186	2SD1273	2SD1273(A), 2SD1944, 2SD2092
2 SD 1777	Hit	Si-N	=2SD1676: SMD	44(C-BE)	SOT-143		-
2 SD 1778(A)	Rhm	Si-N	P, 80/60(A=80/80)V, 4/6A, 40W, 8MHz	17j	TO-220	BD 243 C	BD 243B, BD 537, BD 539B, BD 951, ++
2 SD 1779	Nec	Si-N	60/60, hi-Ueb=15V, 2/3A, 1W, hi-hFE=800...3200	9b			-
2 SD 1780	Nec	Si-N	=2SD1779: integr. Z-Diode(C-B, 60±10V)	9b			-
2 SD 1781K	Rhm	Si-N	SMD, 40/32V, 0,8A, 150MHz, lo-sat<0,4V(0,5A)	35a	SOT-23		(BCW 65...66, BCX 41) ¹⁷
2 SD 1782 K	Rhm	Si-N	SMD, LF Drv, Out, 80/80V, 0,7A, 180MHz	{2SB1198K 35a	SOT-23		BCW 66, BCX 41
2 SD 1783	Rhm	Si-N-Darl+Di	int. Z-Di(C-B), 60/60V, 5/10A, 30W, hFE=2k...30k	17j	TO-220	BD 901	BD 645, BD 897, BDW 23A, BDW 63A, ++
2 SD 1784	Tos	Si-N-Darl	=2SD1140: SMD	39b	SOT-89		2SD1626...1627
2 SD 1785	Sak	Si-N-Darl+Di	P, 120/120V, 6/10A, 30W, 100MHz, hFE>2000	{2SB1258 17c	TO-220 Iso		(2SD1336, 2SD1590) ⁸
2 SD 1786	Rhm	Si-N-Darl	LF Drv, Out, 40/40V, 2A, 0,9W, hFE=20000	7c(9mm)	TO-92L	2SD1153	2SD1153, 2SD1536, 2SD1861, 2SD1929, ++
2 SD 1787	Rhm	Si-N	LF, 50/50V, 0,5A, 0,4W, 250MHz	9c		BC 337	BC 337, BC 635, BC 637, BC 639, ++
2 SD 1788	Shi	Si-N-Darl+Di	S P, Relais Drv, 100/100V, ±4/6A, 25W, 50MHz, hFE=1,5k...30k, <2/17µs	15c	(ITO-220)		-
2 SD 1789	Shi	Si-N-Darl+Di	=2SD1788: 200/200V	15c	(ITO-220)		-
2 SD 1790	Shi	Si-N-Darl+Di	=2SD1788: int. Z-Diode(C-B, 60±10V)	15c	(ITO-220)		-
2 SD 1791	Shi	Si-N-Darl	S P, Relais Drv, 100/100V, 7/10A, 30W, 50MHz, hFE=1,5k...30k, <2/17µs	15c	(ITO-220)	2SD1415	2SD1793, (2SC4062, 2SD1415, 2SD1830, ++) ⁸
2 SD 1792	Shi	Si-N-Darl	=2SD1791: 200/200V	15c	(ITO-220)		2SD1794

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International	
2 SD 1793	Shi	Si-N-Darl	S P, Relais Drv, 100/100V, 10/15A, 50W, 50MHz, hFE=1.5k...30k, <2/17µs	15c	(ITO-220)		(2SC4063) ⁸	
2 SD 1794		Si-N-Darl	=2SD1793: 200V	15c			-	
2 SD 1795	Shi	Si-N-Darl	S P, Relais Drv, 500/400V, 10/15A, 50W, 50MHz, hFE>150, <2/17µs	15c	(ITO-220)		-	
2 SD 1796	Sak	Si-N-Darl+Di	int. Z-Di(C +B, 60V), 60/60V, 4A, 25W, 60MHz, hFE>2000, <5.5µs	17c	TO-220 Iso		2SD1788, (2SD1790, 2SD1987, 2SD1825) ⁸	
2 SD 1797	Fjd	Si-N-Darl	P, 60/60V, 7A, 30W, hFE>800, <1.5/12µs	17c	SOT-186	(BD 901) ³	17j	2SD1416...17, 2SD1791, 2SD1826
2 SD 1798	Hit	Si-N-Darl	P, 300/300V, 0.3A, 15W, hFE=5000	17j	TO-220			2SD1502
2 SD 1799	Say	Si-N-Darl	P, 30/25V, 3/5A, 15W, 120MHz, hFE>4000	30j	TO-251/252			2SC3132, 2SD1222...1223
2 SD 1800	Say	Si-N-Darl	P, 80/50V, 1.5/3A, 10W, 120MHz, hFE>4000	30j	TO-251/252			2SD1817, 2SD1980, 2SD2410
2 SD 1801	Say	Si-N	S P, 60/50V, 2/4A, 15W, 150MHz, lo-sat<0.4V(1A) 60/580ns	30j	TO-251/252	2SC3303	30j	2SC3303, 2SD1815...1816
2 SD 1802	Say	Si-N	S P, 60/50V, 3/6A, 15W, 150MHz, lo-sat<0.5V(2A) 70/685ns	30j	TO-251/252	2SC3303	30j	2SC3303, 2SD1815...1816
2 SD 1803	Say	Si-N	S P, 60/50V, 5/8A, 20W, 180MHz, lo-sat<0.4V(3A) 50/520ns	30j	TO-251/252	2SC3303	30j	2SC3074, 2SC3303, 2SD1805
2 SD 1804	Say	Si-N	S P, 60/50V, 8/12A, 20W, 180MHz, lo-sat<0.4V(4A) 50/520ns	30j	TO-251/252			-
2 SD 1805	Say	Si-N	60/20V, 5/8A, 15W, 120MHz, sat<0.5V(3A), 30/340ns	30j	TO-251/252	2SC3303	30j	2SC3074, 2SC3303, 2SD1803
2 SD 1806	Say	Si-N-Di+R	S P, 40/30V, 2/4A, 15W, 150MHz, Rbe=1kΩ	30j	TO-251/252			-
2 SD 1807	Mat	Si-N	=2SD889: 0.3W	40c		+2SD889		+2SD889
2 SD 1808(A)	Mat	Si-N-Darl	=2SD892(A): 0.3W	40c		+2SD892(A)		+2SD892(A)
2 SD 1809	Rhm	Si-N-Darl	Uni, 60/60V, 1/2A, 0.9W, hFE=15k>2k	7c(9mm)	TO-92L	2SD1153	7c(9mm)	2SD1153, 2SD1660, 2SD1978, 2SD1981, ++
2 SD 1810	Rhm	Si-N	LF Drv, Out, 20/10V, 2A, 0.5W, 80MHz	7c(9mm)	TO-92L	2SD1207	7c	2SC3225, 2SD787...88, 2SD1100, 2SD1207, ++
2 SD 1811	Rhm	Si-N	=2SD1810: SMD	39b	SOT-89			2SC2883, 2SC2982, 2SC3443, 2SC3439, ++
2 SD 1812	Rhm	Si-N	LF Drv, Out, 160/160V, 1.5/3A, 0.9W, 80MHz	7c(9mm)	TO-92L	2SD1812	7c(9mm)	2SC4614, 2SD1665A, 2SD1857A
2 SD 1813	Hit	Si-N	P, 70/50V, 4A, 25W	15c		(BD 243 C) ³	17j	2SC3691, 2SC3746, 2SC3851, 2SD1586, ++
2 SD 1814	Hit	Si-N-Darl+Di	P, 120/120V, 10A, 30W, hFE=5000	15c				2SD1591, (BDT 62C, BDX 33D, 2SD1607, ++) ³
2 SD 1815	Say	Si-N	S P, 120/100V, 3/6A, 20W, 180MHz, lo-sat<0.4V(1.5A) 100/950ns	30j	TO-251/252			-
2 SD 1816	Say	Si-N	S P, 120/100V, 4/8A, 20W, 180MHz, lo-sat<0.4V(2A) 100/950ns	30j	TO-251/252			-
2 SD 1817	Say	Si-N-Darl+Di	P, 80/60V, 3/6A, 15W, hFE>2000	30j	TO-251/252	(BD 679) ⁶	14h	2SD1223, 2SD1520, 2SD1955
2 SD 1818	Nec	Si-N	P, 60/60V, 3/5A, 10W, 120MHz, <0.5/3µs lo-sat<0.25V(1.5A)	14h	TO-126	2SD1348	14h	2SD1348
2 SD 1819	Mat	Si-N	=2SD601:	35a(2mm)	SOT-323			2SC4081, 2SC4128, 2SC4155, 2SC4177
2 SD 1819 A		Si-N	=2SD601A:	35a(2mm)	SOT-323			2SC4117, 2SC4141, 2SC4177
2 SD 1820	Mat	Si-N	=2SD602:	35a(2mm)	SOT-323			2SC4097, 2SC4118, 2SD1949
2 SD 1820 A		Si-N	=2SD602A:	35a(2mm)	SOT-323			-
2 SD 1821	Mat	Si-N	=2SD814:	35a(2mm)	SOT-323			-
2 SD 1821 A		Si-N	=2SD814A:	35a(2mm)	SOT-323			-
2 SD 1822	Mat	Si-N	SMD, LF, 25/20V, 0.5A, 200MHz	35a(2mm)	SOT-323	BC 817	35a	(BC 817...818, BCW 65...66, BCX 19...20, ++)
2 SD 1823	Mat	Si-N	=2SD1030:	35a(2mm)	SOT-323			-
2 SD 1824	Mat	Si-N	=2SD1149:	35a(2mm)	SOT-323			-
2 SD 1825	Say	Si-N-Darl+Di	P, 70/60V, 4/6A, 20W, 20MHz, hFE=5k>2k	17c	TO-220 Iso	2SD1415	17c	2SD1589, 2SD1788, 2SD1933, 2SD2014, ++
2 SD 1826	Say	Si-N-Darl+Di	P, 70/60V, 7/10A, 25W, 20MHz, hFE=5k>2k	17c	TO-220 Iso	2SD1415	17c	2SC4062, 2SD1415...16, 2SD1791
2 SD 1827	Say	Si-N-Darl+Di	P, 70/60V, 10/15A, 30W, 20MHz, hFE=5k>2k	17c	TO-220 Iso	(BDW 93C) ³	17j	2SC4063, 2SD1793, (BDT 63A, BDW 93B, ++) ³
2 SD 1828	Say	Si-N-Darl+Di	P, 110/100V, 3/5A, 20W, 20MHz, hFE=4k>1.5k	17c	TO-220 Iso	(BD 901) ³	17j	2SD1785, 2SD2015, (BDW 53D, BDW 63D, ++) ³
2 SD 1829	Say	Si-N-Darl+Di	P, 110/100V, 5/8A, 25W, 20MHz, hFE=4k>1.5k	17c	TO-220 Iso	(BD 901) ³	17j	2SD1785, 2SD2025, (BD 651, BDW 63D, ++) ³
2 SD 1830	Say	Si-N-Darl+Di	P, 110/100V, 8/12A, 30W, 20MHz, hFE=4k>1.5k	17c	TO-220 Iso	(BD 901) ³	17j	2SD1591, 2SD2025, (BD 651, BDW 73D, ++) ³
2 SD 1831	Mat	Si-N	P, 100/60V, hi-Ueb=15W, 12/15A, 60W, 30MHz hi-hFE=300...2000, 300/2100ns	16c	(TOP-3F)			-
2 SD 1832	Rhm	Si-N	P, 80/60V, 5/10A, 30W, 8MHz	17c	SOT-186	2SD1411	17c	2SC3691, 2SC3746, 2SD1588, 2SD1940
2 SD 1833	Rhm	Si-N	P, 100/80V, 7/10A, 30W, 5MHz	17c	SOT-186	2SD1411	17c	2SC3692, 2SD1411, 2SD1588
2 SD 1834	Rhm	Si-N-Darl	SMD, 60/60V, 1/2A, hFE=15k>2k	39b	SOT-89			BST 50...52, 2SD1470, 2SD1511
2 SD 1835	Say	Si-N	S, 60/50V, 2/3A, 0.75W, 150MHz, lo-sat<0.4V(1A) 60/580ns	7c	TO-92			2SC3328
2 SD 1836	Say	Si-N-Darl+Di	int. Z-Di(C +B, 60V), 60/60V, 2A, 20W, B=4k>1k	17c	TO-220 Iso			2SC3986, 2SD1413, 2SC1983, 2SD2051
2 SD 1837	Say	Si-N-Darl+Di	int. Z-Di(C +B, 60V), 50/50V, 3/5A, 20W, 20MHz, hFE=4k>1k, 0.5/5.5µs	17c	TO-220 Iso			2SC3987, 2SD1413, 2SD1825, 2SD1987
2 SD 1838	Say	Si-N-Darl+Di	int. Z-Di(C +B, 60V), 50/50V, 5/8A, 25W, 20MHz, hFE=4k>1k, 0.6/5.5µs	17c	TO-220 Iso	(BD 901) ³	17j	2SD1790, 2SD1796, 2SD1825, 2SD1987
2 SD 1839	Mat	Si-N-Darl+Di	S P, 365/365V, 5A, 80W, hFE=2000	16c	(TOP-3F)			-
2 SD 1840	Say	Si-N	P, 110/100V, 15A, 100W, lo-sat<0.8V(6A)	18j	TO-3P			-
2 SD 1841	Say	Si-N	P, 110/100V, 25A, 120W, lo-sat<0.8V(10A)	18j	TO-3P			-
2 SD 1842	Say	Si-N	P, 110/100V, 40A, 150W, lo-sat<0.8V(16A)	18j	TO-3P			-
2 SD 1843	Nec	Si-N-Darl+Di	Uni, int. Z-Di(C +B), 60/60±10V, ±1/2A, 1W hFE=2k...30k, 0.5/2µs	9b	(SP-8)			-
2 SD 1843 A		Si-N-Darl+Di	=2SD1843: 80/80V	9b	(SP-8)			-
2 SD 1844	Mat	Si-N-Di	TV-HA, 1500/700V, 1.5/5A, 60W, 2MHz, sat<8V(1A)	16c	(TOP-3F)	S 2055 AF	18c	2SD1553, BU 706DF(2SD1728, 2SD1290...91) ³
2 SD 1845	Mat	Si-N-Di	TV-HA, 1500/700V, 2.5/7A, 60W, 2MHz, sat<8V(2A)	16c	(TOP-3F)	S 2055 AF	18c	2SD1553, BU 706DF(2SC3479, 2SD1290...91) ³
2 SD 1846	Mat	Si-N-Di	TV-HA, 1500/700V, 3.5/10A, 60W, 2MHz, sat<8V(3A)	16c	(TOP-3F)	S 2055 AF	18c	2SD1554, 2SD1650, BU 706DF(2SD1290...91) ³
2 SD 1847	Mat	Si-N-Di	TV-HA, 1500/700V, 5/15A, 100W, 2MHz, sat<8V(4A)	16c	(TOP-3F)	BU 508 DF	16c	BU 508DF, 2SC4122, 2SC4291, 2SD1555...56+
2 SD 1848	Mat	Si-N-Di	TV-HA, 1500/700V, 6/18A, 100W, 2MHz, sat<8V(5A)	16c	(TOP-3F)	BU 508 DF	16c	BU 508DF, 2SC4122, 2SC4292, 2SD1556...57+
2 SD 1849	Mat	Si-N-Di	TV-HA, 1500/700V, 7/20A, 120W, 2MHz, sat<8V(6A)	16c	(TOP-3F)	BU 508 DF	16c	BU 508DF, 2SC4123, (2SC3482...83, ++) ³
2 SD 1850	Mat	Si-N	TV-HA, 1500/700V, 7/20A, 120W, 2MHz, sat<8V(6A)	16c	(TOP-3F)	2SD1577	16c	BU 508AF, 2SC3884A, 2SC3895, 2SD1547
2 SD 1851	Say	Si-N-Darl	=2SD1852: SMD	35a	SOT-23			BCV 47
2 SD 1852	Say	Si-N-Darl	Uni, 80/50V, 0.2/0.4A, 0.3W, hFE>5000	41c	(SPA)	(BC 879) ¹³	7c	MPS-A28...29
2 SD 1853	Say	Si-N-Darl+Di	Uni, 80/60V, 1.5/3A, 0.7W, hFE>2000	7c	TO-92	2SD1153	7c(9mm)	2SD1153, 2SD1660
2 SD 1854	Say	Si-N-Darl+Di	=2SD1853: 1W	7c(9mm)	TO-92L	2SD1153	7c(9mm)	2SD1153, 2SD1660, 2SD1978, 2SD1981
2 SD 1855(A)	Rhm	Si-N	LF P, 80/60(A=80/80)V, 4/6A, 30W, 8MHz	17c	SOT-186	2SD1411	17c	2SC3851, 2SC3691, 2SD1408, 2SD2000, ++
2 SD 1856	Rhm	Si-N-Darl+Di	int. Z-Di(C +B), 60/60V, 5/10A, 25W, B=2k...30k	17c	SOT-186			(2SD1417, 2SD1589, 2SD1595, 2SD1826, ++)
2 SD 1857	Rhm	Si-N	=2SD1665(M): Pins = 14mm	9c		+2SD1665		+2SD1857
2 SD 1858	Rhm	Si-N	=2SD1225(M): Pins = 14mm	9c		+2SD1225		+2SD1225
2 SD 1859	Rhm	Si-N	=2SD1226(M): Pins = 14mm	9c		+2SD1226		+2SD1226
2 SD 1860	Rhm	Si-N	=2SD1228(M): Pins = 14mm	9c		+2SD1228		+2SD1228
2 SD 1861	Rhm	Si-N-Darl	=2SD1536(M): Pins = 14mm	9c				+2SD1536
2 SD 1862	Rhm	Si-N	=2SD1227(M): Pins = 14mm	9c		+2SD1227		+2SD1227
2 SD 1863	Rhm	Si-N	=2SD1293(M): Pins = 14mm	9c		+2SD1293		+2SD1293
2 SD 1864	Rhm	Si-N	=2SD1507(M): Pins = 14mm	9c		+2SD1507		+2SD1507
2 SD 1865	Rhm	Si-N	=2SD1469M: Pins = 14mm	9c		+2SD1469M		+2SD1469M
2 SD 1866(M)	Rhm	Si-N-Darl+Di	=2SD1661(M): Pins = 14mm	9c		+2SD1661		+2SD1661

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International
2 SD 1867(M)	Rhm	Si-N-Darl+Di	=2SD1660(M); Pins = 14mm	9c			-2SD1660
2 SD 1868	Hit	Si-N	LF Vid. 160/160V, 0.1A, 0.9W, 140MHz	7c(9mm)	TO-92L (BF 759) ⁶	13h	BF 391...393, 2SC3248, 2SC3467, ++
2 SD 1869	Hit	Si-N	=2SD1868: 200/200V	7c(9mm)	TO-92L (BF 759) ⁶	13h	BF 391...393, 2SC3467...3469, ++
2 SD 1870	Hit	Si-N	SMD, 30/25V, 1/2A, hi-hFE=1k...3k	39b	SOT-89		2SC3727, 2SD1950
2 SD 1871	Mit	Si-N	P, 40/20V, 2A, 10W	30j	TO-251/252 2SC4135	30j	2SD1078...79, 2SD1801...02, (BD 515,++) ⁴
2 SD 1872	Mit	Si-N	P, 60/40V, 1.5A, 10W	30j	TO-251/252 2SC4135	30j	2SD1079, 2SD1221, 2SD1801...02, (BD 517,+) ⁶
2 SD 1873	Mit	Si-N	P, 110/100V, 0.8A, 10W	30j	TO-251/252 2SC4135	30j	2SD1074...75, 2SD1283...84, (BD 529) ⁶
2 SD 1874	Mit	Si-N	P, 130/120V, 0.8A, 10W	30j	TO-251/252		2SC2983, 2SC4027, 2SD1080...82, 2SD1220, (BD 677, BD 777, 2N6038...39, 2SD1376,++) ³
2 SD 1875	Rhm	Si-N-Darl+Di	P, 50/50V, 1.5A, 10W, hFE=10000	14b	TO-126 Iso (BD 679) ³	14h	(BD 677, BD 777, 2N6038...39, 2SD1376,++) ³
2 SD 1876	Say	Si-N+Di	TV-HA, 1500/800V, 3/12A, 50W, sat<5V(2A)	18c	TO-3P Iso S 2055 AF	18c	BU 706DF, 2SD1553...54, 2SD1650, 2SD2089
2 SD 1877	Say	Si-N+Di	TV-HA, 1500/800V, 4/12A, 50W, sat<5V(2.5A)	18c	TO-3P Iso S 2055 AF	18c	BU 706DF, 2SD1554...55, 2SD1651, 2SD2089
2 SD 1878	Say	Si-N+Di	TV-HA, 1500/800V, 5/20A, 60W, sat<5V(4A)	18c	TO-3P Iso S 2055 AF	18c	BU 508DF, 2SD1555, 2SD2095, 2SD2125
2 SD 1879	Say	Si-N+Di	TV-HA, 1500/800V, 6/20A, 60W, sat<5V(5A)	18c	TO-5P Iso S 2055 AF	18c	BU 508DF, 2SC4294, 2SD1556, 2SD2125
2 SD 1880	Say	Si-N+Di	TV-HA, 1500/800V, 8/30A, 70W, sat<5V(6A)	18c	TO-3P Iso S 2055 AF	18c	BU 508DF, 2SC3893A, 2SC4124, 2SC4531
2 SD 1881	Say	Si-N+Di	TV-HA, 1500/800V, 10/30A, 70W, sat<5V(8A)	18c	TO-3P Iso		BU 2520AF, 2SC4125, 2SC4531
2 SD 1882	Say	Si-N	=2SD1876: ohne/without Damper-Diode	18c	TO-3P Iso S 2000 AF	18c	BU 706F, 2SD1553, 2SD1653, (2SC3483...84,++) ³
2 SD 1883	Say	Si-N	=2SD1877: ohne/without Damper-Diode	18c	TO-3P Iso S 2000 AF	18c	BU 706F, 2SD1544, 2SD1654, (2SC3484...86,++) ³
2 SD 1884	Say	Si-N	=2SD1878: ohne/without Damper-Diode	18c	TO-3P Iso BU 508 AF	16c	BU 508AF, 2SC4142, 2SD1545, 2SD1655, ++
2 SD 1885	Say	Si-N	=2SD1879: ohne/without Damper-Diode	18c	TO-3P Iso BU 508 AF	16c	BU 508AF, 2SC4143, 2SD1546, 2SD1656 ³
2 SD 1886	Say	Si-N	=2SD1880: ohne/without Damper-Diode	18c	TO-3P Iso 2SD1577	16c	BU 508AF, 2SC3896, (BU 908, 2SC3687,++) ³
2 SD 1887	Say	Si-N	=2SD1887: ohne/without Damper-Diode	18c	TO-3P Iso 2SC4924	18c	BU 2520AF, 2SC3897, (2SC3688) ³
2 SD 1888	Rhm	Si-N-Darl+Di	P, 120/120V, 6/10A, 40W, 40MHz, hFE=2k...20k	17j	TO-220 2SD1756	17j	2SC2269, (BD 651, BDT 21, BDW 63D,++) ¹³
2 SD 1889	Rhm	Si-N-Darl+Di	=2SD1888: Iso, 30W	17c	SOT-186		2SD1785, 2SD2025, 2SD1590, (BD649F) ¹³
2 SD 1890	Mat	Si-N-Darl	P, 100/80V, 3/6A, 35W, 20MHz, hFE=5k...30k	{2SB1250 17c	SOT-186	-	-
2 SD 1891	Mat	Si-N-Darl	P, 110/90V, 4/7A, 40W, 20MHz, hFE=5k...30k	{2SB1251 17c	SOT-186	-	-
2 SD 1892	Mat	Si-N-Darl	P, 120/110V, 5/8A, 45W, 20MHz, hFE=5k...30k	{2SB1252 17c	SOT-186	-	-
2 SD 1893	Mat	Si-N-Darl	P, 130/110V, 6/10A, 50W, 20MHz, hFE=5k...30k	{2SB1253 16c	(TOP-3F)	-	-
2 SD 1894	Mat	Si-N-Darl	P, 160/140V, 7/12A, 70W, 20MHz, hFE=5k...30k	{2SB1254 16c	(TOP-3F)	-	-
2 SD 1895	Mat	Si-N-Darl	P, 160/140V, 8/15A, 100W, 20MHz, hFE=5...30k	{2SB1255 16c	(TOP-3F)	-	-
2 SD 1896	Rhm	Si-N	P, 100/100V, 5/10A, 40W, 8MHz	17j	TO-220 BD 243 C	17j	BD 243C, BD 539C, BD 543C, BD 953, ++
2 SD 1897	Rhm	Si-N	=2SD1896: Iso, 30W	17c	SOT-186 2SD1411	17c	BD 953F, 2SC3691, 2SD1407, 2SD1940, ++
2 SD 1898	Rhm	Si-N	SMD, Uni, 100/80V, 1A, 100MHz	39b	SOT-89		BCX 56, 2SD1005, 2SD1386, 2SD1418...19
2 SD 1899(Z)	Nec	Si-N	P, 60/60V, 3/5A, 10W, 120MHz, <0.5/2.5μs, Z: TO-252	30j	TO-251/252 2SC3303	30j	2SC3386, 2SD1221, 2SD1802, 2SD1815...16++
2 SD 1900	Hit	Si-N-Darl	P, 60/60V, 4A, 25W, hFE=5000	15c	(BD 901) ³	17j	2SD1790, 2SD1796, 2SD1825, 2SD1987, ++
2 SD 1901	Hit	Si-N-Darl	P, 60/60V, 8A, 25W, hFE=5000	15c	(BD 901) ³	17j	2SD1416...17, 2SD1793, 2SD1826...27, ++
2 SD 1902	Say	Si-N	LF P, 60/60V, 3/8A, 30W, 40MHz	{2SB1266 30c	(TO-220MF) (BD 243 C) ⁶	17j	2SD1251...52, (BD 241A, BD 535, BD 539A,++) ⁶
2 SD 1903	Say	Si-N	S P, 60/30V, 8/15A, 30W, 120MHz, lo-sat<0.4V(3A)	30c	(TO-220MF)		-
2 SD 1904	Say	Si-N	100/530ns S P, 60/50V, 5/9A, 30W, 30MHz, lo-sat<0.4V(3A)	{2SB1267 30c	(TO-220MF)		2SD1906, 2SD2198, 2SD2200
2 SD 1905	Say	Si-N	100/1600ns S P, 60/50V, 7/12A, 40W, 10MHz, lo-sat<0.4V(4A)	{2SB1268 30c	(TO-220MF)		2SD1907, 2SD2199, 2SD2201
2 SD 1906	Say	Si-N	100/1200ns S P, 90/80V, 5/9A, 30W, 20MHz, lo-sat<0.4V(3A)	{2SB1269 30c	(TO-220MF)		2SD1907, 2SD2200...01
2 SD 1907	Say	Si-N	100/1600ns S P, 90/80V, 7/12A, 40W, 20MHz, lo-sat<0.4V(4A)	{2SB1270 30c	(TO-220MF)		2SD2201
2 SD 1908	Say	Si-N	100/2000ns TV-HA, 330/150V, 7A, 50W, 40MHz, sat<1V(5A)	30c	(TO-220MF) (BU 406) ⁶	17j	(BU 406...408, 2SC3173, 2SD884...885,++) ⁶
2 SD 1909	Mat	Si-N-Darl	P, 500/300V, 6/10A, 45W, 20MHz, hFE=500, 1/15μs	17c	SOT-186 2SD1409	17c	2SD1409
2 SD 1910	Hit	Si-N+Di	TV-HA, 1500/600V, 3A, 40W, sat<5V(2.5A)	=18c	(TO-3PFM) S 2055 AF	18c	2SD1544, 2SD1653, BU 706DF, (2SC3479,++) ³
2 SD 1910 Fi	Tho	Si-N+Di	=2SD1910.	18c	TO-3P Iso S 2055 AF	18c	2SD1544, 2SD1653, BU 706DF, (2SC3479,++) ³
2 SD 1911	Hit	Si-N+Di	TV-HA, 1500/600V, 5A, 50W, sat<5V(4.5A)	=18c	(TO-3PFM) BU 508 DF	16c	BU 508DF, 2SC4293, 2SC4122, 2SD1651, ++
2 SD 1912	Say	Si-N	LF P, 60/60V, 3/8A, 30W, 100MHz	{2SB1273 17j	TO-220 (BD 243 C) ⁸	17j	2SC3252, (BD 241A, BD 535, BD 539A,++) ⁸
2 SD 1913	Say	Si-N	=2SD1912: Iso, 20W	{2SB1274 17c	TO-220 Iso 2SC3299	17c	2SC3299, 2SC3691, 2SC3746
2 SD 1914	Say	Si-N-Darl+Di	P Drv, 100/80V, 2/4A, 10W, hFE=2k...30k	=14h	=SOT-82		(2SD1376, 2SD1953)
2 SD 1915	Mat	Si-N	50/20V, hi-Ueb=25V, 0.3/0.5A, 0.3W, 80MHz, hi-hFE=500...2500	40c	(2SC3225)	7c(9mm)	2SC3615, (2SC3247, 2SD1582)
2 SD 1916	Tos	Si-N-Darl+Di	Uni, 50/50V, 2A, 1W, hFE=5000, <1,2/13,8μs	9c	2SD1153	7c(9mm)	2SD1153, 2SD1809, 2SD1866, 2SD1853, ++
2 SD 1917	Mat	Si-N-Darl	int. Z-Di(C-B, 60V), 60/60V, 1A, B=20000	14b	TO-126		-
2 SD 1918(F5)	Rhm	Si-N	P, 160/160V, 1.5/3A, 10W, 80MHz, F5: TO-252	{2SB1275 30j	TO-251/252		2SC2983, 2SC4027, 2SD1080...82, 2SD2122
2 SD 1919	Rhm	Si-N	=2SD1055: Pins = 14mm	{2SB1277 9c	-2SD1055		-2SD1055
2 SD 1920	Rhm	Si-N	=2SD1469: Pins = 14mm	9c	-2SD1469		-2SD1469
2 SD 1921	Rhm	Si-N	=2SD1787: Pins = 14mm	9c	-2SD1787		-2SD1787
2 SD 1922	Hit	Si-N+Di	int. Z-Di(C-B), 25/25V, 0.8/1.5A, 0.9W hFE=250...1200, lo-sat<0.3V(0.8A)	7c(9mm)	TO-92L		-
2 SD 1923	Hit	Si-N-Darl+Di	P, 80/80V, 4A, 25W, hFE=5000	15c	2SD1415	17c	2SD1589, 2SD1928, 2SD1933, 2SD2014
2 SD 1924	Hit	Si-N-Darl+Di	P, 80/80V, 8A, 25W, hFE=5000	15c	2SD1415	17c	2SC4062, 2SD1415...16, 2SD1793
2 SD 1925	Hit	Si-N-Darl+Di	P, 120/120V, 3A, 25W, hFE=5000	15c			2SD1785, 2SD2015, (BDW 53D, BDW 63D,++) ³
2 SD 1926	Hit	Si-N-Darl	P, 200/200V, 10A, 30W, hFE=5000	15c			2SD1794, (2SD1756) ³
2 SD 1927	Hit	Si-N-Darl+Di	P, 120/120V, 6A, 25W, hFE=5000	15c			2SD1590, (BD 651, BDW 73D, BDW 53D,++) ³
2 SD 1928	Nec	Si-N-Darl+Di	S P, 100/100V, ±8/16A, 25W, hFE=2k...20k, 0.4/3μs	17c	SOT-186 2SD1415	17c	BD 647F, 2SC4062, 2SD1415, 2SD1791
2 SD 1929	Rhm	Si-N-Darl+Di	int. Z-Di(C-B), 60/60±10V, 2A, 1.2W, hFE=1k...10k	7c(9mm)	TO-92L 2SD1153	7c(9mm)	2SD1854, 2SD1931, 2SD1981
2 SD 1930	Rhm	Si-N-Darl	Uni, 100/100V, 2A, 1.2W, hFE=1k...10k	7c(9mm)	TO-92L		2SD1978, 2SD1981, 2SD2206
2 SD 1931	Rhm	Si-N-Darl+Di	int. Z-Di(C-B), 60/60±10V, 1.5/3A, 0.9W, 80MHz hFE=1k...30k	7c(9mm)	TO-92L		-
2 SD 1932	Rhm	Si-N-Darl+Di	P, 80/80V, 4/6A, 35W, 40MHz, hFE=1k...10k	{2SB1341 17j	TO-220 BD 901	17j	BD 717, BDW 32B, BDW 53B, 2SD1147, ++
2 SD 1933	Rhm	Si-N-Darl+Di	=2SD1932: Iso, 30W	{2SB1342 17c	SOT-186 2SD1415	17c	BD 647F, 2SD1589, 2SD1788, 2SD1928, ++
2 SD 1934	Mat	Si-N	=2SD965: 1W	7c(9mm)	TO-92L 2SD2179	9c	2SD966, 2SD1244, 2SD2249, 2SD1961
2 SD 1935	Say	Si-N	=2SD1936: SMD	{2SB1295 35a	SOT-23		2SC3265
2 SD 1936	Say	Si-N	LF, 15/15V, 0.8/3A, 0.3W, 200MHz, sat<0.2V(0.4A)	41c	(SPA) 2SD1207	7c	2SC3225, 2SD1207, 2SD1835
2 SD 1937	Mat	Si-N	=2SD1211:	{2SB1297 7c(9mm)	TO-92L 2SD1812	7c(9mm)	2SC2235, 2SC3228, 2SD667(A), 2SD1616A, ++
2 SD 1938	Mat	Si-N	=2SD1915: SMD	35a	SOT-23		-
2 SD 1939	Nec	Si-N-Darl+Di	S, 150/60V, ±1.5/3A, 0.75W, hFE=2k...30k, 0.5/2μs	7c	TO-92		2SD1579, 2SD1659
2 SD 1940	Say	Si-N	P, 100/85V, 6/10A, 25W, 15MHz, 0.28/4,1μs	17c	TO-220 Iso 2SD1411	17c	2SC3692, 2SD1411, 2SD1588
2 SD 1941	Hit	Si-N	TV-HA, 1500/650V, 6A, 50W, sat<5V(5A)	=18c	(TO-3PFM) BU 508 AF	16c	BU508AF, 2SC4143, 2SD1545...47, 2SD1652, +
2 SD 1942	Rhm	Si-N	LF, 40/32V, 2A, 1.2W	7c(9mm)	TO-92L 2SD1207	7c(9mm)	2SC3328, 2SC4145, 2SD1146, 2SD1207, ++
2 SD 1943	Rhm	Si-N	80/60V, 3/6A, 40W, 50MHz, hi-hFE=400...2000	17j	TO-220 (2SD1273)	17c	2SD2085, (2SD1157, 2SC1983) ⁸
2 SD 1944	Rhm	Si-N	=2SD1943: Iso, 30W	17c	SOT-186 2SD1273	17c	2SD1273, 2SD2092, 2SD2156, 2SD2375, ++
2 SD 1945	Hit	Si-N	P, 1000/1000V, 0.5A, 20W	30j	TO-251/252		(BUX 87) ⁴
2 SD 1946	Hit	Si-N	SMD, 15/10V, 1/2A, hi-hFE=400...2000	39b	SOT-89		2SC4390, 2SD1870
2 SD 1947	Tos	Si-N+Di	100/100V, 10/15A, 70MHz, hi-hFE=500...1500, 0.5/7μs, lo-sat<0.3V(5A)	17c	SOT-186		2SC4024
2 SD 1948	Tos	Si-N+Di	int. Z-Di(C-B, 60V), 60/60V, 5/8A, 110MHz, hi-hFE=500...1500, 0.1/2.5μs, lo-sat<0.3V(3A)	17c	SOT-186		2SD2075...2076

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International	
2 SD 1949	Rhm	Si-N	=2SD1484K:	35a(2mm)	SOT-323	-	-	
2 SD 1950	Nec	Si-N	SMD, 30/25V, hi-Ueb=15V, 2/3A, 350MHz hi-hFE=800...3200, sat<0.3V(1A)	39b	SOT-89	-	-	
2 SD 1951	Nec	Si-N	20/16V, 3/5A, 0.75V, 140MHz, sat<0.5V(3A)	(2SB1300) 7c	TO-92	2SD1347	7c(9mm)	2SC4487, 2SD879, 2SD1617, 2SD1347
2 SD 1952	Nec	Si-N	=2SD1951: SMD	39b	SOT-89	-	-	2SD1119, 2SD1620, 2SD1624
2 SD 1953	Say	Si-N-Darl+Di	P, 120/120V, 1.5/3A, 10W, hFE=2k...30k	14h	TO-126	2SD986	14h	2SD1376
2 SD 1955	Say	Si-N-Darl+Di	P, 110/100V, 3A, 10W, 20MHz, hFE=4k>1.5k	30j	TO-251/252	-	-	2SC4339
2 SD 1956	Rhm	Si-N+Di	P, 120/120V, 7/12A, 40W, 40MHz, hFE=100...500	17j	TO-220	-	-	-
2 SD 1957	Rhm	Si-N+Di	=2SD1956: Iso, 30W	17c	SOT-186	-	-	-
2 SD 1958	Say	Si-N	S P, TV-HA, 200/60V, 4.5/10A, 30W, 10MHz, sat<1V(4A)	17c	TO-220 Iso	-	-	(2SC4153)
2 SD 1959	Say	Si-N	S P, TV-HA, 1400/650V, 10A, 50W, sat<5V(8A)	18c	TO-3P Iso	2SC4924	18c	BU 2520AF, 2SD1548
2 SD 1960	Rhm	Si-N	LF, 30/15V, 5A, 0.75V, 170MHz, lo-sat<0.1V(4A)	7c	TO-92	(2SD2179) ¹⁷	9c	2SC4482, 2SD1145, 2SD2243
2 SD 1961	Rhm	Si-N	LF, Strobo Flash, 50/20V, 5/10A, 1.2W, 150MHz	7c(9mm)	TO-92L	2SD2179	9c	2SC3671, 2SC4482, 2SD1145, 2SD2097, ++
2 SD 1962(M)	Rhm	Si-N	=2SD1961: 0.3W, M=1W(ATR)	9c	(FTR, ATR)	2SD2179	9c	2SC3671, 2SC4482, 2SD1145, 2SD2097, ++
2 SD 1963	Rhm	Si-N	SMD, Blitz/Strobo Flash, 50/20V, 3/5A, 150MHz	39b	SOT-89	-	-	2SC4521, 2SD1624
2 SD 1964	Mat	Si-N	P, 130/80V, 15/25A, 50W, 20MHz, 0.5/2.2µs	17c	SOT-186	-	-	2SC3699
2 SD 1965	Rhm	Si-N	P, 120/80V, 1A, 5W	=14b	SOT-82	-	-	-
2 SD 1966	Rhm	Si-N	P, 80/80V, 0.7A, 5W	=14b	SOT-82	-	-	-
2 SD 1967	Rhm	Si-N-Darl	P, 40/40V, 2A, 5W, hFE=20000	14h	SOT-82	-	-	-
2 SD 1968	Rhm	Si-N	P, 40/32V, 2A, 5W	14b	TO-126 Iso	2SC3422	14b	2SC3422, 2SD1189, 2SD1682, 2SD1818
2 SD 1969	Rhm	Si-N	50/50V, 2A, 0.5W	62b	-	-	-	-
2 SD 1970	Hit	Si-N-Darl+Di	int. Z-Di(C-B), 24/24V, 2/4A, 10W, hFE=7k...30k	14h	TO-126	-	-	-
2 SD 1971	Mat	Si-N	S P, 400/400V, 0.5/1A, 5W, 55MHz, 0.4/4.3µs	14h	TO-126	-	-	2SC2899 ³
2 SD 1972	Mit	Si-N	60/60V, 3/5A, 15W, 100MHz, lo-sat<0.5V(2A) hi-hFE=250...800	(2SB1314) 17c	TO-220 Iso	2SD1273	17c	2SD2092, 2SD2127, 2SD1948
2 SD 1973	Mat	Si-N	80/60V, 2A, hi-hFE=1000	14b	TO-126	-	-	-
2 SD 1974	Hit	Si-N	=2SD1922: SMD	39b	SOT-89	-	-	-
2 SD 1975	Mat	Si-N	P, 180/180V, 15/25A, 150W, 20MHz	(2SB1317) 77j	TOP-3L	2SC3281	=16j	2SC3281, 2SD1704, 2SD1718
2 SD 1976	Hit	Si-N-Darl+Di	int. Z-Diode(C-B), 300/300V, 6/10A, 40W, hFE>500	17j	TO-220	-	-	2SD991, 2SD1071, 2SD1088, 2SD1113, ++
2 SD 1977	Nec	Si-N	P, 120/120V, 8/12A, 65W, 60MHz	(2SB1315) 18c	TO-3P Iso	(2SC2837) ³	18j	2SC4386, 2SC4689, 2SC5100, (BD 245C,++) ³
2 SD 1978	Hit	Si-N-Darl+Di	LF, 120/120V, 1.5/3A, 0.9W, hFE=2k...30k	7c(9mm)	TO-92L	-	-	2SD1579, 2SD1659, 2SD2067, 2SD2213
2 SD 1979	Mat	Si-N	=2SD1915: SMD	35a(2mm)	SOT-323	-	-	(2SC4366)
2 SD 1980	Rhm	Si-N-Darl+Di	P, 100/100V, 2A, 10W, hFE=1k...10k	30j	TO-251/252	(BD 683) ⁶	14h	2SD1223, 2SD1520, 2SD2410
2 SD 1981	Say	Si-N-Darl+Di	LF, 100/80V, 2/4A, 1W, hFE=2k...30k	7c(9mm)	TO-92L	-	-	2SC1879, 2SD1660, 2SD1867, 2SD1978
2 SD 1982	Hit	Si-N-Darl+Di	S P, 300/300V, 6A, 80W, hFE=2000	18j	TO-3P	-	-	2SD1461
2 SD 1983	Rhm	Si-N-Darl+Di	int. Z-Di(C-B, 60V), 60/60V, 1.5A, 20W, hFE=1k...30k	17c	SOT-186	-	-	2SD2051
2 SD 1984	Hit	Si-N	LF, 30/25V, 1/2A, 0.9W, hi-hFE=1k...3k	7c(9mm)	TO-92L	2SC3225	7c(9mm)	2SC3070, 2SC3225, 2SC3726
2 SD 1985(A)	Mat	Si-N	=2SD1252(A): 25W	(2SB1393) 17c	SOT-186	(BD 243 C) ³	17j	BD 935F, 2SC3851...52, 2SD1585, 2SD1913
2 SD 1986	Rhm	Si-N-Darl	P, 60/60V, 4/6A, 35W, 40MHz, hFE=1k...10k	17j	TO-220	BD 901	17j	BD 715, BDW 23A, BDW 53A, 2SD1147, ++
2 SD 1987	Rhm	Si-N-Darl	=2SD1986: Iso, 30W	17c	SOT-186	2SD1415	17c	2SD1595, 2SD1790, 2SD1796, 2SD1933, ++
2 SD 1988	Rhm	Si-N-Darl+Di	int. Z-Di(C-B, 45V), 45/45V, 2A, 25W, hFE=1k...10k	17j	TO-220	BD 901	17j	BD 713, BDW 23, BDW 53, BDW 63, ++
2 SD 1989	Rhm	Si-N-Darl+Di	=2SD1988: Iso, 20W	17c	SOT-186	(BD 901)	17j	BDT 61F, 2SD1790, 2SD1796, 2SD1987, ++
2 SD 1990	Mat	Si-N	P, 80/60V, 4/8A, 35W, 80MHz, 0.3/1.2µs	17j	TO-220	(BD 243 C) ⁸	17j	BDV 10...12, 2SC3253, 2SC3258
2 SD 1991	Mat	Si-N	=2SD636: Pins = 14mm	(2SB1320) 9c	-	-	-	-2SD636
2 SD 1991 A	Mat	Si-N	=2SD637: Pins = 14mm	9c	-	-	-	-2SD637
2 SD 1992	Rhm	Si-N	=2SD938: Pins = 14mm	(2SB1321) 9c	-	-	-	-2SD638
2 SD 1992 A	Rhm	Si-N	=2SD939: Pins = 14mm	9c	-	-	-	-2SD639
2 SD 1993	Mat	Si-N	=2SD661A: Pins = 14mm	9c	-	-	-	-2SD661A
2 SD 1994(A)	Mat	Si-N	=2SD973(A): Pins = 14mm	(2SB1322) 9c	-	-	-	-2SD973(A)
2 SD 1995	Mat	Si-N	=2SD1010: Pins = 14mm	9c	-	-	-	-2SD1010
2 SD 1996	Mat	Si-N	=2SD1302: Pins = 14mm	9c	-	-	-	-2SD1302
2 SD 1997	Say	Si-N+Di+R	SMD, Motor Drv, 40/30V, 3/5A, 100MHz Rb=160Ω, Rbe=800Ω	(2SB1323) 39b	SOT-89	-	-	-
2 SD 1998	Say	Si-N+Di+R	=2SD1997: Rb=0, Rbe=800Ω	(2SB1324) 39b	SOT-89	-	-	-
2 SD 1999	Say	Si-N+Di+R	=2SD1997: 25/20V, 4/6A, Rb=0, Rbe=1.5kΩ	(2SB1325) 39b	SOT-89	-	-	-
2 SD 2000	Mat	Si-N	=2SD1990: Iso	17c	SOT-186	(2SD1411) ⁸	17c	2SC3691, 2SC3746, 2SC4549, 2SC4596
2 SD 2001	Mat	Si-N+Di	S P, TV-HA, 1500/700V, 1.5/5A, 40W, sat<8V(1A)	17c	TO-220 Iso	-	-	BU 505D ²
2 SD 2002	Say	Si-N	S P, TV-HA, 1500/800V, 5A, 50W	18c	TO-3P Iso	BU 508 AF	16c	BU 508AF, 2SC3481...82, 2SC3681, 2SD1731
2 SD 2004	Rhm	Si-N	=2SD1812: 1.2W	(2SB1328) 78b	(MRT)	-	-	2SC2983, 2SC4027, 2SD1918, 2SA2122...23
2 SD 2005	Rhm	Si-N	40/32V, 1/2A, 1.2W, 150MHz, sat<0.5V(0.5A)	(2SB1329) 78b	(MRT)	2SC4135	30j	2SC3076, 2SD1801
2 SD 2006	Rhm	Si-N	80/80V, 0.7/1A, 1.2W, 120MHz, sat<0.4V(0.5A)	78b	(MRT)	-	-	-
2 SD 2007	Rhm	Si-N	40/32V, 2/2.5A, 1.2W, 100MHz, sat<0.5V(2A)	(2SB1331) 78b	(MRT)	2SC4135	30j	2SC3076, 2SD1801
2 SD 2008	Rhm	Si-N	120/80V, 1/2A, 1.2W, 100MHz, sat<0.4V(0.5A)	(2SB1332) 78b	(MRT)	2SC4135	30j	2SC4135
2 SD 2009	Rhm	Si-N-Darl	LF, 60/60V, 1/2A, 1.2W, hFE>2000	78b	(MRT)	-	-	2SC2871, 2SC4500, 2SD1598, 2SD1800
2 SD 2010	Rhm	Si-N-Darl+Di	int. Z-Di(C-B), 60/60±10V, 2/3A, 1.2W, hFE=1...10k	78b	(MRT)	-	-	-
2 SD 2011	Rhm	Si-N-Darl+Di	=2SD1638:	(2SB1333) 78b	(MRT)	(BD 679) ⁴	14h	2SD1955, 2SD1980, 2SD2410
2 SD 2012	Tos	Si-N	LF P, 60/60V, 3A, 25W, 3MHz, hFE=100...320	(2SB1375) 17c	TO-220 Iso	(BD 243 C) ³	17j	BD 935F, 2SD1406, 2SD1585, 2SD1913, ++
2 SD 2014	Sak	Si-N-Darl+Di	P, 120/80V, 4A, 25W, 75MHz, hFE>2000, 1/5.5µs	17c	TO-220 Iso	-	-	2SD1336, 2SD1785
2 SD 2015	Sak	Si-N-Darl+Di	P, 150/120V, 4A, 25W, 40MHz, hFE>2000, 0.6/7µs	17c	TO-220 Iso	-	-	2SD1590, 2SD1789
2 SD 2016	Sak	Si-N-Darl+Di	P, 250/200V, 3A, 25W, 90MHz, hFE>1000	17c	TO-220 Iso	-	-	2SD1789
2 SD 2017	Sak	Si-N-Darl+Di	S P, 300/250V, 6A, 35W, hFE>2000, 0.6/19µs	17c	TO-200 Iso	-	-	2SD1410, (2SD1088, 2SD1113, 2SD1976,++) ³
2 SD 2018	Mat	Si-N-Darl+Di	int. Z-Di(C-B), 60/60V, 1/1.5A, 5W, 150MHz hFE=6.5...40k	14b	TO-126	-	-	-
2 SD 2019	Hit	Si-N-Darl+Di	LF P, 150/80V, 1.5/3A, 10W, hFE=5k...30k	14h	TO-126	2SD986	14h	2SC4342, 2SD985...986
2 SD 2020	Rhm	Si-N	P, 150/150V, 2A, 40W	17j	TO-220	2SD1138	17j	BD 239D, 2SC1669, 2SC2073, 1SD1138, ++
2 SD 2021	Rhm	Si-N	=2SD2020: Iso, 30W	17c	SOT-186	(2SD1138) ³	17j	2SC3566...67, 2SC3695, 2SD1587
2 SD 2022	Rhm	Si-N-Darl+Di	int. Z-Di(C-B, 60V), 60/60V, 1.5A, 25W, hFE=1k...30k	17j	TO-220	BD 901	17j	BD 715, BDW 23A, BDW 53A, BDW 63A, ++
2 SD 2023	Rhm	Si-N	P, 80/60V, 3/6A, 40W, 8MHz	(2SB1033) 17j	TO-220	BD 243 C	17j	BD 241B, BD 537, BD 539B, BD 951, ++
2 SD 2024	Rhm	Si-N-Darl+Di	P, 100/100V, 8/10A, 40W, 40MHz, hFE=1k...20k	(2SB1343) 17j	TO-220	-	-	-
2 SD 2025	Rhm	Si-N-Darl+Di	=2SD2024: Iso, 30W	17c	SOT-186	-	-	-
2 SD 2026	Rhm	Si-N-Darl	SMD, 30/30V, 0.3A, 200MHz, hFE=30000	35a	SOT-23	-	-	2SD1478
2 SD 2027	Say	Si-N	P, 60/60V, 3A, 30W, 8MHz	(2SB1346) 17j	TO-220	BD 243 C	17j	BD 241A, BD 353, BD 539A, BD 935, ++
2 SD 2028	Say	Si-N	SMD, int. Z-Di(C-B), 8/8V, 0.7/1.5A, 200MHz	35a	SOT-23	-	-	-
2 SD 2029	Mat	Si-N	S P, 160/160V, 12/20A, 120W, 20MHz	(2SB1347) 77j	TOP-3L	2SC3281	=16j	2SC3280...32812, 2SD1717
2 SD 2030	Hit	Si-N	=2SD1868: 0.4W	7c	TO-92	BF 420 A	7c	BF 420A, BF 422A, BF 391, 2SC3245A, ++
2 SD 2031	Hit	Si-N	=2SD1869: 0.4W	7c	TO-92	BF 420 A	7c	BF 420A, BF 422A, BF 391, 2SC3467, ++
2 SD 2032	Rhm	Si-N-Darl+Di	P, 80/80V, 4A, 20W, hFE=3000	78c	(HRT)	-	-	-
2 SD 2033	Rhm	Si-N	=2SD1763: 1.8W	(2SB1353) 78c	(HRT)	(2SC3117) ⁴	14h	(2SC2690, 2SC3621, 2SD1563, 2SD1684) ⁴
2 SD 2033 A	Rhm	Si-N	=2SD1763A: 1.8W	78c	(HRT)	(2SC3117) ⁴	14h	(2SC2690A, 2SC3117, 2SC 3902, 2SD1563A) ⁴
2 SD 2034	Rhm	Si-N	P, 80/60V, 3A, 25W	78c	(HRT)	-	-	-
2 SD 2035	Rhm	Si-N	P, 80/60V, 4/6A, 1.8W, 8MHz	(2SB1355) 78c	(HRT)	(BD 189) ⁴	14h	(BD 441, BD 787, BD 789, MJE 240...242) ⁴
2 SD 2036	Rhm	Si-N	P, 100/80V, 7/10A, 1.8W, 5MHz	(2SB1356) 78c	(HRT)	-	-	-

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International
2 SD 2037	Rhm	Si-N	P, 60/50V, 3/4, 5A, 1,8W, 90MHz	{2SB1357 78c	(HRT)	(2SD1348) ⁴	14h (BD 787, BD 789, 2SD1506, 2SD1818,++) ⁴
2 SD 2038	Rhm	Si-N	P, 80/60V, 5/10A, 1,8W, 8MHz	{2SB1358 78c	(HRT)		(BDX 36...37) ⁴
2 SD 2039	Rhm	Si-N-Darl+Di	P, 100/100V, 2/3A, 1,8W, hFE=1k...10k	{2SB1359 78c	(HRT)	(2SD986) ⁴	14h (2SD985...86, 2SD1376, 2SD1953, 2SD2019) ⁴
2 SD 2040	Rhm	Si-N	P, 100/100V, 5/10A, 1,8W, 8MHz	{2SB1360 78c	(HRT)		(BDX 35...37) ⁴
2 SD 2041	Rhm	Si-N-Darl+Di	int. Z-Di(C +B), 60/60±10V, 2/3A, hFE=1k...10k		78c	(HRT)	
2 SD 2042	Rhm	Si-N-Darl+Di	int. Z-Di(C +B), 60/60±10V, 5/10A, hFE=2k...30k		78c	(HRT)	
2 SD 2043	Rhm	Si-N-Darl+Di	P, 120/120V, 6/10A, 40MHz, hFE=2k...20k		78c	(HRT)	
2 SD 2044	Rhm	Si-N	=2SD1943: 1,8W		78c	(HRT)	
2 SD 2045	Sak	Si-N-Darl+Di	P, 120/120V, 6/10A, 50W, 50MHz, hFE>2000		18c	TO-3P Iso	(2SD1170, 2SD1210) ³
2 SD 2046	Hit	Si-N-Darl+Di	int. Z-Di(C +B), 50V, 1,5/3A, 1W, hFE=2k...10k		7c(9mm)	TO-92L	2SD1809, 2SD1866, 2SD1929, 2SD1931, ++
2 SD 2047	Fjd	Si-N	S P, TV-HA, 1500V, 5A, 80W, 8MHz, sat<2V(4,5A)		18c	TO-3P Iso	2SD1577
2 SD 2048	Say	Si-N-Darl+Di	P, 110/100V, 3A, 30W, 20MHz, hFE=4k>1,5k, 0,7/6,2µs		30c	(TO-220MF)	BU 508AF, 2SC3481...82, 2SC3681, 2SD1731
2 SD 2049	Say	Si-N-Darl+Di	P, 110/100V, 5A, 35W, 20MHz, hFE=4k>1,5k, 0,6/6,4µs		30c	(TO-220MF)	
2 SD 2050	Say	Si-N-Darl+Di	P, 110/100V, 8A, 40W, 20MHz, hFE=4k>1,5k, 0,6/µs		30c	(TO-220MF)	
2 SD 2051	Mat	Si-N-Darl+Di	int. Z-Di(C +B, 60V), 60/60V, 1,6/2,5VA, 12W, >200MHz, hFE=4k...40k		17c	SOT-186	2SD1983
2 SD 2052	Mat	Si-N	P, 150/150V, 9/15A, 100W, 20MHz	{2SB1361 16c	(TOP-3F)	(2SC2837) ³	18j (BD 245D, 2SC2837, 2SC3907, 2SD1046,++) ³
2 SD 2053	Mat	Si-N	=2SD2052:	{2SB1362 18j	TO-3P	2SC2837	18j BD 245D, 2SC2837, 2SC3907, 2SD1046, ++
2 SD 2054	Hit	Si-N	SMD, LF, 100/60V, 1A, sat<0,5V(1A)		39b	SOT-89	BCX 56, 2SD1005, 2SD1368, 2SD1418...19, ++
2 SD 2055	Rhm	Si-N	P, 80/60V, 10A, 40W		17j	TO-220	BD 809
2 SD 2056	Rhm	Si-N	=2SD2055: Iso, 30W		17c	SOT-186	(BD 809) 17j 2SC3693...3694
2 SD 2057	Mat	Si-N+Di	S P, TV-HA, 1500/700V, 5/20A, 100W, sat<8V(5A)		16c	(TOP-3F)	BU 508 DF
2 SD 2058	Kec	Si-N	P, 60/60V, 3A, 25W, 3MHz, <0,8/2,3µs		17c	SOT-186	(BD 243 C) ³ 17j 2SC3851...52, 2SD1585, 2SD1985, 2SD2012++
2 SD 2059	Kec	Si-N	P, 100/100V, 5A, 30W, 12MHz		17c	SOT-186	(BD 243 C) ³ 17j 2SC3691, 2SD1588, 2SD1940
2 SD 2060	Kec	Si-N	P, 80/80V, 4A, 25W, 8MHz		17c	SOT-186	(BD 243 C) ³ 17j 2SC3691, 2SC3851, 2SD2000
2 SD 2061	Rhm	Si-N	=2SD2023: Iso	{2SB1187 17c	SOT-186	2SD1411	17c BDT 31F, 2SC3691, 2SC3851...52, 2SD2000
2 SD 2062	Rhm	Si-N	P, 100/80V, 7/10A, 80W, 8MHz	{2SB1345 16c(j)	TO-247	(BD 245 C) ³	18j (BD 245C, BD 545C, 2SC2681, 2SD1840,++) ³
2 SD 2063	Hit	Si-N	LF, 15/10V, 1/2A, 0,9W, hi-hFE=400...2000		7c(9mm)	TO-92L	2SC3225 7c(9mm) 2SC3070, 2SC3225, 2SC3726, 2SD1984
2 SD 2064	Mat	Si-N	P, 120/120V, 6/10A, 70W, 20MHz	{2SB1371 16c	(TOP-3F)	2SC2837	18j (BD 245D, BD 545D, 2SC2706, 2SC2837,++) ³
2 SD 2065	Mat	Si-N	P, 140/140V, 7/12A, 80W, 20MHz	{2SB1372 16c	(TOP-3F)	2SC2837	18j (BD 245D, 2SC2706, 2SC2837, 2SC3907,++) ³
2 SD 2066	Mat	Si-N	P, 160/160V, 12A, 120W, 20MHz	{2SB1372 18j	TO-3P	2SD1047	18j BD 745F, 2SC2987A, 2SC3907, 2SD1047, ++
2 SD 2067	Mat	Si-N-Darl+Di	Uni, 120/100V, 2/3A, 1W, hFE=4k...40k		9c	(MT-1)	2SD1579, 2SD1659, 2SD1978
2 SD 2068	Mat	Si-N-Darl+Di	Uni, int. Z-Di(C +B, 60V), 60/60V, 1/1,5A, 1W, 150MHz, hFE=4k...40k		7c(9mm)	TO-92L	2SD1809, 2SD1866, 2SD1929, 2SD1931, ++
2 SD 2069	Rhm	Si-N	NF, 60/50V, 2/5A, 1W, 210MHz, lo-sat<0,35V(1A)		7c(9mm)	TO-92L	2SD1207 9c(9mm) 2SC3328, 2SC4486, 2SD1207, 2SD2177
2 SD 2070	Mat	Si-N	Uni, 50/50V, 0,1/0,2A, 1W	{2SB1376 9c		BC 546	7a BC 174, BC 182, BC 190, BC 546, ++
2 SD 2071	Mat	Si-N	Uni, 50/50V, 0,5/1A, 1W, 200MHz	{2SB1377 9c		BC 337	7a BC 337...338, BC 635, BC 637, BC 639, ++
2 SD 2072	Mat	Si-N	=2SD661: 1W, Pins = 14mm		9c		-2SD661
2 SD 2073	Mat	Si-N	=2SD1010: 1W		9c		-2SD1010
2 SD 2074	Mat	Si-N	=2SD1302: 1W		9c	(MT-1)	-2SD1302
2 SD 2075	Tos	Si-N+Di	int. Z-Diode(B +C), 60/60V, 10/15A, 90MHz, hFE=500...1500, 0,5/2,6µs, lo-sat<0,3V(5A)		17c	SOT-186	2SD1947
2 SD 2076	Tos	Si-N+Di	100/100V, 5/8A, 90MHz, hFE=500...1500, 0,6/3,8µs, lo-sat<0,3V(3A)		17c	SOT-186	2SD1947
2 SD 2079	Tos	Si-N-Darl+Di	P, 100/100V, 5/8A, 30W, hFE=2k...15k	{2SB1381 17c	TO-220 Iso	2SD1415	17c BD 647F, 2SD1589, 2SD1829...30, 2SD1785++
2 SD 2081	Sak	Si-N-Darl+Di	P, 120/120V, 10/15A, 30W, hFE>2000	{2SB1259 17c	TO-220 Iso		BDT 63CF, BDT 65CF, 2SD1591
2 SD 2082	Sak	Si-N-Darl+Di	P, 120/120V, 16/26A, 75W, hFE>2000	{2SB1382 18c	TO-3P Iso		
2 SD 2083	Sak	Si-N-Darl+Di	P, 120/120V, 25/40A, 120W, hFE>2000	{2SB1383 18j	TO-3P		2SD1597
2 SD 2084	Si-N-Darl	S P, 450/450V, 6/10A, 50W, hFE>1000		17j	TO-220	2SD798	17j BU 810, BU 911...12, 2SD798...99, 2SD1245
2 SD 2085	Rhm	Si-N	80/60V, 6A, 40W, 50MHz, hi-hFE=400...2000		17j	TO-220	(2SC2315...16, 2SC2491) ³
2 SD 2088	Tos	Si-N-Darl+Di	+Z-Di(C +B), 60/60V, 2A, 0,9W, 100MHz, hFE>2000		7c(9mm)	TO-92L	2SD1153 7c(9mm) 2SD1153, 2SD1809, 2SD1854, 2SD1929, ++
2 SD 2089	Tos	Si-N+Di	TV-HA, 1500/600V, 3,5A, 40W, 3MHz, sat<1V(2,2A)		18c	TO-3P Iso	BU 508 DF 16c BU 508DF, 2SD1554, 2SD1650, 2SD2095
2 SD 2090	Rhm	Si-N-Darl+Di	int. Z-Di(C +B), 90/90(+20/-10)V, 2/3A, 25W, 80MHz, hFE=1k...10k		17j	TO-220	
2 SD 2091	Rhm	Si-N-Darl+Di	=2SD2090: Iso		17c	SOT-186	
2 SD 2092	Tos	Si-N+Di	100/100V, 3/5A, 140MHz, hi-hFE=1500, sat<0,3V(1A)		17c	TO-220 Iso	2SD2076
2 SD 2093	Say	Si-N-Darl+Di	110/100V, 10A, 45W, 20MHz, hFE=4k>1,5k	{2SB1388 -18c	TO-3P Iso	(BDW 83 C) ³	18j (BDV 65C, BDV 67B...D), BDW 83D) ³
2 SD 2094	Hit	Si-N-Darl+Di	LF P, 120/120V, 8/12A, 25W, hFE=1k...20k		17c	SOT-186	BD 649F, 2SD1590, 2SD1773
2 SD 2095	Tos	Si-N+Di	CTV-HA, 1500/600V, 5A, 50W, 3MHz, sat<5V(3,5A)		18c	TO-3P Iso	BU 508 DF 16c BU 508DF, 2SD1555, 2SD1651, 2SD2125
2 SD 2096	Rhm	Si-N	=2SD2023: 1,8W	{2SB1496 78c	(HRT)	(BD 189) ⁴	14h (BD 441, BD 787, BD 789, MJE 240...241) ⁴
2 SD 2097	Rhm	Si-N	=2SD1961: Pins = 14mm		9c	2SD2179	9c 2SC3671, 2SC4482, 2SD1145
2 SD 2098	Rhm	Si-N	=2SD1961: SMD		39b	SOT-89	2SD1628, 2SD2402, 2SD2425
2 SD 2099	Say	Si-N+Di+R	Motor Drv, 40/30V, 3/5A, 100MHz, lo-sat<0,3V(1A) Rb=90Ω, Rbe=800Ω	{2SB1394		SOT-89	2SD1624
2 SD 2100	Say	Si-N+Di+R	SMD, 25/20V, 2/4A, 200MHz, Rb=0, Rbe=1,6kΩ lo-sat<0,5V(1A)	{2SB1397		SOT-89	2SD1621
2 SD 2101	Hit	Si-N-Darl	LF P, 200/200V, 10/15A, 30W, hFE>1500		17c	SOT-186	2SD1794
2 SD 2102	Hit	Si-N-Darl	LF P, 60/60V, 4/8A, 25W, hFE=1k...20k		17c	SOT-186	2SD1415 17c BDT 61(A,B,C)F, 2SD1595, 2SD2131, ++
2 SD 2103	Hit	Si-N-Darl	LF P, 60/60V, 8/12A, 25W, hFE=1k...20k		17c	SOT-186	2SD1415 17c BD 643F, 2SD1415...17, 2SD1826...27, ++
2 SD 2104	Hit	Si-N-Darl+Di	LF P, 120/120V, 8/12A, 25W, hFE=1k...20k		17c	SOT-186	BD 649F, BD 651F, 2SD1590, 2SD1773
2 SD 2105	Hit	Si-N-Darl+Di	LF P, 120/120V, 10/15A, 30W, hFE=1k...20k		17c	SOT-186	BDT 63CF, 2SD1591
2 SD 2106	Hit	Si-N-Darl+Di	LF P, 120/120V, 6/10A, 25W, hFE=1k...20k		17c	SOT-186	BD 649F, BD 651F, 2SD1336, 2SD1590
2 SD 2107	Hit	Si-N	LF P, 70/60V, 4/8A, 25W		17c	SOT-186	2SD1411 17c BD 951F, BD 953F, BD 955F, 2SD1407
2 SD 2108	Hit	Si-N-Darl+Di	LF P, 80/80V, 8/12A, 25W, hFE=1k...20k		17c	SOT-186	2SD1415 17c BD 645F, BDT63AF, 2SC4062, 2SD1415...16++
2 SD 2109	Hit	Si-N-Darl	S P, 300/300V, 0,3/0,6A, 15W, hFE=1000		17c	SOT-186	(2SD1502, 2SD1798) ³
2 SD 2110	Hit	Si-N-Darl+Di	LF P, 80/80V, 4/8A, 25W, hFE=1k...20k		17c	SOT-186	2SD1415 17c BDT 61(A...C)F, 2SD1933, 2SD2399, 2SD2478
2 SD 2111	Hit	Si-N-Darl+Di	LF P, 120/120V, 3/6A, 25W, hFE=1k...20k		17c	SOT-186	BDT 61CF, 2SD1892, 2SD2014...15
2 SD 2112	Hit	Si-N-Darl+Di	LF P, 120/120V, 6/12A, 25W, hFE=1k...20k		17c	SOT-186	BD 649F, 2SD1336, 2SD1590, 2SD1785
2 SD 2113	Hit	Si-N-Darl+Di	LF P, 120/120V, 3/6A, 25W, hFE=1k...20k		17c	SOT-186	BDT 61CF, 2SD1892, 2SD2014...15
2 SD 2114 K	Rhm	Si-N	=2SD2132: SMD		35a	SOT-23	
2 SD 2115 L.S	Hit	Si-N	LF P, 150/60V, 2/2,5A, 18W, sat<0,5V(1,5A)		30j	TO-251/252	(2SC4159) ⁶ 17c 2SD1033, 2SD1250(A), 2SD1557
2 SD 2116	Say	Si-N-Darl	Uni, 80/50V, 0,7/2A, 1W, hFE=5000	{2SB1405 9c		2SD1153	7c(9mm) BC 618, BC 877, BC 879, 2SD1153, ++
2 SD 2117	Say	Si-N-Darl	Uni, 80/50V, 1,5/3A, 1W, hFE>4000	{2SB1406 9c		2SD1153	7c(9mm) 2SD1153, 2SD1660, 2SD1853...54, 2SD1981, +
2 SD 2118(F5)	Rhm	Si-N	NF, Strobo, 50/20V, 5/10A, 1W, 150MHz, sat<1V(4A)		30c	TO-251	2SC3303 30j 2SC3072, 2SC3074, 2SD1803, 2SD1805, ++
						F5: TO-252	
2 SD 2119	Rhm	Si-N-Darl	LF P, 90/90V, 4A, 25W, hFE=2k...10k		17c	SOT-186	2SD1415 17c BDT 61BF...CF, 2SD1414, 2SD1788, 2SD2079+
2 SD 2120	Say	Si-N-Darl+Di	Uni, 100/80V, 2/4A, 1W, hFE=2k...30k		9c		2SD1660, 2SD1981
2 SD 2121 L.S	Hit	Si-N	LF P, 35/35V, 2,5/3A, 18W	{2SB1407 30j	TO-251/252	(BD 189) ⁵	14h 2SC3386, 2SD1221, 2SD1802
2 SD 2122 L.S	Hit	Si-N	=2SD2123: 180/120V		30j	TO-251/252	(2SC4159) ⁶ 17c 2SC4027, 2SC1080.82
2 SD 2123 L.S	Hit	Si-N	LF P, 180/160V, 1,5/3A, 18W, 180MHz	{2SB1409 30j	TO-251/252	(2SC4159) ⁶	17c 2SC4027
2 SD 2124 L.S	Hit	Si-N-Darl+Di	LF P, 120/120V, 1,5/3A, 18W, hFE=2k...30k, 0,5/2µs		30j	TO-251/252	2SD1464...65
2 SD 2125	Tos	Si-N+Di	CTV-HA, 1500/600V, 6A, 50W, 3MHz, sat<5V(5A)		18c	TO-3P Iso	BU 508 DF 16c BU 508DF, 2SC3892A, 2SD1556, 2SD1652

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International	
2 SD 2127	Tos	Si-N+Di	int. Z-Di(B-C, 60V), 60/60V, 3/5A, 140MHz, hFE=500...1500, 0.6/2µs, lo-sat<0.3V(10mA)	17c		TO-220 Iso	2SD1948, 2SD1972, 2SD2076	
2 SD 2128	Hit	Si-N-Darl+Di	LF P, 60/60V, 3/6A, 25W, hFE=1k...20k	17c	SOT-186	2SD1415	17c	BDT 61(A...C)F, 2SD1413, 2SD1796, ++
2 SD 2129	Tos	Si-N-Darl+Di	S P, 100/100V, 3/5A, 20W, hFE=2k...15k, 1/7µs	17c	TO-220 Iso	2SD1415	17c	2SD1414, 2SD1788, 2SD1828, 2SD2015
2 SD 2130	Tos	Si-N-Darl+Di	+Z-Di(C-B), 60/60V, 5/4A, 10W, 60MHz, hFE=2k...15k	14b	TO-126 Iso			-
2 SD 2131	Tos	Si-N-Darl+Di	+Z-Di(C-B), 60/60V, 5/8A, 30W, hFE=2...15k, 1/6.5µs	17c	TO-220 Iso	2SD1415	17c	2SD1595
2 SD 2132	Rhm	Si-N	25/20V, hi-Ueb=12V, 0.5/1A, 0.625W, 350MHz, hi-hFE=560...2700, lo-sat<0.4V(0.5A), Ron=0.8Ω	7c	TO-92	(2SC3225)	7c(9mm)	2SC4204, 2SD2144...45, 2SD2191...92
2 SD 2133	Mat	Si-N	LF Out, 60/50V, 1/1.5A, 1.5W, 200MHz	{2SB1413 78b	(MT-3)	(BD 139) ⁴	14h	(BD 135, BD 137, BD 139, BD 226,++) ⁴
2 SD 2134	Mat	Si-N	LF Out, 180/180V, 1/1.5A, 1.5W, 200MHz	{2SB1414 78b	(MT-3)	(2SC3117) ⁴	14h	(2SC3117, 2SC3902, 2SD669) ⁴
2 SD 2135	Mat	Si-N-Darl+Di	+Z-Di(C-B), 60/60V, 1/1.5A, 150MHz, hFE=6.5...40k	78b	(MT-3)			-
2 SD 2136	Mat	Si-N	LF Out.S, 60/60V, 3/5A, 1.5W, 220MHz, 500/2900ns	78b	(MT-3)	(BD 189) ⁴	14h	(BD 177, BD 179, BD 189, 2SD794(A)) ⁴
				{2SB1416				
2 SD 2137	Mat	Si-N	LF Out.S, 60/60V, 3/5A, 15W, 30MHz, 0.3/2.7µs	78c	(MT-4)	(BD 189) ⁴	14h	(BD 177, BD 179, BD 189, 2SD794(A)) ⁴
2 SD 2137 A		Si-N	=2SD2137: 80/80V	{2SB1417 78c	(MT-4)	(BD 189) ⁴	14h	(BD 179, BD 189, 2SD794(A)) ⁴
2 SD 2138	Mat	Si-N-Darl+Di	P, 60/60V, 2/4A, 15W, 20MHz, hFE>1k...10k, 0.4/4µs	78c	(MT-4)			BDT 61(A...C)F, 2SD1413, 2SD1983, ++
2 SD 2138 A		Si-N-Darl+Di	=2SD2138: 80/80V	{2SB1418 78c	(MT-4)			BDT 61(A...C)F, 2SD1414, 2SD1933
2 SD 2139	Mat	Si-N	80/60V, 3/6A, 15W, 50MHz, hi-hFE=500...2500	78c	(MT-4)			2SD1776, 2SD2092, (2SC1983, 2SD1774) ³
2 SD 2140	Mat	Si-N	LF Out, 140/140V, 7/12A, 80W, 20MHz	18j	TO-3P	2SC2837	18j	BD 245D, 2SC2706, 2SC2837, 2SC3182, ++
2 SD 2141	Sak	Si-N-Darl+Di	int.Z-Di(C-B), 380/380V, 6A, 35W, 20MHz, hFE>1500	17c	TO-220 Iso			-
2 SD 2143	Rhm	Si-N-Darl	int. Z-Di(C-B), 60±10V, 2A, 10W, hFE=1k...10k	30j	TO-251/252			-
2 SD 2144(S)	Rhm	Si-N	=2SD2132: 0.3W	41c	(SPT)	+2SD2132		+2SD2132
2 SD 2145(M)	Rhm	Si-N	=2SD2132: 0.4W	9c		+2SD2132		+2SD2132
2 SD 2146	Rhm	Si-N	LF, 60/50V, 3/4.5A, 1.2W, 90MHz, sat<1V(2A)	78b	(MRT)	2SC3303	30j	2SC3386, 2SC4522, 2SD1802, 2SD1221, ++
2 SD 2147	Rhm	Si-N	=2SD2118:	14b	TO-126	(2SC3420)	14b	2SC2270, 2SD826
2 SD 2148	Hit	Si-N	S P, HA, 1500/700V, 8A, 50W, sat<5V(7A)	-18c	(TO-3PFM)	BU 508 AF	16c	BU 508AF, 2SC3886A, 2SC3896
2 SD 2149	Hit	Si-N-Darl+Di	P, 100/100V, 15/20A, 100W, hFE=1k...20k	{2SB1466 18j	TO-3P			BDV 67A...D, BDW 83C...D, 2SD1026
2 SD 2150	Rhm	Si-N	=2SD2152: SMD	39b	SOT-89			2SC4541, 2SD1119, 2SD1624, 2SD2403
2 SD 2151	Mat	Si-N	P, 130/80V, 10/20A, 30W, 20MHz, 0.5/2.2µs	17c	SOT-186			2SC3568, 2SC3698, 2SC4336
2 SD 2152	Rhm	Si-N	LF Drv, 40/20V, 3/5A, 0.75W, 290MHz, sat<0.5V(2A)	7c	TO-92	2SD1347	7c(9mm)	2SC4487, 2SD1507, 2SD1617, 2SD1864, ++
2 SD 2153	Rhm	Si-N	30/25V, 2/3A, 110MHz, hi-hFE=390...2700	39b	SOT-89			2SC3439, 2SC3727
2 SD 2154	Rhm	Si-N	=2SD2152: 0.6W	9c	(FTL)	+2SD2152		+2SD2152
2 SD 2155	Tos	Si-N	HiFi LF Out, 180/180V, 15A, 150W, 10MHz	{2SB1429 77j	TOP-3L	2SC3281	=16j	2SC3281, 2SC4029
2 SD 2156	Mat	Si-N	80/60V, 3/6A, 25W, 50MHz, hi-hFE=500...2500	17c	SOT-186	2SD1273	17c	2SD1944, 2SD2076, 2SD2092
2 SD 2156 A		Si-N	=2SD2156: 100/80V	17c	SOT-186			2SD2076, 2SD2092
2 SD 2157	Mat	Si-N-Darl+Di	P, 60/60V, 4/8A, 25W, 20MHz, hFE=1k...10k, 0.5/5µs	17c	SOT-186	(BD 901) ³	17j	BDT 61(A...C)F, 2SD1825, 2SD1987, 2SD2014
2 SD 2157 A		Si-N-Darl+Di	=2SD2157: 80/80V	17c	SOT-186	(BD 901) ³	17j	BDT 61(A...C)F, 2SD1414, 2SD1788, 2SD1933
2 SD 2158	Mat	Si-N	80/60V, 2/4A, 20W, 40MHz, hi-hFE=500...2500	17c	SOT-186	2SD1273	17c	2SC3852, 2SD1776(A), 2SD1944, 2SD2092 ³
2 SD 2158 A		Si-N	=2SD2158: 100/80V	17c	SOT-186			2SD1776A, 2SD2092, 2SD2156A
2 SD 2159	Rhm	Si-N	LF, 30/25V, 2/3A, 110MHz, 1W, hi-beta=390...2700 lo-sat<0.5V(1A)	7c(9mm)	TO-92L	2SC3225	7c(9mm)	2SC3225, 2SC4389, 2SC4682...83
2 SD 2161	Nec	Si-N-Darl+Di	=2SD1589:	17c	TO-220 Iso	+2SD1589		+2SD1589
2 SD 2162	Nec	Si-N-Darl+Di	=2SD1590:	17c	TO-220 Iso	+2SD1590		+2SD1590
2 SD 2163	Nec	Si-N-Darl+Di	=2SD1591:	17c	TO-220 Iso	+2SD1591		+2SD1591
2 SD 2164	Rhm	Si-N	=2SD2152: 1W	9c	(ATV)	+2SD2152		+2SD2152
2 SD 2164	Nec	Si-N	=2SD1593:	17c	TO-220 Iso	+2SD1593		+2SD1593
2 SD 2165	Nec	Si-N	=2SD1594:	17c	TO-220 Iso	+2SD1594		+2SD1594
2 SD 2166	Rhm	Si-N	=2SD2118: 1.5W	14b	TO-126 Iso	2SC3420	14b	2SC3420, 2SD1685
2 SD 2167	Rhm	Si-N	=2SD2169: SMD	39b	SOT-89			-
2 SD 2168	Rhm	Si-N	=2SD2169	9c	(FTL)			-
2 SD 2169	Rhm	Si-N	int. Z-Di(C-B), 31/31±4V, 2/3A, 0.5W, 100MHz lo-sat<0.5V(1A)	9c	(FTL)			-
2 SD 2170	Rhm	Si-N-Darl+Di	SMD, +Z-Di(C-B), 90/90V, 2/3A, 80MHz, hFE=1...10kΩ	39b	SOT-89			-
2 SD 2171 S	Rhm	Si-N	30/25V, hi-Ueb=12V, 1.5/2A, 0.3W, 200MHz hi-hFE=560...2700	41c	(SPT)	(2SC3225)	7c(9mm)	2SC3070, 2SC4389, 2SD1581...82
2 SD 2172	Rhm	Si-N	=2SD2171S: 1W	7c(9mm)	TO-92L	(2SC3225)	7c(9mm)	2SC4389
2 SD 2175	Rhm	Si-N	Uni, +80V, 0.7/1A, 0.5W	9c	(FTL)	2SD774	7c	BC 639, 2SD774, 2SC3665, 2SD1226, ++
2 SD 2176	Say	Si-N-Darl+Di	SMD, Motor Drv, int. Z-Di(C-B), 50/50V, 1.2/2.5A, hFE=1k...20k	39b	SOT-89			2SD1626
2 SD 2177	Mat	Si-N	LF Out, 50/50V, 2/3A, 1W, 110MHz, sat<0.3V(1A)	9c		2SD1207	7c	2SC3328, 2SD1207, 2SD1835, 2SD2182
				{2SB1434				
2 SD 2178	Mat	Si-N	=2SD2177: 1.5W	{2SB1435 78b	(MT-3)			-
2 SD 2179	Mat	Si-N	Uni, 50/50V, 5/7A, 1W, 80MHz	{2SB1446 9c		2SD2179	9c	2SD1145, 2SD1961...62, 2SD2097
2 SD 2180	Mat	Si-N	Uni, 50/50V, 3/5A, 1.5W, 80MHz	78b	(MT-3)			-
2 SD 2181	Mat	Si-N	Uni, 100/100V, 1/1.5A, 1W, 100MHz, sat<0.3V(0.5A)	9c		(BC 639) ¹⁷	7c	2SC4488, (BC 639, 2SD1616A, 2SD1768) ¹⁷
				{2SB1437				
2 SD 2182	Mat	Si-N	100/100V, 2/3A, 1W, 80MHz, sat<0.3V(1A)	9c				2SC4489, (2SD1015, 2SD1642) ¹⁷
2 SD 2183	Mat	Si-N	=2SD2182: 1.5W	{2SB1438 9c	(MT-3)			-
2 SD 2184	Mat	Si-N	LF, 150/150V, 1/1.5A, 1W, 90MHz, lo-sat<0.3V(0.5A)	9c		(2SD1812) ¹⁷	7c	(2SD1812) ¹⁷
				{2SB1456				
2 SD 2185	Mat	Si-N	=2SD2177: SMD, 3/4A	{2SB1440 39b	SOT-89			2SC4409, 2SD1623
2 SD 2188	Rhm	Si-N	=2SD2085: Iso, 30W	17c	SOT-186			2SC4553, (2SC4558, 2SD1474) ⁸
2 SD 2191	Rhm	Si-N	=2SD2132: 0.4W, Pins = 14mm	9c		+2SD2132		+2SD2132
2 SD 2192	Rhm	Si-N	=2SD2132: 0.4W, Pins = 14mm	9c		+2SD2132		+2SD2132
2 SD 2193	Hit	Si-N+Di	Z-Di(C-B), 25/25V, 0.8/1.5A, 0.9W, hi-hFE>800	7c(9mm)	TO-92L			-
2 SD 2195	Rhm	Si-N-Darl+Di	SMD, Uni, 100/100V, 2/3A, 80MHz, hFE=1k...10k	39b	SOT-89			2SD1472
2 SD 2196	Shi	Si-N-Darl+Di	=2SD1027: Iso, 65W	18c	TO-3P Iso			(2SD1515) ³
2 SD 2197 M	Rhm	Si-N	=2SC2069:	9c	(ATR)	+2SD2069		+2SC2069
2 SD 2198	Say	Si-N	S P, 60/50V, 5/9A, 30W, 30MHz, lo-sat<0.4V(3A)	30c	(TO-220MF)	2SC3303	30j	2SD1904, 2SD1906, 2SD2200
				{2SB1449				
2 SD 2199	Say	Si-N	S P, 60/50V, 7/12A, 40W, 10MHz, lo-sat<0.4V(4A)	30c	(TO-220MF)			2SD1905, 2SD1907, 2SD2201
				{2SB1450				
2 SD 2200	Say	Si-N	S P, 90/80V, 5/9A, 30W, 20MHz, lo-sat<0.4V(3A)	30c	(TO-220MF)	2SC3303	30j	2SD1906...07, 2SD2201
				{2SB1451				
2 SD 2201	Say	Si-N	S P, 90/80V, 7/12A, 40W, 20MHz, lo-sat<0.4V(4A)	30c	(TO-220MF)			2SD1907
				{2SB1452				
2 SD 2202	Say	Si-N	S P, 90/80V, 5A, 25W, 20MHz, lo-sat<0.4V(3A)	17c	TO-220 Iso	2SD1411	17c	2SD1411
				{2SB1454				
2 SD 2203	Say	Si-N	S P, 90/80V, 7A, 30W, 20MHz, lo-sat<0.4V(4A)	17c	TO-220 Iso	2SD1411	17c	2SD1411
				{2SB1455				
2 SD 2204	Tos	Si-N-Darl+Di	int. Z-Di(C-B), 65V, 4A, 25W, B=2k...15k, 1/7µs	17c	TO-220 Iso			-
2 SD 2205	Nec	Si-N-Darl+Di	=2SD1590	17c	TO-220 Iso	+2SD1590		+2SD1590
			1/4, 7µs					

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International
2 SD 2206	Tos	Si-N-Darl+Di	Uni, 100/100V, 2/3A, 0.9W, 100MHz, B>2k, 400/4600ns	7c(9mm)			2SD1978, 2SD1981
2 SD 2209	Mat	Si-N-Darl+Di	int. Z-Di(C +B), 100/100V, 4/8A, 15W, 20MHz, hFE=1k...10k, <0.3/4µs	30j	(I Type)		2SC4345, 2SD1223, 2SD1520
2 SD 2210	Mat	Si-N	=2SD1302: SMD	39b			2SC2982, 2SC3265, 2SD1621
2 SD 2211	Rhm	Si-N	=2SD1918: Min	39b			2SC3649, 2SD1420...21
2 SD 2212	Rhm	Si-N-Darl+Di	SMD, Z-Di(C +B), 60/60±10V, 2/3A, 80MHz, hFE=1...10k	39b			-
2 SD 2213	Hit	Si-N-Darl+Di	LF, 150/80V, 1.5/3A, 0.9W, hFE=5k...30k	7c(9mm)			2SD1579, 2SD1659
2 SD 2214	Mat	Si-N-Darl	S P, 60/60V, 8A, 25W, 20MHz, hFE=2k...10k, 0.5/5µs	17c			-
2 SD 2215(A)	Mat	Si-N	=2SD1249(A): 15W	-30j	(I Type)		2SC3075
2 SD 2216	Mat	Si-N	SMD, Uni, 60/50V, 0.1/0.2A, 150MHz	35a(1.6mm)			2SC4738
2 SD 2217	Nec	Si-N-Darl	=2SD1502: Iso, 25W	17c			2SD2109
				12SB1465			
2 SD 2218	Say	Si-P	P, 60/30V, 8A, 20W, 120MHz, 100/530ns	12SB1467	17c	TO-220 Iso	2SD1411
2 SD 2219	Say	Si-P	P, 60/30V, 12A, 25W, 120MHz, 200/530ns	12SB1468	17c	TO-220 Iso	17c
2 SD 2220	Mat	Si-N-Darl	LF Out, 100/80V, 1/1.5A, 1.5W, 150MHz, hFE=4k...40k	78b			BD 201F, BD 203F, 2SD1411...12, 2SD1668++
2 SD 2221	Mat	Si-N-Darl	160/140V, 7/15A, 100W, 20MHz, hFE=5k...30k	12SB1469	18j		2SC3709, 2SC4065
2 SD 2222	Mat	Si-N-Darl	160/160V, 8/15A, 150W, 20MHz, hFE=3k...30k	12SB1470	77j		-
2 SD 2223	Say	Si-N-Darl	P, 70/60V, 4A, 30W, 0.6/4.3µs, hFE>2000	12SB1471	30c	(TO-220MF)	2SD2255
2 SD 2224	Say	Si-N-Darl	P, 70/60V, 7A, 35W, 0.6/4.7µs, hFE>2000	12SB1472	30c	(TO-220MF)	2SD2250, 2SD2276
2 SD 2225	Mat	Si-N	=2SD1211:	12SB1473	9c		(BDW 23B...C, BDW 63B...D, 2SD1933,++) ⁶
2 SD 2226 K	Rhm	Si-N	=2SD2227S: SMD	35a			(BD 647, BD 899, BDW 73B, 2SD1415...16++) ⁶
2 SD 2227 S	Rhm	Si-N	60/50V, hi-Ueb=12V, 0.15/0.2A, 0.2W, 250MHz	41c			2SC2235, 2SC3665, 2SD667, 2SD1616A
			hi-hFE=560...2700				2SD1938
2 SD 2228	Nec	Si-N	SMD, Uni, 25/16V, 0.5A, 50MHz, sat<0.1V(0.1A)	35a(2mm)			2SC3069, 2SC3071, 2SC3836
2 SD 2229	Nec	Si-N	Uni, 16/16V, 0.5A, 0.25W, 50MHz, sat<0.2V(0.5A)	40c			-
2 SD 2230	Nec	Si-N	=2SD2229: SMD	35a			2SD1012, 2SC4483, 2SD1302, 2SD2322S,++
2 SD 2231	Sak	Si-N-Darl+Di	LF P, 120/120V, 6/10A, 60W, hFE=2k...15k	12SB1476	18j		2SC2350, 2SC4519
2 SD 2232	Mat	Si-N-Darl	S P, 400/300V, 8A, 30W, 20MHz, hFE=3k...20k	17c			2SD1170
2 SD 2233	Mat	Si-N-Darl	S P, 300/250V, 6A, 30W, 20MHz, hFE=2.7k...9k	17c			(2SD1141) ³
2 SD 2234	Fjd	Si-N	S P, 1500V, 3A, 40W, <1/4.5µs, sat<2V(2.5A)	17c			2SD1410, 2SD2017
2 SD 2240(A)	Mat	Si-N	=2SD814(A):	35a(1.6mm)			BU 505F, 2SD1575
2 SD 2241	Tos	Si-N-Darl+Di	P, 100/100V, ±4/6A, 25W, B>2000, 200/2100ns	17c			-
2 SD 2242	Mat	Si-N-Darl+Di	P, 60/60V, 4/8A, 15W, 20MHz, hFE=1k...10k, 0.5/5µs	78c			-
2 SD 2242 A	Mat	Si-N-Darl+Di	=2SD2242: 80/80V	78c			(BDT 61(A...C)F, 2SD1825, 2SD2014,++) ⁴
2 SD 2243	Nec	Si-N	60/60V, 5/8A, 1W, lo-sat<0.3V(2A)	9b			(BDT 61AF...CF, 2SD1933, 2SD2014,++) ⁴
2 SD 2244	Nec	Si-N	60/60V, 3/5A, 1W, hi-hFE=800...3200, lo-sat<0.4V(2A)	9b			2SC4482, 2SD1145
2 SD 2245	Nec	Si-N-Darl+Di	int. Z-Di(C +B), 60/60±10V, ±2/3A, 1W, hFE=2k...20k	9b			-
			0.5/4µs				-
2 SD 2246	Nec	Si-N-Darl+Di	80/80V, ±2/4A, 1W, hFE=2k...20k, 0.4/1.9µs	9b			-
2 SD 2247	Hit	Si-N	Uni, 55/50V, 0.1A, 0.2W, 50MHz, sat<0.2V(10mA)	7c			2SD1153, 2SD1809, 2SD1853, 2SD1866
2 SD 2248	Tos	Si-N-Darl+Di	+Z-Di(C +B), 80/80V, ±2/3A, 0.9W, 100MHz, B>2000	7c(9mm)			BC 167, BC 237, BC 546...547, 2SD767, ++
2 SD 2249	Mat	Si-N	=2SD965: 1W	9c			-
2 SD 2250	Mat	Si-N-Darl	160/140V, 7/12A, 90W, 20MHz, hFE=5k...30k	12SB1490	77j		2SD1244, 2SD1934, 2SD1961...62, 2SD2097++
2 SD 2251	Say	Si-N+Di	=2SC4770: int. Damper-Diode	18c			2SD2222, 2SD2276
2 SD 2252	Say	Si-N	CTV-HA, 1500/800, 7/20A, 60W, sat<5V(5A)	18c			BU 508DF, 2SC3893A, 2SC4123...24, 2SC4769
2 SD 2253	Tos	Si-N+Di	CTV HA, 1700/600, 6/12A, 50W, tf<500ns	18c			BU 508AF, 2SC3885A, 2SC3895, 2SC4770
2 SD 2254	Mat	Si-N-Darl	130/110V, 6/10A, 70W, 20MHz, hFE=5k...30k	12SB1492	77j		2SC4766, 2SC4806
2 SD 2255	Mat	Si-N-Darl	160/140V, 7/12A, 70W, 20MHz, hFE=5k...30k	12SB1493	18j		2SD2222, 2SD2250, 2SD2276
2 SD 2256	Hit	Si-N-Darl+Di	S P, 120/120V, 25/35A, 120W, hFE=2k...20k	12SB1494	18j		2SD2221
2 SD 2257	Tos	Si-N-Darl+Di	100/100V, 3/5A, 20W, 500/2500ns, hFE>2k	12SB1495	17c		2SD2083
2 SD 2258	Mat	Si-N-Darl	=2SD1198A: 1W, Pins = 14mm	9c			BDT 61BF, 2SD1828, 2SD2129, 2SD1788,++
2 SD 2259	Mat	Si-N	=2SD1458: 1W, Pins = 14mm	9c			-2SD1198A
2 SD 2260	Mat	Si-N	=2SD662B: 0.6W, Pins = 14mm	9c			-2SD1458
2 SD 2261	Say	Si-N-Darl	SMD, 80/60V, 2.5A, B>2000	39b			-2SD662B
2 SD 2263	Hit	Si-N+Di	int. Z-Di(C +B), 25/25V, 0.5/1A, sat<0.5V(0.5A)	7c			-
2 SD 2264	Rhm	Si-N	=2SD2152:	9c			-2SD2152
2 SD 2265	Mat	Si-N-Darl	1000V, 1/2A, 35W, 20MHz, hFE=200...900, 1.2/3.85µs	30j			-
2 SD 2266	Mat	Si-N	S P, 80/60V, 4/8A, 15W, 80MHz, 0.3/1.2µs	78j			-
2 SD 2271	Tos	Si-N-Darl	300/200V, ±10/15A, 30W, 40MHz, B>500, <1/14µs	17			(BD 243C) ⁴
2 SD 2273	Mat	Si-N-Darl	P, 100/80V, 3/6A, 45W, 20MHz, hFE=5k...30k	12SB1500	77j		(BD 243B...F, BD 539B...D, 2SC3254) ⁴
2 SD 2274	Mat	Si-N-Darl	P, 110/90V, 4/7A, 50W, 20MHz, hFE=5k...30k	12SB1501	77j		-
2 SD 2275	Mat	Si-N-Darl	P, 120/100V, 5/8A, 60W, 20MHz, hFE=5k...30k	12SB1502	77j		2SD2254
2 SD 2276	Mat	Si-N-Darl	160/140V, 8/15A, 120W, 20MHz, hFE=5k...30k	12SB1503	77j		2SD2254
2 SD 2280	Say	Si-N	P, 60/50V, 7A, 40W, 10MHz, 200/1200ns	12SB1507	18c		2SD2222, 2SD2250
2 SD 2281	Say	Si-N	P, 60/50V, 12A, 45W, >30MHz, 100/1250ns	12SB1508	18c		2SC4385, 2SD2064, (BD 245A...F,++) ³
2 SD 2282	Say	Si-N	P, 60/50V, 15A, 50W, 20MHz, 200/1100ns	12SB1509	18c		(BD 545A...D, 2SC3256, 2SD1064...65,++) ³
2 SD 2283	Rhm	Si-N-Darl+Di	=2SD2090: 1.8W	78c			(BD 545A...D, 2SC3256, 2SD1064...65,++) ³
2 SD 2284	Say	Si-N-Darl	80/60V, 3A, hFE>2000	12SB1510	-12b		-
2 SD 2285	Say	Si-N	P, 60/30V, 20/40A, 40W, 120MHz, 300/620ns	12SB1511	18c		-
2 SD 2287	Hit	Si-N+Di	CTV-HA, 1500V, 3/3.5A, 50W, sat<5V(2.5A)	23a			-
2 SD 2288	Hit	Si-N	CTV-HA, 1500/800V, 3/3.5A, 50W, sat<5V(2.5A)	23a			BU 208D, BU 706D, 2SC3480, 2SD1877, ++
2 SD 2289	Hit	Si-N+Di	CTV-HA, 1500V, 5/6A, 50W, sat<5V(4.5A)	23a			BU 208A, BU 705, 2SC3023, 2SD850, ++
2 SD 2290	Hit	Si-N	CTV-HA, 1500/800V, 5/6A, 50W, sat<5V(4.5A)	23a			BU 208D, BU 706D, 2SC3481, 2SD1878, ++
2 SD 2291	Hit	Si-N+Di	CTV-HA, 1500V, 6/7A, 50W, sat<5V(5A)	23a			BU 208A, BU 706, 2SC2928, 2SC3685, ++
2 SD 2292	Hit	Si-N	CTV-HA, 1500/800V, 6/7A, 50W, sat<5V(5A)	23a			BU 508D, 2SC3682, 2SD1732, 2SD1879, ++
2 SD 2293	Hit	Si-N+Di	=2SD2287:	18j			BU 508A, 2SC3025, 2SC3686, 2SD725, ++
2 SD 2294	Hit	Si-N	=2SD2288:	18j			BU 508D, BU 706D, 2SD1729, 2SD1877, ++
2 SD 2295	Hit	Si-N+Di	=2SD2289:	18j			BU 705, 2SC3484, 2SD1495
2 SD 2296	Hit	Si-N	=2SD2290:	18j			BU 508D, BU 706D, 2SC3481, 2SD1878, ++
2 SD 2297	Hit	Si-N+Di	=2SD2291:	18j			BU 508A, BU 706, 2SC3685, 2SD1496...97, ++
2 SD 2298	Hit	Si-N	=2SD2292:	18j			BU 508D, 2SC3682, 2SD1732, 2SD1879, ++
2 SD 2299	Hit	Si-N+Di	=2SD2287: Iso	-18c			BU 508A, BU 908, 2SC3686, 2SD1497, ++
2 SD 2300	Hit	Si-N+Di	=2SD2289: Iso	-18c			BU 705DF, 2SD1553...54, 2SD1649...50, ++
2 SD 2301	Hit	Si-N	=2SD2292: Iso	-18c			BU 706DF, 2SD1555...56, 2SD1651...52, ++
2 SD 2308	Rhm	Si-N-Darl+Di	LF, 80/80V, 4/6A, 1.2W, 40MHz, hFE=1k...10k	12SB1515	78b		BU 508DF, 2SC3885A, 2SC3895, 2SC4770, ++
2 SD 2309	Rhm	Si-N-Darl	=2SD1986:	78b			2SD1223, 2SD1520
2 SD 2310	Mat	Si-N+Di	S P, TV HA, 1500/700, 1.5/5A, 40W, sat<8V(1A)	17c			2SD1223, 2SD1520
2 SD 2311	Hit	Si-N	=2SD2290: Iso	-18c			BU 505DF, 2SD2001
2 SD 2312	Rhm	Si-N	=2SD2227S: 0.4W	9c			BU 506AF, BU 706F, 2SC3894, 2SD1655...56+
2 SD 2313 M	Rhm	Si-N	=2SD2227S: 0.4W	9c			-2SD2227S
2 SD 2314	Rhm	Si-N	=2SD2227S: 0.4W, Pins = 14mm	9c			-2SD2227S
2 SD 2315	Rhm	Si-N	=2SD2227S: 0.4W, Pins = 14mm	9c			-2SD2227S

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International
2 SD 2318(F5)	Rhm	Si-N	80/60V, 3/4,5A, 15W, 50MHz, hi-hFE=390...1800	30j	TO-251 F5: TO-252	(2SC3808) ⁴	14h 2SD1754(A)
2 SD 2321	Mat	Si-N	LF Out, 40/20V, 5A, 0.4W, 150MHz	41c		2SD2179	9c 2SD1244, 2SD1934, 2SD2249, 2SD2097, ++
2 SD 2322 S	Rhm	Si-N	Uni, 40/32V, 0.8A, 0.3W, 150MHz, lo-sat<0.4V(0.5A)	41c	(SPT)	2SD1207	7c(9mm) 2SC4485, 2SC4488, 2SD1616, 2SD2181
2 SD 2323	Hit	Si-N-Darl+Di	Z-Di(C -B), 300/300V, 6/10A, 30W, hFE=500, 1.2/16µs	17c	SOT-186		-
2 SD 2324	Say	Si-N	SMD, 20/15V, 0.8A, 150MHz, Rbe=1kΩ	{2SB1527} 35a	SOT-23		-
2 SD 2326	Mat	Si-N-Darl	int. Z-Di(C -B), 60V, 1A, 1.2W, 150MHz, B=6...40k	-12b	(MT-2L)		-
2 SD 2328	Mat	Si-N	LF P, 180/180V, 15A, 150W, 30MHz	77j	TOP-3L	2SC3281	≈16 2SC3281, 2SD1975, 2SD2155
2 SD 2329	Mat	Si-N	HA, 1500/600V, 5/10A, -IBp=2.5A, 80W, sat<5V(4A)	16c(j)	(TOP-3F)	BU 508A(F)	18j(c) BU 508A(F), BU 706(F), BU 908(F), ++
2 SD 2330	Mat	Si-N	HA, 1500/600V, 7/20A, 100W, sat<5V(5A)	16c(j)	(TOP-3F)	BU 508A(F)	18j(c) BU 508A(F), BU 2508A(F), BU 908(F), ++
2 SD 2331	Mat	Si-N+Di	HA, 1500/600V, 3/6A, -IBp=2A, 60W, sat<5V(2A)	18c	TO-3P Iso	2SD1555	18c BU 705DF, 2SD1554, 2SD1650, 2SD2089
2 SD 2332	Mat	Si-N	HA, 1500/600V, 3/6A, -IBp=2A, 60W, sat<5V(2A)	18c	TO-3P Iso	2SD1577	16c BU 705F, 2SD1544, 2SD1654, 2SD1883, ++
2 SD 2333	Mat	Si-N+Di	HA, 1500/600V, 5/10A, -IBp=2.5A, 80W, sat<5V(4A)	18c	TO-3P Iso	BU 508 DF	18c BU 508DF, BU 706DF, 2SD1555, 2SD2125, ++
2 SD 2334	Mat	Si-N	HA, 1500/600V, 5/10A, -IBp=2.5A, 80W, sat<5V(4A)	18c	TO-3P Iso	BU 508AF	18c BU 508AF, BU 706F, 2SD1655, 2SD1884, ++
2 SD 2335	Mat	Si-N+Di	HA, 1500/600V, 7/20A, -IBp=3A, 100W, sat<5V(5A)	18c	TO-3P Iso	BU 508DF	18c BU 508DF, 2SD1555, 2SD2095, 2SD2125, ++
2 SD 2336	Mat	Si-N	HA, 1500/600V, 7/20A, -IBp=3A, 100W, sat<5V(5A)	18c	TO-3P Iso	BU 508AF	18c BU 508A(F), 2SC3686, 2SC3895, ++
2 SD 2337	Hit	Si-N	LF P, 200/150V, 2/5A, 20W	{2SB1530} 17c	SOT-186	(2SC4159) ⁷	17c 2SC3298B, 2SC4382, 2SD1587
2 SD 2340	Mat	Si-N-Darl	P, 130/110V, 6/10A, 50W, 20MHz, hFE=5k...30k	{2SB1531} 18j	TO-3P		2SD2221, 2SD2255
2 SD 2341	Mat	Si-N	Uni, 200/180V, 2/3A, 1.5W, 150MHz	78b	(MT-3)		-
2 SD 2342	Hit	Si-N	P, 150/80V, 6/10A, 50W	18j	TO-3P	2SC2837	18j BD2450...F, 2SC2837, 2SC4467, 2SD1046...47
2 SD 2343	Rhm	Si-N	P, 120/120V, 7/10A, 5W, 80MHz	14b	TO-126 Iso	(2SC3117) ³	14h 2SC3621, 2SD1684, (2SC2690(A), 2SD1563) ³
2 SD 2344	Hit	Si-N	P, 350/150V, 7/10A, 20W	17c	SOT-186	BU 12 AF	17c BU 306F, BU 406F, 2SC4130, 2SC4160, ++
2 SD 2345	Mat	Si-N	=2SD1030: SMD	35a(1.6mm)	SS-Mini		-
2 SD 2348	Tos	Si-N+Di	CTV-HA, 1500/600V, ±8/16A, 50W, sat<5V(6A)	18c	TO-3P Iso	BU 508DF	18c BU 508DF, BU 2508DF, 2SC4124, 2SD1880, ++
2 SD 2349	Tos	Si-N+Di	CTV-HA, 1500/600V, ±10/20A, 50W, sat<5V(7A)	18c	TO-3P Iso		++ BU 2520DF, 2SC4125, 2SC4531, 2SD1881, ++
2 SD 2350	Fjd	Si-N-Darl	300/300V, 6A, 40W, hFE>500	17			2SD1071, 2SD1113, 2SD1307, 2SD1976
2 SD 2351	Rhm	Si-N	=2SD2227S: SMD	35a(2mm)	SOT-323		2SC4181, 2SC4413
2 SD 2352	Tos	Si-N	P, 60/60V, 2/4A, 25W, 17MHz, hi-hFE=800...3200	17c	TO-220 Iso	2SD1273	17c 2SC3852, 2SD1776(A), 2SD1944, 2SD2158(A)
2 SD 2353	Tos	Si-N	P, 60/60V, 3/6A, 25W, 18MHz, hi-hFE=800...3200	17c	TO-220 Iso	2SD1273	17c 2SC3852, 2SD1972, 2SD1944, 2SD2127, ++
2 SD 2354	Mat	Si-N	HA, 1500V, 7/14A, -IBp=3A, 100W, sat<5V(4A)	16c(j)	(TOP-3F)	BU 508A(F)	18j(c) BU 508A(F), BU 908(F), BU 2508A(F), ++
2 SD 2355	Mat	Si-N	HA, 1500V, 10/20A, -IBp=4A, 100W, sat<5V(5A)	16c(j)	(TOP-3F)		++ BU 2520A(F), BU 2525A(F)
2 SD 2356	Mat	Si-N	HA, 64kHz, 1500V, 20/30A, 200W, sat<5V(10A)	77j	(TOP-3L)		2SC3997, 2SC4290A
2 SD 2357	Mat	Si-N	SMD, 10/10V, 1A, 120MHz, sat<0.15V(0.5A)	{2SB1537} 39b	SOT-89		2SC2982, 2SC3443...44, 2SD1621...23
2 SD 2359	Mat	Si-N	SMD, 20/20V, 1A, 100MHz, sat<0.2V(0.5A)	{2SB1539} 39b	SOT-89		2SC2982, 2SC3443...44, 2SD1621...23
2 SD 2361	Mat	Si-N	Uni P, 60/50V, 1/1.5A, 1.2W, 150MHz	{2SB1541} =12b	(MT-2L)	(2SC1398) ⁴	17j (BD 517, BD 525, 2SC2194, 2SD1801, ++) ⁴
2 SD 2362	Mat	Si-N	Uni P, 50/50V, 2/3A, 1.2W, 130MHz	{2SB1542} =12b	(MT-2L)	(2SC1398) ⁴	17j (BD 509, BD 515, 2SC3076, 2SD1801, ++) ⁴
2 SD 2363	Mat	Si-N	Uni P, 60/60V, 3/5A, 1.2W, 25MHz	{2SB1543} =12b	(MT-2L)	(2SC3299) ⁶	17c (2SC3386, 2SD1221, 2SD1802, 2SD1805, ++) ⁴
2 SD 2364	Mat	Si-N	Uni P, 80/80V, 1/1.5A, 1.2W, 140MHz	{2SB1544} =12b	(MT-2L)	(2SC1398) ⁴	17j (BD 519, BD 527, BD 529, 2SC4135, ++) ⁴
2 SD 2365	Mat	Si-N	Uni P, 150/150V, 1/1.5A, 1.2W, 90MHz	{2SB1545} =12b	(MT-2L)	(2SC4159) ⁶	17c (2SC2384, 2SC2983, 2SD1220, 2SD1918, ++) ⁴
2 SD 2366	Mat	Si-N	S P, 400/400V, 0.5/1A, 1.2W, 30MHz	{2SB1546} =12b	(MT-2L)		(2SC2752, 2SC3362, 2SC4615, 2SD1053) ⁴
2 SD 2367	Mat	Si-N+Di	HA, 1500V, 3/10A, -IBp=2.5A, 50W, sat<5V(2A)	18c	TO-3P Iso	2SD1555	18c BU 705DF, 2SD1554, 2SD1877, 2SD2089, ++
2 SD 2368	Mat	Si-N+Di	HA, 1500/700V, 3.5/10A, 60W, sat<8V(3A)	18c	TO-3P Iso	2SD1555	18c BU 706DF, 2SD1554, 2SD1877, 2SD2089, ++
2 SD 2369	Mat	Si-N+Di	HA, 1500V, 4/15A, -IBp=2.5A, 70W, sat<1V(3A)	18c	TO-3P Iso	2SD1555	18c BU 706DF, 2SD1555, 2SD2095, 2SD2125, ++
2 SD 2370	Mat	Si-N+Di	HA, 1500/700V, 5/15A, 100W, sat<8V(4A)	18c	TO-3P Iso	2SD1555	18c BU 706DF, 2SD1555, 2SD2095, 2SD2125, ++
2 SD 2371	Mat	Si-N+Di	HA, 1500V, 7/20A, 100W, sat<8V(5A)	18c	TO-3P Iso	BU 508 DF	18c BU 508DF, 2SC3893A, 2SC4124, 2SD1880, ++
2 SD 2372	Mat	Si-N	HA, 1500/600V, 7/14A, -IBp=3A, 100W, sat<5V(4A)	18c	TO-3P Iso	BU 508 AF	18c BU 508AF, 2SC3895, 2SC4757, 2SD2252, ++
2 SD 2373	Mat	Si-N	HA, 1500/600V, 10/20A, -IBp=4A, 100W, sat<5V(5A)	18c	TO-3P Iso	2SC4924	18c BUH 715, 2SC3897, 2SC4542, 2SD1887, ++
2 SD 2374	Mat	Si-N	S P, 60/60V, 3/5A, 25W, 30MHz, 500/2900ns	17c	TO-220 Iso	2SC3299	17c 2SD1762, 2SD1913, 2SC3690
2 SD 2375	Mat	Si-N	80/60V, 3/6A, 25W, 50MHz, hFE=500...1500	17c	TO-220 Iso	2SD1273	17c 2SD1273, 2SD1944, 2SD2092, 2SD2156
2 SD 2381	Hit	Si-N	=2SD2287: Iso, 40W	-18c	TO-3PFM	BU 508 AF	18c BU 706F, 2SD1544, 2SD1654, 2SD1883
2 SD 2383	Nec	Si-N	SMD, S, 400/300V, 20mA, 90MHz, sat<0.5V(5mA)	35a	SOT-23		-
2 SD 2384	Tos	Si-N-Darl	P, 140/140V, 7A, 100W, 30MHz, hFE=5k...30k	{2SB1555} 77j	TOP-3L		2SD2222, 2SD2250, 2SD2276
2 SD 2385	Tos	Si-N-Darl	P, 140/140V, 8A, 120W, 30MHz, hFE=5k...30k	{2SB1556} 77j	TOP-3L		2SD2222, 2SD2250, 2SD2276
2 SD 2386	Tos	Si-N-Darl	=2SD2384: 70W	{2SB1557} 18j	TO-3P		2SD2221, 2SD2255
2 SD 2387	Tos	Si-N-Darl	=2SD2385: 80W	{2SB1558} 18j	TO-3P		BDV 67C...D, 2SD1210
2 SD 2388	Rhm	Si-N-Darl+Di	=2SD2090: 1.2W	78b	(MRT)		-
2 SD 2389	Sak	Si-N-Darl	P, 160/150V, 8A, 80W, 80MHz, hFE=5k...30k	{2SB1559} 18j	TO-3P		BDV 67D, 2SD1123
2 SD 2390	Sak	Si-N-Darl	P, 160/150V, 10A, 100W, 55MHz, hFE=5k...30k	{2SB1560} 18j	TO-3P		BDV 67D, 2SD1123, 2SD1027, 2SD1515
2 SD 2391	Rhm	Si-N	SMD, 60/60V, 2/5A, 210MHz, sat<0.35(1A)	{2SB1561} 39b	SOT-89		2SC4409, 2SD2533
2 SD 2394	Rhm	Si-N	LF P, 80/60V, 3/6A, 25W, 8MHz	{2SB1565} 17c	TO-220 Iso	2SD1411	17c BD 937F, BDT 31...F, 2SC3475, 2SC3851, ++
2 SD 2395	Rhm	Si-N	LF P, 60/50V, 3/5A, 25W, 100MHz	{2SB1566} 17c	TO-220 Iso	2SD1411	17c BD 935F, BDT 31...F, 2SD1585, 2SD1985, ++
2 SD 2396	Rhm	Si-N	=2SD1943: Iso, 30W	17c	TO-220 Iso	2SD1273	17c 2SD1273, 2SD2092, 2SD2156, 2SD2375, ++
2 SD 2397	Rhm	Si-N-Darl+Di	=2SD1764: 1.2W	17c	TO-220 Iso	-2SD1764	-2SD1764
2 SD 2398	Rhm	Si-N-Darl+Di	LF P, 100/100V, 2/3A, 20W, hFE=1k...10k	{2SB1567} 17c	TO-220 Iso	2SD1415	17c 2SD1828, 2SD1890, 2SD2129, 2SD2257, ++
2 SD 2399	Rhm	Si-N-Darl+Di	LF P, 80/80V, 4/6A, 30W, 40MHz, hFE=1k...10k	{2SB1568} 17c	TO-220 Iso	2SD1415	17c BDT 61...F, 2SD1414, 2SD1788, 2SD1933, ++
2 SD 2400	Rhm	Si-N	LF P, 120/120V, 1.5/3A, 20W, 80MHz	{2SB1569} 17c	TO-220 Iso	2SC4195	17c 2SC3364, 2SC3564, 2SC4883(A), 2SD1763, ++
2 SD 2400 A	Rhm	Si-N	=2SD2400: 160/160V	17c	TO-220 Iso	2SC4195	17c 2SC3364, 2SC4159, 2SC4370, 2SC4883A, ++
2 SD 2401	Sak	Si-N-Darl	P, 160/150V, 12A, 150W, 55MHz, hFE>5000	{2SB1570} 20j	(MT-200)		-
2 SD 2402	Nec	Si-N	SMD, S, 50/30V, 5/8A, 170MHz, 275/530ns lo-sat<0.5V(5A)	{2SA1871} 39b	SOT-89		2SD1628
2 SD 2403	Nec	Si-N	SMD, S, 80/60V, 3/5A, 130MHz, 150/665ns lo-sat<0.5V(3A)	{2SB1572} 39b	SOT-89		2SC4541
2 SD 2407	Mat	Si-N	S P, 60/60V, 3/5A, 10W, 220MHz, 500/2900ns	30c	TO-252	2SC3303	30j 2SC4522, 2SD1221, 2SD1760, 2SD1802, ++
2 SD 2408	Mat	Si-N	S P, 50/50V, 2/3A, 10W, 150MHz, sat<0.3V(1A)	30c	TO-252	2SC3303	30j BD 509, 2SC3076, 2SD1078, 2SD1801, ++
2 SD 2409	Mat	Si-N	S P, 50/50V, 5/7A, 10W, 80MHz, sat<0.3V(2A)	30c	TO-252	2SC3303	30j 2SC3072, 2SC3518, 2SC3592, 2SD1805, ++
2 SD 2410	Mat	Si-N-Darl	S P, 100/100V, 2/4A, 10W, 20MHz, hFE=1k...10k	30c	TO-252		2SD1980, 2SD1955
2 SD 2411	Mat	Si-N-Darl	S P, 200/200V, 2/4A, 10W, hFE=1k...10k	30c	TO-252		-
2 SD 2413	Mat	Si-N	SMD, S, 400/400V, 0.1/0.2A, 40MHz	39b	SOT-89		2SC4505, 2SC4548
2 SD 2415	Hit	Si-N	int. Z-Di(E -C), 25/25V, 0.5/1A, sat<0.5V(0.5A)	7c	TO-92		-
2 SD 2421	Rhm	Si-N-Darl+Di	=2SD2422: 1.8W	78c	(HRT)		-
2 SD 2422	Rhm	Si-N-Darl+Di	P, 100/100V, 7/10A, 30W, 40MHz, hFE=1k...20k	17c	SOT-186	(2SD1415) ⁸	17c 2SD1791, (BD 647F, 2SC4062, 2SD1415) ⁸
2 SD 2423	Hit	Si-N-Darl+Di	int. Z-Di(C -B), 50/50V, 1.5A, hFE=2k...10k	39b	SOT-89		-
2 SD 2425	Nec	Si-N	SMD, S, 60/60V, 5/7A, 600/880ns	{2SB1578} 39b	SOT-89		2SD1628, 2SD2098, 2SD2402
2 SD 2426	Say	Si-N-Darl	Uni, 100/80V, 2A, 1.5W, 80MHz	-12b	(FLP)		-
2 SD 2432	Mat	Si-N	=2SD602:	35d	-SOT-23		-2SD602
2 SD 2433	Mat	Si-N	=2SD1030:	35d	-SOT-23		-2SD1030
2 SD 2434	Mat	Si-N-Darl	=2SD1478:	35d	-SOT-23		-2SD1478
2 SD 2436	Mat	Si-N	=2SD1328:	35d	-SOT-23		-2SD1328
2 SD 2437	Sak	Si-N-Darl+Di	P, 120/120V, 6A, 60W, 80MHz, hFE=2k...15k	{2SB1586} 18c	TO-3P Iso		2SD1893...95, 2SD2045
2 SD 2438	Sak	Si-N-Darl+Di	P, 160/150V, 8A, 70W, 80MHz, hFE=5k...30k	{2SB1587} 18c	TO-3P Iso		2SD1894...95, (2SD2221, 2SD2255) ³
2 SD 2439	Sak	Si-N-Darl+Di	P, 160/150V, 10A, 70W, 55MHz, hFE=5k...30k	{2SB1588} 18c	TO-3P Iso		2SD1895, (2SD2390) ³
2 SD 2441	Mat	Si-N	SMD, 10/10V, 1.5/2A, 190MHz, lo-sat<0.25V(1A)	39b	SOT-89		2SC2982, 2SC3443, 2SD1621
2 SD 2457	Mat	Si-N	SMD, 50/40V, 1.5/3A, 150MHz	39b	SOT-89		2SC2873, 2SD1623...24, 2SD2532

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International
2 SD 2463	Nec	Si-N-Darl+Di	int. Z-Di(C +B), 31/31(+4)V, ±2/3A, 1W hFE=2k...30k, 0.5/4µs	9b	(SP-8)		
2 SD 2464	Mat	Si-N	15/10/10V, 5/8A, 0,75W, 170MHz, lo-sat<0.5V(3A)	7c	TO-92	2SD2179	7c(9mm) 2SC4482, 2SD1145
2 SD 2472	Mat	Si-N	SMD, 10/10V, 0.5/0.6A, 120MHz, lo-sat<0.17V(0.25A)	35d	-SOT-23		2SC4577
2 SD 2473	Mat	Si-N	SMD, 20/20V, 0.5/0.6A, lo-sat<0.2V(0.25A)	35d	-SOT-23		2SC4519, 2SC4577
2 SD 2474	Mat	Si-N	SMD, 10/10V, 2/2.4A, 180MHz, sat<0.25V(1A)	{2SD2474} 39b	SOT-89		2SC3443, 2SC2982, 2SD1621
2 SD 2478	Rhm	Si-N-Darl	P, 80/80V, 4/6A, 30W, 40MHz, hFE=1k...10k	17c	SOT-186	(2SD1415) ⁸	17c 2SD1788, (BDT 61BF, 2SD1414, 2SD1589+) ⁸
2 SD 2482	Mat	Si-N	=2SD2472:	35a(2mm)	SOT-323		2SC4555
2 SD 2483	Mat	Si-N	=2SD2473:	35a(2mm)	SOT-323		2SC4555
2 SD 2484	Hit	Si-N	50/50V, 2/3A, 0.9W, lo-sat<0.2V(1A)	7c(9mm)	TO-92L	2SD1207	7c(9mm) 2SC3726, 2SD1207, 2SD2069, 2SD2177, ++
2 SD 2485	Hit	Si-N	=2SD2484: 80/80V	7c(9mm)	TO-92L		2SC3328, 2SC4489, 2SD2182
2 SD 2488	Sak	Si-N-Darl	P, 200/200V, 15A, 130W, 70MHz, hFE=5k...30k	{2SB1620} 18j	TO-3P		
2 SD 2489	Sak	Si-N-Darl	=2SD2488: 17A, 200W	{2SB1621} 20j	TO-3P		
2 SD 2490	Sak	Si-N-Darl	=2SD2488: Iso, 85W	{2SB1622} 18c	(FM100)		
2 SD 2491	Hit	Si-N	Vid Out, 160/160V, 0.1A, 8W, 140MHz	14b	TO-126 Iso	(2SC3601) ³	14h 2SC3788, 2SC3955...56
2 SD 2492	Hit	Si-N	=2SD2491: 200/200V	14b	TO-126 Iso	(2SC3601) ³	14h 2SC3788, 2SC3955...56
2 SD 2493	Sak	Si-N-Darl	P, 110/110V, 6A, 60W, 60MHz, hFE=5k...30k	{2SB1624} 18j	TO-3P		2SD2221, 2SD2255, 2SD2340, 2SD2386
2 SD 2494	Sak	Si-N-Darl	=2SD2493: Iso	{2SB1625} 18c	(FM100)		2SD1893...94, 2SD2438
2 SD 2495	Sak	Si-N-Darl	=2SD2493: Iso, 30W	{2SB1626} 17c	TO-220 Iso		2SD2025
2 SD 2496	Mat	Si-N	=2SD601A:	35d	-SOT-23		-2SD601A
2 SD 2497	Hit	Si-N	40/20V, 5/8A, 0,75W, lo-sat<0.3V(3A)	7c	TO-92	(2SD2179) ¹⁷	9c 2SC4482, 2SD1145, 2SD2243, (2SD2249+) ¹⁷
2 SD 2504	Mat	Si-N	=2SD2464: 5/9A	7c	TO-92	2SD2179	7c(9mm) 2SC4482, 2SD1145
2 SD 2529	Mat	Si-N	=2SD1938:	35d	-SOT-23		-2SD1938
2 SD 2532	Hit	Si-N	=2SD2484: SMD	39b	SOT-89		2SC4409, 2SC4541, 2SD1623...24
2 SD 2533	Hit	Si-N	=2SD2485: SMD	39b	SOT-89		2SC4409, 2SC4541
2 SD 2540	Hit	Si-N	=2SD2497: SMD	39b	SOT-89		2SD1628
2 SF 1168(A)	Mat	50Hz-Thy	200(A=400)V, 6A, Igt/Ih<25/15mA, toff=30µs	22a	TO-66		MCR 218... TAG 625... TAG 651...++
2 SF 1188	Say	F-Thy	TV-HA, +650/-12V, 3.2A(Tc=60°), Igt<30mA, tq<2.5µs (Hinlauf/Trace)	22a	TO-66	TD 3FP 800H1*	17f S 3703, (TD 3F700H, TD 4F700H,++) ¹
2 SF 1189	Say	F-Thy	TV-HA, +600/-6V, 3.2A(Tc=60°), Igt<40mA, tq<4.3µs (Rücklauf/Retrace)	22a	TO-66	TD 3FP 800R1*	17f S 3702, (TD 3F800R, TD 4F800R,++) ¹
2 SF 1418 C...G	Say	F-Thy	200...600V, 3.2A(Tc=60°), 7.5A~, Igt<35mA, tq<4.3µs C=200, D=300, E=400, F=500, G=600V	22a	TO-66	(TAG 626-600) ⁵	17e BTW 27S/..., T 3S..., TAG 670...671S...
2 SF 1420 D...G	Say	F-Thy	300...700V, 3.2A(Tc=75°), 5A~, Igt/Ih<35/<30mA D=300, E=400, F=500, G=600, H=700V	22a	TO-66	(TAG 626-600) ⁵	17e BTW 27S/..., T 3S..., TAG 670...671S...
2 SF 1450-200...600	Hit	50Hz-Thy	=CP 8 C...G				+CP 8...
2 SF 1451-200...600	Hit	50Hz-Thy	=CP 9 C...G				+CP 9...
2SH							
2 SH 11	Nec,Tho	UJT-P	35/30V, 50mA, iEM=2A, 0.45W, Ip<12µA, Iv>7mA, η=0.58...0.75, Rbb=4.5kΩ	2b	TO-5		
2 SH 12	Nec,Tho	UJT-P	=2SH11: η=0.47...0.62	2b	TO-5		
2 SH 13	Tos	UJT-P	55/60V, 50mA, iEM=2A, 0.45W, Ip<6µA, Iv>11mA, η=0.47...0.75, Rbb=4.7...10kΩ	2b	TO-5		
2 SH 14	Tos	UJT-P	=2SH13: Ip<8µA, Iv>8mA, η=0.45...77, Rbb=4.3...12kΩ	2b	TO-5		
2 SH 15	Tos	UJT-P	25/30V, 50mA, iEM=2A, 0.45W, Ip<12µA, Iv>7mA, η=0.47...0.67, Rbb>4.5kΩ	2b	TO-5		
2 SH 16(A)	Nec,Tho	UJT-P	30/30V, 50mA, iEM=1A, 0.25W, Ip<12µA, Iv>4mA, η=0.5...0.84, Rbb=4...9kΩ	7g	TO-92		2N2646P
2 SH 17	Nec,Tho	UJT-P	=2SH16: Ip<4µA, Iv>2mA, η=0.5...0.67	7g	TO-92		
2 SH 18	Gen,Mot	UJT-P	=2SH16: 0.3W	2b,5e	TO-18, -72		
2 SH 19	Gen,Mot	UJT-P	=2SH17: 0.3W	2b,5e	TO-18, -72		
2 SH 20	Tos	UJT-P	55/60V, 50mA, iEM=1A, 0.25W, Ip<3.5µA, Iv>6mA, η=0.7...0.85, Rbb=4...12kΩ	2b	TO-18		
2 SH 21	Tos	UJT-P	=2SH20: Ip<4µA, Iv>4mA	2b	TO-18		
2 SH 22	Tos	UJT-P	25/30, 50mA, iEM=1A, 0.25W, Ip<4µA, Iv>4mA, η=0.65...0.85, Rbb=4kΩ	2b	TO-18		2SH21
2 SH 23	Nec	UJT-P	25/30V, 100mA, Ifm=2A, 0.45W, Ip<4µA, Iv>7mA, η=0.58...0.64, Rbb=8...20kΩ	2b	TO-5		2SH20
2 SH 24	Nec	UJT-P	=2SH23: Ip<12µA	2b	TO-5		
2 SH 25	Nec	UJT-P	=2SH23: 75mA, Ifm=1A, 0.3W	7b	TO-92		
2SJ							
2 SJ 11	Tos	P-FET	Uni, 20V, Idss=0.05...0.9mA, Up=0.7...5V	5n	TO-17		2N2606, 2N5797
2 SJ 12	Tos	P-FET	=2SJ11: Idss=0.09...0.9mA	5n	TO-17		2N2606, 2N5797
2 SJ 13	Tos	P-FET	Uni, 20V, Idss=1...12mA, Up=1...6V	2a(G=case)	TO-5		
2 SJ 15	Fui	P-FET	Uni, 18V, Idss=1.5mA, Up<6V	2a(G=case)	TO-18		2N5460, 2N5463, 2SJ103, 2SJ105
2 SJ 16	Fui	P-FET	Uni, 18V, Idss=1.5mA, Up<6V	2a(G=case)	TO-18		2N5460, 2N5463, 2SJ103, 2SJ105
2 SJ 17	Son	P-FET	LF, In, 20V, Idss>0.11mA	40d			
2 SJ 18	Son	P-FET	VFET, 170V, 5A, 63W, 16Ω	{2SK60} 23a	TO-3		
2 SJ 19	Nec	P-FET	VFET, LF, 140/30V, 0.1A, 0.8W	{2SK69} 2a	TO-5		
2 SJ 20	Nec	P-FET	VFET, 100/40V, 10A, 100W, on=10Ω 2SK70	23a	TO-3		
2 SJ 21	Nec	P-FET	VFET, 160/30V, 15W, Idss=30...300	{2SK71} 22a	TO-66		
2 SJ 22	Son	P-FET	LF, In, 80V, Idss=0.3...0.7mA	2d	TO-18		
2 SJ 29	Hit	P-FET	VFET, 140V, 10A, 100W, on=15Ω	23a	TO-3		
2 SJ 32	Shi	P-FET	LF.S, 150V, 0.6W, on=350kΩ				
2 SJ 33	Shi	P-FET	=2SJ32: 200V				
2 SJ 39	Mit	P-FET	Dual, 50V, 20mA, Idss=1...12mA, Up<6V	7-SIP	(DGSsDGS)		
2 SJ 40	Mit	P-FET	Analog-S, 50V, Idss=0.6...12mA, Up=0.3...6V	{2SK381} 41a			
2 SJ 43	Mat	P-FET	Uni, 50V, 20mA, Idss=0.5...12mA, Up=0.2...3V	{2SK127} 7a	TO-92		2SJ129
2 SJ 44	Nec	P-FET	Uni In, 40V, 30mA, Idss=1...18mA, Up=0.2...1.5V Ur<20mV	7a	TO-92		2N5021, 2SJ74
2 SJ 45	Nec	P-FET	=2SK44: Ur<50mV	7a	TO-92		2N5021, 2SJ74
2 SJ 47	Hit	MOS-P-FET-e	VFET, 100/14V, 7A, 100W, on<1.7Ω, 25/24ns	{2SK132} 23e	TO-3		2SJ55...56, 2SJ160...162
2 SJ 48	Hit	MOS-P-FET-e	=2SJ47: 120/14V	{2SK133} 23e	TO-3		2SJ55...56, 2SJ160...162
2 SJ 49	Hit	MOS-P-FET-e	=2SJ47: 140/14V	{2SK134} 23e	TO-3		2SJ55...56, 2SJ161...162
2 SJ 50	Hit	MOS-P-FET-e	=2SJ47: 160/14V	{2SK135} 23e	TO-3		2SJ55...56, 2SJ162
2 SJ 51	Hit	P-FET	S,LF In, 40V, 200mA, Idss=6...50mA, Up<1.1V	{2SK151} 7a(9mm)	TO-92L		2SJ70
2 SJ 55	Hit	MOS-P-FET-e	VFET, 180/20V, 8A, 125W, on=1<1.7Ω	{2SK175} 23e	TO-3		
2 SJ 56	Hit	MOS-P-FET-e	=2SJ55: 200/20V	{2SK176} 23e	TO-3		
2 SJ 68	Hit	P-FET	S,LF In, 40V, 30mA, Idss=1.6...12mA, Up=0.13...1.5V	7a	TO-92		2SJ104, 2SJ107...108
2 SJ 69	Hit	P-FET	S,LF In, 40V, 30mA, Idss=2.5...20mA, Up=0.13...1.5V	7a	TO-92		2SJ104, 2SJ107...108
2 SJ 70	Hit	P-FET	S,LF In, 40V, 200mA, Idss=6...50mA, Up=0.13...1.5V	7a(9mm)	TO-92L		2SJ51