

> PN rectifiers

Fast recovery, space-saving devices

Nexperia's PN rectifiers deliver high power density while minimizing reverse recovery time and loss. For efficient switching and power conversion applications in automotive, industrial and consumer markets.

Portfolio


- > 200–400 V **Hyperfast** switching parts with optimized recovery time (trr) of < 25 ns
- > 200-400 V **Standard** parts trr > 500 ns
- > High speed switching capability
- **)** Low voltage drop (VF @ $I_{F max} \sim 1 \text{ V}$)
- Low leakage current, also at high temperature
- > AEC-Q101 qualified parts (175 °C T_{J (max)})

Robust & thermally efficient



- High current pulse capability due to solid copper clip-bond
- High power density / high efficiency planar technology
- Low magnetic inductance optimizes switching behavior

Economical use of space



- > Just 1 mm package height for thin PCB designs
- More than 50% footprint savings CFP3 compared to SMA

Key applications

- Polarity protection
- > DC/DC conversion
- > AC/DC conversion
- > Freewheeling of inductive load
- > Standard switching application
- High-speed switching application



| V _R max (V) | V _F max (V) | (A) ₁ (Ø) | I _к max (µA) | (©) V _R (V) | trr max (ns) | Package | CFP5 (SOD128) | CFP3 (SOD123W) |
|------------------------|------------------------|----------------------|-------------------------|------------------------|--------------|------------------------------|------------------|-------------------|
| | | | | | | | | |
| | | | | | | Size (mm) | 3.8 x 2.5 x 1.0 | 2.6 x 1.7 x 1.0 |
| > = | > | @ | | <u>@</u> | Į, | P _{tot} (mW) @ 1cm² | 1050 | 950 |
| 200 | 0.875 | 1 | 0.2 | 200 | 25 | Sm0.35 | | ES1DVR |
| | 0.93 | 1 | 0.2 | 200 | 25 | | | ES1DR |
| | 0.95 | 2 | 0.2 | 200 | 25 | | | ES2DVR |
| | 0.98 | 2 | 0.2 | 200 | 25 | | | ES2DR |
| | 0.95 | 2 | 0.2 | 200 | 25 | | ES2DP | |
| | 0.98 | 3 | 0.2 | 200 | 30 | | ES3DP | |
| | 1.1 | 1 | 3 | 200 | 3000 | | S1DR | |
| 400 | 1.25 | 1 | 0.4 | 400 | 25 | | | ES1GR |

PN rectifiers - Automotive qualified

Types in **bold** represent new products

| V _R max (V) | V _F max (V) | (@) I _F (A) | I _в max (µA) | (@) V _R (V) | trr max (ns) | Package | CFP5 (SOD128) | CFP3 (SOD123W) |
|------------------------|------------------------|------------------------|-------------------------|------------------------|--------------|------------------------------|------------------|-------------------|
| | | | | | | | | |
| | | | | | | Size (mm) | 3.8 x 2.5 x 1.0 | 2.6 x 1.7 x 1.0 |
| | | | | | | P _{tot} (mW) @ 1cm² | 1050 | 950 |
| 200 | 0.93 | 1 | 0.2 | 200 | 25 | and.05 | | PNE20010ER |
| | 0.98 | 2 | 0.2 | 200 | 25 | | | PNE20020ER |
| | 0.95 | 2 | 0.2 | 200 | 25 | | PNE20020EP | |
| | 0.98 | 3 | 0.2 | 200 | 30 | | PNE20030EP | |
| 400 | 1.1 | 1 | 1 | 400 | 1800 | | | PNS40010ER |

© 2018 Nexperia B.V.

All rights reserved. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner. The information presented in this document does not form part of any quotation or contract, is believed to be accurate and reliable and may be changed without notice. No liability will be accepted by the publisher for any consequence of its use. Publication thereof does not convey nor imply any license under patent- or other industrial or intellectual property rights.

Date of release:

February 2018

