




#### **MECHANICAL DATA**

Dimensions in mm (inches)



#### TO-39 (TO205AD)

**Underside View** 

PIN 1 - Emitter PIN 2 - Base PIN 3 - Collector

#### PNP SILICON TRANSISTOR

#### **FEATURES**

- High Voltage
- Hermetic TO39 Package
- Full Screening Options Available

# **ABSOLUTE MAXIMUM RATINGS** (T<sub>case</sub> = 25°C unless otherwise stated)

$V_{CBO}$	Collector – Base Voltage (I <sub>E</sub> = 0)	-300V
$V_{CEO}$	Collector – Emitter Voltage (I <sub>B</sub> = 0)	-300V
$V_{EBO}$	Emitter – Base Voltage (I <sub>B</sub> = 0)	-5V
$I_{\mathbb{C}}$	Collector Current	-0.5A
$P_{D}$	Total Device Dissipation T <sub>C</sub> = 50°C	5W
$T_{stg}$	Storage Temperature	−65 to 150°C
$T_J$	Junction Temperature	200°C
$R_{ heta JA}$	Thermal Resistance Junction to Ambient	200°C/W
$R_{\theta JC}$	Thermal Resistance Junction to Case	30°C/W

Semelab PIc reserves the right to change test conditions, parameter limits and package dimensions without notice. Information furnished by Semelab is believed to be both accurate and reliable at the time of going to press. However Semelab assumes no responsibility for any errors or omissions discovered in its use. Semelab encourages customers to verify that datasheets are current before placing orders.

**Semelab plc.** Telephone +44(0)1455 556565. Fax +44(0)1455 552612. E-mail: sales@semelab.co.uk

Website: http://www.semelab.co.uk

Document Number 6075





## **ELECTRICAL CHARACTERISTICS** (T<sub>case</sub> = 25°C unless otherwise stated)

	Parameter	Test Conditions		Min	Тур	Max	Unit
V <sub>(BR)CEO</sub>	Collector – Emitter Breakdown Voltage	$I_{C} = -10 \text{mA},$	I <sub>B</sub> = 0	-300			V
I <sub>CBO</sub>	Collector Cut-off Current	V <sub>CB</sub> = -200V	I <sub>E</sub> = 0			-5	μΑ
I <sub>EBO</sub>	Emitter Cut-off Current	$V_{BE} = -3V$	I <sub>C</sub> = 0			-5	μΑ
V <sub>CE(sat)*</sub>	Collector – Emitter Saturation Voltage	I <sub>C</sub> =-10mA,	I <sub>B</sub> =-1.0mA			-0.5	
		I <sub>C</sub> =-100mA,	I <sub>B</sub> =-10mA			-1.4	V
		I <sub>C</sub> =-500mA,	I <sub>B</sub> =-100mA			-5.0	
V <sub>BE(sat)*</sub>	Base – Emitter Saturation Voltage	I <sub>C</sub> =-10mA,	$I_B = -1.0 \text{mA}$			-0.8	V
		I <sub>C</sub> =-100mA,	I <sub>B</sub> =-10mA			-0.9	
		I <sub>C</sub> =-500mA,	I <sub>B</sub> =-100mA			-1.2	
h <sub>FE*</sub>	DC Current Gain	V <sub>CE</sub> = -10V	$I_C = -1.0 \text{mA}$	30			_
		V <sub>CE</sub> = -10V	I <sub>C</sub> = -10mA	50		150	
		V <sub>CE</sub> = -10V	I <sub>C</sub> = -100mA	50			

### **DYNAMIC CHARACTERISTICS** (T<sub>case</sub> = 25°C unless otherwise stated)

Parameter		Test Conditions	Min.	Тур.	Max.	Unit
f <sub>T</sub>	Transition Frequency	$I_{C} = -15 \text{mA}$ $V_{CE} = -10 \text{V}$ $f = 35 \text{MHz}$		70		MHz
C <sub>c</sub>	Collector Capacitance	$V_{CB} = -20V$ $I_E = 0$ $f = 1MHz$			15	pF
t <sub>on</sub>	Lurn on Lime	$V_{CC}$ =-31V , $I_{C}$ =-50mA, $I_{B1}$ = $I_{B2}$ =5mA		125		ns
		$V_{CC}$ =-31V , $I_{C}$ =-500mA, $I_{B1}$ = $I_{B2}$ =100mA		125		ns
t <sub>off</sub>	Lurn off Lime	$V_{CC}$ =-31V , $I_{C}$ =-50mA, $I_{B1}$ = $I_{B2}$ =5mA		850		ns
		$V_{CC}$ =-31V , $I_{C}$ =-500mA, $I_{B1}$ = $I_{B2}$ =100mA		125		ns

(\*) Pulse test : Pulse Width  $< 300 \mu s$  , Duty Cycle < 2%

Semelab Plc reserves the right to change test conditions, parameter limits and package dimensions without notice. Information furnished by Semelab is believed to be both accurate and reliable at the time of going to press. However Semelab assumes no responsibility for any errors or omissions discovered in its use. Semelab encourages customers to verify that datasheets are current before placing orders.

E-mail: sales@semelab.co.uk Website: http://www.semelab.co.uk

**Semelab plc.** Telephone +44(0)1455 556565. Fax +44(0)1455 552612.

Document Number 6075

Issue 1